

Australia's Top Selling Electronics Magazine

Electronics Australia

JANUARY

1986

Aust* \$2.75

NZ \$3.50

**Sony's brilliant new
8mm video system**

**How to match
your CD player
to your amplifier**

Reviews:

**Toshiba T-1100
portable computer**

**Carver DTL-100
compact disc player**

**Build
your
own
video
fader**



**Special Supplement:
Compact Disc
Directory**



TU-D99X SLDD Digital Synthesizer Tuner

C-2101 Stereo Control Amplifier

B-2101* X-Balanced Power Amplifier



*RMS power output: 200 watts \times 2 (8 ohms),
20Hz-20kHz, less than 0.003% THD.
Dynamic power output: 680 watts \times 2
(2 ohms).

OWN THE BEST
The best is only as far away as your nearest Sansui dealer.

Sansui

SANSUI ELECTRIC CO., LTD. 14-1 Izumi 2-chome, Suginami-ku, Tokyo 168, Japan
VANFI (AUST.) PTY. LTD. 297 City Road, South Melbourne, Victoria 3205, Australia Tel: 690-6200
283 Alfred Street, North Sydney, N.S.W. 2060, Australia Tel: 929-0293

THIS MONTH'S COVER

Is your favourite record available on compact disc? Find out with our comprehensive compact disc directory. Pt.1 begins on page 97. (Photo by Greg McBean).

Electronics Australia

Volume 48, No.1

January
1986

Features

- 16 SYDNEY'S LAST DC POWER MAIN *The end of an era*
- 24 HOW TO BECOME A COMPUTER TECHNICIAN *Control Data Institute*
- 54 SIMPLE WORLD WAR WIRELESS *Don't fret in the foxhole*
- 62 TOSHIBA'S T1100 PERSONAL COMPUTER *Sits in your lap*
- 97 COMPACT DISC DIRECTORY PT.1 *Special supplement*

Entertainment Electronics

- 8 SONY'S NEW 8mm VIDEO CAMCORDER *Looks well and works well*
- 26 HIFI REVIEW *Carver DTL-100 CD player with digital time lens*
- 92 RECORD REVIEWS *Classical, popular and special interest*

Projects and Technical

- 28 PLAYMASTER STEREO AM/FM TUNER PT. 2 *Full circuit details*
- 42 THE SERVICEMAN *Aversion therapy for the Sony KVA-1830AS*
- 46 BUILD A CD ATTENUATOR *Match your CD player to your amplifier*
- 48 VIDEO FADER CIRCUIT *For home movie buffs*
- 52 CIRCUIT AND DESIGN IDEAS *People monitor & light switch*
- 66 PRACTICAL ELECTRONICS PT.4 *Repairing damaged PC boards*
- 88 BUILD YOUR OWN ROBOT *His name is Algernon*


News and Comment

- 4 NEWS HIGHLIGHTS *Erasable optical discs*
- 14 LETTERS TO THE EDITOR *B-MAC was well planned*
- 15 EDITORIAL *Stop worrying about the electronics industry*
- 72 FORUM *Some rough ideas about video tape*
- 118 INFORMATION CENTRE *Answers to problems*

Departments

- 76 BOOKS AND LITERATURE
- 80 NEW PRODUCTS
- 86 50 AND 25 YEARS AGO
- 116 COMING NEXT MONTH
- 116 EA CROSSWORD PUZZLE
- 121 MARKETPLACE
- 120 NOTES AND ERRATA

Low-cost video fader



Add a touch of professionalism to your home video movies. This simple video fader circuit lets you fade a scene to black (and back again) without loss of picture lock.

What's coming

Next month we intend to describe a radio direction finder. See page 116 for further details.

Carver DTL-100 CD player



This month we review Carver's new DTL-100 CD player with "digital time lens" circuit. Find out how it performs by turning to page 26.

News Highlights



AWA is to supply 260 RT-85 Carphones to the Australian Gas Light Company.

AWA to produce mobile radios locally

Amalgamated Wireless (Australasia) Limited has transferred the manufacture of its RT-85 mobile radios from Japan to its New Zealand company, AWA New Zealand Ltd.

This means that, under CER, the manufacture of the radios is now considered as local, opening the way for additional government contracts to be awarded to AWA.

The VHF-UHF mobile radio is pre-programmable and operator selectable, with 64-channel capacity and a pushbutton digital display control unit with microphone.

The RT-85 Carphone has a wide range of options that can expand the capabilities of the system. Among these are: automatic number identification, selective calling and vehicle to vehicle communication.

AWA has, in fact, recently been awarded a contract to supply the Australian Gas Light Company with 260 RT-85 Carphones for their customer service fleet and the emergency gas maintenance services.

Erasable optical disks are on the way

Impressive advances in optical disk technology were highlighted at the National Computer Conference in Las Vegas last year. This new technology offers 20 times the information density of existing magnetic storage devices at a lower cost per byte.

The technologies for read-only and write-once versions of optical disks are well in hand. What has proved elusive is the formula for an erasable optical disk. One of the leading contenders in this field is Verbatim Corporation who unveiled their new 3½ inch, 40 megabyte (formatted) erasable, removable magneto-optical disk and drive.

Two approaches have been followed in the search for the erasable optical disk; the phase-changing media and the magneto-optical approach. The latter is the basis favoured by the Verbatim Corp and they have a cool \$800,000 staked on their device. It seems appropriate that it was first shown in the city whose name epitomises a gamble.

In magneto-optical recording, the ac-

tive layer of the disk is uniformly magnetised in a direction perpendicular to the plane of the substrate. To write, an electrically modulated laser beam is focused on a 2µm spot of the active layer. The beam raises the temperature only in the spot being irradiated, making the magnetic domains susceptible to reorientation.

A magnetic coil working with the laser can easily reverse the polarity of the domains by applying a bias field of just a few hundred oersteds and allowing it to cool. This typically takes only about a microsecond. To erase a bit, the process is repeated but the field direction is reversed.

The danger of information inadvertently being destroyed is no more likely to occur than with traditional magnetic disks. The sequence of events would have to involve simultaneously applying heat and a magnetic field to the film.

To provide an inexpensive pregrooved disk, two alternatives are being considered by the company. The first is a plas-

tic layer bonded to a glass substrate, but glass is expensive and easily broken.

The second is an injection-moulded plastic substrate impressed with the pregrooved pattern, but this requires an established plant and the use of an expensive sputtering technology.

Verbatim acknowledges that there are still sizeable technical hurdles to overcome. The access time must be made comparable to high-end Winchester technology, slow data-rate transfers must be improved, and an inexpensive alternative to sputtering needs researching.

Wiring AUSSAT

Technicians at STC's Liverpool factory in Sydney are working on a wiring harness for one of the AUSSAT satellites. The harnesses are produced under contract to the Hughes Company of the US and consist of interlinked wiring and electrical components which control the positioning motors and telecommunications equipment. STC wiring harnesses will be built into other satellites currently under contract for Indonesia and the US.

Radar for F/A-18 strike fighter

Australia's new F/A-18 strike fighter will work wonders for the tactical strength of the RAAF and it won't be done with mirrors. It will be performed through the aircraft's radar system.

The tactical radar has five major component parts of which one, the radar data processor (RDP), is being produced by Philips Communications in Sydney. The radar production line at Philips' Moorebank factory is now in full production and employs about 60 people.

The APG-65 incorporates digital technology with full multi-mission capabilities. Advanced radar technology gives it all the necessary features for both air-to-air and air-to-surface missions. The radar provides moving target and fixed target track modes; air-to-surface ranging on designated targets; a terrain avoidance mode for low-level penetration; and a sea-surface mode that adapts its clutter threshold to prevailing sea conditions.

The APG-65 is located in the nose cone of the aircraft. It has its own built in test system which provides a thorough radar checkout prior to operation and continuous monitoring while in use. It can detect 98% of all faults.

Optical fibres will control Sydney Harbour Bridge traffic

The Department of Main Roads has selected Amalgamated Wireless Australasia Limited (AWA) to supply 144 optical fibre lane change indicators for the Sydney Harbour Bridge.

By the time this issue goes to press, the DMR crews, police escorts and rubber lane divider flaps, will be replaced by the programmable easy to read indicators. Costing a total of \$350,000, the indicators will be mounted on eight trusses above the traffic lanes.

Optical fibre traffic indicators are already extensively used in such countries as the UK, France, West Germany, Austria and Singapore.

The advantage of this type of indica-

tor is that it has an unusually high light intensity and is clearly visible at extremely long distances — day and night, in all weather conditions, including Sydney's winter fogs.

The indicator matrix board can accommodate any configuration to produce a symbol, number or word and several different messages can be displayed from the same signal face. The light source comes from quartz halogen lamps with a life of 8000 hours.

Further uses for optical fibres are being researched at AWA and could include traffic control and pedestrian crossing signals.

Columbia modified for re-entry research

Significant changes have been made to NASA's first Space Shuttle orbiter, Columbia, to accommodate three experiments designed to measure orbiter aerodynamic and thermodynamic characteristics.

The most obvious change to Columbia is a cylindrical housing which has replaced the fin top on the vertical tail. The pod contains all the equipment for

the experiments which will be used to obtain high-resolution infrared images of the upper surfaces of Columbia's port wing and fuselage as the orbiter re-enters the atmosphere.

By acquiring data that cannot be adequately simulated in ground tests, NASA will have realistic results on which to base further space transportation developments.

New sonar test facility

Boasting the latest equipment, this advanced underwater sonar test facility for the Department of Defence has been established at the Meadowbank plant of Plessey Australia Pty Ltd.

The \$750,000 test facility, which took 11 months to complete, will be fully operational once the instrumentation is commissioned.

The facility consists of an American Redwood tank 8.7 metres high with a diameter of 7.6 metres, housed in a special building. The tank contains nearly 400,000 litres of water and is mounted on 32 double convoluted air cushions to isolate it from ambient noise.

Plessey is involved in the manufacture of high-sensitivity sonar and sonic equipment for the RAAF and the RAN. This equipment includes the passive Barra sonobuoy and the Mulloka surface ship active sonar.

According to Plessey, the tank will enable the development of improved sensors to keep Australia at the forefront of anti-submarine warfare.

BASF Tape Offer

BASF has advised that their "special tape offer" (EA, November 1985) actually expired at the end of October. The company apologises for any inconvenience this may have caused to readers.




News Highlights

10-inch colour liquid crystal display

Researchers at the Toshiba Corporation have developed a 10-inch colour LCD flat panel — prototype of a device that could be used for future TV displays or home TV receivers. It is an active matrix type LCD with 640 x 480 (307,200) pixels and can display bright, high quality graphic images in up to eight colours.

An active matrix LCD has a transistor at each pixel. This means that the new LCD has 307,200 amorphous-silicon thin film transistors (TFTs). The TFTs function as switches to control each pixel.



The new LCD has a brightness of more than 300 candelas per square metre in white. The picture quality does not deteriorate even under 10,000 lux of lighting and it can display up to eight

colours with two grey scales.

According to Toshiba, the fundamental colours (red, green and blue) are nearly the same as standard colour picture tubes.

Prodigious picture phone potential

Business users are to be the first target for the long awaited launch of the picture phone. Technological trends have finally made this much fabled device a realistic prospect. The ability to send digitally encoded TV signals over relatively low-cost 56kb/s telephone lines (in the US), will give a picture capability to the desk-top picture phone.

Some of the more excited proponents of the device contend that the falling price of the electronic hardware could put this type of telephone into the home, in less than a decade.

One of the trends that is boosting the current enthusiasm for the system is the availability of the switched 56kb/s service. AT&T have a planned 34 cities tied to the network and they hope to add 36 more next year. Other companies such as Argo Communications Corp., New Rochelle and also local telephone companies are seeking the new digital service, thus opening the work even further.

The development of the dial-up 56kb/s service has sparked a race to see who can get the best video codec on the market. These devices are all important if full motion picture telephony is wanted. The key to the device lies in the algorithm which compresses the 4.2MHz video output signal from a camera down

to a 56kb/s digital signal for transmission. In Europe the digital subscriber connections are made at 64kb/s.

A number of companies have come up with systems that include colour monitors, built-in cameras and their own codecs. Some are even offering a local area network to allow multiple phones to share the codec. Others don't believe it will ever take off and are sticking to freeze-framed teleconferencing; which can be transmitted over regular voice-grade phone lines and is certainly much cheaper.

Work on the algorithms being developed by each firm, with an interest in the field, means that in the US there will have to be multiple standards to accommodate each of the companies preferred methods. However the International Telegraph and Telephone Consultative Committee (CCITT) is attempting to produce one standard.

Trouble for those abusing the airwaves

The Department of Communications has been making an effort to curb interference on the airwaves. The account of a recent court action in Adelaide is an indication of the penalties that can be imposed as a result of illegal use of radio equipment or licence breaches.

A south Australian man made the Adelaide CB radio repeater useless for

operation by hundreds of other licensees and was fined the maximum of \$40, with his \$300 transceiver also being confiscated.

Evidence showed that departmental officers traced the man to a site at Mount Gawler where he was found to be making what the Department considered to be unnecessary and unauthorised transmissions on the Adelaide CB radio repeater. In addition to the penalties listed, the defendant was ordered to pay \$17 court costs and \$150 towards the Department's investigation costs.

US-Japan trade war

Citing the Trade Act of 1974, the US Semiconductor Industry Association (SIA) recently filed a complaint with the Office of the US Trade Representative against the Japanese. The complaint alleges unfair trade practices by the Japanese electronics industry and restrictive governmental policies which have limited US chip sales to 10% of the Japanese market.

According to the complaint, the Japanese have relegated American semiconductor manufacturers to the position of "residual suppliers" by only buying from one another rather than on the basis of competitive merit. The SIA is demanding negotiations with the Japanese Government to prevent chip dumping in the US and has called for retaliation if no solution can be found.

Portable voltage standard

Commercial production of an electronic DC voltage transfer standard instrument is the outcome of an 18-month joint project involving CSIRO and Sta-tronics Power Supplies of Sydney.

The device was developed as a replacement for the conventional electrochemical standard cell group. Although electrochemical standard cells have served the international measurement community well, they are no longer readily available. They are also difficult to maintain and transport, and are sensitive to mechanical shock, vibration, temperature change and electrical loading.

This solid-state voltage reference is much more robust, an important consideration when it comes to transferring voltage from one laboratory to another over large distances.

One of the annoying difficulties with

standard cells is that their voltages can be temporarily affected by extremely small charging or discharging currents.

The beauty of an electronic reference is that it can be designed to be completely immune from such loading effects.

The project has resulted in a 6kg device with four 10V and four 1.0186V outputs which are virtually independent of temperature and which are not invalidated by an inadvertent short circuit.

The annual drift of each output is within 3ppm. The instrument has a maximum power rating of 15W and operates within a 20% range of both 240 and 120V at 45-60Hz. Internal standby battery power is provided to ensure 24 hour operation.

The V84 carries a five year warranty and costs \$5820 including initial certification records.

New company backs inventions

A new company, Engineering Innovation Ltd, has been formed to bring Australian engineering inventions to commercial production. The company is jointly owned by McPherson's Ltd and the Australian Industry Development Corporation.

McPherson's and the AIDC will provide funds of up to \$3 million to the venture over the first three years. Further funding would be based on the venture's progress and requirements.

The company plans to work with CSIRO, university and government research laboratories, as well as with private inventors. It has established an office at 6 Buckhurst Street, South Melbourne and is actively seeking products for development.

Your car could stop dead!

Automotive engineers face a continuing design challenge as the electronic content of the car increases. The problem is to prevent critical and not so-critical systems from being zapped by electromagnetic interference (EMI).

For example, improperly installed cellular radio telephones have been a recent headache. A cellular system that is not properly grounded can set up ground or current loops running through the chassis. Some cars have actually stopped due to ignition failure.

EMI generated by radio and TV broadcast stations, mobile radio transmitters and fixed radar installations may also cause problems. They could, for example, interfere with vehicle-control systems in nearby cars, creating potentially dangerous situations.

A number of solutions can be employed to prevent interference, including filtered connectors, shielding, and the future development of fibre-optics systems which are substantially EMI-immune.

Australian company in new non-volatile RAM process

Newtech Development Corp Ltd, an Australian company, has secured the rights to a revolutionary new non-volatile RAM device known as Rampac. Developed by the University of Colorado at Colorado Springs, the new electrically erasable programmable read-only memory (EEPROM) uses a thin ferro-electric layer (potassium nitrate) over silicon to give the non-volatile properties.

The biggest market potential is seen as being in the automotive field. So much so, that the company is reported to be on the verge of signing a licensing agreement with General Motors, for aerospace and automotive applications.

\$30 OFF!

Special End of Year Offer

Offer closes 31.1.86

FLUKE 80TK CONVERTS YOUR DIGITAL MULTIMETER INTO A K-TYPE THERMOCOUPLE THERMOMETER

80TK SPECIFICATIONS

Temperature Measurement Range
-50 to +1000°C
-58 to 1832°F
Battery Life 1600 Hours (9V)



Treat yourself to a new Fluke Digital Multimeter and you can have the 80TK Thermocouple Adaptor for just \$69 (ex tax) or \$81.40 (inc tax) - a saving of \$30 on the recommended price!

The 80TK plugs into any Fluke DMM to give accurate temperature measurements from -50° to +1000°C using a K type bead thermocouple (included). Micro-connector or screw terminals accept a wide range of Fluke or other probes. Measures in °C and °F

See the 80TK and the complete Fluke Multimeter range at participating distributors.

Offer not available in States or Territories where it contravenes applicable laws

ELMEASCO

Instruments Pty. Ltd.

NEW SOUTH WALES	VICTORIA	QUEENSLAND
15 McDonald Street, MORTLAKE P.O. Box 30, CONCORD NSW 2137 Tel: (02) 736 2868 Telex AA25887	12 Maroonah Highway, RINGWOOD P.O. Box 623, RINGWOOD VIC 3134 Tel: (03) 879 2322 Telex AA30418 ELTENT	Tel: (07) 369 8688 S. AUSTRALIA Tel: (08) 344 9000 W. AUSTRALIA Tel: (09) 481 1500

Sony's new 8mm video camcorder

Recently released in Australia, Sony's new CCD-V8 8mm video camcorder (camera/recorder) is a pointer to the shape of things to come. Technically, it is soundly based; commercially, it remains to be seen whether it will signal the beginning of a major worldwide shift towards the new, more compact format.

by NEVILLE WILLIAMS

Most readers will be aware, by now, of the new international 8mm video standard, destined for adoption as and when the existing 12.65mm (half-inch) formats — VHS, Beta and V-2000 — cease to be commercially viable.

Some years ago, in the face of market confusion over the multiplicity of formats, standards and speeds, video manufacturers realised that, if at all possible, they had to avoid a repetition of

the situation. Discussions to that end began in 1980, culminating, in February '85, in ratification by 127 companies of a new international standard 8mm format.

The new format is not based on way-out technology but it does incorporate the most desirable and proven features of existing systems, with the present exception of 6-8 hours playing time.

Sony describes it as "evolutionary rather than revolutionary".

Using a cassette of about the same dimensions as a compact audio cassette, its most obvious attraction is the potential reduction in the size and weight of the associated hardware. This is especially true of portable video camcorders and Sony apparently see them as the most promising point of market penetration for the new format, with the present as the appropriate time to make their move.

In fact, Sony are not the first in the field. Sensing a crisis ahead for 8mm photographic home movies, Kodak announced their plan to market 8mm video in early '84, using hardware manufactured by Matsushita (National) and tape by TDK. Polaroid followed with a similar announcement, naming Toshiba as their principle suppliers.

However, neither Kodak nor Polaroid appear to have ventured beyond their immediate NTSC marketing area, leaving Sony as the true pioneer in the overall electronics marketplace — PAL/SECAM as well as NTSC.

To grab a viable market share is not going to be easy for Sony, in the face of stiff competition from the solidly entrenched VHS system offering VHS-C, VHS Movie from their own Betamovie, and highly specified separate cameras — with new high-tech models just around the corner.

So much for the background; now for a look at the new product:

What you get:

The version supplied for the Australian 240V PAL market is designated as the CCD-V8AS. (We refer to it elsewhere simply as CCD-V8). "CCD" indicates the use of a solid-state charge coupled device in lieu of the usual thermionic camera tube; but more about that later.

The basic camcorder comes, well packaged, in a heavy cardboard carton, complete with supplied accessories: shoulder strap; a 1-hour rechargeable battery pack; a mains power pack cum battery charger; a charger/adaptor to accommodate up to 3 batteries; RF converter, splitter and "antenna" cables to connect to a TV receiver or VCR; a P5-30 metal particle tape for 30-minute recording and playback (or 60 minutes in



From the front, the CCD-V8 looks much like any other modern domestic video camera, except that it is completely self-contained. Unlike Betamovie, it contains full in-built playback facilities.



Apart from the Record State and Telephoto buttons, other controls necessary for picture taking are operated by the fingers of the left hand, as it simultaneously steadies the front of the camera.

LP mode).

While the original packaging could be used initially for in-car transport, a hard-shell LC-V801 carrying case is available, as an optional extra, to accommodate the CCD-V8, along with the standard accessories. This, and a variety of other optional extras should be available by the time you receive this issue.

The basic CCD-V8 measures 117(W) × 193(H) × 344(D)mm with viewfinder folded and weighs 2.3kg, including battery and cassette. It is normally used, resting on the right shoulder and further supported by an adjustable right-hand grip with built-in stop/start and telephoto drive buttons. A supplementary shoulder brace attachment is available, if required.

Viewfinder, lens

Unlike Betamovie, the CCD-V8 has an electronic viewfinder using a quick-heating 25mm (dia) B&W tube, which can be viewed directly or through an adjustable-focus lift-up eyepiece. The viewfinder assembly can be extended, for convenient viewing through either eye, or used in a variety of positions, even detached from the camera, when working from a tripod.

Important also is the fact that it can be used for on-the-spot picture search, review and editing.

Associated with the viewfinder are yellow, red and orange indicators, for low light, tape run/low battery, and white balance.

A rigid slip-off cover protects the front of the camera, involving the lens system and microphone. It can be left in place when the record/replay unit is being used with the camera inoperative.

The lens is a manual focus Sonoptor 6X power zoom, f12-72, F1.4 (1.8 telephoto) with macro facility. Filter diameter is 46mm, with a filter kit

available as an optional extra. At the front of the lens is a removeable, flexible hood, which also accommodates an opaque white-reference filter.

Just above and behind it is a unidirectional electret microphone, readily removeable to permit the substitution of an external unit.

Camera controls

With the left hand steadying the camera, the fingers fall naturally on a number of supplementary controls, relevant to video photography:

- A Camera Power switch which actuates the camera and places the recorder in standby record mode — doubly effective because the CCD is ready for immediate use at switch-on.
- A 3-position switch providing for incandescent lighting (3200K), natural sunlight (5800K) and automatic white balance.
- A 3-position switch providing for normal lighting, back lighting, and strong highlights.
- A "Rec Review" button which automatically replays the last few seconds of the previous recording and readies the camera for the next shot.

When the equipment is in camera record mode, using these controls, they automatically assume priority over the push buttons on the rear of the unit.

Record/replay functions

These controls come into their own when the CCD-V8 is placed flat on a shelf alongside a TV receiver or colour monitor for viewing the tapes. Better than that, the literature shows an optional viewing tray which allows the CCD-V8 to be combined with a power supply and tuner/timer to form a complete video deck.

However presented, the push-button controls are reminiscent of those on separate portable recorders: Power on/off; Eject; Fast forward, Play, Rewind, Stop, Pause, Record.

The tape count plus other information appears in an LCD display window, controlled by Reset and Memory buttons. Also on the panel is an Insert button to facilitate the insertion of titles, &c, a standard/long-play switch, and sockets for a cord remote controller and earpiece.

A 24-pin multiway socket on the right-hand side provides access for the RF output adaptor and/or other possible external fitments — again reminiscent of separate portable decks.

Off-air recording

As much as anything to gain familiarity with the CCD-V8, we set it up initially for off-air recording and replay. In the absence of a companion tuner at the time, this involved interconnecting it with an existing conventional VCR via the respective video and audio input and output sockets, as detailed in the User Manual. (Extra cables are required to do this.)

Unlike the earlier Betamovie, the CCD-V8 processes the signal internally in the standard CCIR/PAL format so that it can operate in conjunction with other PAL-standard equipment — tuner, VCR, receiver or monitor.

Interconnection involves the RFU-85

BRIEF SPECIFICATIONS

Video system	Rotary, two heads, plus erase
Audio system	FM, two rotary heads
Tape speed (mm/sec)	SP:20.051 LP:10.058
Record/play time (mins)	SP:90 LP:180
Fast forward time (mins)	3 (approx.)
Lens	6X power zoom; f = 12-72 F1.4-1.8; macro; 46mm
Colour temp	(1) 5800K; (2) 3200K; (3) auto
Illumination range	22-100,000 lux
Operating temperature	0-40 degree C
Dimensions (approx.)	117 x 193 x 344mm (w/h/d)
Weight (including battery and cassette)	2.3kg
Power sources	rechargeable battery, battery belt, mains adaptor, 12V DC supply adaptor

Sony's new 8mm video camcorder

adaptor (supplied) which plugs into the 24-pin connector mentioned earlier. It carries four RCA sockets for video and audio in and out, plus an antenna style socket for RF out (channels 0-1 selectable on the Australian model). A small switch serves to set the video/audio carrier separation to the normal 5.5MHz ("I" position) or 6.5MHz ("G").

Our first reaction to the RFU-85 was that, for a unit providing the anchor point for several cables, it should lock more firmly into position. In practice, however, it and the cables are likely to be attached more or less permanently to the fixed equipment and simply plugged into the CCD-V8 as necessary.

Using the existing VCR as a tuner (the format is immaterial) we fed a selection of program material and test patterns to the CCD-V8 as direct video and audio, recording it first in standard play (SP) mode and then in the long play (LP) position.

For all practical purposes, in standard play mode, the on-screen program material was indistinguishable from the original or from a similar recording from the standard VCR. Put another way, any differences in the picture quality from the respective sources were less noticeable than variations in the program material itself.

In long play mode, the video noise level was obviously higher, but the picture was still entirely watchable. Interestingly, however, the sound quality remained virtually unchanged at the lower tape speed, due to the fact that, in the CCD-V8, sound is recorded as an FM multiplex component in the video tracks and is not greatly affected by the linear tape speed.

Future potential

In short, while our observations were entirely subjective, they confirmed that, in addition to its size advantage, the format has the capacity to take over from VHS and Beta HiFi in terms of both picture and sound quality.

Playing time for movie length recordings still poses something of a problem, however, involving either some loss in picture quality (in LP mode) or else the ultimate development of longer playing or super quality tape.

We used a 30/60 minute cassette, but 60/120 and 90/180 cassettes (in PAL mode) are due on the market about the time this article is published.

Incidentally, like the Philips V-2000 system, the 8mm format assumes the use of dynamically mounted heads,

obviating the need for a control track on the tape or a manual tracking control on the panel.

Consistent with this, the CCD-V8 uses automatic track following but, with its basic 2-head drum, it does not include provision for viewing noise-free pictures in Pause, Review or Cue mode. Images in the viewfinder allow scenes to be identified for purposes of cueing and editing in the field but they are traversed by noise bars which can become proportionately more intrusive on a large screen.

That aside, there is no reason at all why a CCD-V8 should not fill a dual role in the home: (1) for the production of home video movies and (2) as a back-up VCR for those special occasions when one wants to catch three programs at the one time! How the CCD-V8 can be used in this way is explained in the Manual.

In camera mode

As mentioned earlier, the CCD-V8 uses a solid-state CCD image sensor rather than a camera tube. It saves space, weight and battery drain, provides excellent resolution and sensitivity (22-100,000 lux), avoids screen burn and flare, and is substantially free from "microphonic" image jitter. It is also ready for instant use at switch-on.

Perhaps it is confidence in the CCD that prompts Sony, in the manual, to

instruct the user — without coyness — to place the opaque filter over the lens and point it directly at the Sun or other light source, in order to set the automatic white balance. It is quick and effective and, along with the automatic iris, provides even, well balanced pictures under a wide variety of light conditions.

Specifications and focussing provisions are broadly similar to other video cameras, and pose similar problems as to how to get by with two hands and one brain, when you could really do with an extra one of each! Sony have done their best to rationalise the controls, even to providing a roughened prominence on which to rest that errant right thumb, instead of (inadvertently) on the "Record" button!

Automatic focus would be of considerable assistance but it is still apparently a difficult option to provide in an ultra-compact camera recorder. So one has to rely on familiarity and practice, or else on more frequent resort to a tripod or the VCT-3 Handy Stand for hands-off recording — items listed as optional extras.

When the user is able, with practice, to string together a sequence of acceptable shots, he/she will discover that the CCD-V8 has managed to merge them without noise breaks or other ugly effects. In itself, that's not unique but Sony technology and the new 8mm format provides frame by frame ("flying") erase, achieving more precise juxtaposition of scenes.

In testing the camera, I simply walked around the house and garden, taking



When placed flat on a shelf or in its adaptor tray for playback &c, the CCD-V8 takes on the appearance of a portable deck, with the usual array of user controls. Add a timer/tuner and it becomes a complete VCR.

at the leading edge

100 MBYTE OPTICAL DISK DRIVE MAKES AUSTRALIAN DEBUT

US manufacturer, **ISI**, has commenced shipments of its model **525 IBM-PC** compatible **Write-Once/Read-Mostly** drive. Supplied as a **user installable kit**, the 525 is designed as a rapid access (**100 msec**) archiving and distribution medium for backing up hard disk drives as well as an Online Direct-Access storage for local and distributed databases. The removable cartridge will withstand electromagnetic fields, heat, light and even scratching offering a data integrity exceeding that of the Winchester drive it is designed to back up.

SOFTWARE BACKUP UTILITY ELIMINATES NEED FOR TAPE DRIVES

FASTBACK can back up a full **10 MByte** hard disk on 5.25" floppies in less than 8 minutes on an IBM-PC, XT or compatibles or **20 MByte** in the same time on an **IBM-AT**.

FASTBACK can make either partial or incremental backups or restores with full disk management, sequencing, dating and overwrite protection.

PRIAM RELAUNCHES ITS 14 inch DRIVE SERIES

Following an upsurge in demand for their **6650-10** Winchesters, with **SMART**, **SMD** or **Priam** interface, predictions indicate a record year for the line. Users are citing years of reliable service for the pioneer design a feat some users are claiming is not matched by more recent introductions. Daneva is preparing to restock the old trouser and would like to hear from Australian vendors needing support.

PRIAM CLUSTER TOWER SERVES UP TO 8 IBM PC COMPATIBLES

Designed as a starter for those nearly at the stage of purchasing a local area network, but confused by the array of options, the **Cluster Tower** provides immediate shared storage up to **292 MByte** and dual, concurrent **printer support**. At the same time it is designed to suit any **DOS compatible LAN** purchased in the future.

IBM-PC XT is the registered trade mark of International Business Machines.



daneva australia pty ltd

66 Bay Rd. Sandringham, Vic. 3191
P O Box 114, Sandringham, Vic. 3191
Telephone 598-5622 Telex: AA34439
Suite 28, 47 Falcon Street
Crows Nest, NSW 2065
Telephone 957-2464 Telex: AA20801

Distributors

Adelaide: DC Electronics (08) 223-6946
Brisbane: Baltec (07) 369-5900


If you're into computers you could have a job for life.

If you're interested in the finer points of digital electronics and computers, the computer industry needs you.

Enrol now into Control Data Institute's Computer Engineering course and you could be working in the ever-expanding computer industry in as little as 8 months.

Control Data Institute's flexible study programmes will allow you to study full-time or part-time in subjects such as **Electronics, Microprocessors, Mini Computers, Data Communication, Terminals, Disk Drives, Line Printers and Machine Language Programming.** Or if you choose, you can study individual subjects.

You can even get exemptions if you have some experience in the electronics field. And at the end of your



course of study, you qualify with a Diploma in Computer Engineering.

Control Data is accepting enrolments now for their Computer Engineering courses in Sydney and Melbourne. The demand for Control Data Engineering Graduates has never been higher.

For further information call Control Data Institute now. You can attend special monthly free engineering information seminars or phone Wendy Mason in Sydney on (02) 438 1300 or Sherrill Maconachie in Melbourne on (03) 268 9666 for a personal appointment.

CD CONTROL DATA INSTITUTE

YOUR CAREER BEGINS HERE

An education service of Control Data Australia Pty. Limited.

Burrows Doble Lawrence CDA 1640

Master the Microprocessor

Learn how Microprocessors really work ... the practical way.

The Purpose of this Course

There is a considerable, expanding and world-wide demand for people with a real knowledge of microprocessors and general computer technology. Such people are needed to design and evaluate systems and to assess and develop the enormous range of possible applications, both present and future, of microprocessors and to understand the installation and servicing of the main types of equipment of which they may form the most vital component.

(A microcomputer has already been produced to replace the mechanical programmer on a domestic washing machine, for example.)

This Course provides the necessary basic information to enable a student to really understand the functioning of microprocessors and their supporting circuitry,

usually referred to as the "hardware". This is backed up by showing how to program a microcomputer (or produce its "software") in the most fundamental form of computer language called "machine code". No previous knowledge of computers is necessary, though a little basic knowledge of electronics plus digital and logic circuits will be found helpful.

A special introductory short course is available to provide this back-ground information, if required by an individual student on the course without extra fee.

Student—Tutor Contact

A qualified Tutor is available to every Student throughout this Course in order to deal with any queries which may arise and to assess certain questionnaires which are issued to Students throughout the period of training.

Certificate

Issued to all Students completing the Course successfully. Course covers main requirements of the City and Guilds Certificates in Computers.

Practical Self Study Course

FREE COLOUR BROCHURE

Post coupon now: The Australian School of Electronics Pty. Ltd., P.O. Box 108, Glen Iris, Victoria 3146. Offices at: 120 Hawthorn Rd., Caulfield North.

Please send your brochure without any obligation to:

Name

Address

EA/186

Postcode



How the Course is organised

The basis for the practical work in the Course is the Microcomputer.

This is supplied completely assembled and ready to use.

The Course text is carefully arranged in sequence so that each new section follows logically from previous work. Hardware description and programming technique progress together, so that the Student is discouraged from treating them as distinctly separate subjects.

Following each section of descriptive text, detailed instructions are given in order to use the Microcomputer to provide a practical demonstration of each new function or technique. This provides a very powerful way of learning precisely how the system operates, and enables any possible ambiguities in the Student's mind to be quickly resolved.

Sony's new 8mm video camcorder

numerous independent shots, long distance, close-up and even macro, under a variety of lighting conditions, of flowers and whatnots of every imaginable hue. In between shots, the camera was left sometimes in Pause mode, at other times switched off altogether.

When replayed at the end of the day, the shots were pleasingly consistent in general colour balance, with no obvious missing hues. The pale purples had not washed out to white and there was no mistaking the pink of a *Queen Elizabeth* rose. The greens were all there from the grey-green of the eucalypts to the many hues of a mirror plant.

Overall, my impression was that the CCD image sensor offered results as good, if not better, than its thermionic contemporaries, along with its obvious mechanical and functional advantages.

Inserting, dubbing

As mentioned earlier, the CCD-V8 has an Insert Function, which allows a title, a replacement scene or video/audio from another source to be substituted for an unwanted scene on the tape.

The end of the unwanted segment is located by playback through the viewfinder and pinpointed by pushing the Memory button and setting the counter to 0000. The start of the segment is then located and pinpointed by pushing the "Insert" button, which changes the mode to Record/Pause ready for the new material.

On pressing the Pause or Start button, new incoming video and audio is substituted, without "glitches", between the "Insert" and "0000" points on the tape.

Completed tapes can be replayed directly from the CCD-V8 into a TV receiver or monitor, or readily copied on to tapes of another format by connecting it to a second VCR, preferably at direct video and audio level. Indeed, we were pleasantly surprised at how good such copies turned out.

Incidentally, the CCD-V8 senses whether individual scenes have been shot in SP or LP mode and switches automatically from one to the other during replay, with scarcely a flicker on the screen.

Sound recording

At about 2cm/sec, the linear tape speed of the 8mm format is even less than that of the audio microcassette (2.4cm/sec), falling to 1cm/sec in LP mode. Not only is this too slow for

satisfactory analog audio recording but very thin layer tapes also present a problem.

Recognising these limitations, the 8mm standard specifies the use of an FM sound channel, frequency multiplexed with the video signal, much like the original Beta NTSC hifi system. However, it also reserves space along the respective edges of the tape for possible linear audio and cue tracks, but lists them as optional.

The CCD-V8 provides only for simultaneous mono FM sound recording multiplexed with the video track and there is therefore no way, using the CCD-V8 alone, that a new audio track can be added to an existing video recording.

At first glance, this appears to be a major disadvantage for the amateur video photographer, because he/she would have to provide a spontaneous on-the-spot commentary while, at the same time, composing the picture — a rather tall order.

Experience with the CCD-V8, however, suggests a different approach, rather than an impasse. Thanks to the FM recording system, high quality actuality sound is preserved, along with the picture — evidence, in our case, by the pleasant chirping of birds as we toured the garden.

Such actuality sound would always be available for live presentation of the tape, or for mixing into a rehearsed commentary, where the recording is to be dubbed to another format.

Sony Australia further suggest that full-size domestic 8mm decks will probably carry facilities for adding an extra soundtrack using, not analog, but PCM technology, as envisaged in the standard. Time multiplexed with the video signal, PCM would store a "packet" of audio samples just ahead of the video field information (therefore along the edge of the tape) to be decoded and reassembled during replay.

This aspect of the format would obviously need to be looked into before making a final decision but we would be surprised if the industry in general, and Sony in particular, have not planned adequately for post audio dubbing.

That aside, we were impressed with the CCD-V8 and think that it deserves to do well in the market place.

The basic CCD-V8AS is available now through Sony outlets at \$2199 RRP, and a comprehensive range of accessories should also be on hand by the time you read this. (W.N.W.)

FLUKE 70 SERIES LOW COST ANALOG/DIGITAL MULTIMETERS —



YOUR FIRST CHOICE FOR FEATURES, QUALITY & VALUE

FLUKE 73	FLUKE 75	FLUKE 77
Analog/digital display	Analog/digital display	Analog/digital display
Volts, ohms, 10A, diode test	Volts, ohms, 10A, mA, diode test	Volts, ohms, 10A, mA, diode test
Audible continuity	Audible continuity	Audible continuity
0.7% basic dc accuracy	Autorange/range hold	"Touch Hold" function
2000+ hour battery life	0.5% basic dc accuracy	Autorange/range hold
3-year warranty	2000+ hour battery life	0.3% basic dc accuracy
	3-year warranty	2000+ hour battery life
		3-year warranty
		Multipurpose holster

FROM THE WORLD LEADER
IN DIGITAL MULTIMETERS.



See the 70 Series at leading electronics stores
or contact us for data

ELMEASCO Instruments Pty. Ltd.

NEW SOUTH WALES	VICTORIA	QUEENSLAND
15 McDonald Street, MORTLAKE P.O. Box 30, CONCORD NSW 2137 Tel (02) 736 2888 Telex AA25887	12 Maroonah Highway, RINGWOOD P.O. Box 623, RINGWOOD VIC 3134 Tel (03) 879 2322 Telex AA30418 ELTENT	Tel (07) 369 8688 S AUSTRALIA Tel (08) 344 9000 W AUSTRALIA Tel (09) 481 1500



Letters to the editor

Aussat: bulldust & flies

Through your magazine I would like to point out that due to the development of the AUSSAT domestic satellite service there has been generated a flurry of activity within the electronic industry, in the form of advertising/claims through trade journals, printed media and catalogues.

This activity has also resulted in a number of "fly by niters" emerging from the 4GHz market.

These facts are based on my actual observations and hands on experience.

Therefore, intending dealers/purchasers should obtain in writing a guarantee or similar of warranty cover, after sales service, spare parts back-up and professional installation should this be required.

The operators mainly originate from the capital cities and have no idea what weather conditions can do to electronic equipment.

Remember the Top End of Australia is a rugged place to test electronic equipment. Temperatures range from 0°C to 60°C in the direct sun, and the

wet bulb thermometer pops its cork in the wet season.

In the Centre you have to cope with the bulldust and flies, not to mention the spiders that build nests in the scalar feed assembly.

Severe lightning strikes have knocked out more than one T.V.R.O. installation. And of course there is the usual human abuse to receiving dishes, screens and active components. For example TV transmitters and baseband receivers, together with down converters and L.N.A in remote communities are often pelted with rocks etc. by the children there.

When one drives 700 miles then flies 300 miles to repair this equipment, they are certainly very grateful that it is in operation for their football matches.

The moral to this is that without the crucial back-up service, these operators could end up being hunted off the site, literally.

P.S. The advice issued from time to time by D.O.C. is a sound guide line and very informative.

**Andrew Sutherland,
VK9KAS 8RWB,
Spinafex Electronics,
Tennant Creek, NT.**

B-MAC well-planned and researched

The letter published in your November issue from Garry Crapp of Dick Smith Electronics regarding the cost of HACBSS earth stations and the B-MAC transmission system reveals a surprising lack of comprehension of modern technology. Mr Crapp also, I note, has got his prices wrong.

HACBSS homestead earth stations are currently being marketed by distributors for around \$2300, plus delivery and installation (although these may be installed by the buyer). Dick Smith Electronics has been marketing PAL satellite receiver components for around \$3600, this equipment for use with the Intelsat IVA satellite.

The Department has widely published warnings to earth station buyers about the equipment needed to receive HACBSS broadcasts via AUSSAT satellites.

It is most important that intending purchasers of earth stations are aware that equipment capable of receiving signals from the Intelsat IVA satellite (transmitting on the 4GHz band) is quite incompatible with AUSSAT (broadcasting on the 12GHz band).

They should also be aware that ABC broadcasts via Intelsat IVA are to cease on 18th December, and that satellite is expected to cease functioning in February 1986. It is probable that other television transmissions currently received in Australia via IVA will cease when

Audible distortion on strings

With reference to your discussions in the August 1985 and other issues of EA on audible distortion in "live" instruments (particularly strings), I have some points to make which may be of interest.

Taking the violin as an example, sound is produced by drawing a horse hair bow dusted with rosin across a metal/gut string suspended by a resonating box. This system is far from perfect — non linearities being present at every step. Imperfect distribution of rosin on the bow causes uneven "sounding" of the string. The string itself is constructed of a length of gut wound on metal wire (usually nickel). Most violin

strings are machine wound.

No string is perfect either in consistency of the gut or in perfectly even wiring. As a consequence of this, both mass and compliance vary down the length of the string. When the string is set vibrating, it vibrates in a number of modes (represented "sonically" by a fundamental and a number of partials). Because of the uneven mass and compliance distribution, the higher numbered modes are not exactly harmonically related to the fundamental.

A performer may go through several strings before he/she finds a pleasing combination. The resonator to which the string is fixed is set into sympathetic vibration. It also vibrates in a number of modes, though not at all harmonically related.

The amount that each mode is excited depends on the vibration modes of the string(s). These resonator modes are of course dependant on the construction of the instruments and the wood itself. It is for these reasons that no two instruments sound exactly alike.

It is bad enough considering just the one instrument. When a number of them combine, it is a wonder that the final result is in any way musical. If a number of violins were to play the same note, at least one player would be slightly off note, creating a "beat" in the fundamental. When a note is played on one string, sympathetic vibrations are set up in other strings. It would be almost impossible for every string on every instrument to be perfectly in tune.

The previously mentioned string par-

the satellite "dies", because future Intelsat satellite television services will be transmitted in beams not receivable in Australia.

Mr Crapp is also taking a "television only" view of the satellite broadcasting. He ignores the Department's intensive research in the planning stages of AUS-SAT which revealed that residents of remote Australia considered the reception of radio services to be at least as important as reception of television.

B-MAC, as the article in September 1985 by Neville Williams explained in detail, is capable of transmitting one television and six audio channels (two for television, up to four for radio), as well as Teletext and data. HACBSS will provide two such signals, one to be used by the ABC and the other by commercial licencees in four separate zones of Australia.

Certainly this new technology requires new reception equipment, and considerable resources have gone into planning and developing the MAC system, which is currently being considered as an international satellite transmission standard.

It is sad that those with vested interests in "traditional" equipment should be actively seeking to disparage efforts to bring radio and television services to outback people, many of whom do not receive any such services or have to put up with very poor quality reception.

**R. B. Lansdown, Secretary,
Department of Communications,
Canberra.**

tial vibrational modes, being different for every string, would also beat from one instrument to another. Ditto the sympathetic vibrations of each resonator. On top of this, each player will use a slightly different vibrato technique. One might expect the final result to sound more like a swarm of bees.


Wind instruments are relatively free of these problems — a column of air has more consistent mass and compliance. Consequently, relatively large changes have to be made to the construction of an instrument to cause a significant change to the produced sound.

I hope these points have been of interest.

**A. L. Jones,
Lane Cove, NSW.**

Editorial Viewpoint

by Leo Simpson



Don't worry about the electronics industry

Over the last few months there has been quite a lot of soul-searching in the media concerning the fate of Australia's electronics industry. This has been triggered by the closure of the Rank plant in Sydney which was assembling colour TV sets, microwave ovens and major whitegoods appliances. From that single event there have been forecasts of gloom: no Australian electronics industry at all in a few years time; we'll all be ruined and so on.

Before concluding that Australia's electronics industry is on the ropes it is wise to consider what was the basis for growth of the electronics industry in the past. The first point to consider is that if it had not been for the existence of high import tariffs in the fifties and sixties and the advent of television, first black and white, and then colour, it is unlikely that we would have had much of an electronics industry at all.


Television was a wonderful opportunity for our budding electronics industry. Originally based on valves, and using point-to-point wiring (this was before printed circuit boards arrived on the scene), the manufacture of television sets employed lots of people and the industry had a boom time for quite a few years satisfying a wide-open market.

Today all that has changed. The market is saturated, with many households having two or three colour sets. The sets rarely require service and far fewer people are needed to make sets for what is now a replacement market.

So even without the removal of tariff protection, there was bound to be a great reduction in the number of people employed in making television sets. The removal of tariff protection in 1975 merely accelerated the process. The United States and virtually every country in Europe has experienced a similar scenario, with intense competition from the Asian countries.

So we cannot rely on the consumer electronics market to provide the level of employment that it did in the past. In reality, there is quite a lot of electronic equipment being manufactured in Australia although none of it is intended for the home consumer. Nor is it necessarily being made by the companies which were big in the consumer electronics market years ago.

These days the typical Australian electronics manufacturer is likely to be a relatively small concern and the product is likely to be related in some way to computer technology, possibly for export. There are a few large companies which are happy exceptions to this. They still employ considerable numbers of people and generate a lot of export income.

Some small measure of this can be gathered from the existence of companies such as Printronics. We told the story of this company in our September 1985 issue. This large company exists solely to supply large numbers of double-sided and multi-layer printed circuit boards to the local electronics industry. If the Australian electronics industry was on the ropes, companies such as Printronics and its competitors could not exist. 

The end of an era:

Sydney's last DC power main switched off

by NEVILLE WILLIAMS

Recently, the Sydney County Council turned off the last remaining DC power main, serving Sydney's central business area. The supply had been maintained for just over 81 years but its ultimate phasing out came a neat century after the historic AC/DC confrontation in the USA between the competing interests of Westinghouse and Edison.

Nowadays, because of greater overall economy and versatility, the vast majority of domestic supply mains throughout the world provide consumers with alternating current (AC). The nominal RMS voltage and frequency per phase is most commonly either 117V at 60Hz (American continent, Japan, Taiwan, parts of Asia & Africa) or 240V at 50Hz (Europe, Australia, NZ, Oceania, parts of Asia, Africa).

However, while what was once known as "alternate" current dates back to the original rotating electric generators, it hasn't always been in such a dominant position. This would have been evident to anyone who followed the series of articles in EA from September to November '83, entitled "The inventive genius of Nikola Tesla". As indicated, DC gained a strong lead in the 1890's, before people like Tesla and Westinghouse intervened.

Destined to become a leading proponent of AC technology, Tesla was still a relatively unknown European student/engineer when, in 1879, the American inventor, Thomas Alva Edison, created a whole new scenario with the first

really viable incandescent light bulb, using a carbonised filament.

The basic idea was also being investigated by Swan and others in the UK but, with access to better facilities, including vacuum and de-gassing equipment, Edison was able to work his way systematically through cotton, jute, bast, manilla and hemp fibres, before finally settling on bamboo threads as the most suitable source material for carbon filaments.

Electric lighting would no longer be dependent on the optically harsh and temperamental arc.

Realising that incandescent lamps could open the way to a share of the highly profitable lighting market, currently dominated by the gas industry, Edison immediately turned his attention to the ways and means of generating and distributing electricity to power them.

In September, 1882, he opened the Pearl Street (New York) steam driven power station, with 59 household subscribers, providing them with a 110V DC supply — the first of many such systems to be installed in major American cities.



This view shows the main DC sub-station in Clarence Street as it existed during the 1930s.

Renewed interest in AC

In the meantime, however, the Croatian-born Nikola Tesla had been patiently expanding the concept of AC-based (alternating current) electric power systems but, finding little support for his ideas in Europe, he sailed to America and secured a position with Edison. Perhaps not surprisingly, the association between the two was short-lived and Tesla was left to his own meagre resources.

Despite this initial setback, he managed to document and patent the essential features of a complete AC system in 1887, which duly came to the attention of George Westinghouse, inventor, industrialist and gas tycoon.


With an eye to the future, Westinghouse had just founded the Westinghouse Electric Company and had become personally intrigued by the idea of an AC-based supply, reticulated at high voltage (and low current) but with step-down transformers to serve local areas.

He foresaw that this would get around the line resistance problems which Edison was by then encountering, as his DC systems expanded, with anything up to 30V variations in the nominal 110V supply, depending on the load current and the consumer's remoteness from the power station.

Westinghouse signed a licence agreement with Tesla in 1888, causing Edison to resort to extravagant, even bizarre, propaganda intended to highlight the "dangers" of the AC system, in an unsuccessful effort to discredit the poten-



These battery banks were used to buffer load variations and occupied an entire floor of the sub-station.



A "modern" electric griller and upright toaster, 1921 style, again normally suitable for use on either AC or DC.

How Edison lamps were made:

A bamboo rod is cut to the length required, divested of its hard soliceous coat, and split into six pieces, each one of which is reduced in thickness until its diameter is not much greater than a horsehair.

Each thread of bamboo is then placed in a mould formed by cutting a U-shaped depression in a plate of nickel, another plate of the same metal covering it over. The mould is then placed in a muffle, and is subjected to such a heat that the horseshoe shaped fibre is carbonised.

It is then placed in a glass bulb in connection with an air pump, the two ends of the horse-shoe carbon wire are fastened to platinum wires, which are sealed into the glass, and the ends of these wires form conductors for the electric current.



(From Cassell's
"Science for All",
published
100 years ago.)



These mercury arc rectifiers and transformers replaced the original motor-generator sets. Note the original switchboard on the upper gallery.

The end of an era

tial threat to his own DC technology.

Said Edison: "Just as certain as death, Westinghouse will kill a customer within six months after he puts in a system of any size. He has got a new thing and it will require a great deal of experiment-

ing to get it working practically. It will never be free from danger".

AC on the move

In 1893, Westinghouse won a milestone contract to power the huge Columbian Exposition, which was to spread over an area of 16 hectares and consume more power, at the time, than the entire city of Chicago.

This was followed by contracts to harness energy from Niagara Falls with an ambitious AC hydro-electric system — contracts ultimately shared with the

General Electric Company, which had reluctantly been forced to acknowledge the superiority of AC for the project.

AC technology was clearly on the march but, with many major centres in the USA, by this time, deeply involved with DC systems, there could be no abrupt turnabout and a mix of DC and AC mains was perpetuated way beyond the turn of the century.

In fact, even in the '30s and '40s, the ubiquitous RCA Receiving Tube Manuals were still carrying details of recommended valve types and typical designs for 117V AC/DC receivers.

Behind the lingering support for DC mains, especially in industrial situations, was the greater ease with which DC motors could be set up and controlled. Lighting and heating could use either source and electronic equipment, with its affinity for AC mains, did not become a consideration until at least the mid '20s.

In July 1923, the "Australia Wireless Review" opened an article on Elementary Magnetism and Electricity with the unequivocal statement:

"Direct current is the most suitable current for power purposes."

The Sydney project

Proposals regarding the "Municipal Council of Sydney's Electricity Undertaking" extend back to the early 1880's — approximating the opening date of Edison's original Pearl Street power station.

The basic concept was to provide electric power for the central business area of Sydney — an area which involved a high concentration of commercial and industrial activities, with a potential role for electric motors powering everything from lifts and hoists to factory and workshop machinery.

So it was not surprising, when the worthy councillors sought the advice of Edison, Swan (by then, his British associate) and others, that they should decide in favour of an Edison style, 3-wire DC system.


However, to minimise the effects of mains resistance, they selected a higher voltage: +240V and -240V relative to a common earth return conductor. Subscribers could be connected to one pair of mains for a 240V DC supply, or have access to the full 480V DC for high-power requirements.

The system became a reality in July of 1904, with electric street lights operating from a power station in nearby Pyrmont. And, as planned, the DC mains soon

Australian home-makers in 1921 were tempted by this inducement to get rid of their kerosene lamps, washtubs, wood fires and brooms, and to equip with the very latest in Magnet brand electric appliances, most of them AC/DC compatible. What, no radio, TV or hifi? (From "Sea, Land & Air" magazine).



**If you own an Apple IIc,
you'd have to add all this**



**to match the versatility, expandability
and higher intelligence of the
new Commodore 128**
(and it costs less too).

The new Commodore 128™ personal computer is breakthrough technology at a breakthrough price. It outshines the Apple® IIc in performance capability, performance quality and price. It is expandable to 512K RAM while the IIc isn't expandable at all.

And the new Commodore 128 has a numeric keypad built right into its keyboard that makes crunching numbers a lot easier. And the Commodore 128 has graphic and sound capabilities that far exceed those of the Apple IIc. But the most important news is that

the new Commodore 128 jumps you into a whole new world of business, productivity, education and word processing programs while still running over 3,000 programs designed for the Commodore 64!™ That's what we call a higher intelligence.


COMMODORE 128 ≡ A Higher Intelligence

C= commodore
COMPUTER
Keeping up with you.

BEEMAN MAYRHOFER STOTT/CC422

ELECTRONICS Australia, January 1986

19



This view shows the original motor-generator sets in the Clarence Street sub-station, before their replacement by the mercury arc rectifiers and transformers.

The end of an era:

found their way into commercial and factory premises throughout the central business area.

In due course, as the versatility and economy of the AC system became more apparent, the DC system was

deliberately restricted to the central business area, and subsequent expansion, in both service and generating capacity, was confined to AC technology.

Then, as increasing AC resources became available, the job of supplying the

inner city DC network was taken over by a network of regional sub-stations equipped with large rotary converters — single rotor machines driven by AC from distant power stations and delivering DC to the local mains.


Typical DC sub-station

The 0.5 megawatt rotary converters were designed to produce $\pm 250V$ DC (or 500V) overall at up to 1000A apiece. Across the line was a huge bank of storage cells, each cell measuring about one cubic metre, with the battery bank occupying a complete floor of the large sub-station. By day it would buffer variations in the load; late at night, the rotary equipment would often be shut down.

The basic converter and battery system was designed to feed 250V DC to each line, allowing a 10V margin for voltage drop.

However, associated with the main supply were special “buck and boost” rotary converters, capable of delivering $\pm 10V$ at up to 1000A each. By controlling the field system current and polarity, the output could be added to or subtracted from the line voltage, to maintain it at 250V under a variety of load conditions.

With the emergence of high power



100 years ago, this “Siemens Dynamo Machine” was Britain’s most powerful generator. It weighed just under 190kg, occupied 113 litres, and provided the Lizard lighthouse in Cornwall with a 3,620 candlepower etc.

electronic technology, the rotary machinery and batteries were, in turn, replaced by special transformers providing 12-phase AC input to multi-anode mercury arc rectifiers which, with resonant filters, could produce relatively clean DC.

As a consumer . . .

I knew nothing of all this when, fresh from the country, I obtained my first job as an assembler and wirer with Reliance Radio. It was a new venture — I was their first bench-hand — set up in an old building, demolished later to make way for the AWA head office in York Street.

My introduction to DC mains came when I was shown the ancient wiring and power points and warned that, on no account, was any ordinary radio or test equipment to be plugged into them. The result would be blown fuses and/or a blown power transformer and a very angry employer!

I was then taken down into a dungeon-like basement and shown a small rotary converter whining away in the gloom and turning DC mains power into 240V AC at 50Hz. I was to learn later that both figures were approximate only and that just so many receivers could be tested or demonstrated at the one time.

Even at best, radio reception still had its problems, arising partly from hash produced by the converter itself and partly from the horrendous interference level on the DC mains. After all, every single motor on the mains used a commutator and, fifty years ago, sensitivity about hash suppression was not all that evident.

A rather more dramatic introduction to DC mains followed a few days later, when one of the overhead light globes failed. It was a fairly large globe — about 150W — hung from a porcelain “rose” on the wooden ceiling by a metre or so of twisted, cotton-covered rubber flex.

As the filament parted, it set up an arc between the support wires, which proceeded to track up through the glass base into the bayonet holder, then through that to the flex, thereafter heading up towards the wooden ceiling like a miniature fireball. That was when somebody hit the switch.

I had seen for myself the ability of DC mains to maintain an arc, once started.

Tea . . . DC style

But that wasn't quite as salutary as the experience of a fellow wirer who attempted, one day, to “boil a billy” using an “immersion heater” — a spiral tube

with an internally insulated element, fitted with a couple of metres of twin lamp flex and a bayonet adaptor, and plugged into a lamp socket.

Why would anyone be using such a potentially hazardous contrivance?

This was fifty years ago, remember, when a large proportion of suburban homes had two power points, at most, which could be English style 3-pin round, 2-pin round, American 2-pin flat or even the new fangled Australian 3-pin flat! Any number of gadgets, including the new radio set could end up being plugged into a lamp socket with a little help from a 2-way bayonet adaptor.

Indeed, the men delivering and installing new radio sets encouraged us to despatch them with unterminated power leads, so that they could more easily fit whatever plug proved necessary on arrival. So there was nothing startling about the immersion heater.

The trouble was that the would-be tea maker forgot about the DC supply and simply unplugged the bayonet adaptor with the power still switched on. There was a sizzle and an arc, and he ended up with a handful of fire and smoke!

Somewhat more bizarre was the tale, related to me recently by an engineer friend, concerning a group of tea makers in a small city office, set up by the electronics company from which he recently retired.

They equipped themselves with an electric jug of now unremembered vintage, with an ordinary open element. It

worked apparently normally on the DC mains but, in rather short order, they all went down with some mysterious malady. It was ultimately traced, he said, to a toxic effect caused by a product of electrolysis, resulting from the DC supply.

It was a new one on me!

AC/DC receivers

But my pet hate was undoubtedly DC or AC/DC receivers, for the most part made and sold for use in the adjacent central city area. It generally fell to my lot to test and/or service them.


Being designed to operate without a mains power transformer, there had to be a direct conductive path between the mains and the internal signal circuitry. Even the normally innocuous valve heater wiring was “live”, being a series string fed directly from the mains through a large and very hot resistor or a current regulator (barretter) tube.

In some models, the chassis was also “live”; in others, it was connected to the mains through a bypass capacitor of 0.1 μ F more. And, when operating from earth-positive DC mains, all the normally “earthy” circuitry had to be at -250V for the receiver to operate!

The owners of these rather unpleasant receivers were suitably isolated from them by all-round cabinet work and an interlocking mains plug, but technicians and servicemen had no such protection.

DC or AC/DC receivers designed for 117V mains weren't so bad, because the voltages were modest and the heater series resistor commonly of low enough value and wattage to be incorporated in the mains power cord. But whereas an accident with 117V can be embarrassing and unpleasant, a similar inadvertence with 240V could be decidedly fatal!

It was a fate that I managed to avoid but I was not the least bit sorry to read that, as a guest of the present Sydney City Council, Mrs Lorraine Ashby had switched off that longstanding reason to perpetuate transformerless radio sets — one that had been activated, 81 years earlier by her grandmother, Lady Mayoress Amy Sarah Lees!

Have former customers of the SCC been left lamenting? Not really; the phasing out process has been quite gradual and, with today's technology, there is no special problem for a customer who still needs DC, to produce it on the spot from polyphase AC. 

I am indebted to a former EA staff member, Norman Marks, for his recollections of the Kent/Clarence St, DC sub-station, in which he served part of his apprenticeship in 1944.

Electric lighting in the UK

The principle public installations of the incandescent system in this country have been in the Savoy Theatre, London, which is entirely lighted by Swan lamps; at the International Fisheries Exhibition, 1883, where more than one thousand were seen on one circuit; at Holborn Viaduct, which thoroughfare, with houses adjoining, has been lighted by Edison's lamps; and at the Electrical Exhibition at the Crystal Palace, where the suitability of the system for both public and private use was most successfully demonstrated. To Edison must always attach the credit of having been the first to serve entire streets with a supply of electricity in lieu of gas.

(From "Science for All" published 100 years ago by Cassell & Co Ltd, London).

LITTLE DICK'S SUMMER SIZZLERS



**SUMMER AT SEA IS MORE FUN WITH 'SAFETY'—
GET A RADIO! CLUBS,
MARINERS**

VHF HAND-HELD TRANSCEIVER

Fantastic! Any *Old Salt* can have the security of VHF marine without the budget taking a dive. 12 channel programming for full local area lock-in PLUS re-programming capability. Switchable 0.5/2.5W power output. High sensitivity (better than 0.25uV) and more. Being hand-held (160x60x35mm), you can take it anywhere: home or in a life boat. Cat D-1404

\$399

VHF SEAPHONE MARINE

What a bargain! One of our best transceivers with \$50 saving. Features ALL international channels in the 156 — 163MHz band, switchable 25W power output and Universal mounting. Seaphone service lets you make calls from your craft. Cat D-1401

Was \$449



PLUS VHF antenna
Cat D-4071 for
only \$10 extra!
SAVE \$57.50

NOW \$399

24-HOUR SAFETY MONITORING

— TUNE INTO VALUE!

27MHz MARINE HELICAL ANTENNA

This is it! A whip antenna for glass, wood and cement boats that doesn't need a ground plane. Low price includes mounting base, cable, simulated ground plane. Great value! Cat D-4070

\$54⁵⁰

SWORDFISH 27MHz HALF WAVE

Tough fibreglass half-wave — doesn't need a metal ground plane. Ideal for all hull types. Includes 'any-which-way' base with quick release lever. With mounting hardware. Cat D-4071

\$67⁵⁰

VHF MARINE WHIP FOR 156MHz

Be a winner! You won't lose with this great antenna. Suits most radios — ideal for our 'Seaphone' unit (D-1401). Complete with 'any-which-way' base. Cat D-4016

\$67⁵⁰

HORNET II MARINE AM/SSB

Fantastic! Our Hornet is a real high-flyer with full 27MHz (expandable) marine band, local AM plus SSB for extra range. And it's so versatile — doubles as a PA with optional horn. Features noise limiter and blander, LED display. Cat D-1716

\$299




TUNE THAT SET! SWR/POWER METER

Suitable for 27MHz Marine

Built-in strength field facility indicates precise antenna radiation, other RF energy measurement. SO-239 sockets for permanent antenna line placement. Cat Q-1350

\$24⁷⁵
OR



Only \$10 if purchased with Hornet II (Cat D-1716)

MARINE RADIO HANDBOOK —

this book could save your life!

The mariner's mate! All the *scuttlebutt* about selecting, fitting and using marine radio; rescue organisations. Includes maps, charts and times of monitoring stations. Cat B-9604

\$8⁹⁵



SEAWASP 27MHz MARINE AM

WOW! Just the trick for in-shore boating — with access to all CB frequencies. Plus a host of features. Squelch control, RF gain, channel selection control, CB/WX switch, RF Power/"S" Meter and more! Excellent value and safety. Cat D-1407

\$199

Includes 2 VHF weather channels (Rec only) Too!



Don't leave shore without one!
5W 6-CH. TRANSCEIVER

Fantastic! Famous Uniden reliability plus full 27MHz marine features — all in a hand-held unit. Goes anywhere! Connect to boat/external antenna for maximum power. Cat D-1125

6 CHANNELS FITTED \$179
FREE Alkaline Batteries for Cat D-1125
SAVE OVER \$11

YACHTIES! GET ONE WHILE STOCKS LAST.
MULTI-BAND RADIO/DIRECTION FINDER

Lost? Not for long with this affordable receiver! Built-in radio direction finder pin-points your position against AM stations. PLUS hear FM, CB, VHF and shortwave. Includes manuals. Cat D-2832



\$119

CB RADIO IS BACK IN FORCE!
Hand-held units that are fun and safe. Ideal for cyclists, bushwalkers — in fact, Anyone!

POCKET COM II SHORT-RANGE CB



Cat D-1101
GET TWO FOR \$20
SAVE \$5.90

Really affordable communication! Effective over short distances: for construction sites, sporting teams, etc.

\$12.95

HAND-HELD 3 CH. ... for some more power ... and even more power
1W TRANSCEIVER 2W 3-CH. UNIDEN CB 3W 3-CH. CB



Great for weekend explorers! It's light, compact and features the bushwaking/safety channel 27.620MHz. A real life-saver in emergency situations. Cat D-1102

\$99



One of the most advanced 2W hand-held transceivers available! Gives that extra range when you need it most. With channel 14 crystals. Great features: squelch, battery strength LED and more!

\$119

Cat D-1107



Medium powered CB that could get you out of a 'heavy' situation. Fitted with channel 14 crystals, others left free for your favourite channels. Great Value! Cat D-1106

\$129

AND NOW CBs FOR YOUR CAR, TRUCK OR CARAVAN (or home — with suitable power supply M-9545: \$54.95)

K40 MINI AM With Full Power

WOW! Even on a strict budget you can enjoy CB action. But don't let the ultra-small size and low price fool you. Delivers legal maximum power on ALL 40 channels. With mic. Cat D-1443

DOC Approval No. 249A049



\$109

40-CH. 'MIDLAND' 77-001

Compact! Powerful! Ideal for small cars, cramped trucks — wherever space is limited. Packed with the best features: signal strength meter, LED channel display and more. Cat D-1445

DOC Approval No. 249A046



\$135

HORNET II 40-CH. AM/SSB

Just great! Hornet II proves you don't have to pay more for quality. Features channel and mode selectors, noise blanker/ANL switch, squelch, RF gain, clarifier and much more. Cat D-1710

DOC Approval No. 249A006



\$299

TRUCKIES & CLUBS/ OWNERS — GO FURTHER!

Great Range of Antennae!

Complete from \$28.50

Check our range! DSE have an antenna to suit your needs and budget. Like the 27MHz gutter grip: brilliant reception, easy installation; slips onto car's rain gutter (Cat D-4411). Only \$28.95. PLUS a selection of magnetic, helical, whip and base antennae.

'SUNDOWNER' UHF 40-CHANNEL CB



The pick of the crop! UHF communication that's as clear as country air. Backed with superior features: squelch, duplex repeater, RX/TX LEDs and more. So good, even a city-slicker will love it.

Cat D-1806

\$375

DICK SMITH ELECTRONICS

YOUR NEAREST STORE IS LISTED IN THE MAILER IN THIS ISSUE.

LISTEN TO THE CONFIDENTIAL BANDS! HX-2000 HAND-HELD SCANNER

WOW! Compact, go-anywhere unit 'eavesdrops' on all the action. Take it with you: in the car, to the office. Has many base station features, including priority, scan and search.

Cat D-2815



\$449

MX 4000 'MOBILE' SCANNER

Hear it! News as it actually happens while you're driving ... avoid traffic hazards, delays. Covers 20 channels — all programmable — including 800MHz and air. Loaded with features: priority, scan and searcher, LCD frequency display and more.



Cat D-2818

\$599

BIG DADDY SCANNER! YAESU FRG-9600 UHF/VHF



This is it! The BIG ONE! Covers UHF/VHF, AM/FM and SSB. Hear any type of broadcast: police, military, air and hams. 100 keypad programmable memory takes you through 60-to-905MHz continuously. Features 7 tuning/scanning rates output jacks. Cat D-2825

SPECIAL! Buy our YAESU FRG-9600 and save \$25 on our Broadband 65-520MHz antenna (Cat D-4432). That's 1/2 PRICE!


Don't be fooled by imitations!

\$799

KEEP IN TOUCH WITH OVERSEAS WITH DSE WORLD RADIO RECEIVERS ...

FRG-8800 HF RECEIVER

Yaesu — a respected name in communications. And DSE offers this superb Yaesu HF receiver with a host of impressive features. There are 10 built-in memories, digital frequency entry and manual tuning, a S/SINPO graphic indicator and much more! Plus CAT control and VHF capability.



Cat D-2820

\$899

PORTABLE 9 BAND RADIO

An enthusiast's delight! Tunes in to AM, FM and up to 7 SW bands within the 5.95 and 21.75MHz range. Offers superior selectivity and sensitivity. Ceramic filter cuts interference.



Cat D-2837

\$125

YAESU FRG-8800 (short-wave only)

A real goer! Power and performance to hear the world in your living room. With CAT capability, 10 memories, S/SINPO graphic indicator, dual 24-hour clock and more. Covers 2 — 30MHz. Cat D-2821



\$829

MULTIBAND AM/FM /SW 1.2.3.4.

Great introduction to SW listening. And with the FREE stereo headphones, it's sensational value! Tune into local AM/FM stations PLUS 4 SW bands. Provides endless hours of enjoyment.



Cat D-2835

\$59

SANGEAN ATS-803 MULTIBAND RADIO

It's got the lot! More features than even the most critical enthusiast could demand. Tune into AM/FM or any of the 12 SW bands by either direct frequency key-in, auto or manual scanning ... FIVE tuning functions in all. Adjust audio with treble and bass controls to suit personal tastes. Features sleep button, RF gain control and much more. Cat D-2831

\$329

VHF CONVERTER FOR FRG-8800s

Add versatility to Yaesu FRG-8800 receivers (Cat D-2820/2821). Covers frequency range: 118 — 174MHz. Fits neatly inside receiver. With own telescopic antenna. Cat D-2823

\$189

WORLD RADIO/TV HANDBOOK

A handy reference book every enthusiast should have! A comprehensive listing of valuable information: frequencies of long, medium and short range broadcasters; charts; and more.



Cat B-2886

\$32.50

SAVE! SAVE! SHORTWAVE ANTENNA KIT FREE WITH D-2831/2820/2821
FREE WITH ANY SCANNER BOUGHT — AUSTRALIAN CONFIDENTIAL FREQUENCY LIST
Cat B-9600 \$8.95

New eight-month course from Control Data

How to become a computer technician

The Control Data Institute is well known for training computer operators and programmers. Recently they began a new course for computer maintenance technicians which they hope will be just as successful.

by LOUISE UPTON

Computer Maintenance Technician wanted. Duties include providing maintenance on IBM compatible computer systems and multi-user systems, install and maintain networks. Workshop repair component level. Qualifications: an approved Technical Certificate or equivalent qualifications in a relevant field.

Open the papers today and jobs of this sort jump out at you from everywhere. But how do you qualify? One answer comes from Control Data Institute, which specialises in this field.

The school is at St Leonards in Sydney and offers a number of courses in computing and office skills but the Computer Maintenance Technology course is the newest part of the Institute's services, having begun in April 1985, with the first students having graduated around the middle of December, 1985.

Thirty-four students were enrolled in the first course, two of whom were girls. The number is expected to be higher this year, in line with an Institute survey which highlighted the need for trained technicians.

The Manager of the Education Services, Julia Delavere, feels that, "although many companies were making an effort to train their own maintenance crews, the growth in demand has made starting the course an excellent way for people to upgrade existing skills or start a new career."

The training takes place in groups, al-

though the method is largely a self-teaching one with an instructor on call at all times to give individualised attention as it is needed. The old concepts of chalk and talk are not a part of this school's philosophy.

In comparison to similar courses being offered by technical colleges the Institute's program is expensive. This is mainly due to the method of teaching which is heavily based on using the computer at all times and this is fairly costly. However, the results for the job seeker appear to justify the price.

The course lasts 8½ months on a full-time basis and the Institute awards qualifying students with a Diploma.

Within the course structure, practical

work and gaining experience occupies a vast proportion of the student's school time. Working on prototype boards they learn the uses of the multimeter, oscilloscope and other test instruments for trouble-shooting a computer's printed circuit boards.

Sometimes there will be repairs to make at the component level. But often as not, the checks that these technicians are being taught to run are all a part of what is called preventative maintenance. It is this type of work which will take up the bulk of their time in a job.

The Control Data Institute also offers courses in programming and operating for those who don't feel they have the engineering patience or talent to search for and isolate the fault(s) in a malfunctioning micro. These courses are conducted along much the same lines as the Maintenance Technician course.

It is also possible to buy certain modules or parts of courses if you don't wish to do the whole thing.

The Computer Programming and the Maintenance Technician courses cost \$6,250 and an operator's course is \$4,150.

continued on page 120



The course emphasises the practical aspects of training to be a technician.

CARVER

Powerful · Musical · Accurate



THE CARVER COMPACT DISC PLAYER

**WITH
DIGITAL
TIME
LENS.**

The Carver Compact Disc Player is the world's leading compact disc player to address the problem of the bright, hot, harsh sounding midrange and lack of ambiance and spatial detail characteristic of the majority of compact discs currently available.

The Carver Compact Disc Player answers the audiophile's demand for a CD Player which provides not only the greater dynamic range, quietness, and richer bass expected from compact disk technology, but also the musicality, spectral balance and spatial qualities of well executed high fidelity stereophonic reproduction.

FEATURES:

- 16 Bit D/A Conversion for precise reproduction
- Extraordinary high tracking accuracy by 3 beam laser pick up virtually eliminates distortion.
- Random memory selection.

Sold by leading Hifi dealers and distributed by the **ODYL GROUP OF COMPANIES**, for further information please contact:

THE	ODYL COMMUNICATIONS Melbourne — (03) 846-3022
ODYL	QUEENSLAND (07) 394-8284
GROUP	ODYL DISTRIBUTORS (NSW) PTY LTD Sydney — (02) 212-6617

Carver DTL-100 compact disc player

Coinciding with the relaunch of Carver products onto the Australian market, the company has released its first compact disc player, the DTL-100. The new machine incorporates a unique feature: the Digital Time Lens.

The thinking behind the Digital Time Lens is as follows: Since the introduction of compact discs there have been many unfavourable comparisons with equivalent recorded material on vinyl discs. CDs have been said to lack ambience, musicality and a whole lot of other qualities which have been largely undefined. Bob Carver is one who believes there is a problem with CDs concerning the three dimensional perspective of the sound.

He arrived at this conclusion by comparing 23 compact discs against their analog equivalents on vinyl. By quantifying the differences, Carver came to two conclusions. Firstly, CD sound has more energy above 400Hz than analog recordings and secondly, the L-R channel information differed by 1.25dB.

Carver's Digital Time Lens (DTL) circuitry is designed to correct for these perceived differences. It is supposed to restore the octave balance and L-R component to those of analog record-

ings. It can be switched in or out at will and is likely to cause a lot of debate amongst audio enthusiasts. More on this later.

Operating features

The Carver DTL-100 Compact Disc Player is a large unit suitable for 19-inch rack mounting. It is very well finished with a rugged cast aluminium front panel. The styling is subdued without being spartan and would fit in with almost any decor. Overall dimensions are 485 x 80 x 282mm (W x H x D).

The front loading disc drawer operates very smoothly. It responds promptly to the Open/close switch located immediately to the left of the display. When the draw is open the display says so by showing "OPEN". To close the drawer, you can either press the Open/close switch again or just push gently on the drawer itself to make it withdraw. This feature is a good one since it prevents the drawer mechanism

being damaged should it be forced closed either deliberately or by accident.

If the drawer is closed without a disc, the display indicates a flashing "dISC". If a disc is loaded correctly, the display initially indicates the number of tracks present on the disc and then displays "100". The DTL-10 is now ready to play.

Below the Open/close switch is the DTL switch. When it is pressed in, DTL is selected and an indicating LED lights up.

Pushing the Play switch causes the word "PLAY" to be indicated by the display for a brief period. Then the track number is displayed and the music starts. To display elapsed time, the Display switch is pressed. Press it again to return to display of track number.

If the CD has index codes which sectionalise certain passages of the recording, this fact is displayed by the Index LED. The DTL-100 can be used to search for these index locations by using the fast forward (FWD) or fast reverse (REV) switches.

These FWD and REV switches also give audible cue and review facilities. When either of the switches are pressed, the volume is reduced. For the first three seconds after pressing either switch the rate of incrementing or



Carver's DTL-100 CD player has all the usual features plus the Digital Time Lens circuit.

decrementing the CD recording is in small rapid bursts. After that it moves much faster with larger jumps.

The FWD and REV switches are located to the right of the display along with the Pause/Stop, Play, - and + switches.

The + and - switches control selection of tracks on the disc such that the + switch selects tracks in a forward direction and the - switch for the reverse direction. These switches are also used for programming when chosen combinations of tracks have been selected for playing. Up to nine program selections can be made in any order or combination.

A Repeat switch sets the player to repeat the entire disc or the programmed sequences. This function is indicated by a LED in the display window.

At the rear of the unit are the audio output RCA sockets, voltage selector switch and two-core mains flex. Our review sample had the US-style 110V, 2-pin plug fitted and was not wired to established double-insulation standards. We assume that machines on sale to the public will comply with Australian standards in this regard.

Mechanical details

Internally, the mechanism and the main circuit board all appear to have been produced by Yamaha. Carver have modified the unit by adding a printed board which accommodates ten small integrated circuits (including two pseudo-random digital noise source ICs) and associated passive components.


Carver is certainly not alone in this approach to marketing CD players. Many other companies, Japanese, American and European, have taken a similar approach in taking a standard CD machine and modifying it to their requirements.

The method of signal conversion is to use a single 16-bit digital-to-analog converter with two times oversampling at 88.2kHz. It uses digital filtering and a third order active low pass filter.

Performance

We tested the Carver DTL-100 using a Technics SH-CD001 test disc and Sound Technology distortion measuring equipment.

First, we tested the player with the Digital Time Lens feature switched out. Under this condition, the frequency response was to the expected high CD standard — very flat, with a rise of 0.5dB at 10kHz and 12kHz and falling to -2dB at 20kHz. Signal-to-noise ratio



The DTL-100 uses a Yamaha CD mechanism and main PC board.

with respect to full output was 98dB with a 20kHz low pass filter.

Separation between channels was measured at 85dB at 100Hz, 80dB at 1kHz and 61dB at 10kHz and 20kHz. These results were the same for both channels.

Linearity results were satisfactory, with a 1dB error at -70dB and -80dB. At -90dB signal level, the measured signal level was -90dB, which might lead to the conclusion that there is no error at this level. That is not valid, however, since the measurement was predominantly noise with very little signal component.

This means that the effective signal to noise ratio of the unit is closer to -90dB than to the -98dB figure achieved above.

Total harmonic distortion results were good at .0055% at 20Hz, .013% at 1kHz and 0.1% at 10kHz and 18kHz. The rising level was due to the residual 44.1kHz and higher harmonic sampling artefacts which are not completely removed by the filtering process.

When checking tracking performance with the Philips 4A test disc, the Carver DTL-100 mistracked at the 600µm black dot although it tracked the 900nm interruption layer and simulated fingerprint defects successfully. This performance is not as good as some previously tested CD players although no doubt the Carver will happily play the vast majority of discs without any audible hiccups.

The player was also somewhat susceptible to mistrack if jarred at the sides of the chassis. Again, we have measured other compact disc players which were better in this regard.

Digital Time Lens

We were very interested in the effect of the Digital Time Lens (DTL) on the measured performance. Having already listened to the audible changes it brought about, we were intrigued.


Frequency response with DTL in circuit is quite irregular. There is a broad rise of about 2dB between 50Hz and 200Hz, with respect to the 0dB reference at 1kHz. At the high frequency end of the spectrum, there was another rise, +3.5dB at 18kHz and +2dB up at 10kHz. In the midrange meanwhile, there is a 1.5dB trough in the response between 2kHz and 5kHz.

Signal-to-noise ratio also was different and we suspect that the presence of noise source ICs on the add-on Carver board means that noise has been deliberately added to the output signal, possibly to gain the same benefits given by the addition of dither to CD recordings. As a result, the signal-to-noise ratio with DTL in circuit was 83dB (compared to 98dB without DTL).

Distortion at all frequencies was higher by a factor of two with DTL in circuit. This is probably a natural result of the add-on circuitry rather than by design intention.

The effect on the separation was intended though and amounts to a major reduction on the CD levels down to less than the standard of typical good quality phono cartridges: 16dB at 100Hz, 18dB at 1kHz and 22dB at 10kHz and 20kHz. On the other hand, a good stereo effect can usually be obtained with only 18dB separation.

continued on page 56



Second article has all the circuit diagrams

Playmaster

AM/FM

Pt. 2

stereo tuner

Last month, we introduced our new synthesised AM/FM stereo tuner and described the block diagram. In part 2 this month, we give the full circuit details and list the specifications.

by JOHN CLARKE

The circuit for our new Playmaster Stereo AM/FM Tuner is quite large and, as a consequence, covers several pages. This is something of a blessing, however, since it breaks the circuit into three manageable sections: AM tuner, FM tuner and microprocessor control. We will describe the operation of each circuit section separately.

As discussed last month, microprocessor IC1 performs a major roll in driving

the display, tuning the AM and FM front ends, and switching power to either tuner as appropriate. Before we discuss this further, let's first take a look at the AM and FM tuner circuits.

AM tuner


The AM tuner circuit is a high-performance superheterodyne design employing varicap tuning, a double-balanced mixer, ceramic filters and stereo

decoding. It is a brand new design, developed completely from scratch.

Input signals from the loop antenna are fed to a balanced circuit consisting of toroidal transformer T1. As stated last month, this acts to reduce common-mode interference so that the tuner is provided with a noise-free signal. The unbalanced secondary of T1 is direct-coupled to terminal 5 of antenna coil L1.

The winding across terminals 4 and 5 is a special modification to the standard 7210 coil assembly and comprises a few hand-wound turns on the L1 coil former. These provide very light coupling to the tuned winding across terminals 1 and 2.

RF tuning of the antenna circuit is provided by varicap diode D1 in conjunction with the 3-30pF trimmer connected across the 7210 winding. A tap-



View inside the prototype. The microprocessor chip is at the bottom centre of the photograph.

ping of the winding at terminal 6 directly couples to gate 1 of dual gate MOSFET Q1.

Q1 is used as a self-biased common source amplifier with the L2 winding (7211) forming the drain load. Varicap diode D2 and its associated 3-30pF trimmer are capacitively coupled to L2 to form the second RF tuned circuit. The 1M Ω resistor across D2 discharges the varicap when the control voltage at its cathode is altered.

Note that self-bias for Q1 is provided by the 220 Ω source resistor while the AGC (automatic gain control) voltage is applied to gate G2 via the 100k Ω and 47k Ω resistors.

The output from the second RF stage appears at terminal 6 of L2 and is coupled to the differential input of double-balanced mixer stage IC5 (MC1496) at pins 1 and 4. The open collector outputs at pins 6 and 9 are loaded with the balanced primary windings of L3 and its parallel 560pF capacitor which form a tuned circuit at 450kHz.

Supply decoupling is via a 560 Ω resistor and 0.1 μ F capacitor.

Q4, L5, D3 and the associated 3-30pF

trimmer form the local oscillator. A feedback tapping between Q4's emitter and terminal 4 of L5 ensures continued oscillation, while VR1 sets the level of oscillation. Note that D3 is isolated from the L5 winding via a 680pF capacitor. This reduces the maximum tuned circuit capacitance.

To explain further, the RF stages must be tuned from 522 to 1611kHz which represents a capacitance ratio of 9.5:1 (which is the square of the 1611/522 ratio). The local oscillator, on the other hand, must be tuned from (522 + 450) kHz to (1611 + 450)kHz which represents a 4.5:1 capacitance ratio.

A separate winding on L5 couples the oscillator output to the second differential input stage of the mixer (IC5) at pins 7 and 8.

Because the mixer is a balanced type, only the sum and difference frequencies appear at the output. This fact is very useful since it allows the use of a wide band ceramic filter (SFP450D) in the IF stage.

As stated last month, the filter sharply rolls off the response beyond

± 12 kHz and is 60dB down at ± 40 kHz. However, it also has secondary peaks in its response so that the attenuation of the filter is only 15dB down at ± 150 kHz. Normally, this would render the filter useless, since signals around 600kHz would pass through the IF filter virtually unattenuated.

The balanced mixer neatly solves this problem, however. It rejects both the incoming RF and local oscillator signals, and allows only the mixed signal through to the IF stage. Consequently, the rising response outside the passband of the ceramic filter is unimportant.

The output from the ceramic filter is coupled to gate 1 of Q2, another BFR84 dual-gate MOSFET transistor. L4 and the 390pF capacitor form a tuned drain load for Q2 which provides some gain for the IF stage.

At this point, the IF output is split into two paths. One path is derived from the drain of Q2, amplified by common emitter stage Q3, and applied to a narrow band ceramic filter (SFZ450C3N). This filters a very narrow band centred on 450kHz which means that it passes signal only when

Playmaster AM/FM stereo tuner

the IF stage is centred on 450kHz. In other words, an output from the filter only occurs when the tuner is exactly on station.

The output from the narrow-band filter is rectified by D4 and D5, filtered and applied to the base of Q5. Whenever the signal is sufficiently strong, the base of Q5 is pulled below 0.6V. Consequently, Q5 turns off and supplies a station detect or stop output signal to pin 13 of the microprocessor.

The second signal path from the IF stage is derived from a tapping on L4 (terminal 6) and coupled to the pin 3 input of IC4, an MC13020P Motorola stereo decoder. This versatile chip performs a range of functions. It provides low-distortion synchronous detection of the incoming IF signal, stereo decoding, an AGC output and automatic stereo-mono switching.

A forced mono input (pin 9) allows manual switching to mono operation.

The 3.6MHz ceramic resonator sets the frequency of an internal VCO which therefore operates at eight times the 450kHz IF. In operation, the VCO locks onto the IF and provides a phase reference for stereo decoding. The decoded left and right audio outputs appear on pins 7 and 8 respectively and are fed to the notch and low-pass filter circuits.

The AGC output from IC4 appears at pin 4 and is applied to inverting amplifier IC6b. The resulting AGC output signal appears on pin 7 and is used to control the gain of MOSFET transistors Q1 and Q2 as discussed previously. In this way, a constant signal level is provided at the input to IC4 over a wide range of signal conditions.

Further, IC6a inverts and level shifts the AGC signal to drive an NSM39152 LED-bargraph signal strength meter. This features 10 LEDs and has a logarithmic response. It accepts a DC signal and displays the relative level compared to RLO (ground) and RHI, the high reference set by the 2.2k Ω and 6.8k Ω resistors.

Diode D10 isolates the output of IC6a from the FM signal meter drive circuitry.

The left and right audio outputs from IC4 are fed to 9kHz notch filters based on L6 and L7. These remove any 9kHz whistles caused by adjacent stations. VR2 and VR3 are used to adjust the

depth and sharpness of the notch (in each channel), while tuning is provided by adjusting the slugs in the L6 and L7 inductors.

Following the 9kHz notch filters are active filter stages IC7a and IC7b, each with a gain of 1.2. These filters roll off the response above 10kHz to remove high frequency noise from the audio output signals.

Finally, the left and right audio outputs are applied to IC12, a 4052 CMOS analog switch (shown on the FM tuner circuit) page 37) which selects either the AM or FM tuner outputs.

FM tuner

The FM tuner front end is designed to accept a 75 Ω unbalanced antenna. When used with a balanced 300 Ω dipole antenna, a 300 Ω to 75 Ω balun will be necessary. The standard adaptor type used for television antenna inputs is quite suitable.

L8 is the 75 Ω input and this couples to a double-tuned filter consisting of L9, D19 and L10, D20. The RF output signal from the filter is then applied to gate 1 of Q6, a low noise dual gate MOSFET with L11 as its drain load.

The amplified output appears at the drain of Q6 and is fed via a 1.5pF capacitor to another tuned stage consisting of L12 and varicap diode D21.

AGC is applied to gate 2 of Q6 and operates during very high signal level conditions to prevent overload.

The local oscillator has a tuned circuit comprising L13 and varicap diode D22 for the collector load of Q8. Feedback via the 3.3pF capacitor from emitter to collector ensures that the circuit oscillates. A 2.2k Ω resistor and 6.8 μ F capacitor provide supply decoupling.

Local oscillator injection to mixer stage Q7 is via a 4.7pF capacitor to the base, while the output signal from L12 is also fed to the base via a 6.8pF capacitor.

Mixer stage Q7 has a 10.7MHz tuned collector load consisting of L15 and a 47pF capacitor. The output signal is extracted from pin 3 of L15 and applied to ceramic filter CF1 and to the wide band AGC input (pin 20) of IC2, an LM1865 FM IF/detector chip from National Semiconductor.

Quite a lot happens inside the LM1865. It contains a buffer stage, limiter amplifier, quadrature detector,


Specifications

AM Tuner

Tuning Range	522 to 1611kHz
Frequency Response	-3dB at 5.5kHz (see graph)
Harmonic Distortion	mono: 0.4% at 30% modulation stereo: <1% at 30% modulation
Audio Output	450mV RMS into 4.7k Ω load at 100% modulation
Stereo Separation	typically 30dB
AGC Range	40dB for a 6dB change in audio output
Signal-to-Noise Ratio	70dB with respect to full output for signal levels of 9 and 10 on bar graph display; better than 60dB with respect to full output for signal levels greater than 6
Usable Sensitivity	350 μ V at -6dB audio level

FM Tuner

Tuning Range	87.9 to 107.9MHz
Frequency Response	-1dB at 20Hz, -0.5dB at 15kHz
Harmonic Distortion	mono: 0.15% (100Hz); 0.15% (1kHz); 0.2% (6kHz) stereo: 0.4% (100Hz); 0.4% (1kHz); 0.4% (6kHz)
Audio Output	450mV RMS into 4.7k Ω load at 100% modulation
Stereo Separation	34dB (50Hz); 34dB (1kHz); 36dB (10kHz)
Subcarrier Product Rejection	48dB
19kHz Rejection	62dB
Signal-to-Noise Ratio	see graph



12TU-

- 1 rack-mounting cabinet, 44 x 254 x 430mm (Altronics Cat. No. H-0411)
- 1 screen printed front panel, 486 x 46mm
- 1 negative film, 185 x 31mm
- 1 sheet of neutral perspex, 179 x 24mm x 1.5-3mm
- 2 pieces of tinplate, 101 x 24mm
- 2 pieces of tinplate, 52 x 24mm
- 1 piece of tinplate, 52 x 20mm
- 1 PC board, 330 x 216mm, code 85tu12
- 1 PC board, 66 x 110mm, code 85ps12
- 1 double-sided PC board, 94 x 51mm, code 85fm12
- 1 double-sided PC board, 370 x 35mm, code 85db12
- 1 Ferguson PL24/20VA low profile transformer
- 1 mains cord and plug
- 1 cord grip grommet
- 2 bullet sockets with insulating sleeving
- 4 rubber feet
- 10 6mm spacers
- 4 12mm spacers
- 1 Belling Lee 75 Ω panel-mounting socket
- 1 stereo panel-mounting RCA socket
- 1 2-way panel-mounting screw terminal
- 1 DPDT mini push on/push off switch with 10mm black cap
- 12 snap action black keyboard switches (Jaycar Cat. No. SP-0721)
- 9 Molex 8-way 0.1-inch pin headers
- 8 Molex 8-way 0.1-inch cable connector sockets
- 64 crimp terminals to suit above sockets
- 94 Molex pin sockets
- 50 PC stakes
- 1 TO-220 heatsink, 30 x 27 x 12mm, Thermalloy 8030
- 1 4.5MHz parallel resonance crystal
- 1 earth lug

Wire & cable

- 100mm of 8-way rainbow cable
- 300mm 0.8mm enamelled copper wire
- 25mm 0.6mm enamelled copper wire
- 130mm 26B&S enamelled copper wire
- 220mm twin shielded wire
- 2 metres 30B&S enamelled copper wire
- 37 metres 36B&S enamelled copper wire
- 3 metres hookup wire

Parts List For Synthesised Stereo

Integrated Circuits

- 1 NEC D1710G/016 or /227 MPU
- 1 NEC 553AC dual modulus prescaler
- 1 LM1865 advanced FM IF system (National Semiconductor)
- 1 LM1870 FM stereo demodulator (National Semiconductor)
- 1 MC13020P C-QUAM AM stereo decoder (Motorola)
- 1 MC1496G (metal package) balanced modulator/demodulator (Motorola)
- 2 DS75492 MOS to LED hex digit drivers
- 1 40106, 74C14 hex Schmitt trigger
- 1 4052 2-pole, 4-way CMOS switch
- 2 LF353, TL072 dual op amps
- 1 LF347, TL074 quad op amp
- 3 7805, LM340T-5 3-terminal +5V regulators
- 1 7812, LM340T-12 3-terminal +12V regulator
- 1 7912, LM320T-12 3-terminal -12V regulator
- 1 LM317T adjustable 3-terminal regulator

Transistors and diodes

- 4 BB204B or BB204G varicap double diodes (Philips). Note: do not mix B and G types.
- 3 BB212 AM varicap double diodes (Philips)
- 1 BF450 PNP HF transistor
- 1 BF240 NPN HF transistor
- 1 BF981 N-channel dual gate MOSFET
- 2 BFR84 N-channel dual gate MOSFETs
- 1 BF494 NPN transistor
- 5 BC549 NPN transistors
- 8 BC327 PNP transistors
- 1 BC337 NPN transistor
- 2 BC547 NPN transistors
- 1 2N5485 N-channel FET
- 19 1N4148, 1N914 small signal diodes
- 10 1N4002 1A silicon diodes

Optoelectronic components

- 1 NSM39152 green bar graph display (Geoff Wood Electronics)
- 2 MU03-5201 6 x 9mm green light bar modules (A&R Soanar)
- 2 MU02-5201 14 x 14mm green light bar modules (A&R Soanar)

- 4 NAG163 green common anode 7-segment displays (Stanley, A&R Soanar)
- 6 3mm green LEDs
- 1 3mm red LED

Ceramic filters and resonators

- 2 Murata SFE10.7ML ceramic filters (IRH)
- 1 Murata SFP450D AM stereo IF ceramic filter
- 1 Murata SFZ450C3N ceramic filter
- 1 Murata CSA3.6MT7 ceramic resonator & CSC500K7 50pF capacitor

Inductors

- 2 Neosid type E1 adjustable inductance assemblies
- 1 Neosid type E3 adjustable inductance assembly
- 1 Neosid type A5 adjustable inductance assembly
- 1 Neosid 4329R/2 ferrite ring core
- 1 Jabel 7210 1st RF bandpass coil
- 1 Jabel 7211 2nd RF bandpass coil
- 1 Jabel 9185 IF coil
- 1 22 μ H choke
- 1 18 μ H choke
- 1 6.8 μ H choke
- 1 F16 ferrite slug
- 4 Philips 4322 022 22260 potcores, PL14/8, with nut
- 4 Philips 4322 021 30250 coil formers
- 4 Philips 4322 021 30950 inductance adjusters
- 4 Philips 4322 021 30440 tag plates
- 4 Philips 4322 021 30520 brass containers
- 4 Philips 4322 021 30630 springs

Capacitors & Resistors

AM tuner

Capacitors

- 1 2200 μ F 25VW axial electrolytic
- 2 1000 μ F 16VW PC electrolytic
- 1 470 μ F 63VW axial electrolytic
- 2 470 μ F 25VW axial electrolytic
- 1 100 μ F 25VW axial electrolytic
- 1 33 μ F 16VW PC electrolytic
- 1 10 μ F 25VW PC electrolytic
- 3 10 μ F 16VW PC electrolytic
- 2 4.7 μ F 16VW PC electrolytic

AM/FM Tuner

2 2.2 μ F 16VW PC electrolytic
 3 1 μ F 16VW PC electrolytic
 2 0.47 μ F 16VW tantalum
 11 0.1 μ F ceramic
 4 .056 μ F metallised polyester
 1 .022 μ F metallised polyester
 10 .01 μ F ceramic
 2 .01 μ F (10nF) ceramic plate,
 Philips 222 629 09103
 4 .0033 μ F metallised polyester
 2 .0018 μ F metallised polyester
 1 .001 μ F metallised polyester
 1 .001 μ F ceramic
 1 .001 μ F (1nF) miniature ceramic
 plate, Philips 222 630 09102
 1 680pF miniature ceramic plate,
 Philips 222 630 09681
 1 560pF ceramic
 2 470pF ceramic
 1 390pF ceramic
 1 56pF ceramic
 1 33pF ceramic
 3 5.2-30pF Murata D series
 trimmers

Resistors 0.25W, 5% unless
 stated)

2 x 1M Ω , 1 x 300k Ω 2%, 1 x
 270k Ω , 2 x 220k Ω , 3 x 150k Ω , 1
 x 110k Ω 2%, 7 x 100k Ω , 1 x
 82k Ω , 2 x 47k Ω , 1 x 33k Ω , 2 x
 22k Ω 2%, 2 x 18k Ω 2%, 3 x 12k Ω
 2%, 2 x 10k Ω , 2 x 8.2k Ω 2%, 1 x
 7.5k Ω 2%, 2 x 6.8k Ω , 3 x 5.6 k Ω ,
 1 x 4.7k Ω , 1 x 3.9k Ω , 2 x 3.3k Ω ,
 2 x 2.7k Ω 2%, 3 x 2.2k Ω , 2 x
 1.6k Ω 2%, 1 x 1.2k Ω , 2 x 1k Ω , 1
 x 910 Ω 2%, 1 x 820 Ω , 5 x 560 Ω ,
 1 x 430 Ω 2%, 1 x 270 Ω , 2 x
 220 Ω , 3 x 100 Ω , 1 x 4.7k Ω
 miniature horizontal trimpot, 2 x
 2k Ω miniature horizontal trimpots

FM front end

Capacitors

1 6.8 μ F tantalum
 7 .01 μ F (10nF) miniature ceramic

plate, Philips 222 629 09103
 3 .001 μ F (1nF) miniature ceramic
 plate, Philips 222 629 09102
 1 47pF miniature ceramic plate,
 Philips 222 652 10479
 1 27pF miniature ceramic plate,
 Philips 222 652 10279
 1 6.8pF miniature ceramic plate,
 Philips 222 652 09688
 1 4.7pF miniature ceramic plate,
 Philips 222 652 09478
 1 3.3pF miniature ceramic plate,
 Philips 222 652 09338
 1 1.5pF miniature ceramic plate,
 Philips 222 652 09158
 3 4.2-20pF Murata D series
 trimmers
 1 3-11pF Murata D series
 trimmer

Resistors (0.25W, 5%)

1 x 1M Ω , 4 x 56k Ω , 1 x 33k Ω , 1
 x 18k Ω , 2 x 10k Ω , 1 x 3.3k Ω , 1 x
 2.2k Ω , 1 x 1.5k Ω , 1 x 1k Ω , 1 x
 220 Ω , 2 x 22 Ω

FM IF and stereo decoder

Capacitors

1 220 μ F 16VW PC electrolytic
 2 47 μ F 16VW PC electrolytic
 1 22 μ F 16VW PC electrolytic
 2 10 μ F 16VW PC electrolytic
 2 4.7 μ F 16VW PC electrolytic
 3 2.2 μ F 16VW PC electrolytic
 3 1 μ F 16VW PC electrolytic
 1 0.33 μ F metallised polyester
 1 0.22 μ F metallised polyester
 3 0.1 μ F ceramic
 1 .047 μ F metallised polyester
 4 .012 μ F metallised polyester
 5 .01 μ F (10nF) miniature ceramic
 plate, Philips 222 629 09103
 2 .0056 μ F metallised polyester
 3 .0047 μ F metallised polyester
 2 .0018 μ F metallised polyester
 2 .0015 μ F metallised polyester
 1 .001 μ F metallised polyester
 2 150pF ceramic

1 82pF miniature ceramic plate,
 Philips 222 652 58829

Resistors (0.25W, 5% unless
 stated)

2 x 390k Ω , 2 x 270k Ω , 3 x
 100k Ω , 1 x 47k Ω , 1 x 33k Ω , 2 x
 22k Ω , 2 x 20k Ω 2%, 4 x 15k Ω ,
 1 x 12k Ω , 3 x 10k Ω , 6 x 10k Ω 2%,
 1 x 8.2k Ω , 1 x 7.5k Ω 2%, 2 x
 4.7k Ω , 1 x 4.3k Ω 2%, 2 x 3k Ω 2%,
 1 x 2.2k Ω , 1 x 330 Ω , 1 x 22k Ω
 horizontal cement trimpot, 3 x
 10k Ω horizontal cermet trimpot, 1
 x 5k Ω horizontal cermet trimpot

Tuner control circuit

Capacitors

1 47,000 μ F (.047F) 5VW super
 capacitor
 2 1000 μ F 16VW PC electrolytic
 4 47 μ F 16VW PC electrolytic
 4 10 μ F 25VW PC electrolytic
 4 10 μ F 16VW PC electrolytic
 2 1 μ F 63VW PC electrolytic
 1 1 μ F 35VW PC electrolytic
 1 1 μ F 25VW PC electrolytic
 1 0.33 μ F metallised polyester
 1 0.1 μ F ceramic
 2 .01 μ F ceramic
 2 .01 μ F (10nF) miniature ceramic
 plate, Philips 222 629 09103
 1 .01 μ F metallised polyester
 1 680pF miniature ceramic plate,
 Philips 222 630 09681
 1 100pF miniature ceramic plate,
 Philips 222 652 58101
 2 22pF ceramic
 2 4.7pF ceramic

Resistors (0.25W, 5%)

1 x 1M Ω , 1 x 220k Ω , 1 x 150k Ω ,
 1 x 33k Ω , 9 x 10k Ω , 4 x 5.6k Ω , 2
 x 4.7k Ω , 1 x 2.7k Ω , 1 x 2.2k Ω , 1
 x 1.8k Ω , 7 x 1k Ω , 6 x 820 Ω , 1 x
 680 Ω , 1 x 470 Ω , 1 x 330 Ω , 1 x
 220 Ω , 2 x 120 Ω , 2 x 82 Ω , 2 x
 56 Ω , 4 x 47 Ω , 7 x 22 Ω

signal strength meter drive circuit and
 an AGC output. In addition, it provides
 a stop output which is connected di-
 rectly to the stop input (pin 13) of the
 microprocessor.

The output from the input buffer
 stage of IC2 appears at pin 3 and is fed
 to a second 10.7MHz ceramic filter
 (CF2). It then passes to the limiter am-
 plifier which ensures that the input sig-
 nal is driven well into clipping. The
 limiter, in turn, drives the quadrature
 FM detector associated with the tuned
 circuits on pins 10 and 11.

The circuit effectively performs quad-
 rature detection by measuring the volt-
 age across L16 and the parallel 82pF ca-

pacitor. L17 limits the voltage swing
 across the quadrature coil while the
 4.3k Ω resistor reduces the Q of the
 tuned circuit to provide more linear de-
 tection.

The AGC output is extracted from
 pin 18 and applied to gate 2 of Q6 in
 the front end via a 1k Ω /33k Ω voltage
 divider. It operates when a strong signal
 is present or when a strong out-of-band
 signal is detected at the wideband AGC
 input (pin 20). In the latter case, the
 AGC acts to reduce intermodulation
 distortion.

Pin 8 of IC2 provides the meter out-
 put signal which is split into three sepa-
 rate paths. First, it drives the signal

strength meter via D23. Second, it
 drives the stop threshold (pin 13) via a
 voltage divider consisting of a 4.7k Ω
 resistor and trimpot VR4. And third, it
 drives the blend input of IC3, the
 LM1870 phase locked loop FM stereo
 demodulator.

VR4 sets the stop input threshold
 while VR5 sets the blend threshold (ie,
 the signal level below which blending
 from stereo to mono begins). The idea
 behind blending is to improve the sig-
 nal-to-noise ratio at very low signal
 levels. It does this at the expense of
 stereo separation of the upper treble
 frequencies.

In addition to the blend signal, IC3

JAYCAR JANUARY SPECTACULAR SPECIALS!

SAVE UP TO 70% ON OUR NEW YEAR CLEARANCE

MAIL ORDER HOTLINE
(02) 747 1888

Cat. HB-5020
DIECAST BOX AS USED IN TAI/CDI KITS
WAS \$11.50 SAVE 43%
NOW \$6.50

Cat. HB-5006
4" x 3" x 1" DIE CAST BOX
WAS \$8.50 SAVE 53%
NOW \$3.95

Cat. NA-1020
MOISTURE REPELLENT SPRAY
WAS \$4.95 SAVE 40%
NOW \$2.95

Cat. CT-2002
CONE TWEETER
WAS \$3.95 SAVE 50%
NOW \$2.00

Cat. CM-2062
6" PIONEER MIDRANGE
WAS \$12.50 SAVE 52%
NOW \$5.95

Cat. AC-1600
TAPE HEAD DEMAGNETISER
WAS \$4.95 SAVE 60%
NOW \$2.00

Cat. AS-3011
6" WIDERANGE SPEAKER 4 ohm
WAS \$2.95 SAVE 49%
NOW \$1.50

T199/4A SOFTWARE-BOOK PROGRAMS
Cat. BS-0750 51 EDUCATION PROGRAMS
WAS \$27.95 SAVE 50%

NOW \$12.95
Cat. BS-0752 ENTERTAINMENT/GAMES
Cat. BS-0754 24 BASIC PROGRAMS
Cat. BS-0756 BASIC TRICKS
Cat. BS-0757 GRAPHICS & SOUNDS
WERE \$29.95 ea SAVE 50%
NOW \$14.95 ea

Cat. CX-2615
3-WAY X-OVER 2kHz, 6kHz
WAS \$12.95 SAVE 60%
NOW \$4.95

MADE IN THE U.S.A.
HEWLETT PACKARD

Cat. HP-1103
PACK OF 100 x 5mm LED MOUNTING CLIPS
WAS \$6.50 SAVE 38%
NOW \$4.00

Cat. HP-9520
12" SQUARE BLANK DS F/GLASS RB
WAS \$9.95 SAVE 30%
NOW \$4.95

Cat. HP-9510
12" SQUARE BLANK SINGLE/S F/GLASS RB
WAS \$8.95 SAVE 35%
NOW \$3.95

240V CANNON MAINS PLUGS
Cat. PS-1002 - AXR-LINE-11B (BLACK)
WAS \$9.95 SAVE 70%
NOW \$2.95
Cat. PS-1002 - XLP-LINE-11C (NATURAL)
WAS \$9.95 SAVE 60%
NOW \$3.75

**AEM 10" 3-WAY
SPEAKER SYSTEM**
★ CALL US FIRST ★



PACK OF 100 IC SOCKETS
Cat. PI-6482 - 16 PIN
WAS \$25 SAVE 40%
NOW \$15.00
Cat. PI-6480 - 14 PIN
WAS \$22.00 SAVE 45%
NOW \$12.00
Cat. PI-6484 - 18 PIN
WAS \$28.00 SAVE 43%
NOW \$16.00

Cat. YX-2900
240 VOLT NEGATIVE AIR IONISER
WAS \$69.95 SAVE 28%
ONLY \$49.95

Cat. YT-6505
ELECTRONIC CALL DIVERTER
Note: 2 exchange lines are required for this appliance
WAS \$159 SAVE 15%
NOW \$135.00

Cat. YT-6500
ELECTRONIC TELEPHONE DIRECTORY
WAS \$59.95 SAVE 33 1/3%
NOW \$39.95

Cat. MB-3502
SOLAR BATTERY CHARGER
WAS \$16.95 SAVE 26%
NOW \$12.50

Cat. YS-5600
SOUND (HANDCLAP) TRIGGERED
APPLIANCE SWITCH
WERE \$14.95 SAVE 15%
NOW \$12.70

**GREEN STICKER
BOOK SALE**

All books in our shops that have a green sticker signify that you can take **30%** off of that particular book.

PERSONAL SHOPPERS
CALL IN AND BROWSE

MAIL ORDER CUSTOMERS
Any mail order customer who purchases during January or February will get a **RED STICKER** list of books. This will show even greater book savings!

MULTILAYER CHIP CERMICS PACK 100
Cat. RC-5496 - 0.1uF
WAS \$25.00 SAVE 60%
NOW \$10.00
Cat. RC-5495 - 0.01uF
WAS \$25.00 SAVE 68%
NOW \$8.00



Cat. SL-2700
MAGGYLAMP
WAS \$169 SAVE 15%
NOW \$143.00

Cat. QM-1530
10A DIGITAL MULTIMETER
WAS \$89.95 SAVE 15%
NOW \$76.45

Cat. YS-5035
RECHARGEABLE NiCad TORCH
WAS \$29.99 SAVE 33 1/3%
NOW \$19.99

Cat. QM-1540
10A DIGITAL MULTIMETER/CAPACITANCE METER
WAS \$129 SAVE 15%
NOW \$109.65

UNIQUE CONSTRUCTION



SPARKPLUG LEAD SALE

Because of massive cost increases due to the low Australian dollar we have reluctantly decided to discontinue these French made high-quality leads. We **MAY NOT** have every lead that you require and we obviously cannot back order. To overcome this, we suggest that you allow us to ship the nearest equivalent longer length. This is the chance of a lifetime to get RF suppressed metal plug leads!

RIGHT ANGLE DISTRIBUTOR ENTRY
30cm cable - Cat. WA-5404
40cm cable - Cat. WA-5408
50cm cable - Cat. WA-5412


WERE \$4.95 SAVE 50%
NOW \$2.47 each
RIGHT ANGLE DISTRIBUTOR ENTRY
60cm cable - Cat. WA-5416
70cm cable - Cat. WA-5420

WERE \$5.95 SAVE 50%
NOW \$2.97 each
STRAIGHT ENTRY
30cm cable - Cat. WA-5434
40cm cable - Cat. WA-5438
50cm cable - Cat. WA-5442

WERE \$4.95 SAVE 50%
NOW \$2.47 each
STRAIGHT ENTRY
60cm cable - Cat. WA-5448
70cm cable - Cat. WA-5452
80cm cable - Cat. WA-5456
90cm cable - Cat. WA-5460

WERE \$5.95 SAVE 50%
NOW \$2.97 each
COIL TO DISTRIBUTOR STRAIGHT
30cm cable - Cat. WA-5474
40cm cable - Cat. WA-5478
WERE \$4.95 SAVE 50%
NOW \$2.47 each
COIL TO DISTRIBUTOR STRAIGHT
60cm cable - Cat. WA-5482
WERE \$5.95 SAVE 50%
NOW \$2.97

Cat. XC-0112
TRADITIONAL MECHANICAL TRAVEL CLOCK
WAS \$12.95 SAVE 25%
NOW \$9.95



Cat. AA-0300
30+30 WATT STEREO AMP
INCLUDING PRE-AMP
★ Fully built and tested
★ Separate bass, treble, balance and volume controls
★ Less than 0.1% distortion
★ Mic, phono and aux inputs (line)
★ Power supply components on board
★ Just connect a transformer, speakers, a signal

**WAS \$49.95 SAVE 15%
NOW \$42.45**

**MINIMUM 15%
OFF EVERYTHING
- SAVE UP TO 70%!
SORRY! NO Backorders. Sale only applies to
goods IN STOCK during sale**

ABS PLASTIC CONSOLE BOXES WITH
ALUMINIUM LID
215(w) x 130(d) x 47(h) x 73(h)mm
Cat. HB-6210 - ORANGE
Cat. HB-6211 - GREY
Cat. HB-6212 - BLUE
**WERE \$16.25 SAVE 50%
NOW \$7.95 each**

BLUE COLLAR WORKER BRIEFCASE

This great new Australian made metal parts/tools carry case is
suitable for just about all tradesmen. From plumbers, electricians,
carpenters to security technicians, builders and electronic servicemen.
Advantages include easy storage, easy handling - each compartment
seals tight when closed. One long compartment for tools. Rack
available soon for mounting 2 units in a vehicle. Quality powder
coated green enamel.
Size 362 x 365 x 80mm
Cat. TB-2000

**ONLY \$49.50
WILL LAST FOREVER!**



Cat. MS-4010
SQUEEKY CLEAN MAINS FILTER x4
**WAS \$125 SAVE 15%
NOW \$106.25**

Cat. MS-4102
SQUEEKY CLEAN MAINS FILTER x1
**WAS \$39.50 SAVE 25%
NOW \$29.00**



Cat. XE-4950
UV EPROM ERASER
**WAS \$99.50 SAVE 20%
NOW \$79.50**



MAIL ORDER
HOTLINE
(02) 747 1888

MAIL ORDER
HOTLINE
(02) 747 1888

GREAT SPECIALS!

NEW Low cost Robot Kit

Ref. EA January 1986

This is a true 5-axis pick and place robot with substantial payload
capability that you can connect direct to your P.C. But the best feature is
THE PRICE! You can build the mechanical kit which includes motors, bearings,
arm components, pulleys etc for just \$189! The full construction
manual is just \$10 extra. The motor drive electronics, computer
interface and power supply are also available.


COMPLETE MECHANICAL ROBOT KIT Cat. KA-1625

ONLY \$189.00

COMPLETE CONSTRUCTION MANUAL Cat. BI-8015

ONLY \$10.00

Call in to any Jaycar store or watch next months ads for further details



NEW AM-STEREO/FM-STEREO WIDE BAND TUNER

Ref. EA Dec/Jan onwards

What can I say - it's a world beater. If you want THE BEST at any price
We will not have the kit in stock in January (due to metalwork delays
over Xmas) but it should be available mid-end Feb.

Cat. KA-1635 INTRODUCTORY PRICE

\$399 COMPLETE Remote extra.



"PEST OFF" Ultrasonic Pest Repeller

Ref. EA November 1985

A mozzie season special. See November EA for more info.
Cat. KA-1620

ONLY \$39.95



NEW Mini FM Transmitter

Ref. ETI

Great stable and compact FM transmitter. Tiny!
Cat. KE-4711

ONLY \$8.95



NEW 145 Watt Mosfet Amp

Ref. EA October 1985

This is the high power mono Mosfet amp version of the Playmaster 200.
The shortform amp kit includes all parts except the heatsink
extrusion/bracket which is available separately.

Cat. KA-1622

ONLY \$89.50

NEW CD Attenuator

Ref. EA January 1986

This project enables you to dub from a compact disc to a cassette
without overloading. It attenuates the signal to accommodate the smaller
dynamic range of the cassette medium. Kit includes case
Cat. KA-1624

ONLY \$7.95

Jaycar ELECTRONICS

Incorporating ELECTRONIC AGENCIES

Carlingford, Hurstville, Gore Hill, Brisbane, Mon-Fri 9am - 5:30pm
Sydney and Concord, Mon-Fri 8:30am - 5:30pm
Sydney, Carlingford, Hurstville, Thursday nights until 8:30pm
Brisbane, Thursday night until 8pm
Sydney, Carlingford, Hurstville, Brisbane, Saturdays 9am - 12 noon
Gore Hill, Saturday 9am - 4pm

CONCORD NOT OPEN ON SATURDAYS

NUMBER 1 FOR KITS

N.S.W.
SHOWROOMS

SYDNEY: 117 York Street Tel. (02) 267 1614
CARLINGFORD: Cnr Carlingford & Pennant Hills Road Tel. (02) 872 4444
CONCORD: 115/117 Parramatta Road Tel. (02) 745 3077
HURSTVILLE: 121 Forest Road Tel. (02) 570 7000
GORE HILL: 188/192 Pacific Highway (Cnr Bellevue Avenue) Tel. (02) 439 4795

QUEENSLAND
MAIL ORDERS:
HEAD OFFICE:

BURANDA: 144 Logan Road Tel. (07) 393 0777
P.O. Box 185, CONCORD 2137
115-117 Parramatta Road, CONCORD 2137
Tel. (02) 747 2022 Telex 72293

POST & PACKING

\$5 - \$9.99	\$2.00
\$10 - \$24.99	\$3.75
\$25 - \$49.99	\$4.50
\$50 - \$99.99	\$6.50
\$100 - \$199	\$8.00
Over \$199	\$10.00

COMET ROAD FREIGHT ANYWHERE IN AUSTRALIA ONLY \$13.50



**MAIL ORDER VIA
YOUR PHONE**

Playmaster AM/FM stereo tuner

also accepts the detected audio signal from pin 15 of IC2. This signal is fed via two $2.2\mu\text{F}$ capacitors to pins 2 and 19.

VR6 sets the frequency of the VCO which forms part of the phase locked loop. The PLL locks onto the transmitted 19kHz stereo pilot tone and drives an electronic switch at a 38kHz rate to decode the stereo information.

Q9 connects to the forced mono input (pin 4). When Q9 is on, the input is pulled low and the VCO is stopped, thus forcing mono reception.

The $50\mu\text{s}$ de-emphasis components are at pins 14 and 15. The parallel $15\text{k}\Omega$ and $22\text{k}\Omega$ resistors set the output level.

The left and right channel audio outputs appear at pins 13 and 12 and are AC-coupled to 19kHz notch filters based on L18, VR7 and L19, VR8. Adjustment of the notch filter frequency in each channel is by means of a tuning slug in the relevant inductor, while the associated trimpot adjusts the sharpness and depth of the null.

Following the notch filters are two simple third order low pass filters based on IC8b and IC8c. These roll off the response above 19kHz to remove the residual 38kHz switching components.

The resulting left and right channel audio outputs appear at pins 7 and 8 and are fed to pins 11 and 4 of IC13.

Audio switching

IC13 is a 4052 analog multiplexer/demultiplexer used here as a 2-pole

3-position switch.

The A and B inputs control the switch input selection. Input A selects either the AM or FM audio inputs. When A is high, the FM audio at inputs 3X and 3Y are fed through to the outputs at X and Y. When A is low, the AM inputs at 2X and 2Y are fed to X and Y.

Input B is the mute input and selects either the 0X, 1X or 0Y, 1Y inputs which are all connected to ground. Thus, when B is low (ie, during tuning), the audio inputs are tied to ground and the outputs at X and Y are muted.

Inverting op amps IC8a and IC8d buffer the X and Y outputs of IC13. These each have a gain of 1.44 and provide a nominal 450mV RMS audio output signal.

Microprocessor control

The A and B control signals for IC13 are derived from IC1 which is the NEC microprocessor. In the case of the A input, the control signal is applied from pin 29 via inverters IC9d and IC9e. The B input is direct driven by pin 2.

IC9e also drives Q10, Q11, Q12 and Q13 to switch the power supply rails to the AM and FM tuners. When pin 13 of IC9e is high, Q12 and Q11 are turned on and power is supplied from the +12V regulator to the FM tuner.

When pin 13 of IC9e is low, Q12 and Q11 are off and Q13 is on. This switches on Q10 so that power is now applied to the AM tuner.

Pin 30 of IC1 (ST) controls mono/stereo

switching of the AM and FM tuners. When the tuner is switched to mono, pin 30 goes high and the output of IC9b goes low to switch on the mono LED indicator.

Assuming that FM is selected, Q9 also switches on and pulls pin 4 of the FM stereo demodulator (IC3) low. If AM is selected, pin 7 of IC9b goes low and pulls pin 9 of the AM stereo demodulator (IC4) low via D8.

Pin 9 of IC4 is also connected via D7 to the mute output of IC1. This forces pin 9 low during muting, and enables stereo reception almost immediately a station is received. Without this feature, the decoder would detect noise during tuning and go into a long count mode before switching to stereo.


Control loop

The synthesised control loop for the AM and FM tuners involves local oscillator buffer stages Q16 and Q17, dual modulus prescaler IC11, and error output buffer stage Q15 and Q14.


Pin 11 of IC1 drives the error output buffer. It controls the buffer such that, if the local oscillator frequency is lower than the internal reference frequency, the error voltage is low and Q15 and Q14 turn off.

Conversely, if the local oscillator frequency is greater than the internal reference, the error voltage goes high and Q15 and Q14 turn on. When both frequencies are equal, the error output floats (ie, goes open circuit).

A high voltage supply for the error output buffer is derived from an LM317T 3-terminal adjustable regulator. The $2.7\text{k}\Omega$ resistor connected between the adjust terminal and ground sets the output of the LM317 to +30V. Q15 and Q14 then set the tuning volt-



The new Playmaster tuner is built into a slimline rack-mounting case fitted with a screened front panel.



FM STEREO TUNER

NUMBERS IN BRACKETS CONNECT TO SIMILAR NUMBERS ON OTHER CIRCUITS

VIEWED FROM BELOW

Playmaster stereo tuner

age applied to the varicap diodes in the tuner front ends.

Q16 and Q17 buffer the FM and AM local oscillator outputs. For FM, buffering is achieved using FET Q16 which has L20 as its drain load. This stage drives IC11 which divides by either 16 or 17, depending on the modulus control output from IC1 (pin 16).

The output of IC11 is fed to the FM oscillator input of IC1, divided by an internal programmable divider, and compared with the reference frequency, as discussed last month.

Multiplexing

Apart from synthesis control, IC1 also drives the multiplexed display. D1-D6 are the digit driver outputs while the segment driver outputs are from Sa and Sg.

The D1-D6 outputs are fed to Schmitt trigger inverters IC12a to IC12f and these drive transistors Q18-Q23. Q19-Q22 switch the display digits while Q23 switches the memory indicator LEDs. Q18 switches the FM and AM LED indicators.

The Sa to Sg segment outputs drive

the display via 75492 display drivers. Note that 10k Ω resistors are connected in series with the inputs to these drivers. These reduce the current drawn from the segment outputs of IC1 and thus help reduce the multiplex noise induced into the tuner circuitry.

In addition to driving the display drivers, the Sa, Sb, Sc, Se and Sf segment outputs are also connected via diodes D28-D32 to the switch matrix. The other side of the switch matrix is connected to the K0 to K3 inputs of IC1. These inputs are normally held low with the 5.6k Ω resistors.

When a switch is closed, a high output from one of the segment outputs will pull K3, K2, K1 or K0 high, depending on the particular switch pressed.

Diodes D33-D36 select the various programmed options in IC1. For example, D36 ensures that memory indication is by way of separate LEDs. Without this diode, the memory display output would be in 7-segment format.

Power supply

The tuner circuitry requires several rail voltages and these are derived from a PL24/20VA transformer (shown on the AM tuner circuit).

First, an unswitched positive supply rail is provided by a full wave rectifier circuit consisting of D11, D12 and a 470 μ F filter capacitor. This provides the standby power for the 5V regulator connected to the VDD and INT-bar pins of IC1.


A 47,000 μ F (.047F) super capacitor is also connected to these pins via a 680 Ω resistor. Diode D27 isolates the super capacitor from the regulator output. The supercap retains the station settings in memory when power is removed from the circuit.

Following the power switch is a bridge rectifier (D13-D16) which supplies +15V and -17V rails. These unregulated DC rails drive several 3-terminal regulators to give regulated \pm 12V rails and two +5V rails.


Note that ICs 6,7,8, & 13 are supplied with power via isolating diodes. This has been done to provide a slow turn-off, thus preventing thumps in the audio output when the tuner is switched off.

Diodes D17, D18 and their associated capacitors function as a voltage doubler. The output of the doubler appears at the cathode of D18 and supplies a nominal +51V rail to the LM317 30V regulator.

That completes the circuit description. Next month we will describe construction and alignment.



This graph plots the bandwidth of the AM tuner. The response is 3dB down at 5.5kHz, with a deep notch at 9kHz due to the whistle filter.



This graph plots the performance of the FM tuner. Ultimate signal-to-noise ratio is 75dB in mono and 70dB in stereo.

ALTRONICS

COMPONENTS

Premium Quality Products Direct From the Importer — You Save

Full 12 Months Warranty

Sensational Labtech

Dual Trace 20MHz CRO With Component Tester Now Under \$700!

Definitely Australia's Best Value in Quality Oscilloscope Test Equipment — Just Look at the Facilities

The Inbuilt Component Tester Alone Is Over \$300 Value.



DESCRIPTION:

This model is a dual-trace 20MHz Oscilloscope using high brightness CRT. The vertical amplifiers have high sensitivity of 5mV/Div and the frequency characteristic response with the smooth roll off exceeding 20MHz. The highest triggering sweep speed is 0.2 usec/Div. For component test, special circuit is designed, with which a single component or components in or out of actual circuit board can be easily tested, requiring no power to drive the circuit. The display shows fault of components, size of a component value, characteristics of component, and half-dead components under dynamic test.

FEATURES:

- Component Tester • Wide bandwidth & high sensitivity • Very low power consumption • High sensitivity X-Y mode • Z axis (intensity modulation) • Front panel electrical trace Rotator • Regulated power supply circuit for Accuracy

ALTRONICS FAMOUS SATISFACTION GUARANTEE

We are delighted with our new Labtech Q 0155 Oscilloscope and Component Tester and naturally we are confident you will be too — However, if for any reason you are less than 100% satisfied with your new Labtech CRO you may of course return it to us (in original condition with all instructions, packaging etc.) within 14 days for a full refund less transport costs.

Q 0155 Value **\$699**

Highly Recommended For:

Service Workbench, Design Laboratory, Manufacturers, Universities and the dedicated Enthusiast.

Labtech Test Equipment for Life

Just Compare with Professional DMM's Costing \$150 and More!

Brilliant New Digital Multimeter—Autoranging with Memory Function for Relative Measurements.




Q 1075

- Auto-Range Operation for Voltage and Resistance Measurement - Two User Selected Current Ranges: 20mA or 10A • 3-1/2 Digit Resolution in Auto-Range Mode: 1/2000 • Extended Resolution in Manual Operation: 1/3000 • Triplex (1/3 Bias) LCD Display Decimal Point & Function Annunciator Drive • Five DC Voltage and Ohm Range: 200mV to 1000/200 ohm to 2M ohm • Four AC Voltage and Low Power Ohm Range: 2V to 750V/2K ohm to 2M ohm • AC/DC Voltage and Current measurements with On-Chip AC to DC, Operational Amplifier • Low Power Ohms Model Limits Open Circuit Voltage for In-Circuit Resistance Measurements • Visual Overrange Indication-Plus Audio Tone in Current/Voltage Measurements • CMOS Technology Limits Power Dissipation: 7mW

DCV Accuracy 0.5%+1DGT
ACV Accuracy 0.75%+5DGT
Input Impedance 10M
O/Load Protect. 1100V DC

Amazing Value \$89.95

TYPICAL COMPONENT TEST STATUS PATTERNS



Probe Sets

1:1 or 10:1 Attenuation

Q 0175

\$39.50



LOGIC PROBE

Q 1272

WAS \$34.95

* Directly powered from circuit under test (5V)
Tested to 12.6 MHz • DTL/TTL — CMOS Threshold selector • Circuit loading 30UA approx. • High-Low — pulse or memory led indication. Impulse mode pulse length is extended to enable visual observation. In memory mode any detected level is continuously displayed until reset.

ECONOMY RACK CABINET

- Solid Steel Construction
- Black anodised front panel
- 3 unit (132mm)
- Conforms to International Standards
- Ventilated top and side panels



H 0400 ONLY

\$49.50

\$45

SPEAKER 8 OHM 2 1/4 INCH



From 69c

C 0610

1 - 9 10 - 99 100 up
\$1 90c 69c

Free Holster This Month (Normally \$9.59)

What's this? For want of a better name we've named this thick rubber "Cliparound" protector a "Holster". Great protector for field use, dropping on concrete floors etc — will keep your precious Labtech Q 1075 looking brand new for many a year! Cat. No. Q 1077



Sensational Book Set Offers on Motorola and National Semiconductor

The super low prices on the sets are for Jan-Feb 86' only — or until current stocks are gone. As we expect next book deliveries to be 25-30% dearer we definitely cannot repeat this offer or accept back orders at these prices when current stocks are gone.

MOTOROLA SEMICONDUCTOR

NATIONAL SEMICONDUCTOR

MOTOROLA MECL DATA

Emitter Collector Logic (ECL) is today's fastest form of digital logic providing the most direct way of improving system performance. This previously hard to get manual provides data on the 10KH, 10K and III families. MECL memory and PLL CHIPS.

B 1100 ... \$11.95

MOTOROLA POWER DATA

Motorola are the undisputed world leader in power transistors. Renowned for their low cost and reliability. Book includes a 9 page selection guide, application notes and data sheets for over 700 devices. 989 pages.

B 1101 ... \$19.95

TMOS DATA

This manual is intended to give the users of Power Mosfets basic information on the products, application ideas and data sheets of the broadest line of Mosfets. With over 225 device types in 11 package configurations currently available from Motorola.

B 1102 ... \$11.95

MOTOROLA MASTER SELECTION GUIDE

The most useful book ever printed covers MOS IC's listed by function. LINEAR IC's listed by function. INTERFACE IC's listed by function. LSI memory, TTL ECL power products, SCR's, diodes, transistors listed by application and ratings. Essential data given for all devices. Terrific Value.

B 1104 ... \$7.95

MOTOROLA CMOS DATA

A comprehensive reference covering 40XX, 45XX CMOS family's along with speciality devices such as LCD drivers, telephone and general communication functions and industrial control. 962 pages essential in all spheres of electronics.

B 1105 ... \$12.95

SCHOTTKY TTL DATA

Essential reference for the enthusiast and engineer alike. Designing, building and servicing digital circuitry is an absorbing pastime. Data for the LS, ALS and FAST families along with design considerations and circuit characteristics are logically presented in this manual, making it quick and easy to use.

B 1109 ... \$11.95

MOTOROLA MEMORY DATA

An absolute must for the microprocessor buff. This is the latest reprint of Motorola's famous memory data manual and includes the latest specifications and design application data on TTL RAM, TTL PROM, MECL MEMORY, MECL RAM, MECL PROM, MOS STATIC RAM, MOS EPROM, MOS EE PROM and MOS ROM. Worth many dollars more.

B 1113 ... \$11.95

LINEAR & INTERFACE DATA

Popular data manual. At last readily available. Includes Data design procedures and equivalent listings for 1000's of devices under headings OP AMPS, VOLTAGE REGULATORS, CONSUMER CIRCUITS (e.g. T.V. automotive power), HIGH FREQUENCY CIRCUITS and SPECIAL PURPOSE CIRCUITS. Gives data, design procedures and equivalent listings for MEMORY/MICROPROCESSORS SUPPORT LINE DRIVERS/RECEIVERS, TELEPHONE COMPARATORS, VOLTAGE REFERENCE AND DATA CONVERSION DEVICES. Includes comprehensive selector guide.

B 1114 ... \$22.95

MOTOROLA 8 BIT MICROPROCESSORS AND PERIPHERALS

This manual covers all aspects of Motorola's microprocessor, micro-computer and peripheral components. A clearly written manual providing all the data necessary to design and build a working computer system from scratch. 100's of circuit examples, flow charts, truth tables and programme routines.

B 1125 ... \$16.95

INTERFACE

This data book provides complete specifications for a variety of transmission line drivers/receivers, peripheral power drivers and level translators/buffers. Product selection guides list applications information and operating features. Memory, dynamic memory, micro-processor, data communications and disk support products are also covered in the data book. The interface appendix section contains cross reference guides, the programmable logic section describes the technology, design and gives application suggestions.

Pages: 1520 Year: 1983

B 1005 ... \$13.50

DATA CONVERSION ACQUISITION DATA BOOK

The 1984 edition of the Data Conversion/Acquisition Data book is one of the most comprehensive in the industry. It contains specifications for high technology conversion products in the analog signal path, both preceding and following the conversion process. Combining high volume production capability with leading edge technology such as thin film resistors, laser trimming and advanced micro CMOS and bipolar processing, has helped develop products best suited to your design needs.

Pages: 1232 Year: 1984

B 1007 ... \$13.50

LOGIC DATA BOOK

National's new Logic Data Book covers five of their logic families TTL (54/74) Schottky (54S/74S) low power Schottky (54SL/74SL) high speed (54H/74H) and low power (54L/74L). The Logic Data book — especially organised for quick and easy referencing — offers two complete functional indices and selection guides. One for SSI and one for MSI devices. In addition, it includes over 100 connection diagrams and test waveforms to help speed the design-in cycle. All in all, it's probably the most comprehensive collection of practical information ever assembled on such a broad line of practical components.

Pages: 550 Year: 1981

B 1015 ... \$11.00

LINEAR DATA BOOK

The 1982 edition of the National Semiconductor Linear Data book is the most comprehensive available. It presents approximately 2000 pages of specifications for our high-technology linear products. Applications, descriptions, features and diagrams in this data book include detailed sections for Voltage Regulators, Op Amps, Voltage Comparators, A to D, D to A Converters, Industrial Blocks and Audio and TV Circuits. The data book also features advanced telecommunications devices and speech synthesis (DIGITALK). Plus other non state-of-the-art linear products offering performance, economy, quality and reliability.

Pages: 1552 Year: 1982

B 1010 ... \$15.00

LINEAR SUPPLEMENT

The 1984 Linear supplement provides the most recent information on National's new linear products. This supplement also provides a comprehensive index published in the Master Data book. New products designed are indicated by an Asterisk and in bold type. Revised data sheets are listed in bold type. National's supplement data book system allows you to make product selections of their latest product offerings.

Pages: 566 Year: 1984

B 1011 ... \$7.50

MOS MEMORY DATA BOOK

The 1984 MOS Memory Data book is a comprehensive collection of information advanced, high-density memory products covering the spectrum of this mainstream semiconductor component category. National Semiconductor has an array of advanced technology processes to apply to memory design and development. These range from high-density triplepoly process used in the most advanced RAMs, the small-geometry, silicon gate, oxide-isolated micro-CMOS technology which is now being applied to high performance memory devices for the first time.

Page: 256 Year: 1984

B 1025 ... \$7.50

CMOS DATA BOOK—1984

The CMOS Data Book contains the industry's most comprehensive collection of high-performance CMOS products available. Our early commitment to micro-CMOS technology has made possible the development of a broad spectrum of advanced devices that will simplify your design and ensure state-of-the-art systems. Micro CMOS technology describes

National's array of small-geometry, silicon gate, oxide-isolated processes used to build the products in this book. Using N- or P- well substrates and multiple-layer metal or polysilicon-interconnect structures, micro CMOS processes feature sizes of 3.0, 2.0, or 1.5 microns, with submicron feature sizes in development.

Pages: 1520 Year: 1984

B 1030 ... \$13.50

HYBRID PRODUCTS DATA BOOK

The Hybrid Products Data book is the only National Semiconductor publication that contains complete information on all our hybrid semiconductor products. Included are precision thin film and thick film products which provide the user with standard functions from operational amplifiers to converters with capabilities beyond those of current monolithic technology. Product selection guides and an application section are also included.

Pages: 792 Year: 1982

B 1045 ... \$9.95

TRANSISTOR DATA BOOK

National Semiconductor has added many new transistors and product families since publication of the last data book. Many have already been widely acclaimed by users. In addition to small-signal, power-pipolar and field effect transistors that have been the mainstay of our catalogue, there is a section for multiple-field-effect transistors. More part numbers will be added as market needs expand. To keep current on all new National transistors, please contact your National sales representative or franchised distributor and ask to be placed on the customer mailing list.

Pages: 558 Year: 1982


B 1050 ... \$9.95

VOLTAGE REGULATOR HANDBOOK

With the variety of fixed and variable regulator technology currently available, the 336 page Voltage Regulator Handbook becomes a must for the selection of three terminal and dual tracking components that meet the system requirement while utilizing the most cost effective approach. Beginning with product selection procedure and a data sheet summary, the text continues with easily accessible information about booster circuitry, power transformer and filter specifications, test methods, manufacturers' cross reference and extended use applications for National's regulators.

Pages: 336 Year: 1982

B 1055 ... \$9.95



**Buy the Set of 9
Motorola Titles Only \$79**

**Buy the Set of 10
NatSemi Titles Only \$79**

**SAVE
\$50**

**SAVE
\$32**



VINYL BINDER BARGAIN

Holds 12 magazines, each on a spring out wire rod. Just the shot for each year's set of Electronics Australia, ETI or any of your favourite magazines. Suits all A4 size publications (275 x 210). Very smart Royal Blue colour with beautiful gold embossing.

B 9999 \$5.00 each

10Up \$4.50

We'll Pay You \$5 Cash!

We promise you ★ Product Quality ★ Speediest Delivery in Australia
 ★ Careful Packaging ★ Friendly, technical advice when you require it.
 If we fail you may return your purchase to us for a full refund ★ Plus \$5 for your trouble.
 ★ Less Transport Costs.



New PCB Mount Mains Transformers



7/9 VA Rating. Super Compact, wound on Grain Oriented Steel Core for High efficiency and low temperature rise.

Power Rating:

7VA Load Full voltage +3% - 0%
 9VA Load Full voltage -6% to 8%

Model Prim/SEC's 1+2

M 7012	240/6+6
M 7015	240/7.5+7.5
M 7018	240/9+9
M 7024	240/12+12
M 7030	240/15+15

Overall Height 35mm
 Length 43mm
 Width 36mm

1—9	\$9.80 ea
10—24	\$9.20 ea
25 Plus	\$8.40 ea

240V Mains Power From Your 12V Battery 300 Watt Inverter with Auto Start

(See EA Sept. '85)
 Just think how handy it would be to have 240 Volt AC Mains Power when camping, or for your Boat or Caravan—Well this brilliant new design from Leo Simpson and the design Team at Altronics Australia is the answer.



• Auto Start draws power from your battery only when appliance is plugged in and "turned on" i.e. battery can be left permanently connected if desired • Thermal Over Load • Current Regulated • Current Overload

Complete Kit	K 6752	\$199.00
Fully Built and Tested	K 6754	\$249.00

Treat yourself to the Greatest thing to happen to AM in 60 years

AM Stereo Sensation

★ Am Stereo ★ FM Stereo ★ Auto Reverse Tape Deck



Amazing Price \$189.00

Delightful AM Stereo is now yours for an unbelievable price. This Top Quality Roadsound RCR 760 Stereo AM and FM Receiver boasts 8 watts per channel and high grade Auto reverse tape deck (Metal Compatibility) C 9122

Look At This Superb Quality Nicad's From an Incredible

\$1.50

1—9	\$2.20
10—99	\$1.80
100 plus	\$1.50ea

Save Up to 50%
 Cat S 5020



Solar Energy Kit

Natty Solar Kit—Solar cell converts sunlight to electrical energy which in turn drives motor/propeller. Includes fantastic little booklet on Solar experimentation. Just the shot for school projects. Free energy from the sun. Educational — Great Fun.



A 0960
 Only
 \$12.50


Ideal for the Kids

BICYCLE COMPUTER

INCREDIBLE 12 FUNCTION

For a few dollars more than a digital speedo this superbly accurate computer provides every activity readout the enthusiast cyclist is ever likely to require.

\$49
 Cat No. D 2050




★ Instantaneous Average & Peak Speed Readouts. ★ Measures Calories Used per Trip. ★ Measures Distance. ★ Clock, Stopwatch and journey time

(whilst Mobile) ★ Miles or Kilometres ★ Pacer Tone and Performance Monitor ★ Dual Display ★ Easy Removal for Security ★ Fits to Bike in minutes.

Famous Sparkrite (UK) Electronic Ignition

Bargain of 1985 — Limited Stocks



A basic transistor assisted Electronic ignition system. Keeps ignition in tune. Stops arcing of points, greatly increasing point life. Gives easier starting and smoother running. • Built in timing light • 3 Pos switch to immobilise vehicle and for switch back to conventional system • Only 4 wires to connect • Mounting screws supplied • Fits all 12V neg.earth vehicles including Motorcycles. Full instructions supplied. Cat A 0095

Now \$24.50

Low Power Design also Works as a Battery Charger

12/240v Inverter for Small Appliances

Cat K 6705




\$69.50

The inverter is ideally suited to powering low wattage mains appliances from the car battery while camping. This considerably improves the comfort level of the civilised camper. Similarly, it has uses in boating. Typically, it can be used to power an electric shaver, electric blanket, electric can opener or a 40W light bulb. Alternatively, back in the home (or still on the camp site), frequency sensitive items such as belt or idler driven turntables can be powered at a very precise crystal controlled frequency for accurate sound reproduction. If speed variation over a small range is required, then a switch is provided to change from the crystal based 50Hz signal to a variable oscillator.

Price Break through Solar Cell Array 18V @ 7 Watt

Brilliant New Solar Array at an amazing price. Yes, for less than \$90 we now have just the handiest Solar Modules available (why pay Dick Smith \$239 for a measly 3 additional watts?? Superb for Powering or Charging 12 - 15 Volt circuits - Now there's no excuse for that flat Car, Boat or Caravan Battery. Solar Cells are fixed to a fibre board, front covered with tough EPS and rivetted into stainless steel frame. Cat A 0220



Amazing Price Break Through \$89.95

STATE OF THE ART TOROID POWER TRANSFORMERS



For the same price as your common garden heavy, bulky, buzzing iron (any old iron at that!) transformer you can now design in a superb Toroid Power Transformer from Altronics.

Why a Toroid?

- Smaller size and weight to meet modern "Slimline" requirements
- Low electrically induced noise demanded by compact equipment
- High efficiency enabling conservative rating whilst maintaining size advantages
- Lower operating temperature
- Simple, quick single bolt mounting

Cat No.	Sec V	VA	Ea.	10Up
M 3050	12V + 12V	160W	45.00	43.50
M 3060	25V + 25V	160W	45.00	43.50
M 3065	30V + 30V	160W	45.00	43.50
M 3070	35V + 35V	160W	45.00	43.50
M 3075	40V + 40V	160W	45.50	43.50
M 3080	45V + 45V	160W	45.50	43.50
M 3085	12V + 12V	300W	55.00	52.50
M 3088	25V + 25V	300W	55.00	52.50
M 3090	30V + 30V	300W	55.00	52.50
M 3092	35V + 35V	300W	55.00	52.50
M 3100	40V + 40V	300W	55.00	52.50
M 3105	45V + 45V	300W	55.00	52.50

The toroidal transformer is now accepted as the standard in industry, overtaking the obsolete laminated type. Industry has been quick to recognise the advantages toroids offer in size, weight, lower radiated field and, thanks to Altronics—Low Price.

DIMENSIONS

Diameter 110mm
Height 42mm (160VA Models)
52mm (300VA Models)
Leads 200mm length

Made in UK
Quality


Highly Recommended For:

- Audio Amplifiers • Power Supplies
- Microprocessor/computer equipment

MANUFACTURERS AND BULK USERS PLEASE CONTACT OUR WHOLESALE DEPT. FOR BULK QUANTITY RATES.

Silky Quiet Commonwealth Industrial Corp.

240V Computer Fans
Sealed Sleeve Bearings for long life ★
Sturdy die cast Frame ★ Operating range - 10 deg C to +70 deg.C



Two Models

F 1020 80mm \$19.50
F 1030 110mm \$19.50

Desk Mounted Lamp Magnifier



Only \$169

If you have trouble with fine PCB work or component identification but still want both hands free, this is for you. We thoroughly recommend this quality Australian made product.


TECHNICAL INFORMATION Illumination:
22W Fluorescent Weight: 8.16kg Lateral Extension: 254mm Vertical Extension: 254mm Fixing: Heavy table base (grey & Ivory) with two chrome plated flexible arms. Cat A 0980

Your on Your Way Home from the Office Party, Doing Just a Few K's Over the Limit and You'd Never Guess Just Who's Over the Hill (Unless of course you're already the proud owner of one of these Brilliant Superhet R/D's)


MICRO RADAR DETECTOR-CLIPS ONTO SUNVISOR (INVISIBLE FROM OUTSIDE THE CAR)

Now X band, K band stationary, gun or even Mobile Radar are detected up to an amazing 13Km with the all new "Space Age" Micro Computerized Radar Detector. The very 1st in the world to utilize a custom microprocessor—hence enabling quite incredible sampling/checking detection of incoming signals—and what's more it's so light and compact it simply clips securely on to your sunvisor out of sight of anyone outside the vehicle.

- Detects Mobile Radar equipment even monitors the pulse which is sent to the road from the Police vehicle to enable them to accurately calibrate their own speed • Highway/City Mode switch allows monitoring of City or Highway conditions. By measuring and storing the field strength of each microwave sample taken from the source, the computerized radar will automatically, whilst in City Mode, discriminate between Microwave Alarm Systems and Radar Traps etc. — 21 Day Money Back Guarantee Unconditionally Guaranteed to out perform any other detector you've ever tried or your money back—absolutely no quibbles whatsoever.



Cat A 0920
\$399



12 Key Keypad (Commercial Grade)

These sturdy keypads were previously standard supply on STC telecom phones—so naturally the quality speaks for itself—Brand new fully assembled with PCB and 8 way wiring harness. Just the shot for microprocessor assemblies, combination locks etc.etc. A 0495

1—9 \$3.95 10—24 \$3.00 25Up \$2.50

Ultrasonic Insect and Pest Repeller \$49.50


PESTREPELLER is effective in controlling mice, rats, roaches, flees, flies, crickets, silverfish, waterbugs, moths, ants and most other common pests. Laboratory research has shown ultrasonic sound waves attack the auditory and nervous systems of most common pests causing them pain and discomfort 130 decibels of sound waves are out of the range of hearing of humans and most household pets such as dogs, cats, fish and birds and farm animals. **Specifications—Dimensions:** 100 x 90 x 80 **Power Supply** adaptor supplied 240/9V **Frequency Range** 30KHz to 65KHz variable **Output level** 130db Cat A 0083

BLOOD PRESSURE & HEART RATE MONITOR

Why Risk Unnecessary Heart Attack?

A superb Gift for the dedicated fitness enthusiast **Absolutely essential** for those over 40 and concerned with their health, or on Fitness Therapy. Use this **easy to operate** Monitor, to measure your pulse (or heart rate) and Blood Pressure. Remember high blood pressure is in itself symptomless and the usual forerunner to future chronic heart disease. **Features** include "error" display warning of incorrect use. Handbook supplied will enable anyone in your family to be fully conversant with this monitor in minutes. Easy to read display of Systolic and Diastolic Blood Pressure and Pulse Rate. Cat X 3055

Don't Pay \$150 Now Only \$89



"ALTRONICS DEALERS AUSTRALIA WIDE CHANCES ARE THERE IS AN ALTRONICS STOCKIST RIGHT NEAR YOU. PHONE US NOW FOR DETAILS OF YOUR NEAREST ALTRONICS DEALER."

UV EPROM ERASER

Erase your EPROMS quickly and safely. This unit is the cost-effective solution to your problems. It will erase up to 9 x 24 pin devices in complete safety in about 40 minutes for 9 chips (less for less chips).

- Erase up to 9 chips at a time • Chip drawer has conductive foam pad • Mains Powered • High UV intensity at chip surface ensures thorough erase • Engineered to prevent UV exposure • Long Life UV tube • Dimensions 217 x 80 x 68mm • Weight 670 grams

Cat D 1450

ALTRONICS COMPONENTS

008 999 007 Toll Free
(09) 328 1599

Perth Metro Area
& After Hours Recorded Service
ALL MAIL ORDERS:
BOX 8280, STIRLING ST.
PERTH W.A. 6000


Toll Free Phone Order - Bankcard Holders can phone order toll free up to 6pm Eastern Standard Time. Remember with our **Overnight Jetservice** we deliver next day.

PACKING AND DELIVERY CHARGES


\$3.00 Delivery Australia Wide - We process your order the day received and despatch via Australia Post. Allow approx. 7 days from day you post order to when you receive goods. Weight limited 10Kgs.

\$5.00 Overnight Jetservice - We process your order the day received and despatch via overnight Jetservice Courier for deliver next day. Country areas please allow additional 24-48 hours. Weight limit 3Kg.

\$10.00 Heavy Heavy Service - All orders of 10Kgs or more must travel express Road - Please allow 7 days for delivery.



The Serviceman



Aversion therapy for the Sony KVA-1830AS receiver

It is probably true that most servicemen have an aversion to working on certain makes or models of sets. In many cases that can be justified on the basis of awkward physical design, insufficient data from makers, shortage of spare parts, and so on. But in some cases there is no real justification at all; just a blind prejudice based on hearsay horror stories, or an unfortunate first-time experience.

The truth is that few of us can afford to pick and choose on this basis; we have to take the good with the bad and what we lose on the swings we gain on the roundabouts. Maybe we do miss out once in a while but the benefit in goodwill and public relations usually more than compensates.

These comments were prompted by a set I handled recently and which, for no reason I have been able to discover, seems to have gained a reputation — quite undeserved in my opinion — of being difficult to service. So much so that some servicemen I know simply refuse to even look at them. Others accept them, but always reluctantly.

The set in question is the Sony KV-1830AS, along with the KV-2000AS. The 1830 model uses an 18in (46cm) Trinitron tube while the model 2000 uses a 20in (51cm) Trinitron. Apart from size the main differences are minor cabinet styling details. These sets first appeared on the market about eight years ago.

Just why they seem to have gained a poor reputation among some servicemen is not clear, and my own experience with them suggests that they are no more difficult to handle than the average set. However, in telling this story I will touch on some of the preliminary checks I have developed which assist considerably in pinpointing the general nature of a fault.

The story started with a phone call from the owner's wife, along the lines that their TV set was playing up. When I enquired as to the exact nature of the symptoms the best answer she could give was rather vague; as nearly as I could make out the picture was breaking up in some manner, although the

sound did not seem to be affected.

After a little more questioning I concluded that it did not seem to be an outside interference problem, or even an antenna problem, but almost certainly in the set itself. I also concluded that this would be no "15-minutes-in-the-lounge-room" type of repair; I would need to get it on the bench. In these circumstances, and because the customer lived some distance away, I suggested that they could save some costs if they could bring the set in themselves. This was readily agreed to.

Two symptoms

So the set was duly delivered and I eventually found time to switch it on and see what the trouble was about. The result only seemed to confirm my worst fears; that it wasn't going to be easy. There appeared to be two quite distinct symptoms, though whether they both originated from the same fault I had no way of knowing.

The first symptom I observed consisted of dots and streaks on the screen, rather similar to the effect caused by spasmodic arc-over somewhere in the EHT system, although I could hear nothing to confirm that this was actually happening. Then, as I watched, the second symptom appeared; quite marked variation in picture width, to the extent, at times, of 50mm or so on each side.

This effect was quite random; the width would decrease, jitter around for awhile, open out part way, decrease again, open out fully, and so on. At the same time the dots and streaks were playing havoc with the picture, but I couldn't be sure whether the effects were related or not.

I pulled the back off the cabinet and prepared to make some preliminary measurements. Fortunately, this model is reasonably easy to work on, contrary to what might be implied by those who reject it. My first check, as with most faults, is the HT voltage. This can often reveal a good deal about the likely nature of a fault.

In this set the HT rail should sit at about 135V and is easily checked at the output of the power supply at points F-3 or F-4. And this was the first clue. The value was anything but 135V, varying from a maximum of around 100V down to 90V. On this basis it was surprising that the picture width was holding as well as it was.

But why was the voltage varying? Was it a fault in the power supply, whereby it was unable to generate a steady voltage of the correct value? Or was there a fault somewhere in the set which was imposing a random load on the supply, thus causing it to fluctuate?

EHT checks

One possibility was a fault in the EHT supply system, a situation not unknown in these sets. Fortunately, it is a simple matter to check out this possibility, at least in general terms, by simply pulling out one plug. The horizontal deflection-cum-EHT system is a little unusual in this set, in that the normal line output transformer with EHT overwind is replaced by two transformers; the horizontal output transformer T801 and a step-up EHT transformer, T851, driven by T801.

T801, along with the transistor driver chain and associated circuitry, is accommodated on board E and connected to the rest of the system via five plugs, designated E-1 to E-5. The EHT transformer, T851, is mounted separately, along with the tripler and associated components, on the chassis. It is connected to the board via plug E-1.

So, if one suspects a fault in the EHT transformer, tripler, or associated components, it is a simple matter to isolate this section by pulling plug E-1. On more than one occasion when I have encountered a shut down power supply, pulling E-1 has been sufficient to bring the supply back on line, thus restoring the sound and normal behaviour in the rest of the set. It has then been a mat-

ter of replacing the transformer, tripler, or other faulty component. (Many servicemen who reject these sets are not aware of this simple check.)

In this case the effect of pulling the plug was negative; the HT remained low and fluctuating as before. This suggested another routine check I have found very valuable. This is to measure the total current being drawn by the set, and is relatively easy to perform on the power supply board (board F). There is a small choke, L604, on this board and it is a simple matter to break into the supply rail at this point.

Normal current consumption for this set is around 600mA and, in this case, it was somewhat less and fluctuating in sympathy with the rail voltage variations. More to the point, the test indicated that there was nothing causing excessive current drain, thus suggesting that the fault may well lie in the power supply itself.

From previous experience I mentally nominated a number of likely components on this board which have failed in the past. The first choice was several transistors, particularly Q607 (the main regulator transistor) and Q601 to Q605. Q606 and Q608 were, statistically, less likely contenders, but would have to be tested if all else failed.

Other likely offenders were three thermistors, TH601 and 603, which can become intermittent. Two other resistors were also suspect, namely R628 and R639 which are 1 Ω , 1W units connected in parallel. These can go high resistance and produce some wierd and wonderful effects in the regulator circuit.

If only because it was easiest I checked out the thermistors and the two 1 Ω resistors first. The thermistors are best checked by replacement, and this

check proved negative. The same applied to the two 1 Ω resistors.

Transistor checks

This left one of the transistors as the next likely suspect. Unfortunately, there are no short cuts to checking these. They have to be taken out and, as I have learned the hard way, it is not sufficient to simply check them in a tester. They can check OK but still refuse to work. The only real answer is replacement.

So I went through the ritual of replacing each of them, one at a time, and came up with a complete blank. Which more or less exhausted the possibilities based on previous failures; I would have to search further afield. Based on broad experience, rather than this particular set, my next suspects were the electrolytics.

Two of these were the main filter capacitors associated with the bridge rectifier, 120 μ F, 400V units designated C606 and C621. These were tested on a replacement basis, but I wasn't really surprised when they checked out OK. I was more suspicious of the very small values which, for some strange reason, seem to be the least reliable types.

So began the rather fiddly task of replacing each of the smaller electrolytics in turn. And, of course, Murphy was well to the fore. It was not until I had replaced almost all the units and came to C612, a 3.3 μ F device that I scored. On replacing this the HT rail voltage came up to normal and was rock steady. Even more gratifying was the effect on the set; the picture width was restored and, most importantly, the dots and streaks had vanished. In short the set was back to normal.

This was more than I had hoped for. I had assumed, when I found the faulty

HT rail voltage that this was almost certainly the cause of the width problem, but I imagined the streaks and dots were most likely from another cause. However, it seemed most logical to fix the power supply problem first, then look for the second fault, if there was one. As it turned out, I didn't have to.

Routine checks

After that it was more or less routine; a soak test with the HT rail under surveillance, followed by a routine once-over of controls and adjustments, and a grey scale check. Everything checked out and the set was returned to the customer, who was delighted with the result.

In fact, it turned out that he had been half inclined to write the set off, on the basis that it was a few years old and the fault looked, at least to him, to be pretty drastic. So there was another grateful customer.

But before we leave this story a few more comments about typical behaviour of this set, under fault conditions, may be helpful. I am referring particularly to the behaviour of the power supply under a fault condition somewhere else in the set. Based on experience, most of us have a pretty good idea of the broad nature of a fault by the way the power supply behaves; ie, whether it shuts down or hiccups.


If the power supply in this set shuts down it is a pretty good indication of an over-current condition; ie, a short or heavy load on the HT rail. The most likely cause is, as already mentioned, the EHT transformer, tripler, etc, and can be pinpointed by pulling plug E-1.

Should this fail the line board (E) and associated circuitry is the next place to look. One possible fault is a breakdown of the line drive transistor, Q901, an SCR type SG613. Failure of this device need not indicate any other failure in the set; they can simply fail spontaneously.

Another possibility is the failure of diode D806, the horizontal damper diode. This can become either short circuit or leaky. Similar comments apply to diode D807, rectifier for the G2 supply line. There are also some electrolytics on this board which seem to give more trouble than the rest; C809, C816 and C827 (C827 on KV-2000AS).

Supply hiccups

If the power supply should hiccup it is usually an indication of an under current condition. A typical cause would be a failure of the line drive transistor, Q901, but to an open circuit condition



Above: the power supply circuit for the Sony KV-1830AS TV receiver.

The Serviceman

rather than short circuit. A more complex situation would be excessive current drain on the line board, causing a shut down, followed by hiccups if this board is isolated by pulling plug E-3.

Such a situation could easily "throw" someone not familiar with the set, and particularly those more familiar with the older Philips and Kreisler sets — and others — which characteristically hiccup under over current conditions. I suspect that this behaviour could be another reason why the set has gained a reputation for being difficult to handle.

So there are some points for what they are worth. They are only a few compared with what could happen, but they are the more frequent ones. Together with power supply behavioural characteristics, they make things a little easier for anyone not familiar with this set.

Lightning strikes

To change the subject, here is a story from my colleague on the NSW south coast concerning an electrical storm and the quite unpredictable results of a severe lightning strike. It also gives a new twist to the old gag about lightning never striking twice in the same place. Anyway, here is my friend's story, more or less as he related it.

I was some distance away from my home base when this storm struck; about 15km away in fact, delivering several repaired sets to customers in that area. I had just carried the last set into the house and checked it out when the heavens opened and it rained by the bucketful. It was so bad that I didn't dare try to reach the van parked in front of the house; I would have been drenched to the skin in seconds. Instead I gratefully accepted a cup of morning tea and waited about half an hour for the rain to clear.

During that time there were several moderate lightning flashes, and one quite big one, but all were some little distance away, judging by the following thunder clap. On returning home I learned that the electrical aspect of the storm had been much more severe there than where I had been, and that there had been one extremely violent lightning flash with virtually simultaneous thunder.

However, nothing in the workshop or house appeared to have been damaged and I thought little more about it for about a week, when the first of several calls came in. And, as it ultimately tran-

spired, they were all within about a 2.5km radius of a central point.

In fact, this first call was the most distant one of those that followed, and the location was well out in sparsely populated open country. But it did have a reputation for lightning strikes. There is a pole transformer not far from this customer's home and, on two previous occasions, it has been totally demolished.

At the same time, these strikes have caused a lot of damage in his home; the TV set copped it on one occasion and his masthead amplifier on two occasions — it was literally blown to pieces in one case.

So I wasn't altogether surprised at the call, but I was a little at the victim. This time it was the customer's AM tuner, part of an elaborate AM, FM, tape deck, and amplifier stereo system. And it was his favourite because he was a sports follower and this was the only set

The TV set copped it on one occasion and his masthead amplifier on two occasions.

he had which would bring in his favourite Sydney station and Saturday afternoon sports results. This was really all it was used for, hence the delay in discovering the fault.

The equipment carried the HMV label but, I suspect, came from the General stable. It was some eight or nine years old and this worried me in case a vital component had been damaged for which there were no replacements. A quick inspection in the home confirmed that the AM tuner was completely dead but that everything else — the FM tuner, tape deck, disc player, amplifier, etc — was behaving perfectly.

A simple job

This was no job for the lounge room so I loaded it into the van and brought it back to the shop. In the event, the job proved relatively simple; everything was readily accessible and there was even a circuit diagram pasted inside the cabinet. It didn't take long to pinpoint the mixer/oscillator transistor as the culprit and, although a direct replacement was not available, a suitable substitute was found and fitted. It worked like a beaut and the customer's assessment was that it was better than ever!

But the interesting point is that this was the only device affected. The masthead amplifier, several TV sets, and the other sections of the tuner/amplifier

setup had all escaped. Why, and by what mechanism, did the strike seek out that particular transistor? Or was it just coincidence?

The next call came from a customer who lives only about 500 metres from the first customer, and this time it was the TV set that was in trouble, the picture from both local channels being described as "very snowy". The set was a quite new AWA Thorn Mitsubishi model, purchased less than 12 months previously.


A check with the field strength meter showed that there was plenty of signal coming from the antenna and it didn't take long to confirm that the front end of the tuner had been knocked out. I seldom tackle tuner repairs; I find it much more economical to send them to a tuner specialist in the city. So the tuner was removed and despatched, to be subsequently returned, refitted, and checked out satisfactorily.

But the TV set wasn't the only victim. The customer's phone line had been knocked out, as had that of his next door neighbour; one of the local amateur fraternity. And strangely enough, in spite of a multiplicity of antennas and sensitive equipment, plus the usual TV and domestic radios, that was all that had been damaged.

Incidentally, the owner subsequently made a successful claim against his householder's insurance policy to cover the cost of the repair; something he hadn't thought about until I suggested it.

The third call

The next call came a couple of weeks later from a location several kilometres away, which ultimately proved to be the other extremity of the affected area. Once again the complaint was a snowy picture, but the lady who rang me was a bit vague as to when the trouble had



appeared; she thought it was immediately after the storm, but wasn't sure.

Knowing the location, and the nature and age of the antenna system, I was more or less inclined to suspect that this was the problem, the timing with the storm perhaps being coincidental. But I was wrong. A check on the signal strength from the antenna showed that it was quite adequate. So the tuner came under suspicion again, and this was quickly confirmed. It was duly removed and despatched to Sydney for repair.

But here's the tag line. The set was the same make and model as the first one and, apparently, had suffered exactly the same fate. It had to be pure coincidence of course; not even Murphy would pull a gag like that.

The next job was only a few hundred metres away on the opposite side of the street. Once again the complaint was a snowy picture on each of two sets which this customer uses. And, because of the need to feed two sets, plus a relatively poor signal location, the installation uses a masthead amplifier.

With both sets showing the same symptoms I immediately suspected the amplifier. This proved to be correct and a new amplifier had to be fitted. But, significantly, nothing else in the house had been damaged.

Well that was the end of that story but I subsequently had occasion to talk to another customer who lives about half a kilometre away and, while he had suffered no damage to TV sets or radios, three telephones in his house were all written off. But that was Telecom's problem, not mine.

The next call was from another area again and, as before, involved a snowy picture. Once again, I suspected an antenna problem. (It was now some four or five weeks after the storm). This suspicion was based mainly on the age of the antenna, which I knew had been up for at least 15 years, plus the fact that I imagined that any lightning damage would have been reported much earlier.

But I had jumped to the wrong conclusion. The antenna was not only intact, but was delivering a very substantial signal. And this turned out to be the reason why the owner had not reported the trouble earlier; even with the front end of the tuner knocked out — for this was what I found — there was still enough signal to give a passable picture.

In fact, there was only a hint of snow

on channel 4, but it was rather more obvious on 5A. And so it was that the customer had not been immediately aware of the fault and had not associated it with the storm. It was only when I raised the matter that he realised that the trouble first showed up after the storm.

And so another tuner was removed for despatch to Sydney for repairs. But — wait for it — the set was the same make and model as the other two! And so the lightning, if it didn't actually strike twice in the same place, struck three times at the same place in the same make of set.

So what is the answer? Was it pure coincidence, or is this particular tuner more vulnerable than most to the stress of lightning strikes? I must admit that three in a row seems to be stretching the coincidence theory a bit far, though I suppose it is possible.

Why did three sets of the same model all suffer the same fault

On the other hand I hesitate to point the finger at the set, or criticise it in any way. It is a very good set, with an excellent fringe area performance; a matter of considerable importance in this area and a very good reason why it is often recommended for difficult locations.

Well, that's my friend's story, and a most interesting one it is. As with most lightning strike stories, one of the most puzzling and intriguing features is the completely random nature of the damage. Why is one appliance in a house picked out, or why is one on one occasion but not on another? And why do underground telephone lines appear to be just as vulnerable as when they were above ground, as in the past? Finally,

why did three sets of the same model all suffer the same fault, while other sets were not affected.

I don't profess to have any ready made answers to these questions. The only comment I can make is that, based on published literature, strikes do not involve the component or appliance being struck at all, in the usually accepted sense. In the case of the three TV sets it is possible that neither the antennas nor the power mains were actually struck.

In fact, if they had been struck it is almost certain that the trouble would have been much more severe. The real culprit in these cases would appear to be the intense electromagnetic field generated by the strike and which can damage sensitive components at a considerable distance. In fact, colour tube shadow masks have been severely magnetised from adjacent strikes, without any other damage to the set.

As for the apparent coincidence of the three sets, I can only theorise that the excellent fringe area performance may have been achieved — quite unwittingly — by the use of a front end device which just happens to be more than usually sensitive to these electromagnetic fields.

Perhaps some of our readers may have experiences or comments which may throw some light on the problem.

TETIA Fault of the Month **Toshiba C810**

Symptom. Highlights flare badly as brightness increases. Good pix obtainable only at low brightness level.

Cure. R262 (1120Ω ½W.) not connected to earth track on video output module. This is a design fault — even the board pattern in the service manual shows the resistor unconnected to ground.

VCR FAULT DATA MANUAL

- * OVER 100 SEPARATE VCR FAULTS
- * COVERS COMMON FAULTS IN MOST BRANDS
- * EACH FAULT FULLY DOCUMENTED with
 - * Symptoms * Fault * Remedy
 - * Location (with partial circuit diagrams)

VOLUME 1 NOW AVAILABLE

ONLY \$103.00 + \$2.00 postage & handling

If you repair or service VCR's this manual is a must.

Send to:

OPHIR TV SERVICES
PO BOX 531, ORANGE,
NSW 2800.

ENCLOSED \$105.00 ☐ cheque
☐ Money Order

NAME

ADDRESS

P/Code

Video fader for home movie buffs

Add a touch of professionalism to your video movies with this simple Video Fader circuit. It enables you to fade a scene to black (and back again) without loss of picture lock (sync) or colour.

by COLIN DAWSON


There's no doubt that home movies have been revolutionised by the advent of portable video equipment. Even the

size disadvantage of electronic video gear is steadily disappearing — the new 8mm video camera from Sony, for example, is

not much larger than a typical Super 8 camera.

Electronic video, of course, has the tremendous advantage of instant replay. Additionally, once you get the video home, it's quite a simple matter to duplicate and edit the recorded material.

Unfortunately, the range of effects available for electronic home movies is rather limited unless you have the budget of a television network. That's where this project comes in. It can be built for around \$20 and will allow you to fade smoothly from one scene to




The parts are all mounted on a single PCB. Note that the final version differs slightly from this early prototype.

Looking to purchase instruments

We are stockists of Hitachi, Fluke, Trio, Goodwill, Meguro, Aaron and Kikusui: so if you're in the market for an oscilloscope, think of David Reid.

20 MHz KIKUSUI COS5020 \$629.00


+ 20% Sales Tax
INCLUDING TWO PROBES
NOW WITH 2YR
WARRANTY



(Vertical Axis), 1-2-5 sequence, 10 range; Sensitivity, 5mV/DIV ~ 5V/DIV, (within $\pm 3\%$); Frequency response, DC (AC: 10Hz) ~ 20MHz (-3dB, 8DIV); Operation mode, CH1, CH2, DUAL, ADD, X-Y (DUAL automatic switching ALT and CHOP); (Horizontal Axis), 1-2-5 sequence, 20 ranges; Sweep time, 0.2 μ sec ~ 0.5sec/DIV (within $\pm 3\%$); (with 10 x MAG.), 20nsec ~ 50msec/DIV (within $\pm 5\%$).

40 MHz KIKUSUI COS5041 \$1167.00

+ 20% Sales Tax
INCLUDING TWO PROBES
AND DUST COVER



(Vertical Axis), 1-2-5 sequence, 10 range; Sensitivity, 5mV/DIV ~ 5V/DIV, (within $\pm 3\%$); Frequency response, DC (AC: 10Hz) ~ 40MHz (-3dB, 8DIV); Operation mode, CH1, CH2, DUAL, ADD, X-Y (DUAL automatic switching ALT and CHOP); (Horizontal Axis), (A: Main sweep, B: Delayed sweep); Sweep time, 1-2-5 sequence, A: 20 ranges, B: 11 ranges; A: 0.2 μ sec ~ 0.5 sec/DIV (within $\pm 3\%$); B: 0.2 μ sec ~ 0.5 sec/DIV (within $\pm 3\%$); (with 10 x MAG.), A: 20n sec ~ 50m sec/DIV (with $\pm 5\%$); B: 20n sec ~ 50m sec/DIV (with $\pm 5\%$).

ESCORT MULTIMETERS

EDM 1105 \$75.00
● 3 1/2 digits. ● Six functions: DCV, ACV, DCA, ACA, OHM, Diode Testing.
● 0.8% basic DC accuracy.

EDM 1116 \$100.00
● New model complete with transistor and capacitor tester.

EDM 1125 \$108.00
● 3 1/2 digits. ● Seven functions: DCV, ACV, DCA, ACA, OHM, Diode Testing, Audible Continuity.
● 0.25% basic DC accuracy.

EDM 1135 \$140.00
● 3 1/2 digits. ● Eight functions: DCV, ACV, DCA, ACA, OHM, Diode Testing, Audible Continuity. ● 0.1% basic DC accuracy.

EDM 1346 \$225.00
● 4 1/2 digits. ● Eight functions: DCV, ACV, DCA, ACA, OHM, Audible Continuity Testing, Diode Testing, Data Hold. ● 0.05% basic DC accuracy.

All multimeters + 20% Sales Tax

GAG-808A AUDIO GENERATOR \$203.00

Covers 10Hz to 1MHz

● 20Vp-p open circuit output ● Sine and Square wave outputs ● External sync ● 600 ohm output impedance



ALL PRICES SHOWN DO NOT INCLUDE SALES TAX. ADD 20%

These are just a few of the many 100's of up-to-date Electronic items on display at:



DAVID REID ELECTRONICS LIMITED
127 York Street, Sydney, 2000
or Telephone (02) 267 1385

Video fader

vanced, the base bias on Q3 rises and the video signal is moved towards white; ie, the picture brightness increases. D5 limits the maximum voltage on Q2's base to about 5.6V.


Thus, VR1 shifts the DC level of the video signal between black and white. This DC level-shifted signal appears at

the emitter of Q3 and is applied to the base of Q4 via D8.

The sync and colour burst signals are removed by applying a broad line-frequency blanking pulse to the base of Q4. As we shall see, the sync restoration and burst re-insertion occur later in the signal chain. This is done to ensure that the sync pulse and burst amplitudes remain constant, regardless of the setting of the fader control.

Q4 and Q5 form a differential amplifier with sync re-insertion into the base of Q5. Preset VR2 provides black level adjustment. The output from the differential amplifier appears across the 1.5k Ω resistor and is applied to the base of emitter follower Q6 which provides a nominal 75 Ω output impedance.

Below is an actual-size reproduction of the PC artwork.



Circuit & Design Ideas

Ignition advance for alternative fuels

To obtain reasonable engine performance with alternative fuels such as LPG or CNG, it is necessary to advance the spark ignition, compared to that required for petrol.

This circuit has been proved on the bench and can be connected between the points and a transistor-assisted ignition, or used with the TAI shown (from the December 1979 issue of EA).

All commercial electronic ignition designs for alternative fuels actually delay the spark, so it is necessary to set the points up with the required advance for LPG (or CNG, compressed natural gas) and switch in the delay when using petrol.

A feature of this design is that the points can be set as for the manufacturer's specifications for petrol and then the advance introduced for LPG or CNG.

Therefore it is not necessary to keep moving the points to tune the motor on gas. The advance can be preset or switch-selectable and, in the event of failure, the unit can be bypassed for the engine to be used on petrol.

The concept is to use two counters clocked by a common oscillator. The first counter, IC6, counts up between

two successive openings of the points. The contents of IC6 are then transferred to the "down" counter, consisting of ICs 8, 9 and 10. IC6 is then reset and the cycle begins again.

When the down counter reaches zero the output is used to switch the TAI and hence deliver the spark.

Provided that the counters are both clocked at the same rate, there is no spark advance.

To advance the spark, it is necessary to clock the "up" counter at a slightly lower rate. This means that it will have a lower count at the time its contents are transferred to the "down" counter. The down counter then reaches zero in a shorter time and hence advances the spark.

To provide adjustable advance, 4527 BCD rate multipliers, IC4 and IC5, are used. These divide the clock oscillator by a proportion set on their programmable inputs, either by preset links or thumbwheel switches.

IC4 is the most significant multiplier and would normally be set to multiply by 0.9 whereas IC5 is the least significant, giving an adjustment from 0.9 to 0.99. The amount of advance in degrees depends on the number of cylinders of the engine.

For a four-cylinder engine, the points open twice per revolution and so the

counter contents represent 180 degrees. The BCD rate multipliers provide a resolution of 1% (1-0.99, etc) which is therefore 1.8 degrees of advance. For example, to give 14.4 degrees of advance (over and above the normal petrol ignition advance) the rate multipliers would be set to a value of 0.92. To get this rate, IC4 would have pins 14 and 3 (A & D inputs) and IC5 would have pin 15 (B input) high.


The master oscillator (IC7) is set at a nominal frequency to ensure that the up counter does not overflow at very low engine speeds. Note that any drift in the frequency has no effect because the up and down counters are locked together.

The points are filtered and trigger a monostable (IC1a). This removes the reset from IC2 which then generates the load pulse to store the up counter contents in the down counter and then the reset for the up counter. Finally, it also resets monostable IC1a.


IC3 forms the selector to switch in the advance. When the CNG line is high, the output of the down counter is selected, to trigger the TAI or monostable as shown. During starting, or when not on CNG, the points are switched to the output via the monostable.

D. Preston,
Pakapura, NZ

\$35



Interesting circuit ideas from readers and technical literature. While this material has been checked as far as possible for feasibility, the circuits have not been built and tested by us. As a consequence, we cannot accept responsibility, enter into correspondence or provide constructional details.



People monitor & light switch

This circuit automatically keeps track of the number of people in a room and could be used to switch off lights when nobody is present.

Basically, it consists of two light sensors which are placed 200mm apart in a doorway so that one is tripped before the other. If the detectors are suitably angled, a common light source could be used. The concept is as follows:

When LDR1 is activated by a person walking between it and the light source, Q1 is momentarily biased (as the resistance of LDR1 goes high) on. This produces a negative-going pulse at the CK input of the 7476 dual JK flipflop. This

causes the Q-bar output of IC1a to go low which, in turn, causes the "UP" input of the 74193 up/down counter to also be pulled low.

In addition, the change of state of Q-bar also disables the 74241 Tri-state buffer.

When LDR2 is activated the Q-bar output of IC1b also goes low. This signal is ORed with the Q-bar output of IC1a to turn off transistor Q4 which enables the 555 timer. After a delay set by the resistor and capacitor connected to pin 6, the 555 low going output clears the two flipflops, allowing them to respond to the LDRs again. The up/down

counter now registers one person in the room.

If that person now walks out of the room, LDR2 is activated before LDR1 and the 74193 is made to count down (to zero).

The outputs of the 74193 are monitored by a four-input diode OR gate which turns on the transistor and thus the relay while ever there is more than one person in the room. As it stands, using the 74193 counter, the circuit can monitor the presence of up to 15 persons in a room, provided there is only one entrance.

D. Lilley
Holder, ACT.

\$20

Don't fret in the foxhole . . .

Build this simple World War Wireless

What can you do with a pencil, a razor blade, a paper clip, and a hank of wire? Why, build a radio, of course!

by **PENN CLOWER W1BG**

Hams with TVI problems often learn the hard way how poor metal connections can generate harmonics. Two conductors making partial contact, in gutters for example, can rectify and re-radiate as harmonics part of the signal from a nearby transmitter. What few newer hams realise is that the same phenomenon was crucial to the operation of one of the cheapest receivers ever designed: the Foxhole radio.

The phrase "hurry up and wait" probably predates World War II, but its meaning was certainly driven home then to thousands of hams. Often serving long tours of duty in forgettable places, ham GIs gave top priority to receiving news and entertainment from the nearby Armed Forces Radio Station. Of course, in those days radios used tubes, so the bulk and power requirements of typical receivers limited their availability. This was especially true in forward locations where the Army had more important services to provide — things like food and ammunition.

So some genius, and we can only hope he was a ham, invented the Foxhole radio. Made from commonly available components, its chief distinguishing feature was the use of a razor blade for the detector diode. A flat coil of enamelled wire and a headset (probably "borrowed" from a field telephone) completed the circuit.

While not an outstanding performer, the radio was compact, obtainable, and best of all — it worked! Copies were built and used all over the world.

The original design has several interesting features in addition to the razor blade detector. Note the absence of

a tuning capacitor in Fig. 1(a). The sliding contact on the coil doesn't tune stations so much as it adjusts the match between the antenna and its load. There might be some tuning action if the antenna looks capacitive, but selectivity is sure to be poor. My guess is that it didn't matter because there was probably only one station to listen to anyway.

Puzzled about the wide, flat coil form shown in the photographs? Everyone knows a good efficient inductor is wound as a cylinder no more than two diameters long. The flat coil may be an electrical compromise, but it sure is a lot easier to pack in a knapsack, put in a pocket, or hide in a POW camp.

All in all, the Foxhole receiver is real ham-radio stuff. You scrounge the parts, put them together as best you can, and the result works!

Building the Foxhole radio today is as easy as it was in WWII. The set shown in photograph A is the real thing — a close copy of the receiver described by W8EFW in the *QST* "Hints and Kinks" column for September, 1945. To improve performance, I also built the several accessories shown in photograph B. The biggest gain came from using a capacitor to resonate the coil. In keeping with the spirit of the project, even that component was homemade — with plates snipped from the side of an old tin can.

A Razor-Sharp Detector

The razor-blade detector is the most interesting part of the receiver. To build it, you first need a Gillette Super Blue Blade. Forget about using anything made of platinum or coated with




Photo A. A close replica of a set W8EFW described in 1945, this Foxhole radio can be built for pennies and works amazingly well. The razor blade is the diode. The earphone was borrowed from a telephone.

Photos by Steve Finberg, W1GSL




Fig. 1: Complete schematic of the Foxhole radio. The original circuit (a) was built by GIs all over the world during WWII. The addition (b) of a tuning capacitor and a dry cell (to bias the detector) improves reception.




Fig. 2: Home-brew 250pF (more or less) capacitor.

Teflon™. To simulate war-time conditions, I used my blade for its intended purpose until it hurt — about three weeks. That may not be necessary, but I wanted to do things right and my wife wouldn't let me dig a foxhole in the backyard. Compromises are sometimes unavoidable.

I clamped the used blade to the baseplate with a short woodscrew (W8EFW recommended thumb or carpet tacks). The same mounting screw clamps the contact wire to the blade, so I scraped away some of the bluing to ensure a good contact.

The rectifier contact point is made from a 1-inch (2.54cm) piece of pencil lead. Start by sharpening a pencil, then carefully carve away the wood at the tip. Break off the sharpened length of lead and tightly wrap its blunted end with eight or nine turns of fairly stiff wire. Leave a 1-inch or 2-inch pigtail of wire to clamp under the "phone jack" terminal screw when you mount the rectifier.

In operation, the point of the lead is moved over the surface of the razor blade until a sensitive spot is found. When that happens, the radio starts to work and the lead is carefully released so that its mounting wire holds it in the correct position. I found rectification was best when the point contact was resting on one of the silver letters etched into the blade. Of course, it goes without saying that the blade is thoroughly cleared of soap or oil before rectification is attempted. This is a crude system and a little tricky to adjust, but once set up, it works surprisingly well.

Scrap Wood Chassis

Construction of the rest of the radio is shown pretty clearly in the photographs. The baseplate is a 4-inch by 4-inch square of 3/8-inch or 1/4-inch wood. The coil is about 175 turns of #26 enamelled wire wound on another scrap of the same wood, this one 2-inch by 4-inch. Any wire size from 22 to 28 will work as long as the wire is enamelled to keep the turns from shorting.

The antenna, ground, and headphone

terminals are made from paper clips. The sliding coil contact is a paper clip bent and mounted to maintain downward pressure on the coil. I soldered the pivot end of this arm to a washer and fastened that to the board with a screw. W8EFW simply bent the end of the paper clip around a tack. Running the arm back and forth across the coil several times makes enough of a mark to show where the insulation must be scraped away for the arm to make contact. I also soldered

all the wire connections to improve reliability. The radio will work without that step, but it does make life a little easier.

It goes without saying that this radio, like its brother, the crystal set, needs a good antenna and ground. The easiest thing to use for a ground is the house water supply. An acceptable antenna can be made from 50 feet (16 metres) of wire routed out a window and away from the house. Keep the far end as high as




Photo B. Never content to leave well enough alone, the progressive amateur will be looking for high-performance modifications. Here are two: The homemade tuning capacitor and detector bias pack will boost both selectivity and sensitivity.

World War Wireless

possible and use more wire if you can. As far as this radio is concerned, there can never be too much antenna!

This set works best if the old-style high-impedance headphones are used. The new, low-impedance hifi types would work only with a matching transformer. If the proper phones aren't available, you can always do what the GIs probably did — borrow the earpiece from a telephone handset. The Ma Bell earpiece shown in the photographs has a DC resistance of 6Ω and an AC impedance of about 150Ω . It works almost as well as real headphones.

Operation

There's certainly nothing sophisticated about tuning the Foxhole radio. Check the wiring, hook up the antenna and ground, and connect the earphones. Set the slider to the middle of the coil and start listening. Move the point of the pencil lead slowly across the lettering on the razor blade until you hear a station. Try several different spots because some will work better than others. As a final step, move the slider across the coil until the signal strength is maximised.

The performance of the Foxhole radio will depend on your skill in adjusting the detector and the efficiency of your antenna. W8EFW claimed a range of 25 miles with a good antenna and ground. At my location, two nearby stations (about five to seven miles away) dominate the set so I can't hear anything further away. Those local stations are quite clear, though, and come in with reasonable volume.

Carver DTL-100

continued from page 27

It is interesting that the DTL frequency response is also akin to that available from many typical phono cartridges. Is Carver merely trying to produce phono cartridge sound from CDs? That is what it seems like.

Listening tests

On listening to the Carver DTL-100 without the digital time lens feature switched in circuit, it gave the excellent quality of sound that is expected from compact discs. With DTL in circuit, the sound quality is markedly different.

To begin with, although the specifications show a vast reduction in channel

DX Accessories

There are several ways to improve the performance of this little radio, and luckily they're both cheap and easy. The first thing to add is a capacitor for resonating the coil, as shown in Fig.1b and photograph B. With my antenna, that gave a noticeable boost to headphone volume and also let me separate the local stations. My friend WIGSL found that at his QTH (location) the capacitor worked best when it was in series with the antenna. The capacitor always improved reception, though, so it's certainly a worthwhile addition.

An old 365-pF broadcast variable capacitor is perfect for the job, but you'd be cheating to use one. It's more sporting to make your own capacitor with plates cut from a tin can.

First cut (very carefully, those edges are sharp!) a pair of T-shaped plates, as shown in Fig.2. Smooth the edges with a file and solder on two paper clips as shown. These two plates, separated slightly by an insulator, will be clamped together between wooden blocks to make a fixed 200-pF capacitor. That unit can then ride piggyback on the set, as shown in photograph B.

At first I tried using cellophane tape for the dielectric. That had a lot of DC leakage, so plain writing paper was used in the final version. One layer of paper between the plates makes a nice capacitor and gives about 100pF per square inch of plate area. Any capacitance value between 150pF and 350pF will work, and the final value can be adjusted if necessary by sliding the plates to change the amount of overlap.

The other circuit improvement is the addition of a 1.5V battery to bias the detector further into its non-linear region. What? A "crystal" set with a battery? The idea may seem strange

now, but in the early days of radio that technique was quite common and in fact, necessary with some of the crystal materials used. Current drain is only one or two mA, so battery life shouldn't be a problem.

The battery holder shown in photograph B matches the style of the rest of the "equipment" and is also easy to make. When using the battery, you may find it easier to adjust the detector first and then add the battery bias for a boost in signal strength. The battery simply goes in series with the headphones. Try flipping the battery polarity several times, as one direction may work better than the other.

Conclusions

The Foxhole radio is cheap to build and fun to operate, but it certainly isn't the world's best "crystal" set and you won't spend hours listening to it. Amazingly, though, it does work, and its story is a truly fascinating bit of radio history. More than just a history lesson, however, this project will also leave you with two long-term benefits.

First, it gives you a perfect way to win "sucker bets" with friends who don't believe you can build a working radio using household materials and no commercial tubes, transistors, or diodes.

Second, you'll have a lot more respect for the rectifying properties of imperfect connections. That's helpful in those cases of harmonic-type TVI which occur despite the use of a properly adjusted transmitter and a good low-pass filter. Rectification generates harmonics, but when searching for the diode, it sure is easy for the inexperienced ham to overlook the rusty joints in his neighbour's TV mast!

Reprinted with permission from "73 for Radio Amateurs."

separation on listening, the stereo effect is not noticeably reduced. What does happen, however, is that sounds normally located centrally in the stereo image are broadened so that there is a less precise location of central sounds. Solo instruments or vocalists which are normally able to be pinpointed by the listener, become diffuse.

There is also a subtle change in the tonal balance. Depending on the particular recording, there is a richer sound given to the voice with perhaps a little tendency to edginess. There is also a suggestion of slightly more background hiss.

The overall sound with DTL is more reminiscent of a quality analog disc and cartridge combination. This is not sur-

prising considering the reduction in separation, altered frequency response and higher noise that the DTL circuit provides. To be frank, we preferred the sound quality without the Digital Time Lens although we are prepared to concede that many audiophiles may prefer it with DTL. It should be the subject of animated discussion in many hifi shops. We suggest you go along and have a listen.

Recommended retail price of the Carver DTL-100 compact disc player is \$1590. Carver products are available from selected hifi dealers and are distributed in Australia by Odyi Communications, 6th Floor, 3 Smail Street, Broadway 2007. Phone (02) 212 6617 or 212 6618.(J.C).

You will find plenty to do at Rod Irving Electronics,



HOOK UP WIRE

Cat. No.	Description	Price
W11251	13/12 TLD BLK	
W11252	13/12 TLD BROWN	
W11253	13/12 TLD ORANGE	
W11254	13/12 TLD YELLOW	
W11255	13/12 TLD GREEN	
W11256	13/12 TLD BLUE	
W11257	13/12 TLD WHITE	

PRICES PER 100 METRE ROLL
1-9 \$5.95 10+ \$5.00

Cat. No.	Description	Price
W11260	14/20 RED	
W11261	14/20 BLACK	
W11262	14/20 BLUE	
W11263	14/20 WHITE	

PRICES PER 100 METRE ROLL
1-9 \$12.00 10+ \$10.00

Cat. No.	Description	Price
W11270	24/20 RED	
W11272	24/20 BLACK	
W11274	24/20 GREEN	


PRICES PER 100 METRE ROLL
1-9 \$14.00 10+ \$12.00

Cat. No.	Description	Price
W11280	32/2 BROWN	
W11282	32/2 BLUE	

PRICES PER 100 METRE ROLL
1-9 \$20.00 10+ \$18.00

NEW! 12 WAY TERMINAL BLOCKS

Cat. No.	Description	Price
P18050	240V 10AMP	\$1.50
P18052	240V 15AMP	\$1.75




DIP SWITCHES

Cat. No.	Description	Price
S13402	2Way	\$1.50
S13404	4Way	\$1.70
S13405	5Way	\$1.90
S13406	6Way	\$2.30
S13407	7Way	\$2.40
S13408	8Way	\$2.50
S13410	10Way	\$3.00



ECONOMY ROTARY SWITCHES

Cat. No.	Description	Price
S13021	1 pol 2-12 pos.	\$1.95
S13022	2 pol 2-6 pos.	\$1.95
S13033	4 pol 2-3 pos.	\$1.95
S13035	3 pol 2-4 pos.	\$1.95




TRIGGER TRANSFORMERS

Cat. No.	Description	Price
M10104		\$1.20



QUALITY MOMENTARY (RED BODY)

Cat. No.	Description	Price
SPDT Cat. S11050		\$1.50




LOG SLIDES POTS

We ordered log instead of linear for the graphic equalizer, so take advantage of our mistake!
1-9 \$0.65 10+ \$0.60 100+ \$0.50



10,000uF 75V ELECTRO

25% more microFarads! Ideal for those who want a more powerful amp!
Cat. R16587 1-9 \$10.50 10+ \$9.00



ECONOMY TRANSFORMERS

Cat. No.	Description	Price
2155	1-9 \$6.75 10+ \$5.95	
Cat. M12155		
2156	1-9 \$9.50 10+ \$8.95	
Cat. M12156		
2851	1-9 \$4.50 10+ \$3.60	
Cat. M12851		
6672	1-9 \$9.95 10+ \$9.30	
Cat. M16672		
2860	1-9 \$3.95 10+ \$3.80	
Cat. M12860		

NEW TRANSFORMER!


240V to 15V C.T. at 250 mA
Cat. No. M12860 1-9 \$3.95 10+ \$3.80



50% OFF THESE PRICES! THIS MONTH ONLY!


CENTRONICS

Cat. No.	Description	Price
P12200	36 way plug IDC	\$12.50
P12201	36 way skt IDC	\$13.50
P12203	50 way plug IDC	\$14.50
P12204	50 way skt IDC	\$15.50
P12207	24 way solder plug	\$12.90
P12210	36 way solder plug	\$ 9.50
P12211	36 way sldr line skt	\$15.95
P12213	36 way sldr chss skt	\$15.95



BREADBOARDS

Cat. No.	Description	Price
P11000	100 Holes	\$ 2.75
P11005	640 Holes	\$10.75
P11007	640+100 Holes	\$13.00
P11009	640+200 Holes	\$17.50
P11010	1280+100 Holes	\$19.95
P11011	1280+300 Holes	\$32.50
P11012	1280+400 Holes	\$36.75
P11015	1920+500 Holes	\$57.50
P11018	2560+700 Holes	\$64.95



IC SPECIALS!

Cat. No.	Description	Price
4116	1-9 \$1.80 10+ \$1.70 100+ \$1.60	
4164	1-9 \$1.95 10+ \$1.75 100+ \$1.70	
2716	1-9 \$5.90 10+ \$5.50 100+ \$5.50	
2732	1-9 \$5.25 10+ \$4.95 100+ \$4.50	
2764	1-9 \$6.25 10+ \$5.95 100+ \$5.00	
27128	1-9 \$7.00 10+ \$6.50 100+ \$6.25	
6116	1-9 \$2.50 10+ \$2.25 100+ \$1.95	
41256	1-9 \$7.00 10+ \$6.50 100+ \$6.00	
6264	1-9 \$7.00 10+ \$6.50 100+ \$6.00	

MSM5832 BACK IN STOCK!

Cat. No.	Description	Price
1-9		\$12.50
10+		\$11.50

NEWIC's

Cat. No.	Description	Price
MCS2400	1-9 \$4.90 10+ \$4.75	
41256	1-9 \$9.00 10+ \$8.00	
27128	1-9 \$7.00 10+ \$6.50	
74LS169	1-9 \$2.50 10+ \$2.40	
AY-31050	1-9 \$12.50 10+ \$11.95	
WD2791	1-9 \$69.00 10+ \$67.00	
WD2793	1-9 \$69.00 10+ \$67.00	
WD2795	1-9 \$69.00 10+ \$67.00	
WD2797	1-9 \$69.00 10+ \$67.00	
LM11CN	1-9 \$2.95 10+ \$2.75	
LM1871	1-9 \$5.95 10+ \$5.75	
LM1872	1-9 \$5.95 10+ \$5.75	
Z80ADART	1-9 \$13.50 10+ \$12.95	
LM338K	1-9 \$10.60 10+ \$9.50	
AMIS3530	1-9 \$24.95 10+ \$23.95	
AM7910	1-9 \$49.50 10+ \$45.00	

(World Modern Chip)

UPC1031 \$19.50

R.F. Module

57716 \$64.95 \$59.95

27256 \$69.00 \$59.00

Rod Irving Electronics, No.1 for components!




QUALITY LEDs

Cat. No.	Description	Price
Z10140	3mm Red	\$0.20
Z10141	3mm Green	\$0.30
Z10143	3mm Yellow	\$0.30
Z10145	3mm Orange	\$0.30
Z10150	5mm Red	\$0.15
Z10151	5mm Green	\$0.30
Z10152	5mm Yellow	\$0.30




SPECTROL 43P

Cat. No.	Description	Price
1-9		\$1.75
10+		\$1.50



CRYSTALS SPECIALS

Cat. No.	Description	Price
1-9		\$1.75
10+		\$1.50



NEW JOINABLE PCB MOUNTING SCREW TERMINALS

Cat. No.	Description	Price
P10542	2Way	\$0.50 \$0.40
P10543	3Way	\$0.75 \$0.65




IC SPECIALS! 8000 SERIES

Cat. No.	Description	Price
8085	1-9 \$4.50 10+ \$3.50	
8212	1-9 \$1.50 10+ \$1.40	
8216	1-9 \$1.50 10+ \$1.40	
8226	1-9 \$1.70 10+ \$1.50	
8243	1-9 \$4.50 10+ \$3.90	
8251	1-9 \$3.90 10+ \$3.50	
8253	1-9 \$3.50 10+ \$3.30	
8255	1-9 \$2.90 10+ \$2.50	
8257	1-9 \$3.50 10+ \$3.10	
8259	1-9 \$3.50 10+ \$3.10	
8279	1-9 \$3.50 10+ \$3.10	
2532	1-9 \$7.50 10+ \$6.90	
2764	1-9 \$5.50 10+ \$5.10	
27128	1-9 \$7.50 10+ \$6.90	
1488	1-9 \$5.50 10+ \$5.10	
1489	1-9 \$5.50 10+ \$5.10	



IDC SOCKETS

Cat. No.	Description	Price
P12100	10 pin IDC socket	\$4.95
P12101	16 pin IDC socket	\$5.50
P12102	20 pin IDC socket	\$5.95
P12103	20 pin IDC socket	\$6.95
P12104	34 pin IDC socket	\$7.95
P12106	34 pin IDC socket	\$7.95
P12108	40 pin IDC socket	\$8.95
P12110	50 pin IDC socket	\$9.95




RELAY AND BASE

Can carry 10A at 28V DC or 5A at 240V AC. Supplies with Chassis Mounting Socket with screw terminals. Great for school projects and demonstrations, switching DC power supplies, central circuits and with contacts parallel up to 20A can be switched.
Normally \$8.95
Cat. S14074 NOW \$6.95




ELECTRET MIC INSERTS

Cat. No.	Description	Price
Cat. C10170		
1+		\$1.25
10+		\$1.10
100+		\$1.00



10 TURN WIRE WOUND POTENTIOMETER

Spectrol Model 534
1/4" shaft.
Equiv (Bourns 3540S, Beckman 7256)
Dials to suit 16-1-11, 18-1-11, 21-1-11
1-9 \$9.50 10+ \$8.50



QUALITY RIGHT ANGLE TOGGLE SWITCHES

Cat. No.	Description	Price
S11040	S.P.D.T. RA PCB	\$1.50
S11042	D.P.D.T. RA PCB	\$1.60



MINI JUMPERS


• Contact terminal: Phosphor bronze
• Material: P.B.T. 94V-0
• Gold plated

Qty	Cat. No.	Price
10	P12053	\$ 2.95
25	P12055	\$ 4.95
100	P12057	\$21.95



RS232 & 'D' TYPE CONNECTORS

PART	DESCRIPTION	CAT. No.
1-9		10+
DE 9P	9 Pin Female	P10880
\$1.75		\$1.60
DE 9S	9 Pin Male	P10881
\$2.25		\$2.45
DE 9C	9 Pin Cover	P10992
\$2.55		\$2.45
DA 15P	15 Pin Male	P10894
\$2.10		\$1.95
DA 15S	15 Pin Female	P10895
\$2.10		\$2.10
DA 15C	15 Pin Cover	P10892
\$1.15		\$1.05
DB 25P	25 Pin Male	P10900
\$1.95		\$1.80
DB 25S	25 Pin Female	P10901
\$2.95		\$2.70
DB 25C	25 Pin Cover	P10902
\$1.20		\$1.10



VIDEO RF MODULATOR

At an unbelievable price! Our RF modulators are channel selectable either Channel O or Channel 1.
Cat. S16040
1-9 \$4.95 10+ \$3.95



TDK LINE FILTERS

Cat. No.	Description	Price
240 V 3A		\$12.50

Rod Irving TOP 40 Kits



EA AM STEREO DECODER

AM stereo is now broadcast in Australia on an experimental basis. This add-on decoder works with the Motorola C-QUAM system. (EA Oct '84) 84MS10
Cat. K84100

\$27.50



FUNCTION GENERATOR

This Function Generator with digital readout produces Sine, Triangle and Square waves over a frequency range from below 20Hz to above 160Hz with low distortion and good envelope stability. It has an inbuilt four-digit frequency counter for ease and accuracy of frequency setting. (EA April '82, 82AQA8)
Cat. K82040
Cat. K82041

\$109



CYLON VOICE

Have your voice transformed into that of the sinister sounding Cylons. Great fun and scary! (EA Jan '81)
Cat. K80012

\$19.95



PARABOLIC MICROPHONE

Build a low cost parabola, along with a high gain headphone amplifier to help when listening to those natural activities such as babbling brooks, singing birds or perhaps even more sinister noises. The current cost of components for this project is around \$15 including sales tax, but not the cost of batteries or headphones. (EA Nov '83) 83MA11
Cat. K83110

\$14.95



EPROM PROGRAMMER

If you have ever wanted to rewrite or extend the operating system of your microcomputer or if you're interested in dedicated microprocessor applications then this EPROM Programmer is just the thing. It is an inexpensive unit that uses readily available IC's, interfaces directly to the expansion bus on the back of all the popular 8080/286 microcomputers and programs 2708's, 2716's, 2758's and 2732's. (EA July '80) 80PP71
Cat. (Horwood case supplied)

\$79.50



EFFECTS UNIT

An "effects unit" that can create phasing, flanging, echo, reverb and vibrato effects. (EA June '83) 83GA6
Cat. K83060


\$75.00



CUDLIPP CRICKET

A fascinating Electronic Cricket with just two ICs. The Cudlipp can be used to bug your home, office etc! Great fun! (EA Feb '82) 82EG2
Cat. K82022

\$12.00



50V 5A LABORATORY POWER SUPPLY

New switchmode supply can deliver anywhere from three to 50V DC and currents of 5A at 35V or lower. Highly efficient design. (EA May, June '83) 83PS5
Cat. K83050


\$149



1W AUDIO AMPLIFIER

A low-cost general-purpose, 1 watt audio amplifier, suitable for increasing your computers audio level, etc. (EA Nov '84)
Cat. K84111


\$9.95



30 V/I FULLY PROTECTED POWER SUPPLY

The last power supply we did was the phenomenally popular ETI-131. This low cost supply features full protection, output variation from 0V to 30V and selectable current limit. Most voltages and current metering is provided. (ETI Dec '83) ETI 162
Cat. K41620

\$52.50



TEMP PROBE

Can measure temperature from -50 to 150°C. It simply plugs into your multimeter - great for digital multimeters. Accuracy of 0.1°C resolution of 0.1°C. (ETI June '83) ETI 153
Cat. K41530


\$27.50



VIDEO ENHANCER

Like tone controls in a hi-fi amplifier, touch up the signal with this Video Enhancer. (EA Oct '83) 83VE10
Cat. K83100

\$39.50



VIDEO AMPLIFIER

Bothered by smeary colours, signal beats and RF interference on your computer display? Throw away that cheap and nasty RF modulator and use a direct video connection instead, it's much better! The Video Amplifier features adjustable gain and provides both normal and inverted outputs. Power is derived from a 12V DC plugback supply. (EA Aug '83) 83VA8
Cat. K83081


\$17.95



LOW OHMS METER

How many times have you cursed your Multimeter when you had to measure a low-value resistance? Well with the "Low Ohms Meter" you can solve those old problems and in fact measure resistance from 100 Ohms down to 0.005 Ohms. (ETI Nov '81) ETI 158
Cat. K41580

\$39.50



40 W INVERTER

This 12 240 V inverter can be used to power up mains appliances rated up to 40 W, or to vary the speed of a turntable. As a bonus, it will also work backwards as a trickle charger to top up the battery when the power is on. (EA May '82) 82IV5
Cat. K82050

\$57.50



MUSICOLOR IV

Add excitement to parties, card nights and discos with EAs Musicolor IV light show. This is the latest in the famous line of musicolors and it offers features such as four channel "color organ" plus four channel light chaser, front panel LED display, internal microphone, single sensitivity control plus opto-coupled switching for increased safety. (EA Aug '81) 81MCS
Cat. K81080

\$89



15V DUAL POWER SUPPLY

This simple project is suitable for most projects requiring a dual voltage. (ETI 581, June '76)
Cat.

\$19.50



ELECTRONIC MOUSETRAP

This clever electronic mousetrap disposes of mice instantly and mercifully, without fail. They'll never get away with the cheese again! (ETI Aug '84) ETI 1524
Cat. K55240

\$27.50



VOICE OPERATED RELAY

EA's great Voice Operated Relay can be used to control a tape recorder, as a VOX circuit for a transmitter or to control a slide projector. (EA Apr '82) 82VX4
Cat. K82043

\$17.95



100W SUB-WOOFER AMPLIFIER

Capable of up to 120 watts RMS into 4 ohm loads and up to 80 watts RMS into 8 ohm loads, this power amplifier module has been specifically designed for use as a sub-woofer driver amplifier in a tri-amped hi-fi system. It uses four power Mosfets for rugged, reliable operation. (EA July '82) 82PA7
Cat. K82075


\$97.50



MICROBEE SERIAL-TO-PARALLEL INTERFACE

Most microcomputers worth owning have an "RS232" connector, or port, through which serial communications (input/output) is conducted. It is a convention that, for listing on a printer, the BASIC LLIST or LPRINT command assumes a printer is connected to the RS232 port. Problem is, serial interface printers are more expensive than parallel Centronics interface printers. Save money by building this interface. (ETI Jan '84) ETI 675
Cat. K46750

\$59.00



HEADPHONE AMPLIFIER

PRACTICE WITHOUT ANNOYING THE FAMILY! If you play any type of electronic instrument, this headphone amplifier will surely interest you. It will let you practice for hours without upsetting the household or you can use it to monitor your own instrument in the midst of a rowdy jam session. (EA Feb '84) 83MA11
Cat. K83011

\$29.95



300 BAUD DIRECT CONNECT MODEM

Modem? What do I want with a modem? Think of these advantages:
• Can't afford a floppy disc? Use your telephone to access one for the cost of a coin.
• Bored with your old programs? Download hundreds of free programs.
• Want to get in touch with fellow computer enthusiasts? Use "electronic mail".
• Ever used a CP/M system? CP-DOS? UNIX? Well a modem will make a your computer a remote terminal on some of the most exciting systems around. Save on ready built modems.
Cat. K97050

\$99



STEREO ENHANCER

The best thing about stereo is that it sounds good! The greatest stereo hi-fi system loses its magnificence if the effect is so narrow you can't hear it. This project lets you cheat on being cheated and creates an "enhanced stereo effect" with a small switch attaches to your amp. (ETI 1405, ETI, MAR '85)
Cat. K54050

\$79.50



TRANSISTOR TESTER

1000's SOLD Have you ever desoldered a suspect transistor, only to find that it checks OK? Trouble-shooting exercises are often hindered by this type of false alarm, but many of them could be avoided with an "in-circuit" component tester, such as the EA Handy Tester. (EA Sept '83) 83TT8
Cat. K83080

\$17.95



ELECTRONIC WATT METER

This unit will measure the power consumption of any mains appliance with a rating up to 3 kilowatts. It makes use of a special op amp called an "output transconductance amp" or OTA. For short. (EA Sept '83) 83WM8
Cat. K83082

\$89.95



RADIOTELETYPE CONVERTER FOR THE MICROBEE

Have your computer print the latest news from the international shortwave news service. Just hook up this project between your short wave receivers audio output and the Microbee parallel port. A simple bit of software does the decoding. Can be hooked up to other computers too. (ETI Apr '83)
Cat.

\$19.95



ZENER TESTER

A simple low cost add-on for your multimeter. This checks zeners and reads out the zener voltage directly on your multimeter. It can also check LEDs and ordinary diodes. (ETI May '83) ETI 164
Cat. K41640

\$9.95



MOSFET POWER AMPLIFIER

Employing Hitachi Mosfets, this power amplifier features a "no compromise" design, and is rated to deliver 150 W RMS maximum and features extremely low harmonic, transient and intermodulation distortion. (ETI 477, ETI Jan '81) (Single module only)
Cat. K44770
Plus power supply (No trans) \$49
Plus transformer PF4361/1 \$49.50

\$79.50



PARALLEL PRINTER SWITCH

Tired of plug swapping when ever you want to change from one printer to another? This low-cost project should suit you down to the ground. It lets you have two Centronics-type printers connected up permanently, so that you can select one or the other at the flick of a switch. (ETI 666, Feb '85)
Cat. K46660

\$69.95



BIPOLAR PROM PROGRAMMER

Every digital workshop should have one! Can be used to program the popular fusible-link PROMS like the 74S188-288, 82S23 & 82S123 etc. (ETI June '83) ETI 688
Cat. K46880

\$49.50



ELECTRIC FENCE

Mains or battery powered, this electric fence controller is both inexpensive and versatile. Based on an automotive ignition coil, it should prove an adequate deterrent to all manner of livestock. Additionally, its operation conforms to the relevant clauses of Australian Std 3129. (EA Sept '82) 82EF9
Cat. K82092


\$19.50



FAIR DINKUM RS232 FOR MICROBEE

The Microbee, among other home computers, has a "sort of" RS232 port in that it doesn't implement negative-going portion of its output signal (TxD). Most peripherals with an RS232 input can cope with that, but inevitably, there are those that can't. This project fixes that. (ETI 676, ETI FEB '84)
Cat. K67680

\$34.95



PHONE MINDER

Dubbed the Phone Minder, this handy gadget functions as both a bell extender and paging unit, or it can perform either function separately. (EA Feb '84) 84TP2
Cat. K84021

\$27.50



AUDIO TEST UNIT

Just about everyone these days who has a stereo system also has a good cassette deck, but not many people are able to get the best performance from it. Our Audio Test Unit allows you to set your cassette recorder's bias for optimum frequency response for a given tape or alternatively, it allows you to find out which tape is best for your recorder. (81AO10) (EA Oct '81)
Cat. K81101

\$47.50



LAB SUPPLY

Fully variable 0-40V current limited 0-5A supply with both voltage and current metering (two ranges 0-0.5A/0-5A). This employs a conventional series-pass regulator, not a switchmode type with its attendant problems, but dissipation is reduced by unique relay switching system switching between taps on the transformer secondary. (ETI May '83) ETI 163
Cat. K41630

\$182.50



300W "BRUTE" AMPLIFIER

The "Brute" develops 300W into 4 ohms, 200W into 8 ohms! For many audio applications there's no substitute for sheer power - low efficiency speakers, outdoor sound systems, or maybe you like the full flavour of the dynamic range afforded by a high power amp. Whatever your requirement - this "super power" module should fill the bill. (ETI 465, Feb '85)
Cat. K44650
(Heatsink not included)

\$89.95



LOW BATTERY VOLTAGE INDICATOR

Knowing your batteries are about to give up on you could save many an embarrassing situation. This simple low cost project will give your early warning of power failure, and makes a handy beginner's project. (ETI 280, March '85)
Cat. K42800

\$7.95



MOTORCYCLE INTERCOM

OVER 300 SOLD! Motorcycling is fun, but the conversation between rider and passenger is usually just not possible. But build this intercom and you can converse with your passenger at any time while you are on the move. There are no "push-to-talk" buttons, adjustable volume and a handy built-in speaker! (EA Feb '84) 84MC2
Cat. K84020


\$45.00



LOW-COST BIPOLAR MODEL TRAIN CONTROLLER

Here is a simple model train control for those enthusiasts who desire something better than the usual rheostat control. It provides much improved low speed performance and is fully overload protected, yet contains relatively few components. Best of all, you don't need to be an electronic genius to construct it. (80TC12) (EA Dec '80)
Cat. K80120

\$39.95



AUDIO/MIKE PROFESSIONAL MIXER

This compact mixer has a host of unique features and is ideally suited for the most discerning user. Just look at these features...

- Two microphone inputs with pan-pot control and high/low impedance selectors
- Stereo 8 segment LED level meters to monitor outputs
- Two stereo phono inputs with magnetic/ceramic selectors and fader control
- Two stereo tape inputs with dubbing outputs
- Two stereo line inputs
- Slide master volume control
- Rear/front microphone input selector
- Talkover switch with talkover variable volume control
- Cannon socket for talkover microphone
- AC operation

Input Sensitivity:

Mic. Low 0.3mV 600 ohms High 3mV 50k Ohms
Phono Mag. 3mV 50k ohms Ceramic 150mV 50k Ohms

Tape/Tuner 150mV 50k ohms

T.H.D.: Less than 1%

S/N Ratio: More than 58dB

Crosstalk: Better than 50dB at 1kHz

Frequency Response: 20 - 20kHz RIAA + 2dB

Output Level: 900mV at 600 ohms

Recording Output: 280mV at 60 ohms

Talkover Range: 0 - 24dB


Power Source: 240V AC 50Hz

Size: 355 x 230 x 75mm

Weight: 3.2kgs

RRP \$357

OUR PRICE \$319



UNIVERSAL STEREO MIXER WITH GRAPHIC EQUALISER

The MM4 is our most flexible mixer. Incorporating the most advanced IC technology for performance and reliability. Built in graphic equaliser virtually eliminates the need for a pre-amplifier. Features 4 stereo program and 2 microphone inputs.

SPECIFICATIONS:

Input Sensitivity:

Mic. 1.5mV at 10k ohm

Phono. 1.5mV at 50k ohm

Line 75mV at 50k ohm

Rated Output:

Amp 1V/600 ohms

Rec. 1V/600 ohms

T.H.D.: Less than 1% at 1kHz

Hum and Noise:

Mic. -52dB

Phono -62dB

Line -65dB

Frequency Response:

Mic. 30 - 16kHz (-1dB)

Phono 30 - 20kHz (RIAA + -2dB)

Line 20 - 30kHz (-1dB)

Power Source: 240V AC 50Hz

Size: 360 x 260 x 85mm

Weight: 2.9kg

EQUALISER SECTION

Control of Frequency: 60Hz, 250Hz, 1kHz, 3.5kHz, 12kHz


Control Range: +12dB boost or cut - centre detent

Headphone Output: (Cue) 50mW at 75 ohm at 0.5% T.H.D.

Talk Switch: -14dB

RRP \$354

OUR PRICE \$319



DISCO MIXER WITH GRAPHIC EQUALISER

This stereo mixer is especially designed for discotheques and radio studios. It is a versatile rack or console mounting mixer with varied features which enable high quality broadcasts through its 3 microphone inputs, 3 phono inputs or 3 line inputs.

- 6 channel monitoring system
- 9 point dual LED output level display
- Output panpot
- 3 outputs
- Adjustable talkover with LED display
- Master level control

SPECIFICATIONS

Input:

Talk Mic. 47k ohms nominal 5mV

Mic. 2.3 47k ohms nominal 5mV

Phono 1, 2, 3 47k ohms nominal 5mV

Line 1, 2, 3 37k ohms nominal 300mV

Output 1k ohm nominal 0.775V

Rec. Out 1k ohm nominal 250mV

Line Out 1k ohm nominal 250mV

Frequency Response:

Talk Mic. 150Hz - 7kHz - 3dB

Mic. 2, 3 15Hz - 30kHz - 3dB

Phono 1, 2, 3 20Hz - 20kHz - 2dB

Line 1, 2, 3 15Hz - 100kHz - 3dB

S/N Ratio: (IHF-A input short)

Talk Mic. -73dB/5mV

Mic. 2, 3 -73dB/5mV

Phono 1, 2, 3 -76dB/5mV

Line 1, 2, 3 -80dB/300mV

Crosstalk: Better than 60dB/1kHz

T.H.D.: Less than 0.1%/1kHz

H.P. Out Level: 55mW/80 ohms - 1k ohm

Eq. Frequency: 60/250/1k/4k/12kHz - 12dB

Talk Over Level: -14dB

Master Level: 0dB = 0.775V/1.5V

Power Consumption: 15 watts


Power Supply: 240V 50Hz

Dimensions: 482(W)x222(H)x130(D)mm

Net Weight: 4.5kg

RRP \$649

OUR PRICE \$579



12 CHANNEL STEREO MIXING CONSOLE

Loaded with professional features but simple to operate. A 3 position attenuation switch with -15dB, 0dB, +15dB, together with separate mic. and line inputs allows perfect matching with any input signal. Foldback with the pre-fade send or on stage monitoring. Includes bass and treble controls plus a left and right 5 band graphic equaliser. Other features include effect return panning, P.P.I. overload indicators and stereo headphone monitoring. Ideal for disco's with 2 stereo disc inputs with cross fade. A high quality 12 channel mixer for the professional enthusiast.

SPECIFICATIONS

Inputs:

12 x Mic -46dB at 47k ohm

12 x Line -20dB at 20k ohm

12 x Phono -52dB at 50k ohms (approx 2mV at 1kHz)

Effect Return -20dB at 50k ohm

Outputs:

PGM Out 0dB at 10k

F/B Out 0dB at 10k ohm

Effect Send 0dB at 10k ohm

Rec. Out -4dB at 10k ohm

Headphones +10dB at 600 ohm (100 - 1k ohm)

Equaliser (Channel): Bass + -12dB (100Hz), Treble + -12dB (10kHz)

Equaliser (Master): 100/330/1k/3.3k/10kHz, (5 band stereo) + -12dB

Frequency Response: 20 - 20kHz (+1dB, -3dB)

S/N Ratio (IHF-A): 120dB

T.H.D.: 0.15% at 1kHz

Peak Indicators: 12 x LED

Power Supply: 240V AC 50Hz

Power Consumption: 8W

Dimensions: 662(W) x 356(D) x 105(H)mm

Weight: 8kg

RRP \$999

OUR PRICE \$899

THE BRILLIANT SERIES 5000

INDIVIDUAL COMPONENTS TO
MAKE UP A SUPERB HIFI SYSTEM!

PRICES MUST RISE!
STRICTLY LIMITED STOCK
AVAILABLE AT THESE PRICES.


POWER AMPLIFIER

WHY YOU SHOULD BUY A "ROD IRVING ELECTRONICS"
SERIES 5000 POWER AMPLIFIER....

- 1% Metal Film resistors are used where possible.
 - Aluminium case as per the original article.
 - All components are top quality
 - Over 1000 of these kits now sold.
 - Super Finish front panel supplied at no extra cost.
- Please note that the "Superb Quality" Heatsink for the Power Amplifier was designed and developed by ROD IRVING ELECTRONICS and is being supplied to other kit suppliers.

SPECIFICATIONS: 150 W RMS into 4 ohms
POWER AMPLIFIER: 100W RMS into 8 ohms (+ -55V Supply)
FREQUENCY RESPONSE: 8Hz to 20kHz +0 -0.4dB 2 8Hz to 65kHz
+0 -3dB. NOTE: These figures are determined solely by passive filters
INPUT SENSITIVITY: 1 V RMS for 100W output
HUM: 100 dB below full output (flat)
NOISE: 116 dB below full output (flat, 20kHz bandwidth)
2nd HARMONIC DISTORTION: -0.001% at 1 kHz (0.0007% on Prototypes)
at 100W output using a + -55V SUPPLY rated at 4A continuous -0.0003% for all
frequencies less than 10kHz and all powers below clipping
TOTAL HARMONIC DISTORTION: Determined by 2nd Harmonic Distortion
(see above)
INTERMODULATION DISTORTION: 0.003% at 100W (50Hz and 7kHz
mixed 4:1)
STABILITY: Unconditional

Cat. K44771 Will be \$359, limited stock available at \$319
Assembled and tested \$525
packing and post \$10




PREAMPLIFIER

THE ADVANTAGES OF BUYING A
"ROD IRVING ELECTRONICS" SERIES 5000
PREAMPLIFIER KIT ARE....

- 1% Metal Film Resistors are supplied.
 - 14 Metres of Low Capacitance Shielded Cable are supplied (a bit extra in case of mistakes).
 - English "Lorlin" switches are supplied (no substitutes here.)
 - Specially imported black anodised aluminium knobs.
- Available Assembled and Tested. (We believe that dollar for dollar there is not a commercial unit available that sounds as good!)

SPECIFICATIONS:
FREQUENCY RESPONSE: High-level input 15Hz - 130kHz - 0 - 1dB
Low-level input conforms to RIAA equalisation + -0.2dB
DISTORTION: 1kHz - 0.003% on all inputs (limit of resolution on measuring
equipment due to noise limitation)
S/N NOISE: High-level input, master full, with respect to 300mV input signal at
full output (1.2V) -92dB flat -100dB A-weighted, MM input, master full, with
respect to full output (1.2V) at 5mV input 50ohms source resistance connected
-86dB flat -92dB A-weighted MC input, master full, with respect to full output
(1.2V) and 200uV input signal -71dB flat -75dB A-weighted

Cat. K44791 Will be \$289, limited stock available at \$269
Assembled and tested \$599
packing and postage \$10



THIRD OCTAVE GRAPHIC EQUALIZER

SPECIFICATIONS:
BANDS: 28 Bands from 31.5Hz to 16kHz.
NOISE: -0.008mV, sliders at 0, gain at 0 (-0.3dB)
20KHz BANDWIDTH DISTORTION: 0.007% at 300mV signal,
sliders at 0, gain at 0, maximum 0.01% sliders at minimum
FREQUENCY RESPONSE: 12Hz - 105kHz, +0 -1dB, all
controls flat
BOOST AND CUT: 14dB

Cat. K44590 1 Unit ... \$199
2 Units ... \$394
packing and postage \$10

SERIES 4000 SPEAKERS

- 8 Speakers On ... \$295
- 8 Speakers with Crossovers ... \$499
- Speaker Boxes (assembled with grill
and speaker cutout) ... \$325
- Crossover Kits ... \$199
- Complete kit of parts (speakers,
crossovers, screws, innerband
boxes) ... \$799
- Assembled, tested and ready to
hook up to your system ... \$895

Errors and Omissions Excepted



SUPER HORN TWEETER

- Requires no crossover and handles up to 100W!
 - Sensitivity 100dB/0.5m
 - Frequency Response: 3kHz - 30kHz
 - Impedance 8 OHMS
 - Size 96mm diameter
- Cat. C12102 normally \$14.95
NOW \$12.95




SUPER HORN

- Wide dispersion tweeter, handles up to 100W.
 - Sensitivity 105dB/0.5m
 - Frequency Response: 3kHz - 30kHz
 - Impedance 8 OHMS
 - Size: 145x54mm
- Cat. C12103 normally \$14.95
NOW \$12.95



10W RMS SPEAKERS

Including boxes! At this price you can afford to put a set of speakers in every room!
Dimensions: H 4 1/2" x W 2 1/4" x D 1.900mm
Cat. C12002 Per Pair \$59.50




PHILIPS SPEAKERS

"Hopefully, we should have Philips speakers back in stock by the time you read this." - Rod

- Cat. C12030 AD01610 T8 \$12.95
- Cat. C12040 AD02160 S08 \$34.95
- Cat. C12045 AD70620 M8 \$49.00
- Cat. C12050 AD12550 W8 \$79.00 (or Philips equivalent supplied)

COMPUTER CHESS! by SciSys.


SciSys computer chess games are endorsed by Garry Kasparov, world's highest rated chess player, and are available from Rod Irving Electronics!



ELECTRONIC CHESS MK10

- Streamline design tabletop chess.
- New 8 level program from beginners to experts.
- Ideal teacher or strong opponent.
- Turn on/off any time. One year memory.
- 1,000 hours play with 3AA batteries.
- Optional mains adaptor available.
- Take back moves, verify, solve problems to mate in 3 and beyond.
- Player vs. player mode, thinks on opponents time, built in opening library.
- Beginner to expert, Estimated 1,500 Elo.

MK10 offers so much for so little!
Cat. C30002 \$149



TRAVEL MATE

- World's most compact sensor chess.
- Ideal teacher or strong opponent.
- Turn on/off anytime. It remembers positions for up to one year.
- Plays for over 6 months on 3AA batteries.
- Knows all the rules and will not accept illegal moves.
- Low cost, 4 powerful skill levels.
- Estimated 1,400 Elo

Cat. C30000 \$99



COMPANION 11

- SciSys No.1 selling full size computer!
- Very strong chess program.
- 9 levels with special zero level for beginners.
- Ideal teacher or formidable opponent.
- Turn on/off anytime, one year memory.
- 6 months play on 3AA batteries or optional mains adaptor available.
- Take back moves, verify, solve problems to mate in 4 and beyond.
- Player vs. player mode, thinks on opponent time, built in opening library and strong end game.
- Beginner through club player to expert. Estimated 1,650 Elo


Cat. C30004 \$199



3 IN 1 GAMES

- CHESS, TIC TAC TOE, AND CHECKERS!
- CHESS: 8 levels, solves up to mate in 4 moves.
- TIC TAC TOE: 4 levels of skill, big easy to use pieces, quick response, take back facility.
- CHECKERS: 8 levels of skill, take back facility.

Perfect for the whole family!
Cat. C30008 \$149



EXPRESS 16K

- Instant response hand held chess computer.
- Instant response - uses opponents thinking time to prepare instant replies to several alternative opponent moves.
- Strong program beats 90% of all chess players (estimated SciSys-Elo 1800).
- Automatic Display Move function
- Extra flat. High-value metallic finish.
- Fast 8 MHz 16K chip.
- 17 playing levels: 1 beginner, 8 casuals, 6 club, 2 special (analysis and problem to Mate in ten moves).
- Very long battery life, 1000 hours playing, one year memory.

Cat. C30006 \$199



TURBO 16K

This brand new chess computer sets new standards in user convenience, and beats 92% of all chess players with its powerful 16K program.

- Features:
- Instant response
 - Solves mate in 10 moves
 - Internal clock with 2 LCD displays
 - Displays moves considered
 - Thinks in opponent's time
 - Takes back
 - 17 Levels
 - 2 Year memory
 - Mains adaptor socket

Cat. C30010 \$295



1/4" FLOPPY DISK SPECIALS!

XIDEX	1-9	10+
S/D/D	\$31.00	\$29.00
Cat. C12401		
D/S/D	\$38.95	\$36.50
Cat. C12410		
VERBATIM DATALIFE		
S/D/D	\$27.95	\$26.95
Cat. C12501		
D/D/D	\$39.95	\$37.95
Cat. C12504		
VERBATIM VALULIFE		
S/D/D	\$24.95	\$22.95
Cat. C12421		
D/D/D	\$31.95	\$29.95
Cat. C12425		

3 1/2" XIDEX DISKETTES!

Yes, that's right, we now have 'hard to get' 3 1/2" diskettes!

Cat. C12600 S/S box of 10 \$65.95

Cat. C12602 D/S box of 10 \$89.95



DELUXE 5 1/4" DISK STORAGE UNIT

- Features...
- Clear smoked plastic lid
 - Diskette fan display system elevates the disks for easy identification and access.
 - Lockable lid (2 keys supplied)
 - High impact plastic base
 - 45 diskette capacity


Cat. C16050 \$49.50



MINI DISK STORAGE BOX

Holds up to 30 x 5 1/4" diskettes.

Cat. C16020 \$16.95



RS232 MINI PATCH BOX

- Interface RS232 devices
- With male to female 25 pin inputs
- 25 leads with tinned end supplied
- Complete with instructions

Cat. X15654 \$25.95



RS232C NULL MODEM ADAPTOR

- Male to female connections
- Pins 2 and 3 reversed
- All 25 pins connected

Cat. X15658 \$19.95



TELEPHONE CABLE UNIT

Allows 15 metres of telephone extension cable to be neatly wound into a portable storage container. The reel sits on a squared off base and the reel has a handle to wind cable back on to it after use. No tangles - no mess! Ideal for the workshop, around the house, office pool etc.

Cat. Y16013 \$24.95



TELEPHONE CABLE UNIT


Ideal for modem connections.

Cat. Y16014 \$12.95



NEW PHONE PLUGS & SOCKETS

We hear on the grapevine that all future installation will use the U.S. A type of plug and sockets for communication lines.



TELEPHONE CURL CORD

- U.S. plug to U.S. plug
- Replacement hand set cord
- Length 4.5 metres
- Colours: cream, dark brown

Cat. Y16022 \$7.95



TELEPHONE ADAPTOR

- Australian plug to U.S. socket
- Length 10cm
- Cream colour cable

Cat. Y16026 \$6.95



MAINS MUFFLER

Sudden mains disturbances can seriously affect your computer equipment, and stored data. Why risk it when you can have a Mains Muffler, particularly when the cost of one failure is likely to be greater than the purchase price! So Vanish these dangerous clicks and Voltage spikes forever with the Mains Muffler.

Specifications:

Maximum total load: 1000W 4 AMP 250V 50Hz

First Stage: Single PI Section

Attenuation: 150KHz - 40dB

500 KHz - 65dB

10 KHz - 80dB

Second Stage: Dual T Section

Attenuation: 150KHz - 20dB

500 KHz - 60dB

10 KHz - 70dB

VDR Transient Suppression

Surge capacity 2000 AMP 8x20 uS

Cat. \$249



1200/75 BAUD RATE/BIT CONVERTER

For computers not capable of split baud rates. Buffers characters at 1200 and converts to 75 baud

Cat. X19105 \$99




COMPUTER CASSETTES

Quality 20 minute tapes.

Cat. D11141

1-9 10+ 100+

\$1.50 \$1.40 \$1.20




QUALITY SWITCH MODE POWER SUPPLY FOR APPLES

INPUT: AC 240V

OUTPUT: DC +5V 5A +12V 4A

DC -5V 5A -12V 5A

Cat. X11095 \$139



130W IBM COMPATIBLE SWITCH MODE POWER SUPPLY

DC output: +5/13A, -5V/0.5A

+12V/4.5A -12V/0.5A

AC input: 240V AC +15% 1.5A

47Hz - 63Hz

Cat. X11096 \$239



MODEM PHONE

Check the features and the value for money of this stylish new modem phone...

- Auto/Manual Answer, Manual Originate, Auto Disconnect.
- Speaker Phone with Built-in Amplifier for Detecting Busy Signal during communication.
- Carrier Detect Indication.
- 20 Memories (each with 18 Digits Capacity) for Auto-dialling.
- BELL 103 CCITT V21 Compatible.
- 300 BPS Full Duplex.
- Last Number Redial.
- Pushbutton Keyboard.
- Volume High or Low Control.
- "In-use" Dialing Indicator.

Cat. X19105 only \$174

(Not Telecom approved)



RITRON MULTI PURPOSE MODEM

Our New RITRON Multi Purpose Modem has arrived and has all the standards you require.

Just check the Ritrone's features.

- CCITT V21 300 Baud Full duplex
- CCITT V23 1200/75
- Bell 103 300 Full duplex
- Bell 202 1200 Half duplex
- Auto answer, auto disconnect.

Telecom Approval No. C84/37/1134

\$379



RS232C NULL MODEM ADAPTOR

- Male to female connections
- Pins 2 and 3 reversed
- All 25 pins connected


Cat. X15658 \$19.95



RS232 GENDER CHANGERS


- Saves modifying or replacing non-mating RS232 cables by changing from male to female to male
- All 25 pins wired straight through

Cat. X15650 \$19.95




Male to Male

Cat. X15650 \$19.95



Female to Female


Cat. X15652 \$19.95



RS232 MINI TESTER

- Male to female connections
- All pin wired straight through
- Dual colour LED indicates activity and direction on 7 lines
- No batteries or power required
- T D Transmits Data
- R D Data Set Ready
- R D Receive Data
- C D Carrier Detect
- R T S Request to Send
- D T R Data Terminal Ready
- C T S Clear to Send

Cat. X15656 \$39.95



APPLE JOYSTICKS


Ideal for games or word processing. Fits most 6502 "compatible" computers.

Cat. C14200 \$29.95



NEW PHONE PLUGS & SOCKETS

We hear on the grapevine that all future installation will use the U.S. A type of plug and sockets for communication lines.



TELEPHONE CURL CORD

- U.S. plug to U.S. plug
- Replacement hand set cord
- Length 4.5 metres
- Colours: cream, dark brown


Cat. Y16022 \$7.95



TELEPHONE ADAPTOR

- Australian plug to U.S. socket
- Length 10cm
- Cream colour cable

Cat. Y16026 \$6.95



MAINS MUFFLER

Sudden mains disturbances can seriously affect your computer equipment, and stored data. Why risk it when you can have a Mains Muffler, particularly when the cost of one failure is likely to be greater than the purchase price! So Vanish these dangerous clicks and Voltage spikes forever with the Mains Muffler.

Specifications:

Maximum total load: 1000W 4 AMP 250V 50Hz

First Stage: Single PI Section

Attenuation: 150KHz - 40dB

500 KHz - 65dB

10 KHz - 80dB

Second Stage: Dual T Section

Attenuation: 150KHz - 20dB

500 KHz - 60dB

10 KHz - 70dB

VDR Transient Suppression

Surge capacity 2000 AMP 8x20 uS

Cat. \$249




5 1/4" DISK STORAGE

Efficient and practical. Protect your disks from being damaged or lost!

Features...

- Smoked plastic cover
- Lockable (2 keys supplied)
- High impact ABS plastic base
- Dividers/spacers


Cat. C16020 \$29.50



JOYSTICK FOR IBM

Features Selectable "Spring centering" or "free floating" Electrical adjustments on both axis. 360 degree cursor control

Cat. C14205 \$39.95



APPLE JOYSTICKS

Ideal for games or word processing. Fits most 6502 "compatible" computers.

Cat. C14200 \$29.95



COMPUROBOT

Simply key in a list of commands to the amazing CompuRobot and watch him go about performing even your most complex maneuvers - up to 48 steps! Forward, backward, left/right turn, left/right curve, robot noises, flashing lights and a multi speed gearbox!

Cat. \$49.50



IC SPECIALS!

	1-9	10+	100+
4116	\$1.80	\$1.70	\$1.60
4164	\$1.95	\$1.75	\$1.70
2716	\$5.90	\$5.50	\$5.50
2732	\$5.25	\$4.95	\$4.50
2764	\$6.25	\$5.95	\$5.50
27128	\$7.00	\$6.50	\$6.25
6116	\$2.50	\$2.25	\$1.95
41256	\$7.00	\$6.50	\$6.00
6264	\$7.00	\$6.50	\$6.00

MSM5832 BACK IN STOCK!

1-9 10+ 11.50

NEWIC's

	1-9	10+
MCS2400	\$ 4.90	\$ 4.75
41256	\$ 9.00	\$ 8.50
27128	\$ 7.00	\$ 6.50
74LS169	\$ 2.50	\$ 2.40
AY-3-1050	\$12.50	\$11.95
WD2791	\$69.00	\$67.00
WD2793	\$69.00	\$67.00
WD2795	\$69.00	\$67.00
WD2797	\$69.00	\$67.00
LM11CN	\$ 2.95	\$ 2.75
LM1871	\$ 5.95	\$ 5.75
LM1872	\$ 5.95	\$ 5.75
Z80ADART	\$13.50	\$12.95
LM338K	\$10.60	\$ 9.50
AM153530	\$24.95	\$23.95
AM7910	\$49.50	\$45.00
(World Modern Chip)		
UPC1031	\$19.50	
R.F. Module		



**APPLE* COMPATIBLE
SLIMLINE DISK DRIVE**
Japanese Chinon mechanism
Normally \$225 This month \$195
(*Apple is a registered trademark)



**ADD ON HARD DISK
DRIVE FOR IBM**
Includes disk controller card
Available and installed free only at
our city store
Cat. X20010
10 M Byte \$1,195
20 M Byte \$1,350



**MITSUBISHI DISK
DRIVES**
MF353 (3 1/2" DRIVE)
Double sided, double density,
1 MByte unformatted, 80 track per
side
Cat. C11953 \$280

MF351
3 1/2" Standard size disk drive
Single sided, double density
Cat. C11922 \$225

M2896-63
Slimline 8" Disk Drive. Double sided
Density No AC power required 3ms
track to track, 1.6 Mbytes
unformatted, 77 track side 10s/5u10
bit soft error rate
Cat. C11916 \$550
Case & Power Supply to suit
Cat. X11022 \$159

M4854
Slimline 5 1/4" disk drive. Double
sided, double density, 96 track/inch,
9621 bit/inch, 1.6 Mbyte unformatted
3ms track to track access, 77 track/
side
Cat. C11904 \$350
Case & Power Supply to suit
Cat. X11011 \$109

M4853
Slimline 5 1/4" disk drive. Double
sided, double density, 1 Mbyte
unformatted, 3ms track to track 80
track/side, 5922 bit/inch
Cat. C11903 \$260


M4851
Slimline 5 1/4" disk drive. Double
sided, double density 500K
unformatted, 40 track/side. Steel
band drive system.
Cat. C11901 \$199




KEYBOARD AND CASE
A stylish low profile case to give
your system the professional look it
deserves. Comes with an attached
encoded, parallel output keyboard
and provisions for 2 x 5 1/4" slimline
disk drives
Cat. X11080 \$249




**"IBM AT STYLE"
COMPUTER CASING**
Our latest computer casing, featuring
security key switch, 8 slots, and
mounting accessories etc.
Dimensions: 490(W)x145(H)x400(D)
Cat. X11091 \$139




**"IBM PC TYPE"
COMPUTER CASING**
Give your kit computer a totally
professional appearance with one of
these "IBM type" casings. Includes
room for 2 5 1/4 inch disk drives,
connection ports and mounting
accessories etc.
Dimensions: 490 x 390 x 140mm
Cat. X11090 \$119



**THE 'C' PROGRAMMER'S
HANDBOOK**
This handbook is an introduction
and a reference to the C programming
language, both for beginning and
experienced programmers. C is a
general purpose language featuring
economy of expression, and modern
flow control and data structures.
Concise structure and fast execution
make C the ideal language for
applications and system-level
programming
\$27.50



INSIDE CP/M
A Guide for users and programmers
with CP/M-86 and MP/M2, by David
Cortesi.
This book is both a guide and a
reference manual for CP/M, an
operating system for small computers.
The book has two sections. The
Tutorial presents the basics of the
management, use, and programming
of a small computer and CP/M. In the
Reference, CP/M information is
organised for quick access by
programmers and users.
\$47.50



READY MADE CABLES
Serial to serial. 2 m
Cat. P19011 \$24.95
Parallel centronics to centronics. 2m
Cat. P19013 \$29.95



**SOLDER CENTRONICS
PLUGS**
Cat. P12210 only \$4.50



**REPLACEMENT
KEYBOARDS**
• For Apple
• 42 single key BASIC command
• One chip custom design encoder
• Made by ALPS, life time,
10 million operations
• Dimension: L340xW110xH42mm
Cat. K12010 \$79.50

• For Apple
• 45 built in function keys. BASIC
and CP/M command.
• 45 user defined keys
• Built-in shift keys
• Made by ALPS, life time,
10 million operations
• Dimension: L340xW130xH42mm
Cat. K12012 \$99.00



**COMPUTER AND DISK
DRIVE CASES AND
POWER SUPPLIES**
5 1/4" DRIVES
1 x 5 1/4" Slimline Drive Case
X11001 Bare Case \$49
X11011 Case and Pwr Supply \$109
2 x 5 1/4" Slimline Drive Case
X11002 Bare Case \$69
X11012 Case & Pwr Supply \$149
1 x 5 1/4" Standard Drive Case
X11003 Bare Case \$45
X11013 Case & Pwr Supply \$109
2 x 5 1/4" Standard Drive Case
X11004 Bare Case \$59
X11014 Case & Pwr Supply \$149
8" DRIVES
1 x 8" Standard or 2 x 8" Slimline.
and computer Case (BB1)
X11006 Bare Case \$39
X11016 Case & Pwr Supply \$399
2 x 8" Slimline Drives and
Computer Case (BB1 and BB2 etc)
X11007 Bare Case \$145
X11017 Case & Pwr Supply \$399
1 x 8" Slimline Drive Case
X11020 Bare Case \$95
X11022 Case & Pwr Supply \$159
Dual 8" Slimline Drive Case
X11025 Bare Case \$99
X11026 Case & Pwr Supply \$275

Save on peripherals at Rod Irving Electronics,



**APPLE COMPATIBLE
CARDS!**
PRINTER CARD
"Grappier" style card allows hi-
resolution screen dumps to your
Epson compatible printers. Fully
functioned for flexible flow of output
Cat. X17029 \$89

80 COLUMN CARD
Ideal for use with CP/M. Your
computer becomes capable of
upper and lower case, with a full
width screen of 80 characters. If you
want to run Wordstar, or any good
wordprocessing software, get this
card.
Cat. X17019 \$85

P.A.L. COLOUR CARD
Get some colour into your games.
Use your Apple or compatible on the
second television. Has both UI-
and composite video outputs. Fully
adjustable so you can fine tune it for
a crisp clean image.
Cat. X17025 \$95

SUPER SERIAL CARD
No card does it better. Want to hook
in to bulletin boards or mainframes?
Turn your computer into a dumb
terminal. That's right! This serial
card comes complete with software
Cat. X17035 \$129

SPEECH CARD
Simple to use, software controlled
speech synthesiser kit. Complete
with demonstration programs and
text to speech software. Impress
your friends with your talking Apple!
Cat. X17009 \$69

MUSIC CARD
Three channel synthesiser can
create a single polyphonic output or
three monophonic outputs. Control
of pitch and volume is possible. Up
to three cards can be used at the one
time. Complete with demonstration
software.
Cat. X17011 \$99

RGB CARD
True high definition colour for your
Apple or compatible
Cat. X17039 \$79



IBM COMPATIBLE CARDS
MULTIFUNCTION CARD
(384K RAM) Parallel, serial and
game port. Plus battery backup clock
Cat. X18013 \$429

DISK CONTROLLER CARD
Controls 2 slimline drives
Cat. X18005 \$149

**HIGH RESOLUTION
MONOCHROME GRAPHICS CARD**
Give your IBM real graphics capability
Cat. X18007 \$249

512K RAM CARD
(Includes RAM)
Cat. X18015 \$399



NEW TTL MONITORS
Fantastic resolution! Enjoy a crisp,
sharp image with these new Ritron
TTL monitors! IBM* compatible,
green display, swivel and tilt base.
Cat. X14510 \$265




MITSUBISHI MONITORS
Green Cat. X14514 \$199
Amber Cat. X14516 \$209



RITRON 1
Our most popular model in a steel
cabinet to minimise R.F.I.
interference.
Green Cat. X14500 Save \$30 \$169
Amber Cat. X14502 Save \$30 \$179



RITRON 2
Stylish swivel base monitor,
available in amber or green.
Green Cat. X14500 \$215
Amber Cat. X14500 \$219




**XIDEX PRECISION
SCREEN**
Headaches, fatigue and tired eyes
are a common complaint from users
of CRT's. But studies have reported
that the use of the Xidex Precision
Screen, actually increases
efficiency 20% while relieving eye
strain, headaches and general
fatigue.
Available in two sizes
7 7/8" x 10 1/2" Cat. X99997 \$49.95
8 1/2" x 11" Cat. X99999 \$49.95




PHOENIX 5
Suits Apple, Commodore, even your
VCR!
• Pal and R.G.B.
• Normal Resolution
• 13" CRT Dot Pitch 0.65mm
• Horiz. Resol. 320 TV lines
• Vert. Resol. 560 TV lines
• Display Characters 1,000
Ch (40x25)
• 16 Colours (Pal)
• Green text display
Cat. X14522 \$499

PHOENIX 4
• R.G.B.
• High Resolution
• 13" CRT Dot Pitch 0.31mm
• Horiz. Resolution 720 dots
• Vert. Resolution 240 T.V. Lines
• Display Characters 2000
Ch (80 x 25)
• 8 Display colours and intensity
• Green text display
Cat. X14520 \$799



RITRON 2
Stylish swivel base monitor,
available in amber or green.
Green Cat. X14500 \$215
Amber Cat. X14500 \$219



COMPUTER LEADS
We have a wide range of computer
leads available, all at very
reasonable prices!

APPLE:
• Apple II, IIe, II+, with parallel
interface card
• Dual 10 pin (20 contacts)
connector to Centronics 36 pin plug
• Length 2.4 metres
Cat. P19025 \$24.95

IBM
• IBM PC, XT, and look alikes with
25 pin "D" plug on computer end
to Centronics 36 pin plug on
printer end
• Length 2.1 metres
Cat. P19029 \$34.95

TANDY
• For models II/12/16/2000,
with dual 17 pin female on
computer end to Centronics 36 pin
plug on printer end (Equivalent to
26-1323)
• Length 2.4 metres
Cat. P19027 \$29.95


• For models I/III/4/4P, with 34 pin
edge connector on computer end
to Centronics 36 pin plug on the
printer end. (Equivalent to 26-1401)
• Length 2.4 metres
Cat. P19028 \$32.50



180 CPS PRINTER!
KAITEC KAI 180 EX
Standard 80 column Dot Matrix
Printer. High quality printing by
NLQ mode. 3K Buffer. High-speed,
low-energy consumption 9 wire
dot head allows 180 characters
per second.
Logic seeking printing or incremental
printing with high response, stepping
motor. Use of fan-fold, roll or
cut-sheet paper is possible with
adjustable sprocket pin feed and
friction feed. Both fixed and
proportional character pitches are
available. Emphasized and double
print modes are possible. 9 graphic
modes are available. 8 language
international character font
internalized.
SPECIFICATIONS:
Printing Type: Impact Dot
Matrix
Maximum Printing Range: 203mm
Print Types: ASCII 96 Others 7
language
Character Format: Character
Mode Standard 9 x 9 dots
NLQ 18 x 20 dots Graphic Mode
Printer Modes: (a) Fixed pitch mode
(b) Proportional pitch mode
Character Size: 2.42(H) x 1.99(W)
Printing Speed: 180 Character
per sec. (picp)
Paper Feed Method: (a) Adjustable
sprocket pin feed paper width 4-10
inch (pull through) (b) Friction feed
paper width 4-5.5 inch
Interface: Parallel interface 8-bit
printer (Conforms to Centronics)
Cat. C20020 Only \$499



BX RANGE OF PRINTERS!
BX 100 \$370
BX 130 \$440
BX 130W (15") \$595



PRINTER RIBBONS
CP80, BX80, DP80, BX100, MB100
\$9.90



COMPUTER PAPER
Top quality at a very affordable price!
Blank 11 x 9 1/2", 2,000 sheet
quality 60 gsm bond paper
Cat. C21001 \$34.50



MINI JUMPERS
• Contain terminal Phosphor bronze
• Material: P.B.T 94V-0
• Gold plated
Qty Cat. No Price
10 P12053 \$ 2.95
25 P12055 \$ 4.95
100 P12057 \$21.95

IBM* COMPATIBLES from \$1,495!




Incredible deals to suit everyone
including our special package
deals!

256K RAM: Colour Graphics, Disk
Controller Card, 1 parallel port,
2 disk drives and 3 months warranty
only \$1,495

640K RAM: Colour graphics,
Multifunction Card, Disk Controller
Card, 2 serial and 1 parallel ports,
2 disk drives and 3 months warranty
only \$2,100

256K PACKAGE DEAL: Includes
Colour Graphics Card, Multifunction
Card, Disk Controller Card, 2 serial
and 1 parallel ports. A 120 C.P.S.
printer and a monochrome monitor
and 3 months warranty! only \$2,400

640K PACKAGE DEAL: Includes
Colour Graphics Card, Multifunction
Card, Disk Controller Card, 2 serial
and 1 parallel ports. A 120 C.P.S.
printer, a monochrome monitor and
3 months warranty! only \$2,500
*IBM is a registered trademark



ROD IRVING ELECTRONICS
425 High Street, NORTHCOE, 3070
VICTORIA, AUSTRALIA
Phone (03) 489 8866
48 A Beckett St, MELBOURNE, 3000
VICTORIA, AUSTRALIA
Ph. (03) 663 6151
Mail Order and correspondence:
P.O. Box 620, CLAYTON 3168
TELEX AA 151938



MAIL ORDER HOTLINE
(03) 543 7877
(2 lines)

POSTAGE RATES

\$19.99	\$2.00
\$19.99 - \$24.99	\$3.00
\$25.00 - \$49.99	\$4.00
\$50.00 - \$99.99	\$5.00
\$100.00 - \$199.99	\$7.50
\$200.00 - \$499.99	\$10.00
\$500.00 plus	\$12.50

This is for basic postage only. Comet
Road freight, bulky and fragile items
will be charged at different rates.
Certified Post for orders over
\$100 included "free!"
Registered Post for orders over
\$200 included "free!"
All sales tax exempt orders and
wholesale inquiries to RITRONICS
WHOLESALE, 56 Renner Rd., Clayton,
Phone (03) 543 2166



Errors and Omissions Excepted.

Get rid of your secretary . . .

Toshiba's T1100 sits comfortably on your lap

For anyone still under the impression that portable lap-top computers are little more than toys, the new Toshiba T1100 should be a real eye-opener. Functionally it's near enough to a portable equivalent to the IBM-PC, crammed into a case only 310 x 316 x 66mm — and able to operate for up to eight hours from its internal rechargeable batteries.

by JIM ROWE

Lap-top portable computers have been available for a couple of years now, and have sold in reasonable numbers. They've been popular with journalists as portable word processors, and also with gad-about executives, who found that they could use them for "homework" on business trips. At least this was the theory.


In practice, I wouldn't be at all surprised if many of those early lap-top portables are now quietly gathering dust in cupboards, because they weren't actually capable of much serious use. With painfully small display screens, limited memory and generally rather crude tape cassette storage for files, they were really little more than executive toys. If you wanted a serious personal computer, you had to go for a "solid" desktop model taking up most of a desk and powered from the mains.

But things are now changing. Lap-tops are rapidly coming of age, and have now reached the point where you can have serious computing power and portability in the one machine.

The Toshiba T1100 is an example of this new breed of lap-tops, and a very impressive example it is. With an 8/16-bit CPU, 256K bytes of inbuilt RAM (expandable to 512K) and an inbuilt microfloppy disk drive taking 720K byte



Toshiba's T1100 lap-top computer — a portable equivalent to the IBM PC.



Despite compromises, the keyboard is of professional quality and pleasant to use.

double-sided double density disks, it offers more computing power than most desktop machines — plus a very high level of compatibility with the industry reference IBM-PC.

Display screen

Instead of the cramped 1-line or 4-line displays of earlier lap-tops, the T1100 features a large swing-up LCD screen with an active area measuring 223 x 97mm. This displays exactly the same amount of data as the monitor screen of the IBM-PC and many other desktop machines — 25 lines of 80 characters. It has the same graphics resolution too: 640 x 200 pixels, although they're all in LCD-grey rather than colour.

As an alternative to the inbuilt LCD screen, the T1100 will also operate with a normal external monochrome or colour video monitor (either composite or RGB). Not that you'd want to lug such a monitor along with you on the plane, of course, but it does allow you to get a full colour display when you're back at the desk.

Along with the LCD screen, the T1100 provides a keyboard with 83 keys — the same number as the IBM-PC, and although there are differences the two are functionally very close.

The T1100 also provides an inbuilt Centronics-type parallel printer port, with a 25-pin D-type connector pin-compatible with that on the IBM-PC.

In short, then, the T1100 offers virtually everything you get with the base level IBM-PC — *plus* the fact that it is portable and can run for up to eight hours from inbuilt NiCd batteries. Back

at the desk, you charge the batteries via an 18V/600mA plugpack power adaptor, which can also run the computer as a desktop unit when the batteries are charged.

All this in a trim and compact package measuring only 310 x 306 x 65 mm, and weighing about 4kg — less than all but the lightest and most flimsy portable typewriters!

So it's a powerful little package, and anything but a toy. In fact I can well imagine people buying it in preference to full size desktop models like the IBM-PC, not because they want to take it on their travels, but simply because of its neatness and compact elegance. Even as a desktop it will have considerable appeal — especially if you don't want to expand it dramatically.

Expansion

Needless to say, in the T1100's compact little case there just isn't space for the usual row of "expansion slots" beloved of committed computer freaks. But the machine is still capable of quite a deal of expansion — probably quite enough for the majority of professional and business users.

For example, there's a 37-way D-type connector at the back to plug in a second disk drive, and Toshiba provides a choice of two add-on drives. There's another 3½ inch microdrive to add a second 720K bytes of storage, or a 5¼ inch minifloppy with the standard 360K bytes of storage if you want to be able to swap data and/or software with an IBM or more conventional IBM clone.

Interestingly enough, the add-on 3½ inch drive has an inbuilt NiCd battery,

like the T1100 itself. So if you really need to, you can take the second drive away on your travels — or do your homework in comfort out on the patio, without having to search for an extension cord! The 5¼ inch drive doesn't offer this feature.

Of course the inbuilt Centronics-type printer port lets you hook up the T1100 to a wide variety of standard printers. It worked quite happily with my TEC-Itoh F-10/40 daisywheel, for example.

Incredibly enough, the T1100's designers have allowed space inside its compact case for two further internal expansion options. There's provision for an RS-232C serial communications adaptor, so you can hook it up to a telephone modem, a serial printer or some other serial format peripheral. The second option is a memory expansion card providing an additional 256K bytes of dynamic RAM.

By the way, these expansion options are quite independent of each other. You can fit either or both as you wish. The RS-232C port adaptor fits just inside the rear of the case, which has a small break-out piece to allow access to the adaptor's 9-pin D type connector.

So if you wish, the T1100 can be expanded to a full-blown system with RGB colour monitor, 512K bytes of RAM, two disk drives with 1.44 Megabytes of storage, a printer of your choice and a communications modem. This is more powerful than most existing IBM-PC systems in use, and quite sufficient for a lot of serious work.

Software

On the software side, as I mentioned

Toshiba's T1100

earlier, the T1100 offers a high order of compatibility with the IBM-PC. It runs with MS-DOS, and also seems to be able to run a majority of programs written for the IBM and its clones. This suggests that its BIOS routines are functionally very close to those in the IBM, making it about as close to the IBM as you can get.

I have been able to try out the sample machine with quite a few programs, either as supplied with the sample unit on 3½ inch micro disks or on 5¼ inch disks which I know to run on my IBM. Just about all of them worked normally, including Flight Simulator — which often comes to grief on “compatible” machines, because it makes direct call to the the graphics hardware.

Wordstar and Multiplan seemed to work quite happily, as did Crosstalk — although I couldn't try this out properly as the sample machine wasn't fitted with the RS-232C port.

I tried booting up PC-DOS itself, using the external 5¼ inch drive (the T1100 has a slider switch on the back which allows you to make the external drive the “A” drive, and the internal drive “B”, if you desire). Although it seemed to function quite normally handling programs and files on its own drive, it didn't like trying to find files on disks in the microdrive — presumably the directory is formatted differently.

Similarly the IBM version of BASICA wouldn't run, no doubt because this version is designed to graft itself onto



The T1100 features an in-built 3½ inch microfloppy disk drive.

the IBM's ROM BASIC and the Toshiba doesn't have any. But a program called BASICA that I found on one of the T1100's microdisks did run some programs written on and for the IBM without any problems.

Even though this was called BASICA on the microdisk directory, presumably it is really a version of Microsoft's sister product GW-BASIC, tailored for the T1100. Its file size on the disk is shown as 53440 bytes, which suggests the free standing RAM resident GW-BASIC rather than BASICA.

Not that these complications with the DOS and BASIC are of any real consequence, I hasten to add. Since the T1100 comes with its own version of MS-DOS and (ultimately) BASIC, and both seem to be able to cope directly with IBM software, it's fairly easy to do almost anything most people are ever likely to want.

Using the T1100

Right then — so much for the basic hardware and software capabilities of

the Toshiba T1100. But what's it like to use?

Generally, very nice indeed, although it does have a few shortcomings. There are also a few things which are bound to irritate anyone like myself, used to using an IBM. I'll go through these in approximate order of importance.


Probably the first thing that struck me when I fired up the sample T1100 was the modest contrast and visibility of the LCD screen, particularly in certain types of ambient lighting. After having used it for a few days now, I'm inclined to think this is probably the machine's main shortcoming.

Being a passive display, the LCD panel is very dependent on the surrounding light level — without any ambient light, there's no display. So you must have a reasonable amount of light; yet at the same time you can't have it coming from an angle such that it produces annoying reflections from the front glass. Diffused light seems to be best, but here again if it's too bright, you tend to get an annoying reflection of yourself.

Like all LCD displays the T1100 screen has to be tilted at just the right angle for best contrast, too, producing a further element of complication.

Mind you, I'm not suggesting that the T1100 is any worse than any other machine with an LCD display. At this stage of their development LCD displays are rather more finicky and a little inferior to CRT screens in terms of readability. But they do have one big advantage, that of compactness and the ability to consume very little power. So if you want a truly portable machine like the T1100, an LCD screen is really the only choice.

In the case of the T1100, my reaction is that despite the limitations of the



The external 5¼ inch minifloppy drive adds an extra 360K bytes of storage.

LCD screen, it will still be found quite acceptable when the machine is used as a portable. But back at home base when it is used on the desk top, most people will find that a conventional CRT-type monochrome or colour monitor makes a very worthwhile addition.

By the way the T1100 does provide a control to adjust LCD contrast, and this does help in getting the best display.

One further point should be noted about the LCD screen. Unlike a CRT monitor, it can't provide two levels of display contrast to correspond to the IBM's "normal" and "enhanced" character display modes. The T1100 designers have apparently elected to substitute a flashing underline for the "enhanced" mode, when the LCD screen is being used. This causes a further problem with some software programs which happen to make extensive use of the enhanced mode.

I discovered this initially with Wordstar, which uses the enhanced mode for displaying all of your text. This means that on the T1100's LCD screen, every single character of your text is displayed with a flashing underline. The problem is that Wordstar also uses a flashing underline as its cursor, so the "real" cursor tends to get lost in a forest of pseudo cursors. It can be quite irritating.

Fortunately, when you switch the T1100 over for use with an external video monitor, it changes over to the usual "enhanced" display mode — so the problem disappears (another reason for using an external monitor when you are back at the desk).

Keyboard

The only other area in which the T1100 seems to have a few shortcomings concerns the keyboard. Basically, these seem to be the result of some inevitable compromises forced upon the Toshiba designers in achieving their goal of squeezing a keyboard of 83 keys into an area only 281 x 138 mm.

Like the IBM, the T1100 combines the cursor control keys with the numeric keypad. However, because of the space limitation these keys are no longer in the familiar and convenient square array to the right of the main QWERTY section. Instead they're in two horizontal rows, above the number/punctuation row of the main section. The odd numbered keys are in the top row, with the even keys below them.

I guess the designers had little choice about this, but it has made the numeric keypad as such virtually useless; you're better off using the normal number

keys. The cursor control keys are also considerably less convenient than on the IBM and similar machines, although you would probably get used to them if you were using the T1100 all the time.

The programmable function keys F1-F10 are also in two horizontal rows above the main section of the keyboard, to the left. This is again not quite as convenient as having them in two vertical columns at the far left. There are also quite a few minor differences from the IBM keyboard, such as the double quote mark being in the shift position on the "2" key like a normal typewriter keyboard. But as before, if you're using the T1100 all the time you'd no doubt adjust to these differences in short order. They are really quite minor points.

On the positive side, the keyboard seems quite positive in its action and is pleasant to use. The highly important (ENTER) key is better shaped and more conveniently placed than on the IBM, as are the two SHIFT keys. The (ALT) and (CAPS LOCK) keys are also one removed from the space bar at each end, making it rather less easy to hit them by mistake. The (NUM LOCK) key also has the word STOP engraved on its front, making it easier to remember its control function with MS-DOS.

So all in all, the pros and cons of the keyboard should balance out reasonably well, particularly if you're going to use the T1100 by itself and not flit back and forth between it and another machine.

Conclusion

In summary, I have to say I am most impressed with the Toshiba T1100. It is a very professional machine, and is far more powerful than you'd normally expect to find in something so compact. In

fact it's the nearest thing you're likely to find to an IBM-PC, squeezed into a lap-top case and able to operate from batteries.


Whether you're after a serious portable PC, or just a serious desktop PC that takes up less space, it has to be a strong contender.

The review sample came from Dick Smith Electronics, who quoted a price of \$2995 for the basic 256K machine complete with inbuilt 720K microdrive, power adaptor/charger, operating manuals, MS-DOS system disk and two disks with "Access-4", an integrated spreadsheet/desk manager package. This sounds very good value for money.

The add-on 720K 3-1/2 inch microdrive costs a further \$899, while the alternative 5-1/4 inch minifloppy drive costs \$699. Both come complete with power adaptor and connection cable. The optional 256K RAM expansion board costs \$649, and if you want the RS-232C communications adaptor this costs \$165.

At the time of writing, the T1100's version of BASIC is not yet available for sale, but is expected shortly. Other systems and applications software should also be coming along soon, and may well be available by the time this is published. It is also likely that a lot of the software becoming available on 3-1/2 microdisks for the IBM model JX will run quite happily on the T1100, and suppliers like Dick Smith Electronics will no doubt be able to advise you regarding specific programs.

For those readers who have somehow managed to get this far without becoming aware of Dick Smith Electronics (!), the company has stores in most cities and large towns. If there isn't one near you, their head office address is PO Box 321, North Ryde 2113. The head office phone number is (02)888-3200.



The rear panel has ports for an external disk drive and printer plus sockets for RGB and composite video outputs.

Salvaging damaged PC Boards

Most printed circuit boards will survive reasonable abuse during their useful life, repairs being mainly confined to the components mounted on them. However, they may be damaged in various ways and must be either salvaged or replaced.

by KINGSLEY HOWE

Ordering a new board may involve lengthy delivery delays, during which time, the owner is deprived of the use of the equipment. In such circumstances, the costs may be considered excessive.

Boards can often be salvaged at a reasonable cost unless they are severely damaged. In this article, two approaches are considered: (1.) re-assembly of the broken board and (2.), duplication of the board by the repairer.

Removing the board

Before removing the board for service, examine both sides for cable connections. Draw an outline of the board first, then draw lines representing each cable. List the colour of the cable, and its use in the circuit; also, its point of connection at the other end (transformer, switch etc).

You will need these listings in case you forget the exact location when re-assembling the board. Drawing the outline of the components near to the cable connections will help locate the correct position from your diagram.

You may find several cables with the same colouring. In this case, label the wiring with masking tape before removing it from the board. Make sure the wording is listed against the corresponding line on your diagram.

Where a circuit board has a large number of connecting cables, and several hundred pads (such as a car radio-cassette), it will be practical to draw a

layout such as the one described above. In this case, even the removal of one wire may make the original connection point difficult to locate.

About the only solution to this is to cut the cable using side cutters. Cut close to the board, leaving 3 or 4 mm of insulation still attached to the joint. This will enable positive identification amongst a mass of 'look-alike' pads. Where a colour has been used twice, cut one cable off at right angles, and the other at 45 degrees, so there is no confusion. Make sure that you match the ends before stripping and resoldering, otherwise the identity of the cable may be lost.

Work only on one wire at a time. On some units there may not be enough slack cable to enable rejoining, if the suggested 3-4mm is left on the board. You will then be forced to cut much closer to the surface, leaving only a small 'ring' of insulation remaining. Care must be exercised so as not to accidentally remove this small ring, by dragging the board across the bench, or brushing it off.

One precaution to note with the system is to make sure that all the strands of short wire are removed from the copper pad before attaching the original cable. Should a pad lift from the surface, it may be fixed to the board by a drop of contact adhesive applied on the end of a toothpick. Further security may be obtained by a small dab on the component leads on the other side as well.

Some boards are more conveniently removed with the cables attached, disconnecting the ends from transformers or sockets, etc. A diagram of the connections to the boards is still advisable (apart from the diagram of cut connections), because in handling the board during the course of repair, one or several wires may break off.



Damaged PC boards can often be salvaged. This article tells you how.

A fairly practical method to reduce the likelihood of accidental fracture is to tape the cables to the board with masking tape. A break may still occur, but in this case the offending piece will be held in position and the broken end then points to its proper place.

Also, with the loose cables taped down, handling of the board becomes easier. Removal of the tape when repairs are effected should be done slowly.

The most convenient method of anchoring cables to the board is to feed the cables to the edge and tape them down firmly. Leave about one centimetre or so of tape over the edge, then apply a similar length of tape to the other side, again allowing about a one centimetre overhang. The two adhesive surfaces should now be brought together, so as to form a 'sandwich', with the cable and board in the middle.

This relieves any strain on the joints caused by the cables swinging with mobile use or in places where there is constant vibration.

Whilst the adhesive will eventually dry out and become hard, this may take several years, and it is more likely that the board will require servicing well before this occurs.

PVC based electrical tape is not suitable for this purpose, as there is insufficient adhesive coating. The best tape to use for this work is medical tape, which has a heavy woven cloth base and a very tacky white coating.

Hairline cracks

Hairline cracks can occur through shock loading on a board (eg. when the device is dropped) or when insufficient support causes deformation by heavy components. Cracks can also be made by excessive external pressure on board-mounted switches or pots, etc. The latter are, in general, restricted to the locality of the said pressure point and are fairly easy to locate and rectify.

The other type (pre-assembly fracture) may take place if the board is bent during manufacture or transport. The latter are sometimes not visible and, in instances where a batch of several thousand boards is involved, quite a few may pass through unnoticed.

The hairline crack often does not become apparent until the board is fully assembled and tested. The most obvious way to find the fault is to apply pressure to the board by use of an insulated tool, such as a plastic rod. The fault may come and go as the board is flexed, or the circuit may cease to function entirely. Noting which area is the most sensi-

tive to this treatment usually pinpoints the particular tracks. It is then merely a matter of bridging the fracture with wire links and plenty of solder.

Transport damage to a unit is the most noticeable form of physical abuse. The cabinet or metal housing may have dents on one face, or a corner may be pushed in. Sudden shocks from this sort of treatment may cause heavy components to pull right off the board, or cracks may occur when the housing distorts, straining the board with the change of shape.

In salvaging those boards it is important to firstly restore the original shape of the housing, such that the mounting holes in the board match those of the cabinet. Fitting a repaired board without doing this will apply undue pressure to the board and consequently a re-occurrence of the fault condition. In some cases, enlargement of the holes may be the only solution.

A more subtle condition arises when a unit is dropped dead flat. No external damage is apparent, but the innards may have taken a severe jolt. Removal of the cover may reveal a loose transformer, and various screws may have pulled away.

A safe bet in the above cases is to examine the board close to the mounting

posts. Often, these are rigid and inflexible; any sort of fracture near them should arouse suspicion.

Large capacitors, such as filter types, can exert enough stress on impact to cause hairline cracks. Grasp the capacitor body firmly then rock the component slightly. This may reveal a crack that is otherwise hidden underneath. Otherwise, the board may have to be removed and carefully examined.

Locating hairline cracks

Several methods are applicable in aiding crack detection in PCBs.

A slight flexing of the board when removed can show up the larger cracks, while lesser cracks may be seen when the board is held up to the light. It is preferable to use daylight as a source, holding the board in a vertical position, and then tilting it to and fro slightly to show the slight difference in colour between the main (unaffected) base colour and the lighter shade exhibited by the crack.

The most difficult of all to find are the very fine fractures. Some of these are so slight that they are not visible, even with a good light and strong magnifier. Some of these may be confined to only one or two tracks, being very



Get the competitive edge with

ECS

TOMORROW'S TECHNOLOGY TODAY.

Eclipse Computer Systems are proud to present their new range of Australian made and designed computers, offering unparalleled performance in a desktop computer. Advances in design and technology mean that the ECS Computers can complete a task up to 7 times faster than the older generation of computers:- Features which include

- State of the Art Technology C.P.U.
- Runs all popular operating systems
- High density floppy disc drive
- Up to 1Mb. parity checked RAM. on board with no wait states.

The ECS computer was designed for those with applications where performance is critical such as spreadsheets, word processing, accounting, engineering and program development.

SINGLE BOARD COMPUTER KITS ALSO AVAILABLE

*Based on the average of 4 Bench Tests the Eclipse Computers are 2.8 times faster than the new IBM AT and 7.2 times faster than the IBM XT.

542 Riversdale Road, Camberwell, Victoria 3124 Telephone: (03) 813 3447

NEW YEAR SPECIAL



TOSHIBA T1100
Portable Computer

\$2995 Sales tax included

with
Bonus Dotmatrix Printer
worth \$499 retail

MSDOS System Disk
Power Adaptor and
Manuals.
(R.R.P. \$3695)

**SAVE
\$700!**

Optional

512K Upgrade Card .. . \$535
RS232C Card/Cable .. . \$145
Carry Case .. . \$49
5¼" External Disk Drive .. . \$690

Toshiba P1340 Printer .. . \$945
Toshiba P1351 Printer .. . \$1575
Toshiba P351 Printer .. . \$1775

Sales tax included

COPISPEC PTY. LTD.
Bay Street, Port Melbourne
Lonsdale Street, Melbourne
PH: (03) 647 9111

Toshiba's main Victorian dealer

Salvaging damaged PC boards

localised. Flexing the board in this case will achieve nothing positive, as some of these do not penetrate the board, being confined to the surface only.

A more extreme and frustrating condition arises where only the copper track is fractured. The board has flexed in such a way that the copper has reached the elastic limit and parted at the weakest point. This does not imply that the narrow part of the track is the place to look. The particular track under these conditions may appear intact.

In some cases, the gap at the point of fracture will have closed physically, but not electrically. Even worse, the application of multimeter probes to a track in this condition to test continuity will read dead short. The current passing across the small point of contact is enough to operate the meter, but will not carry the load current to allow the circuit to function properly, if at all.

With plain copper tracks, the solution is to power up the circuit, provided it operates on low voltages or proper safety precautions have been observed, and the said board is rigidly fixed in place. Now take a hard "lead" pencil, such as a 2H or 3H type, and carefully run the tip over the suspect track. Make sure that you do not run off the track onto the board, as the graphite is conductive and will short out adjacent tracks.

On crossing the fracture the pencil effectively bridges the fine gap and its exact position is then apparent.

Note that the pencil should be covered with clear PVC tubing, such that the top end is covered by an extension of at least 25mm. The graphite core of the pencil is live when in contact with the circuit, and should be well insulated to prevent shock.

Boards covered with a solder-resistant lacquer present problems not found with uncoated boards. Firstly, the green coating obscures all but the most serious cracks, when attempting to use the backlighting technique. The suspect area may require removal of the lacquer to expose the copper.

Before this is done, however, examine the board with a good magnifier. Some-



Hairline cracks can develop for all sorts of reasons.

times the copper will show at the edge of the fracture, the red colour contrasting well with the green coating. Removing the lacquer by scraping with a sharp knife may well hide the gap entirely.

One type of fracture shows up as a spidery pattern (multiple fracture running from one point). These are commonly found where heavy components are mounted on the board or at corners where the board is fixed by means of screws to posts or insulated mounts. These should be reinforced, as described later in this article.

Regardless of the type of crack, small or large, steps should be taken to determine the direction of the crack. The tracks along the path of the crack should also be bridged with wire reinforcing, in the event that the crack runs further.

Board reinforcing methods

All damaged boards should be strengthened to minimise further breakdown.

The most important aspect of board repair is the correct adhesive and surface treatment. Super Glue (cyanoacrylate), has good penetrating ability, but is too brittle when set for butt joints. Araldite will cover the crack and adhesion to the board is good, as long as the components are well mixed before applying.

An easy, low cost, and less messy method is to apply a coat of Bear Contact Adhesive to both surfaces of a broken board, and then push these together.



Sufficient adhesive should be used so that a bead of adhesive forms at the line of contact. Support of the whole board overnight is suggested until curing is complete. Clothes pegs may be employed to hold the edges level; these act as spring-loaded clamps. To prevent a peg sticking to the board, apply a piece of sticky tape to each jaw. The pegs can then be removed after setting has taken place, and the tape then peeled from the board.

Where space permits, scrap pieces of circuit board cut to suit, may be glued on the board across the crack. This supplies rigidity to the repaired board and prevents sagging at the joint.

Partly cracked boards may be strengthened in the same way. Boards with corners broken off require a patch to be glued to the affected area. Glue the piece on the top of the main board (make sure that the copper foil is removed from the scrap piece), even if the piece required covers some component holes. These holes can be drilled out the following day and the parts re-mounted on the new piece.

Styrofoam blocks may be used to support the board after repair. Blocks may be cut from ceiling tiles, which are of a convenient thickness and readily available from hardware and home decorator outlets. Blocks may be joined using Aquadhere Adhesive. This glue will join a styrofoam block to timber or metal.

With metal, allow 24 hours for complete setting, due to its non-porous nature. Provided there is no oil on the metal surface, the bond is very strong, in fact, the block will break into pieces, before it will lift from the metal. Painted surfaces will also hold well if cleaned first with methylated spirits.

Leads protruding through the underside of the board need not be trimmed when using foam blocks for board supports. These will penetrate the foam easily, and aid in holding the board in place.

Burnt boards

Burnt boards are not a rarity. Many TV sets use SRBP for all their boards.

These can fall victim to the heat from high-wattage wire wound resistors. Several types of burn occur:

- (1). Dark brown area with board intact.
- (2). Charred patch with raised blister.
- (3). Hole burnt right through the board.

In category (1) the area affected has a level but discoloured surface, and the most serious problem could be the state of the tracks.

A typical history of such a board would be heat from the leads causing deterioration of the adhesive bond between the copper track and the board. Along with this, the solder loses its tin content, and appears dull grey and wrinkled. The weight of the resistor then causes the leads to sink through the board, and detachment of the copper track begins.

These boards can be salvaged by fitting a piece of uncoppered board over the area and fixing this with 6BA screws. This done, attach wire links to the resistor in place of the burnt tracks. Double-sided copper circuit boards may be cut to a suitable size, drilled, and slid onto the resistor legs. This arrangement acts as a heatsink, and reduces the amount of heat reaching the main board. Solder should be applied to both sides of the foil.

On badly burnt boards, it may be easier to cut two pieces of uncoppered board to cover the area where the resistor leads fit the board. Fit one piece on each side and drill through the original holes, then fix both with 6BA screws.

The resistor leads may now be soldered directly to the screws after wrapping several turns around them.

In groups 2 and 3, the boards would be in very poor condition. If they are small, it may be practical to reproduce the board. A quick method is to firstly draw a diagram of the layout, and mark the identity of each component. Then remove all the components from the board. Cut a fresh piece of board to the same dimensions, lay this copper side up, then place the old board track side up and use it as a drilling template.

Drill one hole and insert a thick wire or a board pin, then drill the next hole and insert another pin or wire. This will prevent the boards from moving when the other holes are drilled. After all the holes are drilled, lay the boards side by side, and then copy out the tracks with a Dalo etch resist pen, using the original board as a guide. Check the track pattern before etching.

Some burnt areas may be small, and

not warrant a reproduction. If some of the tracks are destroyed, the area may be removed by a drill or file. A small 'sub-board' can be built from Vero-board, and the parts concerned mounted on this. Solder stiff wire through the holes in the Veroboard, then drill holes in the main board to enable reconnection. The finished 'sub-board' should then look something like an overlarge IC, sitting clear of the surface.


With vertically mounted resistors, a piece of board may be inserted between the body and lead, and the lead soldered to the copper. Tinning the board with solder, and cleaning and tinning the resistor lead will enable a quick secure joint to be made.

Copper tracks

Copper tracks may be found to have burnt and lifted from the board. It is not advisable to glue these back into place and then attempt to solder in replacement components. The condition of the tracks renders them virtually unsolderable, they are physically weak, and their current carrying capacity is reduced. Replacement of the tracks is possible using a self-adhesive copper foil.

Remove the old foil back to a clean shiny area, then attach the new copper strip directly from the roll. Should the foil not adhere, roughen up the surface with emery cloth.

Wire links may be used to replace burnt tracks. Note that the wire will need to be fixed to the board with glue. Care must be taken when soldering component leads to wire; these joints often prove to be unreliable unless a small loop is made on the end of each wire to substitute for the copper pads. ②



JAYCAR MASSIVE KIT WAREHOUSE CLEARANCE - WE'RE DREADFULLY OVERSTOCKED ON MANY KIT LINES & HAVE NO ROOM FOR THE GREAT NEW RANGE PLANNED FOR 1986. RUSH IN NOW FOR THE BARGAIN OF A LIFETIME!

NEW Video Fader

Ref. EA January 1986
Fades video signal to black and up again without loss of sync PCB project. Plugpack and box extra.
Cat. KA 1626


ONLY \$19.95



Hands-Free Telephone Adaptor

Ref. EA November 1985
Jaycar now has stocks of this superbly designed project. Call in and check it out now! Note: this unit is ORIGINAL to the design.
Cat. KA 1640

ONLY \$79.00



NEW KITS FROM "AUSTRALIAN ELECTRONICS MONTHLY" AEM 6010 Ultra Fidelity Preamp

Ref. AEM Oct - Nov 1985
We now have stocks of this project in kit form including the original case, components etc. Nothing else to buy! Chassis is pre-punched with original front panel.
Cat. KM-3030

ONLY \$269.00

AEM 4600 Dual Speed Modem

Ref. AEM December 1985
This is the ultimate kit modem. Dual 1200/300 Baud, case etc all included.
Cat. KM-3040

ONLY \$169.00



★★★ SPECIAL
FULLY IMPORTED 'POWERTRAN' MIDI-CONTROLLED SAMPLER
- see review in August 1985 Sonics
KIT VERSION **\$800**
BUILT VERSION **\$1,000**
UNDER 1/2 PRICE

OTHER KIT BARGAINS Save up to 50%

Cat. KJ-6602
"CLEF" (UK) MICROSYNTH KEYBOARD SYNTHESIZER COMPLETE KIT
WAS \$399 SAVE 50% NOW \$199.00

Cat. KJ-6652
"SPARKRITE" TX-2002 ELECTRONIC IGNITION
WAS \$129.00 SAVE 24% NOW \$99.00

Cat. KS-8117
HOUSE AND CAR ALARM KIT
WAS \$19.95 SAVE 50% NOW \$9.95

Cat. KS-8123
ALIEN INVADERS KIT
WAS \$15.50 SAVE 50% NOW \$7.95



8 SECTOR BURGLAR ALARM


Ref. EA Jan/Feb 1985
Why buy a commercially made up unit for more when you can buy this kit and SAVE money! A unique feature of this kit is the fact that you can wire N/O and N/C alarm sensors ON THE SAME LINE.
★ 8 SECTORS ★ 2 delayed entry sectors ★ steel box ★ includes battery and siren driver in the price ★ variable exit and entry delays.
Cat. KA-1580

ONLY \$149.00

AEM 3500 'The Listening Post'

Ref. July 1985
Decode all that info on your short wave radio to show Morse code, RTTY, weather maps etc. Wonderful!!! (A personal computer is required).
Cat. KM-3015

ONLY \$29.50



MAIL ORDER HOTLINE (02) 747 1888

GRAPHIC EQUALISERS UNBEATABLE BARGAINS 2010 MkIIA

The 2010 is a one control per octave equaliser. This gives you tremendous room for equalisation. There are separate controls for right and left channels plus there is a multifunction control pushbutton. A superb kit which is supplied with a pre-punched 88mm (2 rack unit) cabinet which matches other ETI 5000 system components.

NORMALLY \$135 SAVE \$36 or 26% JAN SPECIAL \$99

2801 1/3 OCTAVE UNIT

The 2801 comes with a complete fused power supply for 240V AC operation. It is also fitted with standard Cannon Male/Female chassis connectors for professional ease of use. It is output short circuit proof and will drive very long unbalanced lines without degradation. Naturally it comes in a rugged 19" road quality rack cabinet. ANOTHER SUPERB KIT FROM JAYCAR!

NORMALLY \$225 SAVE \$50 JAN SPECIAL \$175



PLAYMASTER SERIES II MOSFET AMP KIT

Ref. EA Jan/Feb/March 1985
"... s stereo amplifier that will equal or better just about any integrated commercial amplifier, regardless of price". Leo Simpson, Editor of EA, February 1985.

MAIN FEATURES

- Switchable phono input for MM and MC cartridges
- Electronic signal switching
- Full facilities for dubbing between two cassette decks
- Monitor loop for either of two cassette decks or a signal processor
- Click action pushbutton switches for selection of sources, dubbing and tape monitor with LED status indicators
- Centre detents on bass, treble and balance controls, multiple detents on volume control
- Heavy duty heatsinks
- Power transformer for low hum and noise
- Easy to build - all parts except power supply mount directly on the two printed circuit boards; wiring has been kept to an absolute minimum
- 100 watts RMS per channel into 8 ohm load
- Less than 0.01% total harmonic distortion

Cat. KA-1500

ONLY \$429.00



JAYCAR NO1 KITS

EA KIT BARGAINS Save up to 43%

Cat. KA-1055
SUPER SIREN (FULL KIT)
Ref. EA November 1982
WAS \$19.95 SAVE 25%
NOW \$14.95

Cat. KA-1484
SUPER SIREN (SHORT FORM)
Ref. EA November 1982
WAS \$8.50 SAVE 41%
NOW \$5.00

Cat. KA-1118
VIDEO ENHANCER
Ref. EA October 1983
WAS \$39.50 SAVE 25%
NOW \$29.50

Cat. KA-1478
STEREO SYNTHESIZER (FULL KIT)
Ref. EA December 1982
WAS \$59 SAVE 20%
NOW \$47.00

Cat. KA-1476
STEREO SYNTHESIZER (SHORT FORM)
Ref. EA September 1982
WAS \$43.50 SAVE 25%
NOW \$32.50

Cat. KA-1492
pH METER LCD
(Meter only - not probe)
Ref. EA December 1982
WAS \$79 SAVE 24%
NOW \$60.00

Cat. KA-1520
3.50 VOLT POWER SUPPLY
Ref. EA May/June 1983
WAS \$179 SAVE 16%
NOW \$149.00

Cat. KA-1547
EA DIGITAL FREQUENCY COUNTER
ADD-ON
WAS \$17.50 SAVE 43%
NOW \$10.00

Cat. KA-1557
EPROM COPIER
Ref. EA December 1984
WAS \$75.00 SAVE 35%
NOW \$49.00

Cat. KA-1558
UNIVERSAL MOTOR SPEED CONTROLLER
Ref. EA December 1984
WAS \$24.95 SAVE 20%
NOW \$19.95

Cat. KA-1564
BRAKE LAMP FLASHER
WAS \$16.50 SAVE 22%
NOW \$12.95

Cat. KA-1592
"BUSKER" AMPLIFIER
WAS \$125 SAVE 20%
NOW \$99.00

Cat. KA-1593
WOODEN CABINET FOR BUSKER
WAS \$30.00 SAVE 33 1/3%
NOW \$20.00

★ NEW ★ NEW ★ ELECTRIC FENCE CONTROLLER

Ref. EA December 1985
High power and lower current drain. No
auto coil needed. Compact and all parts
included.
Cat. KA-1660

ONLY \$45.00


WARNING! ELECTRIC FENCE

ELECTRONICS
AUSTRALIA

AEM 6103 10" 3-WAY SPEAKER SYSTEM

Ref. AEM January 1986

- ★ WE HAVE THE
SPEAKERS
- ★ WE HAVE THE
CROSSOVERS
- ★ WE WILL HAVE THE
CABINETS
CALL IN!



ETI KIT BARGAINS Save up to 42%

Cat. KE-4554
ETI 760 VIDEO MODULATOR
WAS \$23.50 SAVE 28%
NOW \$16.95

Cat. KE-4654
ETI 733 RTTY CONVERTER
WAS \$24.95 SAVE 28%
NOW \$17.95

Cat. KE-4570
ETI 162 1A/30V ADJUSTABLE
POWER SUPPLY
WAS \$65.00 SAVE 23%
NOW \$49.95

Cat. KE-4671
PARALLEL INTERFACE KIT
FOR MICROBEE
WAS \$15.95 SAVE 22%
NOW \$12.50

Cat. KE-4683
"MASTERPLAY" AMPLIFIER
(untable extra)
WAS \$69.95 SAVE 29%
NOW \$49.95

Cat. KE-4696
MICROBEE DIALLER
WAS \$23.95 SAVE 42%
NOW \$13.95

Cat. KE-4700
ETI 1404 4 INPUT MIXER
WAS \$99.00 SAVE 20%
NOW \$79.00

Cat. KE-4703
ETI 341 ELECTRONIC JUMPER LEADS
WAS \$39.95 SAVE 20%
NOW \$31.95

BEGINNERS KITS Save up to 53%

Cat. KE-4000
ETI 048 BUZZ BOARD
WAS \$8.50 SAVE 53%
NOW \$4.00

Cat. KE-4001
ETI 061 BASIC AMP KIT
WAS \$8.90 SAVE 45%
NOW \$4.90

Cat. KE-4002
ETI 065 ELECTRONIC SIREN
WAS \$8.90 SAVE 45%
NOW \$4.90

Cat. KE-4003
ETI 068 LED DICE
WAS \$8.90 SAVE 45%
NOW \$4.90

Join the Compact Disc
Owners Club - ring (02)
747 1888 or call in to
one of our stores for
details.

☆☆ NEW ☆☆ 300 WATT INVERTER WITH AUTO START NOT A KIT - BUILT, TESTED & GUARANTEED

This is the built version of the "Electronics Australia"
September 1985 project!
Just think how handy it would be to have 240 volts AC
mains power when camping, or for your boat or
caravan - well this brilliant new design is the answer
• Super compact - tough ABS case • Uses high
efficiency toroid transformer which keeps the weight
down, battery drain and heat dissipation • Auto
start draws power from your battery when appliance
is plugged in and "turned on" i.e. battery can be left
permanently connected • Thermal overload
automatically shuts down if/when output stage is
overheated (through high ambient temperature and
high load or combination thereof - automatic reset •
Current regulated inverter ensures the unit is being
used within designed overload limits • Current
overload unit self limits - LED indicates overload
condition

COMPLETE KIT VERSION

Cat. KA-1610
ONLY \$199.00
FULLY BUILT & TESTED
Cat. MI-5000
ONLY \$249.00



MAIL ORDER HOTLINE
(02) 747 1888

☆☆ NEW ☆☆ Motor/Gearbox Kit

This fantastic new kit enables you to produce a shaft
speed between 3 and 2,000 RPM!
It uses a small DC motor with a "modular" gearbox
attached. You are supplied with gearwheels, spacers
etc to configure your gearbox to almost any speed
within the 3-2,000 RPM range. Measures only 48(H)
x 25(W) x 37(D)mm (not including output shaft)
Cat. YX-2600

ONLY \$14.95


Bench Type Digital
Capacitance Meter - Ref.
EA August 1985 - measure from 1pF to 99.9uF with
this handy piece of equipment
Cat. KA-1595

ONLY \$79.95

DWELL/TACHOMETER

Ref. EA Sept. 1985
Tune up your car quickly and easily with this handy
piece of gear. The Jaycar kit includes case, large
meter and Scotchcal meterscale
Cat. KA-1612

ONLY \$34.95
Suits 4-6 or 8 cylinder
cars



MAIL ORDER
HOTLINE
(02) 747 1888

Jaycar

ELECTRONICS

Incorporating ELECTRONIC AGENCIES

Carlingford, Hurstville, Gore Hill, Brisbane Mon-Fri 9am - 5:30pm
Sydney and Concord Mon-Fri 8:30am - 5:30pm
Sydney, Carlingford, Hurstville Thursday night until 8:30pm
Brisbane Thursday night until 8pm
Sydney, Carlingford, Hurstville, Brisbane Saturdays 9am - 12 noon
Gore Hill Saturday 9am - 4pm

CONCORD NOT OPEN ON SATURDAYS

NUMBER 1 FOR KITS

N.S.W.
SHOWROOMS

QUEENSLAND
MAIL ORDERS:
HEAD OFFICE:

SYDNEY: 117 York Street Tel (02) 267 1614
CARLINGFORD: Cnr Carlingford & Pennant Hills Road Tel (02) 872 4444
CONCORD: 115/117 Parramatta Road Tel (02) 745 3077
HURSTVILLE: 121 Forest Road Tel (02) 570 7000
GORE HILL: 188/192 Pacific Highway (Cnr Bellevue Avenue) Tel (02) 439 4799

BURANDA: 144 Logan Road Tel (07) 393 0777
P.O. Box 185, CONCORD 2137
115-117 Parramatta Road, CONCORD 2137
Tel (02) 747 2022 Telex 72293

POST & PACKING
\$5 - \$9.99 \$2.00
\$10 - \$24.99 \$3.75
\$25 - \$49.99 \$4.50
\$50 - \$99.99 \$6.50
\$100 - \$199 \$8.00
Over \$199 \$10.00

COMET ROAD FREIGHT ANYWHERE IN AUSTRALIA ONLY \$13.50



MAIL ORDER VIA
YOUR PHONE



FORUM

Conducted by Neville Williams

Some rough ideas about video tape!

If a reader from Concord, NSW is to be taken seriously, BASF must be coating their video tape with raw emery powder rather than "tiny, smooth chromium dioxide particles" densely packed in a "mirror finished" binder. Take your pick as to whether the letter revives or discredits a once lively argument.

In so phrasing the above introduction, I am not seeking to ridicule the correspondent. He is, I feel, genuinely disappointed and genuinely puzzled, although possibly misinformed. We'll go into that later but first read his letter:

Dear Sir,

"Buy our super-duper chrome audio and video tapes for better results", the advertisements tell us.

But in what way are the results better? Are we being conned?

Let me explain: Last December I invested in a Beta video camera to replace an aging Bell & Howell 8mm sound movie camera that was objecting to present-day film cartridges.

The salesman stressed the need not to use cheap tapes, only top brands, so I chose BASF Chromdioxid. All the family, especially the grandchildren, were delighted with the results.

After 7 months use and perhaps 6 hours of taping, the new camera ceased to function. It was taken to the vendor for repair under guarantee and, after explaining the problem, the technician asked what tape had been used.

On being told it was BASF chrome, he said that could be the cause of the trouble; please call back in 7 days. A week later, and the repair complete, I asked what had gone wrong.

Well, the Record head was judged to be 25% worn out and the running mechanism clogged with dust from metal particles — all due to the allegedly abrasive nature of the tape coating.

Chrome is a hardening agent used in steel making, the technician explained and, while picture quality is boosted, so

is the wear rate on components. This is more apparent on cameras and car tape players than it is on domestic systems, which are larger and inherently more robust.

He strongly urged that only non-chrome tape such as TDK Super Avilyn be used in cameras and car tape players. I should mention that the camera is still performing faultlessly, after many hours of use.

I have not seen this matter discussed in the many tape reviews in EA and other magazines and you may care to comment. (I really enjoy your Forum articles, and the magazine as a whole).

W.S. (Concord, NSW).

By way of response, let's recall what gave rise to the "once lively argument":

As you may be aware, BASF produced the world's first commercial consignment of ferric oxide recording tape in Ludwigshafen, Germany, in 1934, in collaboration with AEG.

In the following years, ferric oxide tape technology was progressively refined but, in 1971, BASF took up an American DuPont development and released a new line of high-bias, high performance tape coated with chromium dioxide (CrO₂).

According to company literature, the new chromium formulation offered reduced modulation and bias noise, increased MOL (maximum output level), wider frequency response with greater dynamic range, a more durable coating and better retention of the recorded information.

Companies which were committed to ferric technology had to embark on an

intense program of research, involving more extensive processing and/or the use of dopants such as cobalt, in an effort to match the performance figures of chromium formulations.

They certainly closed the gap but their upgraded tapes also benefited from an allegedly inspired notion that chromium dioxide particles, being harder than ferric oxide, caused significantly greater head wear.

BASF and other CrO₂ licencees denied this most vigorously in their literature, but I was subsequently able to discuss it at a personal level with BASF engineers, here and in Germany. They made the following points with apparent conviction:

- As a powder, the harder but finer particles of CrO₂ do have a different frictional characteristic from their ferric equivalent, being slightly more abrasive to harder heads (oxide and sendust) but less abrasive than the larger ferric particles to softer heads (e.g. mu-metal).
- When embedded in a highly calendared binder, however, as on plastic tape, it is the binder, the surface finish and the environment, rather than the powder, which determines head abrasion.
- In any case, the surface texture is specified to manufacturers licenced to JVC (for VHS) and Sony (for Beta) such that it will burnish the heads, without causing unnecessary wear.
- In practice, the differences between premium quality tapes in terms of head wear are marginal — something that may not be true for tapes of dubious origin.

Head life

Over and above arguments about tape formulation, there was a lot of apprehension, early on, about possible head fouling and head wear in domestic VCRs, with talk of heads needing to be cleaned every few months and replaced altogether at somewhere between 1000 and 2000 hours.

Nowadays, the subject hardly rates a mention, possibly because other consumers have shared my own experience in this respect.

In early '82, I took delivery of a then new National NV-7200A domestic VCR for review in the April/May issue of "VideoMag". I liked it well enough to acquire it for permanent domestic use and, while I have reviewed various other VCRs since then, there has been no particular urge to make a change.

So, for well over 3 years or 1300-odd

days, the 7200A has been churning away, at the beck and call of various members of the family. It requires an average of less than two hours per day, recording or playing back, to aggregate 2500 hours of operation — at least!

In all that time, it has never missed a beat. The heads have never been cleaned and to the eye, as judged on program material or test patterns, the on-screen picture is much the same as it ever was.

Yes, it has been protected from fumes, dust and extremes of temperature, and kept covered when not in use. But it has also spent a lot of hours playing BASF Chromdioxid tape of various grades, along with PD-DuPont CrO₂, and a variety of non-chromium brands.

The foregoing remarks are not intended as a gratuitous plug for National

VCRs, because there are possibly plenty of others around that could match those figures. But they do indicate that the early speculation of up to 2000 hours of head life was realistic, even conservative, tape formulation notwithstanding.

Back to the camera

In the face of that experience and expectation, the present proposition that any top brand tape could be so abrasive that it would visibly wear the head and clog the mechanism of correctly designed normally operating video equipment after just 6 hours of taping is manifestly ludicrous.

The tape would indeed have to be coated with raw emery powder!

There just has to be another dimension to the story, beyond any arguable characteristic of chromium coated tape.

- Did the camera have a pre-history unknown to the correspondent?
- Was the record head cracked or out of position enough to gouge the coating from the tape?
- Is the camera now working correctly because the head or the mechanism was readjusted?
- In any case, why would a technician blame CrO₂ tape before even looking inside the camera?
- How could he believe that a top-selling tape, running for thousands of hours in other equipment, could ruin this camera in 6 hours?
- Prejudice? A handy cop-out? Or is there something odd or critical about the particular model?

I'll leave the matter open for discussion, W.S., to see what it brings to light but, in the meantime, I haven't the

RSI: Not a programmers' problem!

I refer to the letter "Beat Repetitive Strain Injury" from B. Daniells in the September issue of EA, page 29.

I am NOT a computer programmer, nor am I any longer a mere "typist". The "typing" pool has been largely taken over by word processors, the majority of which are mini-computer based.

Mr Daniells has made several good points with which I concur. However, as noted in Mr Muscio's letter in "Forum" in the same issue, much of the RSI problem can be traced to the design of keyboards.

I have been typing for over twenty years and have played the piano for thirty. I have never had an aching joint until I began using a PC based word processor three months ago. Prior to that, my hands might have suffered some muscular tiredness after a busy day; I now type for only 30 minutes before my wrists and forearms begin to ache.

To use an analogy, I expect my back to ache after I have dug up the garden; I don't expect it to do so when I pick up the shovel!

Mr Muscio makes the point that typists' hands no longer have the support of the home keys and that the problem may be so simple that it has been overlooked. More than that; it has been dismissed as irrelevant. I have been voicing the same opinion to my colleagues (programmers), my employer (software company) and my family (mostly computer buffs).

Programmers, in their "hunt and peck" immunity, assure me that the height of the keyboard is the problem. Hardware manufacturers advise altering the height of the keyboard, monitor, &c.

Both reflect the attitude that I am "moaning" or "looking for a reason to bludge".

The company staff representative assures me that drinking less water will lower the fluoride level in my bloodstream, and the chance of developing severe RSI. However, since I live in the country and run my house on tank (rain) water, my fluoride intake is fairly low.

If a keyboard could be designed to incorporate Mr Daniells' "striking force" arguments and Mr Muscio's "wrist strain" logic, I believe the RSI problem could be alleviated. (I would expect any form of wrist support to detract from a typist's speed and accuracy.)

Mr Daniells may spend several hours daily at his keyboard but I wonder how much time he actually spends implementing continuous keystrokes. Any typist worthy of the title can type at least 60wpm accurately and will do so consistently for several hours in a working day.

Modern computer keyboards not only require a typist (as opposed to a programmer) to maintain speed and accuracy on a constant, repetitive basis, but to do so much with the hands in a state of constant muscular strain.

On an overly sensitive keyboard, the hands are maintained at a constant UN-NATURAL upward angle, with the wrist joint and tendons bearing the strain, while the forearm muscles and elbow joint bear the constant supporting load.

The trend in the business and technical community is to alleviate postural RSI by the provision of adequate worksta-

tions, chairs, &c, although companies, which don't wish to admit to the problem, try simply to sweep it under the carpet.

Hardware design companies seem to have fallen into the trap of seeking the opinion of their "hunt and peck" engineers and programmers. When will manufacturers realise that the real expertise in keyboard comfort lies in their secretarial and typing pool?

Computer programmers mostly suffer neck, back and shoulder strain, which is fairly easily alleviated by improving posture, positioning and alternate activity levels, as noted by Mr Daniells. Unless they are good (touch) typists, programmers generally do not suffer hand and wrist problems.

There are some thirty programmers and five secretary/typists where I work. No programmers have any problem as yet but we have two typists with diagnosed RSI. On a percentage basis, this would indicate that the major risk area is in the continuous, high volume keystroke occupations.

Hardware manufacturers have an obligation to keep their designs within reasonable limits, remembering that the human animal has not evolved in any measurable form for several thousand years.

My Cro-magnon ancestors had the same finger and wrist joints that I have. This may offend the highly technical but natural evolution cannot be speeded up to match technical advances. It would seem logical to me that technical advances must be kept within the capacity of Nature's ability to cope.

Mrs J.H., Lower Macdonald, NSW.

When it comes to
computer components

is for Adaptive Electronics

Sole authorised Australian Distributors for Tandon floppy and hard disk drives.
Importers of DTC and KONAN controllers, power supplies, etc.

HARD and FLOPPY drives for

- IBM, PC, XT and AT, and compatibles
- Tandy TRS80 Model 2 & 3
- Apple IIe and compatibles

10, 20, 30, 36, 50, 85, 130 MBYTE

Tape backup units also available

418 St Kilda Road, Melbourne 3004. ☎ (03) 267 6800

WE SPECIALIZE IN BEING CHEAP!!

New and Second Hand Computers for Sale

**NEW!
BRAND
NEW**

IBM Workalikes
\$1300 — Check
out the quality
Monitors \$169

SPECTRAVIDEO
328 with CP/M
disc drive & basic
Printer port, etc.
\$599

SPECTRAVIDEO
Model 328 w. data
cassette, joystick
10 pcs. software
\$299

IBM compatible
floppy \$149
hard \$899

APPLE MAC
Best Price in town
Modems from \$99
Epson Printers

Manufacturers and retailers surplus stocks

**SECOND
HAND
SPECIALS!**

VIDEO TERMINALS
from \$99 working
Printers
from \$50

Cromemco
Computers
from \$999

Instrument Cases
\$10

Disk drives
from \$10

Diskettes \$199
Paper \$10
SV Cartridges \$20

Computers in stock
IBM, APPLE, NCR,
Spectravideo.

We also desperately require stock — New and Second hand ask us to quote

COMPUTER SECOND

The home of the affordable computer

76 St Kilda Road

(03) 537 2267

FORUM — continued

slightest intention of discarding the BASF tapes on my shelf. If they haven't ruined or clogged the faithful old 7200A during its 2500+ hours, they're hardly likely to do so in the foreseeable future.

RSI: another viewpoint

To change the subject, RSI or repetitive strain injury has been the subject of considerable debate during the past year but I feel that the letter herewith, from Mrs J.H. of Lower Macdonald (via Wiseman's Ferry) NSW, adds an interesting dimension to what has been said.

If you haven't done so already, I suggest you read it now.

Quite fairly, I think, the writer points out that most of the opinions about RSI — its nature, cause and cure — have been expressed by males: doctors, managers, programmers, engineers, technicians, staff officers, technical writers and computer buffs. Few such people, she believes, have actually experienced the symptoms of RSI or are ever likely to.

The reason: they simply do not use keyboards in the manner of a professional, full-time typist. They may encounter postural problems but, having dealt with them, seem to think that they have dealt with RSI. I guess that I stand accused, along with the rest!

If Mrs J.H. is right — and her reasoning makes a lot of sense to me — the one EA correspondent who seems clearly to have picked the problem is Winston Muscio, in the September "Forum". B. Daniells mentions it but only in a context of other observations to do with posture, &c.

Mrs J.H. isn't impressed by the notion of supplementary wrist supports, presumably because of their possible interference with the fluidity of movement. Nor does she seem to be optimistic about typists being physically able to adapt to feather touch keyboards.

Could it be that the only real solution is to produce word processor keyboards with a touch more like that of traditional typewriters — deliberately designed to provide the optimum degree of "home key" support?

My use of the word "traditional" was quite intentional in that I gather, from conversation with another professional typist, that feather touch electric typewriters pose much the same RSI hazard as that of computer based word processors. When using either, she has to take the 10-minute break in every hour, ob-

ligatory in Government departments.

Maybe we need to be reminded that machines should be designed to serve people, not to frustrate them!

Something of that same thought is behind a brief letter from a Queensland reader, voicing objection to something that most will have noticed at one time or another, but tamely accepted: the confusing hotch-potch of controls on typical bedside clock radios.

Dear Sir,

The attached sheet is intended for your Editorial Consultant, who may be able to use it in "Forum". My only comment: "what a mess!" Surely the controls on clock radios could be simplified, if not actually standardised. Most old people must be flat out to discover, and remember, how to work them.

One other observation: Isn't it amazing how the quality of headphones has improved in the last few years — even the cheap ones?

H.S. (Bulimba, Qld).

To make his point, the writer encloses a sketch of the control arrangements on seven current model clock radios, although a tour of the stores would probably have yielded still more variations.

Those illustrated use a conglomeration of push-buttons, pads, slide switches and rotary switches, variously branded, with no two the same. All differ, in turn, from the one that adorns my own bedside table, or from those I've encountered from time to time in hotels and motels.

If they're confusing when you're awake and alert, they're doubly so when you're crawling into bed, without your glasses, already half asleep — or still semi-conscious in the pale light of dawn.

You have a point H.S. and you've made it, but one would have to be a supreme optimist to expect standardisation of a cut-priced product churned out by every second radio factory in Asia!

Your observation about the headphones is certainly valid, especially to anyone who is old enough to have been brought up on the old black bakelite magnetics. They were about as comfortable as a concrete pillow and as musical as an Edison phonograph!

By comparison, modern stereo dynamics — even the cheap ones — are better in every way except perhaps for resolving faint Morse Code signals.

Morse what?



KNOXTRONICS ELECTRONIC SERVICES

(EASTERN VIDEO CENTRE)
PROP. LEON AARONS, M.T.E.I.(Aust.)

**8 DARRYL STREET,
SCORESBY, VIC. 3179
PHONE (03) 763 8425**

SEE US FOR THE
BEST PRICES

on 27 MHz and UHF CB radios,
antennas and accessories.



ELECTROPHONE
27 MHz TX526 AM only, 40ch.
TX565 AM/SSB, 40ch.
UHF TX470T 40ch.
inc. repeater switch.

JAN SPECIAL
All 27 MHz radio
include FREE MOBILE
ANTENNA BASE AND LEAD



UNIDEN AX144AM/SSB
• Full range of mobile
antennas and
fittings genuine station master
¾W base antenna
• Complete after sale service
• Sundowner UHF 40ch.

**VIATEL
VIDEO TEX TERMINALS**
From only \$499



Call in for demonstration
Mail orders welcome
Bankcard—Mastercard—Visa

**FULL AFTER SALES
SERVICE FACILITIES**




SEMICONDUCTORS LTD

A **RAYTHEON** Company

LEADERS in SCR and Triac Technology

The following is a selection of the broad range of stock held by their Australian Distributor **ADILAM ELECTRONICS**.

TYPE NO.	IRMS A	VDRM V	Igt mA	Package
SCR				
P0102DB	0.8	400	0.2	RD26
X0403DE	4	400	0.2	TO 202-1
S0807BH	8	200	10	TO 220
S1010DH	10	400	25	TO 220
S1010MH	10	600	25	TO 220
S1610NH	16	800	25	TO 220
S2512NH	25	800	50	TO 220
S2512DK	25	400	50	RD 101 iso
S4012MK	40	600	50	RD 101 iso
S4012NK	40	800	50	RD 101 iso
TRIAC				
Z0409DE	4	400	10	TO 202-1
T0612MJ	6	600	50	TO 220 iso
T0805MH	8	600	5	TP 220
T1013DH	10	400	50	TO 220
T1213DJ	12	400	50	TO 220 iso
T1613DH	16	400	50	TO 220
T2512NH	25	800	50	TO 220
T2512MK	25	600	50	RD 101 iso
T4012MK	40	600	50	RD 101 iso
DIAC				
D0201YR	32V Trigger diode			DO 35



CONTACT US NOW FOR DATA AND PRICING



**Adilam
Electronics**
Pty Ltd

Melb — Suite 7, 145 Parker St, Templestowe (03) 846 2511
PO Box 52 Bulleen, 3105 Tlx 151369
Syd — 30 Colson Cres, Monterey 2217 (02) 587 1554
Adel — K. D. Fisher (08) 277 3288
Bris — F. Hoe & Sons (07) 277 4311
Canb — Electronic Components (062) 80 4654
Perth — Atkins Carlyle (09) 321 0101
Prospect (09) 362 5011

Books & Literature



Electronic Manuals

A number of Japanese IC data manuals covering various types of integrated circuits are now available from Hi-Com Unitronics International Pty Ltd, 7 President Lane, Caringbah, NSW 2229. The following titles are available for \$22.95 each:

The Transistor Manual; The Transistor Substitution Manual; The Interface IC Device Manual; The Diode Manual; The TTL IC Manual; The Microcomputer Peripheral LSI Manual; The A/D:D/A Converter IC Manual; The FET Manual; The Op Amp Manual (monolithic op amps).

Electromagnetic design for AC power equipment

Low Frequency Electromagnetic Design: by Michael P. Perry. Published by Marcel Dekker Inc, New York, 1985. Hard covers, 160 x 236mm, 243 pages, illustrated with diagrams and photographs. ISBN 0-8247-7453-1. Price \$US59.50

This book is likely to have rather limited appeal, despite the fact that it is well researched and written. It presents formulae, explanations and data likely to be of use to engineers working in the field of power transmission or similar areas. It is not a student text with questions and worked examples and the subject treatment is rather more rigorous than a typical engineering degree student would require.

There are only four chapters, entitled Introduction, Series and Parallel Concentric Coils, Low Frequency Cables and Shielding, Torque and Braking in a Magnetic Field. In addition, there are four appendices, on Properties of Bessel functions, Integral Formulas for Bessel functions and on Surface Impedance.

For those people involved in relevant areas of the industry, it is likely to be a useful though expensive source of information not otherwise readily available. Our copy came direct from the publisher. (C.D.)

Programming the 8086 and 8088



Programming the 8086, 8088: by James W. Coffron. Published by Sybex of Berkeley, first edition 1983. Soft covers, 148 x 228mm, 311 pages, illustrated with diagrams. ISBN 0-89588-120-9. Recommended retail price \$22.95

Although one might expect that a book about programming 16-bit micro-

Digital Electronics



Crash Course in Digital Technology: by Louis E. Frenzel, Jr. Second edition published 1984 by Howard W. Sams & Co. Inc. Soft covers, comb binding, 222 x 280mm, 198 pages, illustrated with diagrams and photographs. ISBN 0-672-21845-3. Recommended retail price \$34.95

processors would be heavy going, this one is particularly easy to read. Beginning with an introduction to programming, this book examines flow charting, chip architecture, and then the various aspects of programming the 8086 and 8088. No prior knowledge of programming would be necessary.

The 8086/8 programming book deals with the devices strictly from the software point of view. Even though peripheral devices are described, along with suitable interface commands, we were not able to find any pin out diagrams. The book is clearly intended for use by people with a built-up development system, or something more sophisticated.

The last few chapters are dedicated mainly to program development for the IBM personal computer (which uses the 8088 microprocessor). An example program is suitable for transmitting the data held in the buffer to a printer via an RS-232 interface.

The full instruction set for the 8086/8 is given, along with comments and some examples. Ideally, the comments might have been more comprehensive. The chapter on the instruction set is more difficult to follow than the rest of the book.

Overall, this book might best be regarded as an assembler language programming guide for the IBM. It is generally readable and offers good explanations. Our copy was supplied by Dick Smith Electronics. (C.D.)

Here is a book intended as a stand-alone introduction to digital electronics. This is a rather ambitious objective — to provide a grounding in logic circuit analysis, design and troubleshooting, without any other reference material or tuition.

The text is arranged in an example/question format. A description of each concept is given, followed by a question (there are no answers at the back of the book). Each chapter has a self test, with answers given at the end of the chapter.

Topics such as binary counting and arithmetic, Boolean algebra, ASCII codes, IC families, flip-flops and gate types are dealt with. Explanations are easy to follow and sufficiently detailed for the intended readership.

For someone with little or no experience in digital circuits, this book would make interesting reading, as well as providing a lot of useful information. Our review copy came from Jaycar Electronics. (C.D.)

INTERESTED IN ELECTRONICS? THEN WHY NOT TURN YOUR HOBBY INTO A CAREER?



Alan Mulraney, Stott's Graduate, in his workshop.

In this fast-changing electronic world people with interest and training are going to be in demand. Turn your interest into a lucrative career in any one of the following fields:

**Computers • Industrial Controls • Medicine
Radio Communications • Domestic Radio & Television**

Electronics plays an important role in these and many other fields. With a Stott's Home Study Course, training is easy, and will prepare you for a career in the manufacture, installation, commissioning, sales or servicing of electronic equipment.

You'll have experienced, professional instructors who will guide you through an integrated theory/practical program. They'll give you individual attention and advice, and prompt replies to all test assignments and queries. And best of all, you'll study at your own pace, in your own home.

Send the coupon today. It may be the smartest move of your life.

Stotts



CORRESPONDENCE COLLEGE

The name to trust in correspondence education.

Please send me free, and without obligation,
full details of the following courses:

(PLEASE PRINT)

MR MRS. MISS _____ AGE _____

ADDRESS _____

POSTCODE _____

Stott's undertake that no sales counsellor will visit you.

Melbourne, 140 Flinders Street, 3000. Tel: 63 6212
Sydney, 383 George Street, 2000. Tel: 29 2445
Brisbane, 65 Mary Street, 4000. Tel: 221 3972
Adelaide, 226 Pulteney Street, 5000. Tel: 223 3700
W. Perth, 25 Richardson Street, 6005. Tel: 322 5481
Hobart, 150 Collins Street, 7000. Tel: 34 2399
New Zealand, Box No. 30-990, Lower Hutt. Tel: 676 592

The Stott's range of courses
in Electronics is:

Intro to Electronics
Digital Electronics for
Technicians/Servicemen
Microprocessors
Radio Receivers
Radio/TV Servicing
Colour Television

ALA/ST5303/EA186

WIRELESS WEEKLY. Our own time machine! It may look like a book, but don't let it's appearance fool you. There are no whirling dials and control levers; but once you open the cover, it'll take you on an incredible journey backwards in time. You'll find yourself back in the 1920's, when Australia's first few radio stations were just getting established and a typical radio set cost ten weeks' wages. We've chosen a collection of highlights from the 1927 issues of 'Wireless Weekly': You'll find some front covers, a few editorials, the best new items, a collection of typical do-it-yourself radio set designs, and some selected pages from the programme listing. Plus a sprinkling of the original advertisements, of course. These are particularly fascinating because they show prices and put everything into proper context. Send today for *The Best of Australia's Wireless Weekly in 1927*... A fascinating and nostalgic trip into our radio past. **N0049A**

\$3.95

ELECTRONIC PROJECTS FOR YOUR CAR. How can you extend the performance of your car without it costing an arm and a leg? With these selected projects from *Electronics Australia* you can add all of the gadgets you've dreamed of: Cruise Control, Courtesy Light Delay, Deluxe Burglar Alarm, Headlight Reminder, Audible Reversing Alarm, Transistor-assisted Ignition with Optoelectronic Trigger, Driveway Sentry, Speed Sentry, Tacho/Dwell Meter, Breakerless Ignition, Audible Turn Signal and more easy-to-build projects to add value, interest and safety to your pride and joy! PLUS Feedback from those who have built the projects themselves and Bright Ideas for you to develop yourself: Automatic Antennae Retraction, 6V Car Adaptor, Fuse-Failure Indicator and more... **C0064A**

\$3.95

ELECTRONIC TEST GEAR TO BUILD. Why buy it? These valuable projects from *Electronics Australia* will add a new dimension to your workshop! Detailed, step-by-step instructions guide you through the construction of the most useful of electronic workshop test gear: 500 MHz 7-digit Frequency Meter, Wheatstone Bridge and Resistance Box, AC Millivoltmeter, DC Voltmeter, LCR Bridge, Modulated Signal Injector, Audio Prescaler. PLUS Feedback from those who have built the projects themselves and Bright Ideas for you to develop yourself: Linear Frequency Controller, Dummy Loads, General Purpose Counter Timer and more... **Never built a project before?** What better way to get started than by building the test instruments needed to begin a workshop? **Build it yourself to save and learn at the same time!** **F0067A**

\$3.95

EASY-TO-UNDERSTAND GUIDE TO HOME COMPUTERS. Confused by all these computer terms? This clearly written book from the editors of *Consumer Guide* tells exactly what computers are, how they work and why they are so amazingly useful, all in plain English. Here is all of the information needed to understand and use computers, and even to start programming. A special buying section compares the most popular home computers. This book is your ticket to the computer age! Spiral bound, 96pp. **H0066G**

\$8.50

THE USER'S GUIDE TO APPLE. The editors of *Consumer Guide* have compiled a thorough introduction to the Apple IIe and II Plus computers, software and peripherals. With colour illustrations and a clearly written text, this reference will guide the newcomer through all phases of learning how to use the computer: From setting the system up, learning what each key does, expanding the system with peripherals, to buying new software. Specific exercises are included for each of the keys. Spiral bound, 80pp. **H0061G**

\$8.50

THE USER'S GUIDE TO COMMODORE 64 & VIC 20. The editors of *Consumer Guide* have compiled a thorough introduction to the Commodore 64 and Vic 20 computers, software and peripherals. With colour illustrations and a clearly written text, this reference will guide the newcomer through all phases of learning how to use the computer: From setting the system up, expanding the system with peripherals, to buying new software. Specific exercises are included for each of the keys. Spiral bound, 80pp. **H0065G**

\$8.50



MAGAZINE BINDERS **B901EA**

Ready to use binders with easy, clip-in fastener, covered in soft, decorator brown vinyl. Holds 12 issues of *Electronics Australia*.

\$7.50

Postage and packing additional.

MAGAZINE HOLDERS **H951EA**

Big, easy to assemble holders, covered in soft, decorator brown vinyl. Holds 12 issues (at least) of *Electronics Australia*.

\$7.00



**SAVE
WITH SIX**

6 Holders — only **\$37.50**
6 Binders — only **\$39.95**

Book Sales

FREEPOST 4 (No stamp needed)
The Federal Publishing Company,
PO Box 227, Waterloo, NSW 2017
Tel: (02) 663-9999. Tlx: AA74488



DIGITAL ELECTRONICS. Electronic equipment plays an important role in almost every field of human endeavour and every day, more and more electronic equipment is 'going digital'. Even professional engineers and technicians find it hard to keep pace. In order to understand new developments, you need a good grounding in basic digital concepts and *Introduction to Digital Electronics* can give you that grounding. Tens of thousands of engineers, technicians, students and hobbyists have used this book to find out what the digital revolution is all about. This new fourth edition has been updated and expanded to make it of even greater value. No previous knowledge of digital electronics is necessary — The book includes an excellent coverage of basic concepts. **A0079A** **\$4.50**

BASIC ELECTRONICS. This popular text has now been re-issued. *Basic Electronics* is almost certainly the most widely used reference manual on electronics fundamentals in Australia. Written as a basic text for the electronics enthusiast, it is also being used by radio clubs, secondary schools and colleges, and in WIA youth radio clubs. It begins with the electron, introduces and explains components and circuit concepts and progresses through radio, audio techniques, servicing test instruments, television, etc. If you've always wanted to know more about electronics, but have been scared off by the mysteries involved, let *Basic Electronics* explain them to you. Easily understood diagrams and text make this the perfect introduction to the growing and exciting world of electronics. We've even included five electronic projects for the beginner. **A0074A** **\$4.50**

PROJECTS & CIRCUITS. If you like building electronic projects in your spare time, you can't afford to miss out on this exciting book of popular projects from *Electronics Australia*. Just look what's inside! **Audio and Video Projects:** Video Amplifier for Computers and VCRs, Video Enhancer, Vocal Canceller, Stereo Simulator for Tuners and VCRs, Guitar Booster for Stereo Amplifiers. **Automotive Projects:** Transistor-assisted Ignition System, Breath Tester, Low Fuel Indicator, Speed Sentry, Audible Turn Indicator. **Mains Power Control Projects:** Musicolor, Photographic Timer, Driveway Sentry, Touch-lamp Dimmer. **Power Supplies and Test Equipment:** Battery Saver for Personal Portables, Dual Tracking $\pm 22V$ Power Supply, 3 1/2-Digit LCD Capacitance Meter, In-Circuit Transistor Tester. **Plus EA's 10-year project index.** **C0069A** **\$4.50**

THE BEST VIC/COMMODORE SOFTWARE. Trying to find the most suitable software for personal computers can be frustrating. The editors of *Consumer Guide* have compiled comprehensive reviews of VIC 20 and Commodore 64 programs based on ratings by user groups; further evaluation is given by the editors and Commodore software experts Jim and Ellen Strasma. Each review describes the program's purpose and features, detailing both the good points and bad. Each program has been rated for ease of use, clarity of written and on-screen instructions, and overall performance. The program's price, publisher, format and hardware requirements are also included. The reviews are presented in sets by topic: Word Processing, Business, Home, Education, Networking, Strategy Games, Arcade Games and Programming Aids. Spiral bound, 192pp. **K0052G** **\$8.50**

THE BEST APPLE SOFTWARE. The editors of *Consumer Guide* have compiled comprehensive reviews of Apple II, II Plus and IIe programs based on ratings by user groups; further evaluation is given by the editors and Apple software expert Roe Adams. Each program has been rated for ease of use, clarity of written and on-screen instructions, and overall performance. The program's price, publisher, format and hardware requirements are also included. The reviews are presented in sets by topic: Word Processing, Business, Home, Education, Networking, Strategy Games, Arcade Games and Programming Aids. Spiral bound, 160pp. **K0060G** **\$8.50**

EA-1-86	BOOK TITLE/PRODUCT NAME	CODE NUMBER	QTY	PRICE TOTAL

**POSTAGE
AND
HANDLING
CHARGES**

ORDER VALUE	ADD
1 Book	\$1.50
Up to \$9.99	\$2.25
\$10 to \$19.99	\$4.25
\$20 to \$39.99	\$5.25
\$40 to \$99.99	\$6.25
\$100 and over	\$7.25

Cheque*/Money Order ☐ *Please make payable to the
 Federal Publishing Company Pty. Ltd.
 Put your cheque or money order in an envelope. No postage stamp
 Mail to Freeport 4, PO Box 227, Waterloo, NSW 2017 required in Australia.
 Mastercard ☐ American Express ☐ Bankcard ☐ ☒ Tick
☐ ☐ ☐ ☐ ☐ ☐ ☐ ☐ ☐ ☐ Credit Card No.
 (Unsigned orders cannot be accepted)
 Card Expiry Date..... Signature.....
 Allow up to 6 weeks for delivery.

NAME:
 ADDRESS:
 POSTCODE:

For airmail to
 New Zealand,
 Papua New Guinea,
 Oceania and
 Southeast Asia,
 add \$6.00 to these
 charges.

New Products...

Product reviews, releases & services

Digital multimeter checks transistors and capacitors

Jaycar has recently added the Metex digital multimeter to its range of test equipment. It is aimed at the low-price portable DMM market, although it has some handy features not found in most other instruments in the same price bracket.

These days, nearly all test equipment submitted for review in *Electronics Australia* is well up to standard. The Metex 3530 is a typical case. Priced at \$129, it is within the reach of most hobbyists and has a performance which would easily meet their needs.

The 3530 is a manually adjusted 31-range instrument. The 10A DC current range is selected by inserting the test lead into a separate socket: this is virtually standard for DMMs. The remaining 30 ranges are selected by positioning the front panel rotary switch.

Operation of the switch is firm and positive — it sits cleanly in the detents. It does, however, lack the solid feel of more expensive instruments. The multi-coloured front panel artwork is particularly good and indicates clearly which mode and range have been selected.

A feature which we wholly approve of is the separate On/Off switch. This is much more convenient than including an Off position for the rotary switch.

The unusual features of the 3530 DMM are the capacitor and transistor testing facilities. There are five ranges of capacitance, from 2000pF to 20 μ F. The capacitor under test is inserted into special sockets on the front panel — it is not necessary to use the test leads.

The capacitance ranges must be manually zeroed using a small knob on the front panel. Although the zeroing is quite easy to perform, it is necessary to readjust when changing ranges.

Accuracy of the capacitance ranges appears to be quite acceptable. The readings corresponded closely to those on our workshop capacitance tester.

By setting the rotary switch to "hfe", transistors can be tested by means of a special socket, again on the front panel. This socket is arranged in PNP

and NPN halves, each having the format E B C E.

The socket is circular, but not entirely compatible with the pin configuration. For most PNP transistors, the pin layout is correct. For most NPNs, the base pin is offset the wrong way.

The low resistance range (diode test) also incorporates a continuity tester. This has audible and visible indicators.

It's as good as any continuity tester we've seen on a DMM.

One particularly impressive feature of the 3530 is the fuse. This is accessible through the battery compartment, which is a much better arrangement than having to remove the back panel as with some instruments.

With respect to general accuracy, we found the 3530 to be within the claimed range of $\pm 0.5\%$. Using a 10.00V standard, a value of 10.02V was indicated.

The operating manual seems to be clear and easy to follow. It is quite up to standard for this type of instrument.

Supplied with the instrument are test leads and a protective carry box. The test leads are flexible and of sufficient length. The protective box can be closed completely, with the front cover clipping shut.

In practice, though, a protective cover is generally a hindrance and is eventually discarded, irrespective of its protective value.

Overall the Metex 3530 is a useful test instrument for the hobbyist or serviceman. For further information contact Jaycar Electronics, 115-117 Parramatta Road (PO Box 185), Concord 2137. Telephone (02) 747 2022. (C.D.)



Multimeter works in the dark


A novel low-power fluorescent strip backlighting option in Philips' new extended four-digit PM 2518X hand-held digital multimeter enables the LCD to be read in low-light conditions, such as aircraft cockpits or behind instrument racks, yet gives 10 times the battery life of equivalent LED instruments.

The PM 2518X provides comprehensive bench-top specifications, including 0.1% accuracy, in a compact and highly portable package. The new multimeter offers DC voltage and current ranges, true RMS AC voltage and current, and resistance measurements. In addition, dB measurements, diode voltage drop,

audible continuity testing and temperature measuring facilities are included. A simple zero-set facility permits direct reading of tolerances and variations on all ranges.

Measurements are possible for voltages up to 1000V DC or 600V RMS AC with a maximum resolution of 100 μ V; current, both AC and DC, up to 20A with a maximum resolution of 10 μ A; and resistance up to 100M Ω with a maximum resolution of 100m Ω .

For further information contact: Philips Scientific & Industrial, 25-27 Paul St, North Ryde 2113. Phone: (02) 888-0403



New personal computer from Amstrad

Amstrad's new PCW 8256 computer comes with 256K of RAM and the CP/M Plus operating system which allows access to over 5,000 commercial applications programs including spreadsheets, databases and communications. It also comes complete with a variety of extra programs including Dr Logo and the GSX Graphics Extension.

The computer has a high resolution green screen monitor, an 82-key keyboard and a built-in disc drive operating on 3-inch disks. Price is under \$1500, including the printer which has letter or draft quality modes.

For further information or demonstration contact AWA-Thorn, PO Box 11, Rydalmere 2116. Telephone: (02) 638-8444.

PLASMA DISPLAY SEMINAR

A one day seminar will be presented by overseas speakers on this new, flat panel technology.

Topics covered will include:

- Comparisons of the various display technologies
- Manufacturing process
- Current applications
- Technical aspects of designing with plasma displays.

Location and dates:

ADELAIDE Monday 24th February 1986
MELBOURNE Tuesday 25th February 1986
SYDNEY Thursday 27th February 1986

For further information and bookings please contact

Adelaide: Vaughan Wilson 42 6655

Melbourne: Bob Jackson 555 2477 Sydney: Peter McBride 728 2121

Lunch,
morning and
afternoon
tea will be
provided.

AMTEX
ELECTRONICS

A DIVISION OF TLE ELECTRICAL PTY LIMITED
(Incorporated in New South Wales)

36 Lisbon Street Fairfield, NSW 2165 Australia
Telephone (02) 728 2121, 727 5444 Telex AA27922 ATTN AMTEX

New Products...



Table top drill for short run PCB production

Amden have released a new table top drill for short-run printed circuit board production and prototyping in-house.

The drill is easy and clean to operate. It features an adjustable, tilting work-table which is footswitch activated, and it has a dust absorbing vacuum system

which keeps the work area and surrounding atmosphere free of fibreglass dust. The unit is powered by a 90 watt motor running at 30,000rpm, and the precision is enhanced by continuous variable control of the stroke speed.

For further information contact: Circuit Components (A'Asia) Pty Ltd, 383 Forest Rd, Bexley, NSW 2207. Telephone: (02) 59-3720.

Portable EPROM/EEPROM programmer

The SE-4942 is a fully portable programmer that fits easily into a briefcase. Weighing only 1.8 kg and having a wide operating voltage range from 85 to 249 volts AC makes this unit ideal for field service.

Nine standard transfer formats enable the user to down or up-load data. Full remote control is available via the RS232 port. The SE-4942 offers programming facilities and does extensive checking on the EPROM to ensure faulty devices do not pass.

For more information contact Alfa-tron Pty Ltd, 1761 Ferntree Gully Rd, Ferntree Gully, Victoria 3156. Telephone: (03) 758-9000.

PRODATA	Special OEM prices for IBM® PC XT AT etc.	Qty prices excluding tax
DTC 5150 BXD6 controllers for "PC/XT"		\$222
DTC 5290 Controllers for "AT"		\$430
20MB to 86 MB Winchester Drives		\$CALL
DP100 10" dot matrix Printers		\$279
DP150 15" dot matrix Printers		\$468
Fujitsu DPL24 and SP830 printers		\$CALL
(07) 289 1955		PO Box 51 SAMFORD 4520

Scanning receiver

Recently released by Dick Smith Electronics Pty Ltd, the HX 2000 AM/FM programmable hand-held scanning receiver covers seven frequency bands and boasts 20 channel memories, a liquid crystal display, and automatic search and scanning controls. The unit is supplied complete with a small whip antenna.

For further information contact Dick Smith Electronics Pty Ltd, PO Box 321, North Ryde, NSW 2113. Telephone: (02) 888-3200.




Personal alarm for mugging deterrent

The Electro-Guard Personal Alarm from ACS Systems is a pocket-sized unit which doubles as a convenient torch. Pressing a button causes it to emit a piercing alarm sound. It can also be used as a simple door alarm or window alarm to guard against intruders. It is priced at \$9.95.

For further information contact ACS Systems, 109 Alexander Street, Crows Nest 2065. Telephone: (02) 437-6206.

DAVID TILBROOK DOES IT AGAIN!



vifa



We're talking about the exciting new David Tilbrook designed speaker kit which uses VIFA's high performance drivers from Denmark. His 2-way, digital-ready 100 Watt capable masterpiece. The name Tilbrook is synonymous with brilliant design and performance characteristics and this new system keeps the legend alive and well. The magazine 'The Australian Electronics Monthly' - where David is Project Manager - published full details of the design in their August issue. Already there has been considerable interest and many speakers have now been built with superb results.

You'll save around \$800 when you hear what you get from this system when compared to something you buy off the shelf with similar characteristics. If you compare its performance to fully imported, high priced speakers from Mission, Heybrook, Monitor Audio, Bang & Olufsen and many others, you'll see that they too use these VIFA speakers.

This kit of 2-P21WO Polycone Woofers and 2-D25TG-55 Ferrofluid Cooled dome tweeters with Polymer Diaphragms, is available for \$350. Cross-overs, cabinets and loudspeaker stands are also available. For further information and a reprint of the full details of the Tilbrook project, please contact the Sole Australian Distributor or your nearest dealer. Stocked by Jaycar Electronics and leading hi-fi and electronic stores.

Sole Australian Distributor:
SCAN AUDIO PTY. LTD., P.O. Box 242,
Hawthorn 3122. Telephone (03) 429 2199.

Queensland Distributor:
Queensland Stereo Visual Supply
Telephone (07) 265 7945.

Dealers: Sydney - Jaycar Electronics
7472022. Brisbane - Queensland
Stereo Visual 265 7945. Melbourne -
Radio Parts 211 8122.

Build one of the world's finest 2-way speakers. \$907



For the unadulterated pleasure of pure, detailed and accurate sound, it is generally accepted that the starting point just has to be Danish Dynaudio drivers.

Dynaudio drivers use hexagonal voice coil wiring and magnetic voice coil oil for extremely high power handling, woofers with symmetrical drives, voice coil sizes of up to 4", and brilliantly designed crossover networks.

For the recommended retail price of \$907 we can show you how to enjoy a quality of sound you have probably never experienced before. Call your nearest Dynaudio dealer today.

Sole Australian Distributors: SCAN AUDIO Pty. Ltd., P.O. Box 242, Hawthorn, Victoria 3122. Telephone (03) 429 2199.

Dealers: Melbourne - Tivoli Hi-Fi 813 3533 Adelaide - Blackwood Sound 278 6888 Sydney - Appollo Hi-Fi 560 9019 Brisbane - Ipswich Hi-Fi 281 5485, City Hi-Fi 832 4498, Queensland Stereo Visual 265 7945.



DYNAUDIO
AUTHENTIC FIDELITY

SCAN SPEAK 200.



The professional kit from the kit professionals.

The Scan Speak 200 Kit offers you the opportunity to build and enjoy a speaker system which produces magnificent results over the entire sonic spectrum - at a price which would be trebled, or more, in ready-made speakers.

The key to performance lies in the components used. Both the woofer (180mm) and tweeter (19mm) are manufactured in Denmark by Scan Speak - and are the same as those chosen by such world leaders as ProAc, Carlsson, Linn, and NAD - just to name a few.

Frequency Response is 50 to 20KHz \pm 3db, Sensitivity (1mtr/lw) is 89db, Crossover Frequency is 3000Hz and Distortion on 2nd and 3rd harmonics 100 to 20KHz is less than 0.7%.

At around \$800, the kit comes with complete technical data plus easy-to-follow instructions. All exposed cabinet areas are timber veneer. When assembled, each speaker measures 650 x 260 x 360mm.

For further details please contact the Sole Australian Distributor or your nearest dealer.



scan·speak

SCAN AUDIO Pty. Ltd.
PO Box 242, Hawthorn, Victoria 3122.
Telephone (03) 429 2199.

Dealers: Melbourne - Penny Lane Audio
259 9641, Diamond Hi-Fi 435 8400. Sydney -
Dave Ryall Electronics 982 7500. Brisbane -
Sound Centre 221 0821. Adelaide -
The Sound Craftsmen 272 0341.

New Products...



Laser module with 10mW output power

By using an improved optical resonator and a higher quality mirror, Siemens have been able to boost the output power of their HeNe laser module to 10mW, making it a good choice for use in laser printers.

The specified 10mW output refers to the "end-of-life" condition, with life expectancy being 25,000 hours. All the HeNe laser tubes and modules from Siemens except the 25mW version feature coaxial design and integral mirrors, with output power ranging from 0.5mW upward.

The tubes are manufactured using glass to metal and ceramic-to-metal technology. For further information contact Siemens Ltd, 544 Church St, Richmond, Vic 3121. Telephone: Sydney (02) 436-8720.

Miniature air variable capacitors

The Murata-Erie Miniature MVM series of air-variable capacitors are suited to VHF, UHF, microwave military communications, navigation, fire control, and various RF applications.

The MVM has internal air meshing shells which are silver plated to provide conductivity and long life. The high density ceramic insulator is used be-

tween stator and mounting bushing and this construction contributes to the overall strength. A rubber gasketed threaded end cap effectively seals the unit against humidity and contamination.

The MVM series have a maximum working voltage of 250VDC and capacitance ranges from 0.8-10 pF to 1.0-20 pF.

For further information contact IRH Components, 32 Parramatta Road, Lidcombe 2141. Telephone: (02) 648-5455.

Business Brief

Data Cable Pty Ltd have moved. Their new address is 538 Mountain


Highway, Bayswater, Victoria, 3153. The company has installed a toll-free number for interstate callers. This is 008 33 7463, while the normal telephone number is (03) 729 0044.

Weatherproof UV-resistant plastic enclosure

The Amalgamated Instrument company originally designed this weatherproof case for their range of swimming pool test equipment.

The main body of the unit is moulded from a plastic material called ASA which is highly UV resistant. The front is made from toughened acrylic which is also UV resistant.

The enclosure can be surface or panel mounted. Retail price is \$22.50.



For further information contact Amalgamated Instrument Co Pty Ltd., PO Box 134, Terry Hills 2084. Telephone: (02) 450-1744.

Power amplifiers for 900 MHz cellular radios

Motorola has power amplifiers for 900 MHz portable cellular radios. They are the MHW802-1 and the MHW802- which are rated at 2.2 watts output power and are intended for one watt portables. They provide over 3dB reserve power to compensate for normal duplex filter losses. The amplifier operates at a supply voltage of 9.4V DC.

The MHW802 is packaged in a rugged housing designed to provide a self-contained heat sink permitting safe operation of the module at case temperature up to 100°C.

Hitachi 40MHz digital storage scope

The Hitachi VC6041 features 40MHz channel operation in conventional mode and in digital mode, a large memory capacity of 4000 words/channel in each of the inputs, data save and display memories and a horizontal axis resolution of 400 words/div with x100 magnification.

The dual save memories enable the display of newly stored and save memory comparisons and the cursor functions display time and voltage information on the LED and annunciation panels.

Most of the features are selected by single pushbutton operation and the scope is backed by a two-year warranty.


For further information contact IRI Components, 32 Parramatta Road, Lidcombe 2141. Telephone: (02) 648-5455.

Modular work benches and cabinets

Lamson Engineering has extended its range of material handling products by acquiring full production and marketing activities for modular work benches and dense storage tool cabinets.

The modular work benches are available in a variety of standard sizes with above bench shelf levels and below bench cupboard and drawer units available as easy add-on equipment to match individual requirements.

For further details contact: Lamson Engineering, 165 Rockwood Rd, Bankstown 2200. Telephone: (02) 70-0381.



HomeWatch

PROFESSIONAL COMPUTERISED SECURITY KIT



**INSTALL IT
YOURSELF**

Deluxe kit illustrated.

2 Kits available—Standard or Deluxe. 4 sector Control with switch selection of its many pre-programmed functions. Quality components for reliability. Comprehensive instructions included.

Literature, prices and further information available from:




I.E.I. (Aust) Pty. Ltd.

15-17 Normanby Rd, Clayton, Vic, 3149
Tel (03) 544 8411. Telex AA35780

248 Johnston St, Annandale, NSW, 2038
Tel (02) 692 0999

31 Phillips St, Thebarton, SA, 5031
Tel (08) 352 2066



50 and 25 years ago...

"Electronics Australia" is one of the longest running technical publications in the world. We started as "Wireless Weekly" in August 1922 and became "Radio and Hobbies in Australia" in April 1939. The title was changed to "Radio, Television and Hobbies" in February 1955 and finally, to "Electronics Australia" in April 1965. Below we feature some items from past issues.



January 1936

Missed opportunities: most of the radio factories closed down right over the holiday season and missed untold business. Apparently a lot of suburban and country dealers managed to sell sets in far greater numbers than expected, and we had the unusual experience of answering phone calls from dealers making frantic inquiries as to where to obtain sets.

Car radio trends: with the advent of all steel car bodies, the roof type of antenna has had to be discarded in favour of various types of under-car antennas. As these antennas have proved to have considerably less pick up, more sensitive receivers have had to be designed. The latest have a sensitivity factor of a third to half a microvolt!

Windmill power: the International Radio Company of Sydney always seems to be adding something new to its line up. The latest is the Pioneer "Air-flo" battery charger. In a nutshell, it is a battery charger generator driven entirely by a small windmill.

The job is a neat and compact unit which will charge batteries of six volts at up to five amperes., having a specially designed blade which takes the greatest possible power from even slight breezes.

Frequency modulation: there is little chance of stagnation in radio development. It was revealed by Major E.H. Armstrong at a recent meeting of the Institute of Radio Engineers in USA that he has been working on a system of frequency modulated transmissions. Major Armstrong will be remembered for his work in connection with early superheterodynes and super-regenerators.

He announced that for some months

past he had been carrying out practical tests with a new transmitting technique, with which he established more consistent communication over a distance of 85 miles than did the 50kW broadcast stations, although the power used was only 2 kilowatts. The transmissions were in the ultra-short wavelength of between 7 and 8 metres.

Making radium: the value of radium for medical treatment is colossal, but so too is the price. As a result, many laboratories have their research workers trying to create inexpensive radium substitutes.

Considerable steps have been taken in the production of a radium substitute with the manufacture of a huge electron whirligig. This device does away with the need for very high voltages, having an acceleration chamber with a strong magnetic field.

TV in Hollywood: the Twentieth Century studies are opening the first Hollywood television stage, making it a memorial to the late Will Rogers.



January 1961

World's largest: a fantastic spider web covers an entire peninsular at the easternmost tip of Maine, USA. — 750 acres of bronze lace 800 feet and more above the ground. This is the antenna for the most powerful transmitting station ever built. Its purpose — to talk to submarines under water.

Ordinary radio signals cannot penetrate water. Until the new 2,000,000 watt station goes on air early this year, submarines must raise their antennas above the ocean surface to receive messages.

Boeing helicopter: a new era of helicopter transportation was ushered in re-

cently with the first flight of the Boeing Vertol 107. The result of a completely new concept in helicopter design, the 107 is said to be the fastest, smoothest and most versatile helicopter flying today.

The twin rotor Boeing Vertol is the culmination of a four year program to produce the best configuration for a medium transport helicopter in the turbine era of the 1960s. Powered by two General Electric turbines of 2,300 horsepower, it can carry from 26 to 30 passengers and can cruise in excess of 155 m.p.h.

Car 45 player: the new car type record player, manufactured by Philips, was shown recently at the British Motor Show. It takes 45 r.p.m. records and is designed to play through any standard car radio. The makers claim that it is unaffected by bad roads, acceleration or braking.

New transformer: in the trend towards smaller and lighter electronic equipment one component, the transformer, has proved a stumbling block. The materials from which it is made are naturally heavy, while there is a limit to the miniaturisation possible without seriously degrading performance.

Serious attempts to replace the electromagnetic transformer are underway following the development of lead zirconate-titanate piezo electric ceramics. Two piezo electric elements are mechanically coupled. By electrically energizing one of the elements, it is possible to produce a strain and thereby a voltage in the other.

Sintered magnet: a stronger type of magnet has been obtained by sintering insulated magnetic flakes instead of the usual nickel-iron powders.

The magnetic flakes align themselves before pressing. This means there are fewer air gaps in the finished component. This in turn can double the amount of magnetism carried by the pressing.

Threshing machine: a novel type of threshing machine, or combine harvester, weighs only two thirds of a ton compared to the usual weight of three tons. It depends on the fact that the grain is threshed against a rubber roller filled with air instead of the usual threshing board.

LITTLE DICK'S SUMMER SIZZLERS




WIRELESS BURGLAR ALARM

Crime is on the increase! Your home, unit or office needs 'effective' security. And with DSE's Wireless Alarm System, you'll have total protection and enjoy peace of mind. This is a complete package. Included with the sophisticated Central Processor are a **passive infrared sensor** for whole room monitoring, **remote reed switch** for guarding entry/exit points and **personal remote control**. You can even extend the system by adding on more of these affordable peripherals shown below. And because it's wireless there are no expensive installation costs. Just plug the Central Processor into the power point, connect the peripherals and set the alarm. As simple as that! It's like having a personal security guard — but without the cost. Cat L-5120



ALL THIS
FOR ONLY
\$349



Extend your system by adding 'more' of these. . .

PERSONAL REMOTE CONTROL

Use to remotely turn the alarm on and off. Convenient!

Cat L-5124
\$39⁹⁵

PASSIVE INFRARED SENSOR

Monitors whole rooms (covers 64sq m.). Any movement is instantly transmitted to the CPU.

Cat L-5122
\$119

REMOTE REED SWITCH

Guards entry/exits. Any intrusion and the alarm sounds. Cat L-5126

\$39⁹⁵

LOCAL AUDIO ALARMS

LARGE PIEZO ELECTRONIC

Compact but it delivers an earsplitting sound! Ideal for car, home or van alarms. Operates from 12V DC at 500mA; 110dB output at 1m. Cat L-7030

\$24⁹⁵




REDUCED!

PIEZO ELECTRONIC ALARM

What a bargain! Amazing output for such a tiny unit! Suits most systems. Working voltage: 7.5-15 (200mA at 12V). Sound output: 110dB at 1 m. Frequency: 2800Hz.

~~\$14.95~~
NOW \$9⁹⁵




Cat L-7025

VALUE!!

REMOTE SWITCHED CAR ALARM

Stops thieves 'stealing off' with your valuable car! Hard to imagine that real protection could be so affordable — but DSE covers all the angles. Features boot and bonnet trigger, ignition cut-out, battery backup capability and more. Loud 110dB siren should scare off thieves instantly. Cat L-5096

\$159




CAR COMMANDER

Tells you what's happening under the bonnet!

Incredible! Every family car can have the monitoring facilities of a Formula One racer with this inexpensive unit. An LCD displays the status of vital functions: oil pressure, RPM, voltage and water temp. Programmable RPM and water temp. alarm warns of impending problems. Built-in stopwatch too! Cat Y-3011

\$84⁹⁵



BARGAIN!

B.093/MM

DICK SMITH ELECTRONICS

PTY LTD

NOW AVAILABLE AT ALL 52 DSE STORES THROUGHOUT AUSTRALIA & PARTICIPATING RESELLERS.

Algernon:

a low cost robot for any 8-bit computer

If you've always had a hankering to get involved in robotics but could never justify the expense, Jaycar's new robot kit is cheap enough to put you in the picture. This is a real do-it-yourself project with plenty of challenge for imaginative constructors and computer hackers.

by COLIN DAWSON

With powerful personal computers available to hobbyists, robotics is now a more practical hobby than ever. The only obstacle preventing hobbyists from developing a reasonably sophisticated system has been the cost of the robot itself.

Even quite elementary robot arms usually have a price tag with four figures. At \$189 for the basic kit, Jaycar's new robot opens up the field for a lot of people on a low budget.

An unlikely combination of printed circuit board copper laminate, radio dial


drives and pulleys, electric motors, rubber bands and other commonplace items, the new kit can be assembled into a versatile computer controlled robot arm. Its impressive "experimental" appearance is also a good talking point — it never fails to elicit an exclamation of "What's that thing?"

In fact, we thought that the new robot had so much "character" that he, it (she?) ought to be christened. We cast about for a moniker suitable for such a personage and came up with "Algernon". Yup. Algernon. He is quite a capable fellow and can be controlled by a Microbee or ultimately, any eight-bit computer.

Algernon compares well with other robot arms in terms of movement and freedom: it has separately controllable waist, shoulder, elbow, wrist and grippers, 270 degrees of rotation (at the waist), position sensors for all of its (his?) joints and pressure type limit switches for the fingers. Its only real limitation is that the wrist does not rotate.

The basic kit contains all of the parts needed for the arm assembly, including motors and position sensors. Not included are the motor control board and the computer interface board, both of which are available as separate kits. The interface board is suitable for use with the parallel ports of the Microbee but could be adapted to any 8-bit parallel computer port.

Two manuals are supplied with the basic kit. One contains the mechanical



Is it a bird? Is it a plane? It's Algernon and you can have him for your very own.

details and the other is the construction manual. Both are illustrated — the mechanical details manual also has PCB artworks for the arm assembly.

Most of the rigid structure for the robot arm is copper clad phenolic board — the raw material of printed circuit boards. Certainly, this is an unusual application for the PCB, but it actually works very well. The phenolic board provides a strong and lightweight backbone for the robot, while the copper cladding makes it easy to solder joined pieces together.

Phenolic board is also very cheap, which has been a major factor in keeping the cost of the kit low.

The robot is powered by five permanent magnet DC motors. These are used to actuate the waist, shoulder, elbow, wrist and gripper. Each motor has a rated current drain of 1A.

They could all be operated simultaneously if your robot control program is sufficiently comprehensive but a simpler program would operate each motor in sequence, thereby keeping the total current drain to a reasonable figure.

Drive is transmitted from the motors to the various knuckle joints of the arm through a system of quite large diameter pulleys. These were originally intended for use in radio dial drives and vary in size from 42mm to 112mm and are driven by nylon cords and rubber bands. Yep. It sounds a bit Heath Robinson-ish but it works!

To limit the amount of free play in the system, all of the longer drive cords have tensioners operating on them. This prevents jerkiness in operation and permits the operator to position the arm more accurately. However, the arm will still flex a little and the maximum practical load would be around 200 to 300 grams.

The position sensors for the waist, shoulder, elbow and wrist joints all have a resolution of one part in 192.

They each consist of an etched PCB disc carrying a matrix of eight diodes. The PCB pattern is arranged such that there are three concentric rings. The inner ring has eight pads, the second 64 and the outer 192 pads. A slide contact operating on each of the rings provides a unique code for each of the 192 positions.

The gripper sensor is a linear contact system with eight pads giving a position resolution of only one part in eight, but pressure limit switches on the grippers themselves compensate for their reduced resolution.

In preparing a control program, the



Algernon consists of PCB laminate, dial drums, rubber bands and electric motors.

range of positions can be equated to codes either by calculating all the possible codes or by "reading them in" from the sensor disc. This would necessitate setting up the computer port to read the disc output code whilst moving the joint through its full range of movements.

If the position codes are to be calculated, location of the slide contacts will be critical. For the alternative method, positioning of the contacts is not particularly important. Each position will correspond to some unique code — it does not matter what this code is.


The interface board is designed so that each of the motors can be operated at two speeds, in forward or reverse. The lower speed is achieved by operat-

ing the motor with a pulsed waveform. The pulse duty cycle can be easily set by selecting RC components.

We understand that a microprocessor controller for the robot is under development. This would eliminate the need for a computer and allow the arm to be controlled by a simple array of switches.

There are two low speed circuits available, although the particular circuit to be used with each motor must be nominated during construction. When the motors are operated at maximum speed, the chopper circuit is bypassed.

Next month we will describe how Algernon is put together. By the looks of it, the only tools required will be a screwdriver and soldering iron.



This view shows the various sub-assemblies, prior to final assembly.

Don't buy a new amplifier . . .

Build this CD Adaptor

Inexpensive and easy to build, this CD Adaptor will match your fancy new compact disc player to your stereo amplifier. All you need is a switch, a few resistors and four RCA sockets.

by COLIN DAWSON

Compact disc players have become enormously popular, with many people buying them for their convenience as much as for their sound quality. But beware! Your fancy new CD player might not be compatible with your amplifier.

While it is true that many amplifiers do not have the performance to take full advantage of a CD player's potential, this is not the main factor affecting compatibility. The problem is that the signal level from the CD player may exceed the maximum level permitted for the amplifier input.

Let's take a closer look at this. Prior to the advent of CD players, the auxiliary inputs on most amplifiers were rated at about 500mV sensitivity. This means that a signal of 500mV RMS must be fed in for the amplifier to deliver its rated output.

And that's where the problem comes in. Compact disc player manufacturers seem to have standardized on a 2V output level and this can overload the auxiliary inputs of some amplifiers. This particularly applies to low-cost amplifier systems where the volume control follows the tone control circuitry. The result is unpleasant distortion regardless of the volume control setting.

Where the volume control comes straight after the auxiliary input, the fact that the CD player signal is so high still causes a problem because the vol-

ume control has to be at such a low setting for normal listening levels. At such low settings the volume control will probably have very poor channel balance, as well as being quite "savage" in action. Fortunately, there is a simple cure.

The circuit

Basically, all that is needed is a resistive attenuator between the CD player and the amplifier. In this instance, we've taken the concept a little further

by devising a switchable attenuator. The circuit is shown in Fig.1.


As shown, the output of our CD Adaptor is switchable between four levels. In addition to the full 2V output, there are three levels of attenuation. These correspond to output levels of 1V, 600mV and 300mV respectively.

While much the same result could be achieved using only a dual gang potentiometer, the matching between the tracks on most pots is not up to standard. In addition, there is always the risk that the pot will become noisy.

The use of a switchable attenuator makes this a virtually universal circuit. It can be used to match a CD player to almost any amplifier without any component changes.

Construction

Because the circuit is so simple, we have not bothered to design a printed



Compare this inside view with the wiring diagram at far right.



The circuit is built into a low-cost plastic case.

circuit board. All of the resistors are mounted on the back of the switch as shown in the wiring diagram (Fig.2).

The prototype was mounted in a plastic project box measuring 130 x 67 x 40mm. Use the type with an aluminium lid as this can be used for the circuit earth. In addition to the rotary switch, the only other components required are the input and output RCA sockets.

Most of the constructional details can be gleaned from the photographs and the wiring diagram. Note that the resistors should be mounted close to the switch terminals so that they will clear

the bottom of the box.

Artwork for the front panel is reproduced actual size with this article and can be used as a drilling template for the front panel. A self-adhesive label made from photosensitive aluminium (Scotchcal) could also be used if available.

Although the lid of the box serves as the signal earth, the attenuator circuit also needs an earth. We made this connection via an earth lug attached to one of the input sockets. Use light-duty hook-up wire to complete the wiring connections between the switches and the sockets.

PARTS LIST

- 1 3-pole 4-position rotary switch
- 1 plastic project box, 130 x 67 x 40mm
- 4 panel-mounting RCA sockets (2 red, 2 black)
- 1 Scotchcal artwork (optional)
- 5 80mm lengths insulated hook-up wire

Resistors (0.25W, 5%)

2 x 4.7k Ω , 2 x 2.2k Ω , 4 x 1.5k Ω

Testing

To test the circuit, connect the outputs from your CD player to the CD Adaptor inputs. The output terminals of the CD Adaptor go to the amplifier auxiliary inputs. Switch on and check that the audio level shifts dramatically each time you alter the switch setting.

The correct switch setting can easily be found by trial and error. All you have to do is switch the level back until the signal is free of obvious distortion. At the same time, the audio level from the amplifier should be about the same as for other signal sources (volume control kept constant).




Fig.1: here is the full circuit diagram.




Fig.2: construction is easy — just follow this simple wiring diagram.

REVIEWS OF RECENT

Records & Tapes

CLASSICAL • POPULAR • SPECIAL INTEREST



MOZART

Quartet for Oboe, Violin, Viola and Cello. Divertiment: for Oboe, Cor Anglais, Two Horns, Double Bass and String Quartet. Heinz Hollinger (oboe), Hermann Baumann (horn), and the Orlando String Quartet. Philips digital disc 412 618/1.



In the Oboe Quartet the oboe takes the place of the first violin, the other instruments — second violin, viola and cello — make up the four. This gives the oboe prominence, even dominance in the score, a responsibility Heinz Hollinger assumes with graceful virtuosity.

After composing 15 quartets Mozart abandoned this form for 10 years except for four works for strings and flute and the oboe quartet under review. It may well be regarded as the first example of the composer's maturity in this form of writing. The first movement is lively, the scoring a continuing delight.

It can be roughly divided into three parts with a very brief silence between them and provides a constant joy in listening to playing of this perfection.

The second movement consists mainly of a long oboe solo, most elegantly played and though brief, continuing a little cadenza for the solo instrument. There are some excellent whispered pianissimos.

The finale is a jolly 6/8 rondo played with the nicest imaginable sense of rhythm unruffled by a sudden break into 4/4 time for a moment or two.

Here again the oboe's virtuosity is gallant but never flashy. It contains a lovely long serious melody in a pensive mood and I found the whole disc a total delight.

The Divertimento written to celebrate his well-loved sister Nannerl's birthday, is a suite of seven short pieces each for a different combination of instruments — oboe, cor anglais, two horns, double bass and string quartet and is a continuing wonder of originality. In this work the oboe is less prominent than in the quartet but is none the less always in evidence. Everything so affectionate that it warms the hearts of listeners.

The suite is played throughout with complete accuracy, perfect intonation, peerless coordination and unanimously subtle phrasing and inflections. This abiding pleasure is also light-hearted, described in the sleeve notes as social music, an opinion this reviewer endorses. Everything shines with the innocence of genius. (J.R.)

CHAUSSON

Concert for violin, piano and string quartet. Itzak Perlman (violin), Jorge Bolet (piano), Juillard Quartet. CBS Masterworks Digital Disc D37814.

There's a great meeting of talents in this fine recording. Chausson was working in France towards the end of the 19th century when the whole musical world was influenced by the musical genius of Wagner. Chausson, and a great many of his fellow-countrymen, engaged in a lifelong struggle against Wagnerism with varying records of success.

Chausson was a rich amateur with no pressing pecuniary influences to sway him from one style to another but he was as enthusiastic an anti-Wagnerist as the next. But this did not prevent Wagner's influence from creeping in momentarily here and there; not however in conflict with typical French sensibility in this Concert — not Concerto.

The delightful scoring has all the transparency of the French school. There are many sudden changes of key which, however, do not, in the first

movement, disguise the influence of Cesar Franck, himself influenced by Wagnerism.

The busy piano is always nicely balanced against the other instruments. A grave-voiced cello adds to the charm. The music is always fresh despite an occasional intrusion of memory. The brief second movement is a swooping waltz, all very easy on the ear.

The third movement is funereal but shows no great profundity. It is characterised by the complete ease of the players. Here is a case of Chausson challenging Fafner with a quill. The Finale consists of a set of Variations on a syncopated theme. The engineering is most lifelike and the cooperation of the players of the highest sensitivity.

The form is cyclic, everything is vigorously musical and the scoring of beguiling clarity. To sum up the "concert" is more in the manner of a sextet than anything else and the composer's conflicts of style developed ultimately into the delights of Debussy and Ravel and other charmers. If your enthusiasm for French music about the turn of the century is strong this is certainly for you. (J.R.)

BARTOK

The Six String quartets played by the Juillard Quartet. CBS Masterworks Portrait. Three boxed analog discs. M3P 39817.

The Juillard have recorded these quartets three times. They are probably the greatest examples of their kind since the posthumous set of Beethoven's. It is a fine issue which, however, faces tough competition from other similar combinations.

It may be interesting to note that though this is the Juillard's first go at the set only one of the original players is now in the present group. He is the leader, Robert Mann.

Amongst the stiff competition that faces the present Juillard issue the strongest comes, in my opinion, from the Tokyo set, put out by DGG some four or five years ago. I still have it and play it alongside the Juillard.

Despite the many merits of the latter I favour ever so slightly the Tokyo issue. The edge, however, is the slightest imaginable and is based on detail — and occasional at that — only. The playing of the Juillard may be described at the least as illustrious despite a tendency to a slightly too wide a vibration sometimes in the leader's tone.

When we come to the sound the Tokyo's has a slightly wider dynamic than the Juillard's and they seem to me to apply just a little more passion, not noticeable, however, until you know the works really well — no easy task. But the Juillard wins No. 3 hands down.

Detailed examination of both these examples of the recording leaves one with nothing but admiration for both the Juillard and Tokyo sets, though I must repeat here that my preference goes ever so slightly to the latter. But do not let this sway you. Either set is of the highest standard and would make a valuable addition to any music library. A pity some of the discs are not available separately. Juillard's is in a boxed set.

The present issue is a re-engineered set of the original 1949 mono issue but you will be surprised at the quality of the sound. (J.R.)

STRAUSS

Ein Heldenleben (A Hero's Life) Tone Poem. The Cleveland Orchestra conducted by Vladimir Ashkenazy. Decca Digital Disc 414 292.

Ein Heldenleben (A Hero's Life) is just what the title indicates — the life of a noble fellow, in this case the composer.

In this monstrous autobiography we have him as a swaggering youth, fighting off spiteful critics, going into battle, making love and settling down in peace. There is no question of his death, for this Strauss would probably have us go to his Death and Transfiguration which also has a noble ascension to somewhere or other at the end.

But all this is not to undertake it as music. It has great moments and is vividly graphic, especially in the haunting love music with its alternative chattering and eroticism in which Strauss leaves nothing to the imagination and much to the memory.


The work despite its many merits is one of the least often recorded of the Strauss poems. Its faults must be weighed against its virtues — the autobiographical bombast and vulgarity of the battle music against — I must repeat it — the beauty of the love music. In this last the very difficult solo violin part is admirably played by Daniel Majesky.

The music follows on from there so beguilingly that one is happy to delay as long as possible the vulgar battle music that follows. In this the hero plunges radiantly into combat, lays about him lustily and, of course, emerges scatheless and victorious.

This egocentricity precedes the hero's earlier victories, signified by quotations from his earlier works. Peace, pipes its joys and contentment with Ashkenazy doing full justice to every bar in the splendidly scored piece. It is a brilliant reading in which he controls everything with complete understanding. Strauss fans of all but the most selective kind will adore it. (J.R.)

BIG BAND RE-MASTERED

Ray Noble with Al Bowlly & Glen Miller. The Great Bands in Digital Stereo — Vol III. Simulated stereo LP, RCA Victor VPLI-0465.



Here is yet another in the recent series of albums compiled from original 78s, reprocessed by recording engineer Robert Parker. (See E.A. Sept. '84 p20).

Whereas earlier recordings in the series have been mainly orchestral — big band and jazz — this one has vocalist Al Bowlly up front in most of the tracks singing hits of the '30s. Also on hand is the vocal group the Freshmen. As such, the album will probably have a nostalgic appeal to a wider audience.

Glen Miller, who had helped form the band, played trombone for Ray Noble and assisted with the arrangements, before ultimately forming his own highly successful orchestra.

And Al Bowlly? Who else, asks Ron

FROM CASHMORE'S — MIRROR BALLS — STROBES — UFO'S — CHASERS — COSMO BALLS — SPINNERS — FOG MACHINES — POLICE BEACONS — PIN SPORTS — POWER AMPS — DISCO'S — HIRE — SALES — INSTALLATION SERVICE



\$800 **SOUND CENTRE MK II DISCO MIXER**
2 Mic Inputs with vox.
3 band eq. Deck start sw/s
Tape in + out, Aux in + out

BIG CHASERS



4 X 1 kw
P.CH.

Inbuilt
mic.

\$240 **Multiple Auto Function**

PINSPOTS



\$38

6 ARM SPINNERS \$290



REHEARSAL STUDIO'S AVAILABLE BROCHURES — PRICE LISTS AVAILABLE TLX AA7459
CASHMORE SOUND 354 LIVERPOOL RD, ASHFIELD 2131 (02) 798 6782

Ian J. Truscott's

ELECTRONIC WORLD

MORE & MORE

People are discovering us each week. Both the home enthusiast through to the small manufacturer.

★ ★ ★

COMPONENTS • TOOLS • KITS

In any quantity, buy one, or one thousand, we're happy to oblige

SCHOOLS • CLUBS ETC.

Inquire about our bulk discount deals

Save yourself a trip to the city - come to

**30 LACEY STREET
CROYDON**

OR PHONE

**(03) 723 3860/
723 3094**

Mail orders welcome.

EP-232 SERIAL INTERFACE EPROM PROGRAMMER

A COST EFFECTIVE SOLUTION TO EPROM PROGRAMMING



- EP-232 will program all 27-series of Eeprom from 2716 to 27256.
- Simple Interface to any computer using RS232 port.
- All functions controlled from computer console giving easy operation.
- User friendly MSDOS or CP/M software is included providing program-verify-read-blank commands, as well as editing and disk file I/O.
- TTL Prom programming personality modules available.
- Australian made EP232 costs a fraction of imported units.

CALL FOR PRICE AND DETAILS

DIAMOND SYSTEMS

(03) 714 8269

P.O. Box 105 Hurstbridge 3099

Records & Tapes

Will the producer of the record, can claim to have made over a thousand different records — in a space of 13 years?

To modern ears, Al Bowlly might have less appeal than vocalists such as Bing Crosby, Frank Sinatra or Perry Como but he certainly wowed them in the '30s!

There are 16 tracks on the album, with Al Bowlly's hit songs include: A Little White Gardenia, Top Hat, Lazy River, Red Sails in the Sunset, You and the Night and Music, and many more. Non-vocal tracks are: Bugle Call Rag, Way Down Yonder in New Orleans, and Dinah.

As we've come to expect, Robert Parker's re-mastering has again transformed noisy, acoustically dead, mono 78rpm recordings to virtually noise-free, discreetly simulated stereo with ambience, undoubtedly getting much closer to the true sound of the original performance.

If you have an interest in musicians and music of the '20s and '30s, I doubt that you will hear them to better advantage than in this series of discs — including the present one. (W.N.W.)

THEATRE ORGAN

Five Alive, Premiere Recording on the Capri Theatre Pipe organ, Goodwood S.A. Digitally mastered stereo LP, Digi-pipe WB-1001. [From "Five Alive", TOSA (S.A. Div.), GPO Box 595, Adelaide 5001]



This new recording is certainly "alive" with interest for Australian fans of the theatre pipe organ but, in terms of organ sound, it is best regarded as an indication of what's in store for the future.

The intriguing story behind the Capri

organ is summarised on the jacket but was related at greater length in the brochure issued for the inaugural concert in April '83.

Originally installed in the Brisbane Wintergarden theatre in 1923 as a 2-manual 7-rank Wurlitzer, it was transferred to the Sydney Plaza and enlarged in 1940. Dismantled in the mid '50s, it was purchased by organist Penn Hughes and installed in his Sydney home, along with extra ranks from redundant instruments in Burwood NSW, Dunedin NZ, Southampton UK and elsewhere.

The current 4-manual console was a surplus "slave" unit obtained from the State Theatre, Melbourne.

At about this stage in its evolution, the organ was purchased by an overly ambitious enthusiast from Darwin but subsequently found its way back to Adelaide as the property of the Theatre Organ Society of Australia (S.A. Div.), being installed in their own theatre — the Capri at Goodwood. As a 4/22 instrument, it is probably destined to be the largest and most valuable theatre organ ever installed in this country.

The recording features tracks by five highly regarded local organists: Tony Fenelon, Neil Jesen, John Atwell, David Johnston and Ray Thornley who, between them, offer over 52 minutes of the instrument.

Involving five different artists over a three month period, the presentation lacks a sense of occasion but the most serious limitation has to do with mic. placement and building acoustics. The bass is rather boomy, while low frequency ambient (air?) noise is much too high by modern standards.

As the inaugural recording of Australia's largest theatre pipe organ, it will have its own historic appeal but, overall, the sound quality can only be described as average. The recording is available from the address given above for \$14 (incl. P&P) to anywhere in Australia or New Zealand. (W.N.W.)

CLASSICAL FLUTE

James Galway plays Schubert: Sonata for Flute & Piano in A minor, D821; Introduction & Variations on a theme from Die Schone Mullerin, D802; Serenade, D957, With Phillip Moll, Piano, RCA digital stereo LP, VRLI-7486.

In the wake of a number of recordings of popular-level material, this one

LOST CHANNEL 0? THEY'VE MOVED TO UHF!



Economy UHF/VHF

It's made for those good reception areas! If you're close to the transmitter you won't suffer on quality but you will save money. Channels 0 to 11 VHF, FM and UHF Band 4 including Channel 28! Cat L-4027



Combined UHF/ VHF Antenna

Why use two antennas when one will handle the job? Our combined UHF/VHF antenna is one of our most popular models. It's ideal for metropolitan reception areas! Great value for a dual purpose antenna! Cat L-4020



UHF/VHF Antenna With Reflector

It's top of the range! Particularly suited to fringe (or poor reception) areas you'll get a clear sharp picture with this one. Both VHF and UHF Band 4 & 5 with inbuilt reflector for maximum gain/minimum ghosting! Cat L-4018

JUST **\$39⁹⁵**

VALUE **\$59⁹⁵**

ONLY **\$79⁹⁵**

STORE LOCATIONS

NSW

Swift & Young Sts.
T55 Terrace Level
Shop 1, 65-75 Main St
613 Princess Hwy
Oxford & Adelaide Sts
531 Pittwater Rd
Campbelltown Mall Queen St
Shop 235, Archer St Entrance
147 Hume Hwy
164 Pacific Hwy
315 Mann St
4 Florence St
Elizabeth Dr & Bathurst St
450 High St
173 Maitland Rd, Tighes Hill
Lane Cove & Waterloo Rds
George & Smith Sts
The Gateway High & Henry Sts
818 George St
125 York St

Albury 21 8399
Bankstown Sq 707 4888
Blacktown 671 7722
Blakehurst 546 7744
Bondi Junction 387 1444
Brookvale 93 0441
Campbelltown 27 2199
Chatswood Chase 411 1955
Chullora 642 8922
Gore Hill 439 5311
Gosford 25 0235
Hornsby 477 6633
Liverpool 600 9888
Maitland 33 7866
Newcastle 61 1896
North Ryde 88 3855
Parramatta 689 2188
Penrith 32 3400
Railway Square 211 3777
Sydney 267 9111

Treloar's Bldg, Brisbane St
263 Keira St
ACT
96 Gladstone St
VIC
Creswick Rd & Webster St
145 McCrae St
Shop 46, Box Hill Central, Main St
Hawthorn Rd & Nepean Hwy
260 Sydney Rd
1150 Mt Alexander Rd
Nepean Hwy & Ross Smith Ave
Shop 9 110, High St
291-293 Elizabeth St
Bridge Rd & The Boulevard
Springvale & Dandenong Rds
QLD
157-159 Elizabeth St
166 Logan Rd
Gympie & Hamilton Rds

Tamworth 66 1961
Wollongong 28 3800
Fyshwick 80 4944
Ballarat 31 5433
Bendigo 43 0388
Box Hill 890 0699
East Brighton 592 2366
Coburg 383 4455
Essendon 379 7444
Frankston 783 9144
Geelong 43 8522
Melbourne 67 9834
Richmond 428 1614
Springvale 547 0522
Brisbane 229 9377
Buranda 391 6233
Chermside 359 6255

Queen Elizabeth Dr & Bernard St
Gold Coast Hwy & Welch St
Bowen & Ruthven Sts
Ingham Rd & Cowley St West End
Cnr Pacific Hwy & Kingston Rd
SA
Wright & Market Sts
Main South & Flagstaff Rds
Main North Rd & Darlington St
24 Park Terrace
WA
Wharf St & Albany Hwy
66 Adelaide St
William St & Robinson Ave
Centraway Acde, Hay St
TAS
25 Barrack St
NT
17 Stuart Hwy

Rockhampton 27 9644
Southport 32 9863
Toowoomba 38 4300
Townsville 72 5722
Underwood 341 0844
Adelaide 212 1962
Darlington 298 8977
Enfield 260 6088
Salisbury 281 1593
Cannington 451 8666
Fremantle 335 9733
North Perth 328 6944
Perth City 321 4357
Hobart 31 0800
Stuart Park 81 1977

Dear Customers,

Quite often, the products we advertise are so popular they run out within a few days, or unforeseen circumstances might hold up shipments so that advertised lines are not in the stores by the time the advert appears. And very occasionally, an error might slip through our checks and appear in the advert (after all, we're human too!) Please don't blame the store manager or staff; they cannot solve a dock strike on the other side of the world, nor fix an error that's appeared in print. If you're about to drive across town to pick up an advertised line, why not play it safe and give them a call first....just in case! Thanks. Dick Smith Electronics

MAJOR RESELLERS

NSW: • Ballina: A. Cummings & Co. 91-93 River St 86 2284 • Bathurst: Electronic Shop 74 Berrick Street, 31 4421 • Bowral: Barry Gash Electronics, 370 Bong Bong St 61 2577 • Broken Hill: Hobbies & Electronics, 37 Oxide St 88 4098 • Charlestown: Newtronics 131 Pacific Hwy 43 9600 • Coffs Harbour: Coffs Harbour Electronics, 3 Coffs Plaza, Park Ave. 52 5684 • Deniliquin: Deni Electronics, 220 Cressy St. 81 3672 • East Maitland: • Gosford: Tomorrow's Electronics & HiFi, 68 William St. 24 7246 • Lismore: Decro 3A/6-18 Carrington St. 21 4137 • Port Macquarie: Hall of Electronics, Horton Centre, Horton St. 83 7440 • Orange: Fyle Electronics 173 Summer St. 62 6491 • Tumut: Tumut Electronics Wynyard St. 47 1 631 • Tweed Heads: Stuarts Electronic Sales, Sh 3, 4 Stuart St. • Swansea: Swansea Electronics, 184 High St. 71 1674 • Wagga: Phillips Electronics 82 Forsyth St. 21 6558 • Windsor: M & E Electronics, Sh 7, McEwans Arcade, 206 George St. 77 5935 • Young: Keith Donges Electronics 186 Boorowa 821 279 VIC: • Hamilton: John Thompson & Co. 138-148 Gray St. 72 2000 • Echuca: Webster Electronics, 220 Packeham St 82 2956 • Mildura: McWilliams Electronics 110A Langtree Ave. 23 6410 • Morwell: Morwell Electronics, 95 George St. 34 6133 • Shepparton: GV Electronics Centre 100 High St. 21 8866 QLD: • Atherton: Maatens Music Centre 55 Main St. 91 1208 • Bundaberg: PM Electronics, Takalvan St. 72 8272 • Cairns: Electronic World Shop 27 K-mart Westcourt Plaza. 518 555 • Gladstone: Purely Electronics Shop Cnr Hebert & Auckland Sts 72 4321 • Mackay: Stevens Electronics, 42 Victoria St. 51 1723 • Maryborough: Keller Electronics, 218 Adelaide St. 21 4559 • Mt Isa: Outback Electronics 71 Barkly Hwy 433 331 • Rockhampton: Purely Electronics, 15 East St. 21 058 SA: • Mt Gambier: Hutchessons Communications, 5 Elizabeth St. 25 6404 • Whyalla: Eyre Electronics Shop 2 Forsythe St. 45 4764 WA: • Albany: Micro Electronics 133 Lockyer Ave. 41 3432 TAS: • Launceston: Advanced Electronics 5A The Quadrant. 34 1399 NT: • Darwin: Ventronics 24-26 Kavanagh St. 81 3491

DSX

PRESS ORDER SERVICE

Use your Bankcard, Mastercard or Visacard.
Just phone **008 226610** (toll free) for
fast 24 hour despatch of your order.
Enquiries: By mail, or phone (02) 8882105


POST & PACKING CHARGES

Order Value	Charge	Order Value	Charge
\$5.00 - \$9.99	\$2.00	\$50.00 - \$75.00	\$6.00
\$10.00 - \$24.99	\$3.50	\$75.00 or more	N.A.
\$25.00 - \$49.99	\$4.50		

Terms available to approved applicants

SA Customers: Credit facilities available through

Adelaide: 10 Pulteney St, Adelaide



DICK SMITH ELECTRONICS

PTY LTD

P.O. Box 321, North Ryde N.S.W. 2113. Tel: 888 3200

Records & Tapes

comes as an eloquent reminder of James Galway's alter ego. Maybe I should have put it the other way round but, whichever of his "alters" you prefer, he remains an outstanding musician/entertainer!

Galway is ably accompanied here by pianist Phillip Moll, who also provided the detailed jacket notes. Not surprisingly, his notes tend to concentrate on the genesis and structure of the works, with appropriate references to the composer, but with not as much as a mention of Galway or himself.

As Moll points out, Schubert had a short and productive life (1797-1828) but certainly not a merry one. He had no talent for dealing with publishers and little empathy with the Viennese musical establishment.

He relied on friends and supporters for his meagre income and introduced many of his works at "Schubertiads" — evenings with a few musicians and music lovers who "had grown devoted to the good-hearted little man with his seemingly inexhaustible outpouring of inspired melody."

The D821 Sonata on side 1 was written in 1824 as a Sonata for Arpeggione and Piano. Schubert coined the word Arpeggione to describe a six-string guitarre d'amour or guitar-violoncello, that had been devised a year earlier. The instrument was soon forgotten but its name still serves to identify the Sonata, ultimately published in 1871, and commonly performed since then on various instruments of the string family or, in this case, on flute. It comprises three movements: Allegro Moderato, Adagio and Allegretto.

The Introduction and Variations on side 2 was also written in 1824, again arising from an interest shared with a small circle of friends, including flautist Ferdinand Bogner. As finally published in 1851, the work comprises an introduction, the theme and seven variations, summarised in Moll's jacket notes.

Whether or not you are familiar with the major works, you will certainly recognise their final item, one of several songs written just before Schubert's death, and described by Moll as "the world's best loved serenade".

If the contents appeal, you need have no apprehension about the recording itself. "Mastered on Sony digital equipment in the CBS, London studios, it offers clean, well balanced sound, free of surface noise. A good one. (W.N.W.)

TRUMPET CONCERTOS

Trumpet Concertos, Ludwig Guttler, with the Neues; Bachisches Collegium musicum Leipzig and the Kammerorchester Berlin, conducted by Max Pommer. Compact disc, Capriccio 10-009. [From P.C. Stereo Pty Ltd, PO Box 272, Mt Gravatt, Qld 4122, Phone (07) 343 1612]

This is a similar disc to one reviewed in the June issue (Capriccio 10-010) — another recital by Ludwig Guttler with essentially the same orchestra and conductor but playing compositions by Mozart, Molter, "Anonymus" (an unidentified contemporary) and Haydn.

On this present recording, the concertos are by Theodore Schwartzkopff, Franz Querfurth, Johann Hummel and, again "Anonymus" but provisionally identified here as Ernst von Sachsen Weimar.

Unfortunately, the notes supplied

with this disc are in German only and will therefore be incomprehensible to most prospective purchasers. However, while somewhat frustrating, lack of notes need not compromise your enjoyment of this very listenable music.

For your guidance, Ludwig Guttler is a professor at the Academy of Music in Dresden, has travelled as soloist with the Bach Orchestra and the Berlin Chamber Orchestra and since 1969, has been resident trumpet soloist with the Dresden Philharmonic.

Tracks 1 to 5 carry the quite brief movements of Schwartzkopff's Overture in C-major for Trumpet, Strings and Basso Continuo (8'04"). This is followed on tracks 6-8 by Querfurth's 3-movement Concerto in C-sharp major, again for Trumpet, Strings and Basso Continuo (12'41").

Sachsen Weimar's (?) Concerto in C-major for Trumpet, Strings and Basso Continuo has 5 movements and a playing time of 6'57".

Consistent with the instruments of the baroque period in which they were written, the foregoing concertos are all pitched predominantly in the clarino (high) register.

The final and major work, Hummel's Concerto in E-major for trumpet and orchestra (3 movements, 16'11") was written after the development of Weidinger's new and much improved trumpet with its extended range, particularly in the low register. As such, it provides a fitting climax to the recital.

Manufactured in Japan by Sanyo, the recording provides clean, noise-free sound and excellent balance between soloist and the supporting orchestra. As with its companion disc, it's one that will appeal to those partial to small or chamber groups and, of course, to anyone interested in solo orchestral trumpet. (W.N.W.)

A change in direction

Next month the format of our record reviews will change. We will be reviewing compact discs exclusively, in two broad categories, popular and classical.

This is in recognition of the rapid rise in popularity of compact discs and the renewed interest in recording quality on the part of audiophiles.

Our new reviewers, to be introduced next month, are especially well qualified to write on contemporary and classical music.

We thank Julian Russell and Neville Williams, our long-standing reviewers, for their valued contribution to these pages over a period of 25 years.

TEST EQUIPMENT

Melbourne's largest range of secondhand:

Hewlett Packard
Tektronix
Marconi
Solartron
Boonton
BWD
Bruel & Kjaer

Oscilloscopes, sig gens, spectrum analysers, multi meters. Wide range of valves, coaxial connectors and test accessories. Repairs and service to all makes and model.

ELECTRONIC BROKERS AUSTRALASIA

20 Cahill St Dandenong 3175
(03) 793 3998
168 Elgar Rd Box Hill South 3128
(03) 288 3611

CD Player Directory

The following information was compiled from manufacturers' literature and with the help of most local distributors. It was correct at time of preparation but it is likely that some prices and specifications have changed since then. You should check prices and other information before making any purchase.

BRAND	MODEL	Loading system — Front/Top?	Frequency response: Hz-kHz ± 0.5 dB	Signal-to noise ratio @ 1kHz re 0dB	Channel separation @ 1kHz re 0dB	Total harmonic distortion % @ 1kHz @ 0dB	D-A conversion — bits	Oversampling?	Headphone output?	Fixed or Variable line output?	Remote control	Warranty — years	Dimensions mm (W x H x D)	Weight kg	Recommended retail price
ADC	CD-100X	Front	20-20	96	90	.004	16	No	No	Fixed	No	1	341 x 88 x 293	3.3	499.00
AIWA	DX-1200	Front	2-20	96	90	.003	16	Yes	Yes	Var.	No	3	330 x 71 x 298	5.8	899.00
AKAI	CD-A7	Front	5-20	90	85	.005	16	No	Yes	Fixed	IR	2	440 x 76 x 255	5.8	699.00
AKAI	CD-M88	Front	5-20	90	85	.005	16	No	Yes	Fixed	IR	2	350 x 72 x 255	5.3	699.00
B&O	CDX	Top	20-20	90	90	.004	14	Yes	No	Fixed	No	1			1500.00
CARVER	DTL-100	Front	5-20	96	86	0.05	16	Yes	No	Fixed	No	1	485 x 80 x 282		1590.00
dbx	DX-3	Front	20-20	96	90	.002	16	Yes	No	Var.	No		435 x 94 x 290	4.6	n.a.
DENON	DCD-1800	Front	5-20	96	94	.003	16		Yes	Fixed	No	2	464 x 110 x 372	9.5	1079.00
DENON	DCD-1800R	Front	5-20	96	94	.003	16		Yes	Fixed	IR	2	464 x 110 x 372	9.5	n.a.
DUAL	CD-130	Front	5-20	95	94	.003	16		Yes	Fixed	IR	3	435 x 110 x 264		599.00
HITACHI	DA-800	Front	5-20	95	92	.003	16	No	Yes	Fixed	No	1	435 x 83 x 264	5.9	599.00
HITACHI	DA-501	Front	5-20	95	92	.003	16		Yes	Fixed	IR	1	435 x 88 x 264	4.3	699.00
JVC	XL-400	Front	5-20	96	90	.002	16	No	Yes	Fixed	IR	1	435 x 93 x 294	4.0	849.00
JVC	XL-200	Front	5-20	96	90	.002	16	No	Yes	Fixed	No	1	435 x 93 x 294	3.8	579.00
JVC	XL-V20	Front	5-20	96	90	.002	16	No	Yes	Fixed	No	1	340 x 80 x 294	3.4	579.00
KENWOOD	DP-1100/2	Front	2-20	95	90	.0015	16	No	Yes	Fixed	Yes	1	440 x 88 x 310	6.8	1390.00
KENWOOD	DP-900	Front	4-20	95	90	.002	16	No	Yes	Fixed	No	1	440 x 88 x 310	6.0	1074.00
KENWOOD	DP-840	Front	5-20		90	.003	16	No	No	Fixed	No	1	420 x 84 x 310	4.8	799.00

BRAND	MODEL	Loading system - Front/Top?	Frequency response: Hz-kHz ± 0.5 dB	Signal-to-noise ratio @ 1kHz re 0dB	Channel separation @ 1kHz re 0dB	Total harmonic distortion @ 1kHz ± 0 dB	D-A conversion - bits	Oversampling?	Headphone output?	Fixed or Variable line output?	Remote control	Warranty - years	Dimensions mm (W x H x D)	Weight kg.	Recommended retail price
LUXMAN	D-405	Front	5-20	96	90	.003	16		Yes	Fixed	No	5	438 x 84 x 313	6.0	990.00
LUXMAN	D-03	Front	5-20	90	90	.004	16		Yes	Fixed	IR	5	453 x 90 x 360	8.1	1400.00
MARANTZ	CD-44	Front	20-20	90	90	.003	14	Yes	No	Fixed	No	2	320 x 90 x 300	6.0	499.00
MARANTZ	CD-54	Front	4-20	90	90	.003	16	No	No	Fixed	No	2	320 x 85 x 275	6.5	599.00
MARANTZ	CD-74	Front	4-20	90	90	.003	16	No	Yes	Fixed	No	2	416 x 85 x 300	8.0	699.00
MARANTZ	CD-84	Front	4-20	90	90	.003	16	No	Yes	Fixed	IR	2	416 x 85 x 300	8.0	799.00
MERIDIAN	MCD	Top	20-20	90	90	.004	14	Yes	No	Fixed	No	1	320 x 90 x 291	6.5	985.00
MISSION	DAD-7000	Front	20-20	90	90	.004	14	Yes	No	Fixed	No	1	320 x 90 x 305	7.0	1000.00
MITSUBISHI	DP-205	Front	5-20	94	90	.003	16	No	Yes	Fixed	No	1	424 x 79 x 300	5.4	859.00
NAD	5255	Front	20-20	98	90	.001	16	Yes	No	Fixed	No	5	420 x 83 x 330	5.3	899.00
NAKAMICHI	OMS-5	Front	5-20	92	92	.003	14	Yes	Yes	Fixed	No	2	435 x 100 x 308	7.5	1795.00
NAKAMICHI	OMS-7	Front	5-20	92	92	.003	14	Yes	Yes	Fixed	IR	2	435 x 100 x 308	7.5	2400.00
NEC	CD-705	Front	5-20	90	70	.01	16	No	Yes	Fixed	IR	1	430 x 120 x 360	10.5	969.00
NEC	CD-607	Front	5-20	90	70	.01	16	No		Fixed	No	1	430 x 90 x 320	9.8	699.00
ONKYO	DX-150	Front	10-20	96	90	.005	16	Yes	No	Fixed	No	5	435 x 92 x 350	5.0	649.00
ONKYO	DX-200	Front	2-20	96	93	.003	16	Yes	Yes	Var.	IR	5	435 x 102 x 350	6.0	1199.00
PHILIPS	CD-10	Top	20-20				14	Yes	Yes	Fixed	No	1	126 x 142 x 40	2.2	459.00
PHILIPS	CD-104	Front	20-20	90	90	.004	14	Yes	No	Fixed	No	1	320 x 90 x 300	7.0	499.00
PHILIPS	CD-204	Front	20-20	90	90	.004	14	Yes	Yes	Fixed	No	1	320 x 90 x 300	7.8	599.00
PHILIPS	CD-304	Front	20-20	90	90	.004	14	Yes	Yes	Fixed	IR	1	320 x 90 x 300	8.0	799.00
PHILIPS	CD-555	Front	20-20	90	90	.004	14	Yes	Yes	Fixed	No	1	320 x 220 x 90		899.00
PIONEER	PD-9010	Front	2-20	98	95	.001	16	No	Yes	Fixed	IR	1	420 x 91 x 310	4.9	1040.00
PIONEER	PD-7010	Front	2-20	96	93	.0015	16	No	Yes	Fixed	IR	1	420 x 91 x 310	4.7	819.00
PIONEER	PD-5010	Front	2-20	96	93	.002	16	No	Yes	Fixed	No	1	420 x 91 x 320	4.7	599.00

	Pioneer	P-DX500	Front	20-20	95	93	.0045	16	No	No	Fixed	No	1	360 x 98 x 260	4.6	2200.00
PIONEER	PIONEER	CDX-1	Car player with AM/FM radio													
REALISTIC		CD-2000	Front	5-20	95	90	.004	16	No	No	Fixed	No	1	320 x 84 x 306	4.9	499.95
REVOX		B-225	Front	20-20	90	90	.0005	14	Yes	Yes	Fixed	IR	1	450 x 109 x 322	8.5	
SANSUI		PCV-1000	Front	5-20	96	90	.003	16	Yes	Yes	Fixed	IR	2	430 x 111 x 297	8.6	1299.00
SANSUI		PCV-500	Front	5-20	96	90	.003	16	Yes	No	Fixed	No	2	430 x 111 x 297	8.4	999.00
SANSUI		PCV-300	Front	5-20	96	90	.005	16	Yes	No	Fixed	No	2	346 x 94 x 288	3.8	699.00
SANYO		CP-667	Front	5-20	96	92	.003	16	No	No	Fixed	No	1	420 x 75 x 275	3.3	429.00
SHARP		DX-110H	Front	5-20	96	90	.005	16	Yes	Yes	Fixed	No	1	330 x 80 x 297	4.7	499.00
SHERWOOD		CDP-100	Front	5-20	96	90	.002	16	No	Yes	Fixed	No	2	350 x 92 x 290	3.6	499.00
SONY		D-50	Top	20-20	90	85	.01	16	No	Yes	Fixed	No	1	127 x 37 x 133	0.6	479.00
SONY		CDP-7	Top	20-20				16	No	Yes	Fixed	No	1			569.00
SONY		CFD-5	Portable music system including CD player													999.00
SONY		CDX-5	Car CD player													899.00
SONY		CDX-R7	Car CD player with AM/FM tuner													1099.00
SONY		CDP-30	Front	2-20	90	90	.004	16	No	No	Fixed	No	1	355 x 70 x 275	3.8	529.00
SONY		CDP-70	Front	2-20	90	90	.004	16	No	Yes	Fixed	Opt.	1	430 x 70 x 280	4.1	599.00
SONY		CDP-102	Front	2-20	96	95	.003	16	No	No	Fixed	IR	1	355 x 80 x 335	5.7	869.00
SONY		CDP-302	Front	2-20	96	95	.003	16	No	Yes	Fixed	IR	1	430 x 80 x 235	6.7	1049.00
SONY		CDP-502	Front	2-20	96	95	.0025	16	No	Yes	Vari.	IR	1	430 x 80 x 335	8.8	1649.00
TEAC		PD-500	Front	3-20	96	95	.0015	16	Yes	Yes	Fixed	IR	1	435 x 93 x 290	4.8	799.00
TECHNICS		SL-PX7	Top					16	No	Yes	Fixed	No	2	126 x 32 x 126	0.5	529.00
TECHNICS		SLP-1	Front	4-20	96	100	.003	16	No	No	Fixed	No	2	430 x 82 x 334	5.1	719.00
TECHNICS		SLP-2	Front	4-20	96	100	.003	16	No	Yes	Fixed	IR	2	430 x 82 x 334	5.3	849.00
TECHNICS		SLP-3	Front	4-20	96	100	.003	16	No	Yes	Vari.	IR	2	430 x 82 x 334	5.3	889.00
TOSHIBA		XRV-11	Front	5-20	96	90	.003	16	No	Yes	Fixed	No	1	340 x 84 x 308	4.1	479.00
YAMAHA		YCD-1000	Car CD player with AM/FM radio													
YAMAHA		CD-X2	Front	5-20	95	90	.005	16	Yes	Yes	Fixed	No	5	340 x 92 x 290	3.6	499.00
YAMAHA		CD-3	Front	3-20	95	90	.004	16	Yes	Yes	Fixed	IR	5	435 x 93 x 290	4.8	599.00

1986 compact disc catalogue

COMPILED BY DAVID FRITH

ADAMS, John

Harmonium; San Francisco Symphony Orch;
Edo Dewaart cond.
ECM 821 465-2

ALBENIZ

Echoes of Spain; John Williams, guitar
CBS CD 36679

ALBINONI

Adagio; plus — Pachelbel; Bach; Boccherini;
etc; Stuttgarter Kammerorchester; Karl
Munchinger cond.
Decca 411 973-2

Adagio in G minor; plus — 'La Notte'
(Vivaldi); Overture No 3 — Air (Bach); Canon
and Gigue (Pachelbel); Serenata Notturna
(Mozart); etc; Berlin Philharmonic Orch;
Herbert von Karajan cond.
DG 413 309-2

ALLEGRI

Miserere; plus — Victoria; Palestrina;
Monteverdi; Westminster Cathedral Choir;
Stephen Cleobury cond.
Argo ZH 410 005-2

BACH, CPE

Four symphonies for string orchestra; Franz
Liszt Chamber Orch.
Teldec 8.42 843

BACH, J.S.

6 cello suites; Lynn Harrell, cello
Decca (2CDs) DH2 414 163-2

6 Partitas; Andras Schiff, piano.
Decca (2CDs) DH2 411 732-2

A Musical Offering, BWV1079: authentic
instruments.
Capriccio 10.032

Art of the Fugue, BWV1080
Capriccio 10.026-2 (2CDs)

Art of the Fugue; Zoltan Kocsis, piano.
Phillips (DDD) 412 729-2

Art of the Fugue; The Musical Offering;
Canons (special box set); Ton Koopman, organ;
Trevor Pinnock, harpsichord.
Archiv 413 638-2

Brandenburg concertos No 1, 2 and 3: Linde
Consort.
EMI 747045

Brandenburg concertos No 3, 4 and 5: Linde
Consort.
EMI 747046

Brandenburg concertos — complete: Festival
Strings Lucerne, Rudolf Baumgartner cond.
Ariola-Eurodisc 610 123-232 (2CDs)

Brandenburg Concertos — complete: Academy
of Ancient Music, Christopher Hogwood cond.
L'Oiseau Lyre (2CDs) 414 187-2

Brandenburg concertos — early and late
versions.
Capriccio 10.025

Brandenburg concertos No 1, 2 and 3: English
Concert, Trevor Pinnock cond.
DG 410 500-2

Brandenburg concertos No 1, 2 and 4:
Concentus Musicus Vienna; Nikolaus
Harnoncourt cond.
Teldec 8.42 823

Brandenburg concertos No 1, 3 and 4:
Amsterdam Baroque Orch; Ton Koopman
cond.
Erato ECD-88 054

Brandenburg concertos No 1-3, BWV1046-48
Capriccio 10.041

Brandenburg concertos No 1-6: Hermann
Baumann, horn; Heinz Holliger, oboe; Klaus
Thuneman, bassoon; Guy Touvron, trumpet;
Michael Copley, recorder; I Musici.
Phillips (DDD) 412 790-2 (2CDs)

Brandenburg concertos No 2, 5 and 6:
Amsterdam Baroque Orch; Ton Koopman
cond.
Erato ECD-88 055

Brandenburg concertos No 3, 5 and 6:
Concentus Musicus Vienna; Nikolaus
Harnoncourt cond.
Teldec 8.42 840

Brandenburg concertos No 4, 5 and 6: English
Concert, Trevor Pinnock cond.
DG 410 501-2

Brandenburg concertos No 4-6, BWV1049-51.
Capriccio 10.042

Brandenburg concertos No 4-6: Carl Pini;
Henryk Szeryng; Michala Petri; Heinz Holliger;
Andre Bernard; Elizabeth Selin; Jean-Pierre
Rampal; George Malcolm; Academy of St
Martin-in-the-Fields, Neville Marriner cond.
Philips (ADD) 400 077-2

Brandenburg concertos, No 1-3: Carl Pini;
Henryk Szeryng; Michala Petri; Heinz Holliger;
Andre Bernard; Elizabeth Selin; Jean-Pierre
Rampal; George Malcolm; Academy of St
Martin-in-the-Fields, Neville Marriner cond.
Philips (DDD) 400 076-2

Cantata BWV 211 'Coffee'; Cantata BWV 212
'Peasant'; Julia Vardy; Aldo Baldin; Dietrich
Fischer-Dieskau; Academy of St
Martin-in-the-Fields.
Philips (DDD) 412 882-2

Cantatas — 'Coffee' and 'Peasant': Laki; Gati;
Capella Savaria; Hungaraton
HCD 12462-2

Cantata BWV205 'Aeolus Propitiated': Kenny;
Lipovsek; Equiluz; Schoenberg Choir;
Concentus Musicus Vienna, Nikolaus

Harnoncourt cond.
Teldec 8.42 915

Cantatas BWV140 and BWV147: Concentus
Musicus Vienna, Nikolaus Harnoncourt cond.
Teldec 8.43 203

Cantatas from the archive of early Bach
Capriccio 10.029

Cantatas Vol 1, BWV 1-4: Concentus Musicus
Vienna, Nikolaus Harnoncourt cond.
Teldec 8.35 027 (2CDs)

Cantatas Vol 2, BWV5-8: Concentus Musicus
Vienna, Nikolaus Harnoncourt cond.
Teldec 8.35 028 (2CDs)

Cantatas Vol 3, BWV9-11: Concentus Musicus
Vienna, Nikolaus Harnoncourt cond.
Teldec 8.35 029 (2CDs)

Cantatas Vol 36, BWV 147-151: Concentus
Musicus Vienna, Nikolaus Harnoncourt cond.
Teldec 8.35 654 (2CDs)

Cantatas Vol 37, BWV 152-156: Concentus
Musicus Vienna, Nikolaus Harnoncourt cond.
Teldec 8.35 656 (2CDs)

Cantatas Vol 4, BWV12, 1,314, 16: Leonhardt
Consort, Gustav Leonhardt cond.
Teldec 8.35 030 (2CDs)

Cantatas Vol 5, BWV17-20: Concentus Musicus
Vienna, Nikolaus Harnoncourt cond.
Teldec 8.35 031 (2CDs)

Cantatas Vol 6, BWV21-23: Concentus Musicus
Vienna, Nikolaus Harnoncourt cond.
Teldec 8.35 032 (2CDs)

Cantatas Vol 7, BWV24-27: Concentus Musicus
Vienna, Nikolaus Harnoncourt cond.
Teldec 8.35 033 (2CDs)

Cantatas Vol 8, BWV28-30: Concentus Musicus
Vienna, Nikolaus Harnoncourt cond.
Teldec 8.35 034 (2CDs)

Cantatas with corno di caccia (hunting horn)
Capriccio 10.027

Cantatas, BWV128-130
Teldec 8.43 096

Cantatas, BWV56 and 82: Siegfried Lorenz,
bass.
Capriccio 10.028

Cantatas: Nun Komm der Heiden Heiland;
Christ lag in Todesbaden: Ich will den
Kreuzstab gerne tragen: etc: Peter Schreier;
Hertha Toepper: Edith Mathis; Ernst Haefliger;
Hermann Prey; Munchner Choir and Orch;
Karl Richter cond.
Archiv 413 646-2

Cello suites 1-2: Paul Tortelier, cello
EMI 747090

Cello suites 3-4: Paul Tortelier, cello
EMI 747091

Cello suites 5-6: Paul Tortelier, cello
EMI 747092

Chorals: Schuebler, BWV147, 622, 734:
Marie-Claire Alain, organ
Erato ECD-88 030

Christmas oratorio — complete: Equiluz;
Watkinson; Lausanne Vocal Ensemble and
Chamber Orch; Corboz cond.
Erato ECD-88 059 (3CDs)

Christmas oratorio — complete: Peter Schreier,
Adam, Burmeister; Dresden Kreuz Choir and
Philharmonia, Flamig cond.
Ariola-Eurodisc 610 134-233

Christmas Oratorio: Gundula Janowitz; Ludwig
Wunderlich; Munchner Bach Chorus and Orch;
Karl Richter cond.
Archiv 413 625-2

Christmas Oratorio: Concentus Musicus Vienna,
Nikolaus Harnoncourt cond.
Teldec 8.35 022 (3CDs)

Concerto for three and four pianos: Beroff;
Collard; Rigutto; Tacchino; Wallez
EMI 747063

Concerto for violin and oboe in C minor, BWV
1060; Oratorium Festo Paschali, BWV249; plus
— concerto in G minor for violin, oboe and
orch (Vivaldi); concerto for violin and two
horns (Vivaldi): Heinz Holliger, oboe; Gidon
Kremer, violin; Academy of St
Martin-in-the-Fields, Heinz Holliger cond.
Philips (DDD) 411 466-2

Concerto in D minor, BWV1060; Concerto in A
major, BWV1044: Maurice Bourge, oboe;
Jean-Jacques Kantarow, violin; Andras
Adorjan, flute; Netherlands Chamber Orch;
Kees Bakel cond.
Denon C37-7064

Concertos for solo instruments: Simon
Standage, violin; Lisa Beznosiuk, flute; David
Reichenberg, oboe; The English Concert,
Trevor Pinnock cond.
Archiv 413 731-2

Concertos for two and three harpsichords: The
English Concert, Trevor Pinnock cond.
Archiv 400 041-2

Concertos for two harpsichords: The English
Concert, Trevor Pinnock cond.
DG 415 131-2

Concertos; suite No 3; cantata, BWV51: RTL
Symphony Orch; Leopold Hager cond.
Forlane UCD-16 535

Die grosse Silbermannorgel des domes zu
Freiburg; Toccato con Fuga D-moll, BWV565;
Schubler Chorales; Praeludium et Fuga G-moll,
BWV535; Trio C-moll BWV585; Fantasia, c-dur
BWV570; Trio D-moll BWV583; Praeludium et
fuga C-dur, BWV545; Fuga G-moll, BWV578;
Hans Otto, organ
Denon C37-7004

Favourite Bach Melodies: Siciliana — Sonata
for flute and harpsichord; Air — suite No 3;
Prelude — The Well Tempered Clavier I; etc:

A Adorjan, flute; H. Dreyfus, harpsichord,
Societas Musica Chamber Orch; H. Dreyfus
cond. Y. Takahashi, harpsichord; H. Rilling,
organ; Sofia Chamber Orch; V. Kasandjiev
cond.
Denon C36-7148

Fifteen two-part inventions, BWV772-786; 15
three-part inventions, BWV787-801: Kenneth
Gilbert
Archiv 415 112-2

Goldberg Variations: Glenn Gould, piano
CBS CD37779

Greatest organ works, Vol 1: Toccato and
fugue, BWV565; prelude and fugue, BWV552;
etc: Herbert Tachezi, Silbermann organ, Court
Church, Dresden
Teldec 8.43 119

Greatest organ works, Vol 2: Toccata, adagio
and fugue, BWV564; trio sonata, K526; partita,
BWV768; etc: Herbert Tachezi, Silbermann
organ, Dresden.
Teldec 8.43 191

Guitar Bach — guitar, bass and drums
Delta 11.001

Harpsichord concertos, BWV1052, 1057, 1064:
Gustav Leonhardt, Anne Uittenbosch, Alan
Curtis, harpsichords; Leonhardt Consort
Teldec 8.43 116

Harpsichord concertos, BWV1053-1056:
Leonhardt Consort, Gustav Leonhardt cond.
and harpsichord
Teldec 8.43 033

Harpsichord concertos: Igor Kipnis,
harpsichord; Stuttgart Chamber Orch; Karl
Munchinger cond.
EMI 860954

Harpsichord works, BWV915, 916, 989, 992
Capriccio 10.034

Historical Organ Concert at Waalse Kerk,
Amsterdam: Praeludium in G minor, BWV568;
Sonata in E minor; Praeludium et fuga in D
major, BWV532; etc: Jacques van Oortmerssen.
organ (Christian Muller 1772)
Denon C37-7376

Isaac Stern 60th Anniversary Concert —
concerto in D minor for two violins and orch;
plus — concerto in F major for three violins
(Vivaldi); sinfonia concertante in E flat major
(Mozart): Pinchas Zukerman, Itzhak Perlman,
Isaac Stern, violins; New York Philharmonic,
Zubin Mehta cond.
CBS CD 36692

Italian concerto in F BWV 971; prelude in A
minor BWV992; fantasia and fugue in A minor
BWV904; chromatic fantasia and fugue in D
minor BWV903; chorale prelude Ich ruf zu dir,
Herr Jesu Christ BWV639; chorale prelude
Num komm der Heiden Heiland BWV659:
Alfred Brendel
Philips (ADD) 412 252-2

Italian concerto, BWV971; fantasia BWV906;
capriccio BWV992; chromatic fantasia and
fugue, BWV903; four duets, BWV802-805:
Tatyana Nikolayeva, piano
Ariola-Eurodisc 880 017-231

Lute works, BWV996-1000
Capriccio 10.033

Magnificat BWV243; Jauchzet Gott in allen
Landen BWV 51: Emma Kirkby; Nancy
Argenta; Patrizia Kwella; Charles Brett;
Anthony Rolfe-Johnson; David Thomas;
English Baroque Soloists, John Eliot Gardiner
cond.
Philips (DDD) 411 458-2

Magnificat in D major; also — German
Magnificat in A minor (Hoffmann): Jane
Bryden, soprano; Jullianne Baird, soprano;
Jeffrey Gall, alto; Frank Hoffmeister, tenor;
Bach Ensemble, original instruments, Joshua
Rifkin cond.
Pro Arte PA-CDD 185

Magnificat in D Major; plus — Utrecht Te
Deum (Handel): soloists; Concentus Musicus
Vienna, Nikolaus Harnoncourt cond.
Teldec 8.42 955

Mass in B minor — complete: Concentus
Musicus Vienna, Nikolaus Harnoncourt cond.
Teldec 8.35 019 (2CDs)

Mass in B minor — complete: Lucia Popp;
Watkinson; Buchner; Lorenz; Radio Chorus
Leipzig; New Bach Collegium Musicum Leipzig;
P. Schreier cond.
Ariola-Eurodisc 610 089-232 (2CDs)

Mass in B minor, BWV232: Bach Ensemble,
Joshua Rifkin dir.
WEA 79036-2 (3CDs)

Motets BWV225-230: Rostock Motet Choir
Capriccio 10.030

Motets Vol 2, BWV226, 228, 229, 230
Bellaphon 690.01.011

Motets, BWV225-31; cantatas, BWV4, 50, 118:
soloists, Monteverdi Choir, English Baroque
Soloists, John Eliot Gardiner cond.
Erato ECD-88 117 (2CDs)

Motets, Vol 1, BWV 225,227
Bellaphon 690.01.005

Music in the Bach Household: Peter Shreier,
tenor
Capriccio 10.031

Musical offering, BWV1079: Soloists of
Jean-Francois Paillard Chamber Orchestra
Denon C37-7048

Oboe concertos in E, BWV1053; in A,
BWV1055; in D minor, BWV1059: Heinz
Holliger, oboe; Academy of St
Martin-in-the-Fields, Iona Brown cond.
Philips (DDD) 412 851-2

Orchestral suites No 1 and 2, BWV1066-67
Capriccio 10.011

Orchestral suites No 1 and No 2: English
Baroque Soloists, John Eliot Gardiner cond.
Erato ECD-88 048

Orchestral suites No 1-4, BWV1066-69: Festival
Strings Lucerne, Rudolf Baumgartner cond.
Ariola-Eurodisc 610 127-232 (2CDs)

Orchestral suites No 3 and 4, BWV1068-69
Capriccio 10.012

COMPACT DISC CATALOGUE

Orchestral suites No 3 and 4: English Baroque Soloists, John Eliot Gardiner cond.
Erato ECD-88 049

Orchestral Works (special box set): 6 Brandenburg concertos; 4 overtures; triple concerto: Simon Standage, violin; Lisa Beznosiuk, flute; The English Concert, Trevor Pinnock cond.
Archiv 413 629-2 (4CDs)

Organ music — fantasia and fugue in G minor, BWV542 "The Great"; etc: Michael Murray, the Great Organ at Methuen
Telarc 80049

Organ music — toccata and fugue in D minor; prelude and fugue in B minor; concerto No 2 in A minor; etc: Michael Murray, organ (Skinner-Schlicker).
Telarc 80088

Organ music: David Sanger, organ
Meridian ECD-84 081

Organ works, BWV541, 544, 546, 548, 653, 655, 659:
Capriccio 10.038

Organ works, BWV545, 552, 769: Trost organ at Altenburg
Capriccio 10.036

Organ works, BWV565, 542, 572, 547
Capriccio 10.035

Orgelmeisterwerke: Toccato and fugue in D minor, BWV565; fugue in G minor BWV578; prelude and fugue, BWV544; etc: Helmuth Rilling, organ of Gedachtniskirche, Stuttgart
Denon C37-7039

Overtures No 1 and 2, BWV1066-67: La Petite Bande, S. Kuijken cond.
Harmonia Mundi 567-1 99 930-2

Overtures No 1 and 2, BWV1066-1067: Concentus Musicus Vienna, Nikolaus Harnoncourt cond.
Teldec 8.43 051

Overtures No 3 and 4 BWV1068-69: La Petite Bande, S. Kuijken cond.
Harmonia Mundi 567-1 99 931-2

Overtures No 3 and No 4, BWV1068-69: Concentus Musicus Vienna, Nikolaus Harnoncourt cond.
Teldec 8.43 052

Partita in D minor BWV1004; suite in C BWV 1009; Pepe Romero, guitar
Philips (DDD) 411 451-2

Six chorale preludes (Scubler Chorales); fantasia in G BWV 572; partita Sei gegrusset, Jesu gutig BWV768; Daniel Chorzempa, organ
Philips (DDD) 412 117-2

Six partitas, BWV825-830: Huguette Dreyfus, harpsichord
Denon C37-7333

Six suites for violincello solo senza basso, BWV1007-1012; Mari Fujiwara, cello
Denon C37-7373-5 (3 CDs)

Six violin sonatas BWV 1014-1019: Monica

Huggett, baroque violin; Ton Koopmann harpsichord
Philips (DDD) 410 401-2 (2CDs)

Sonatas and partita for flute: sonata in A major, BWV1032; sonata in B minor, BWV1030 for flute and harpsichord obbligato; partita in A minor, BWV1013 for flute; etc: Aurele Nicolet, flute; Christiane Jaccottet, harpsichord; Mari Fujiwara, cello
Denon C37-7331

Sonatas and partitas for violin: Shlomo Mintz, violin
DG 413 810-2 (3CDs)

Sonatas BWV1001, 1005, 1012: Gustav Leonhardt, harpsichord.
Harmonia Mundi 567-1 69 528-2

Sonatas for flute and harpsichord obligato, based on various trio sonatas: Aurele Nicolet, flute; Michio Kobayashi, harpsichord
Denon C37-7058

Sonatas for flute: Beaucoudray, flute; Christie, harpsichord
Harmonia Mundi HM 90.0065

St John Passion (special box set): Evelyn Lear; Hertha Toepper; Ernst Haefliger; Hermann Prey; Munchener Choir and orch; Karl Richter cond.
Archiv 413 622-2 (2CDs)

St John Passion — complete: Concentus Musicus Vienna, Harnoncourt cond.
Teldec 6.35 018 (2CDs)

St Matthew Passion (special boxed set): Dieter Fischer-Dieskau; Edith Mathis; Janet Baker; Peter Schreier; Munchener Bach Choir and Orch; Karl Richter cond.
Archiv 413 613-2

St Matthew Passion — complete (live recording). Concertgebouw Orch; Amsterdam, Nikolaus Harnoncourt cond.
Teldec 8.35 668 (3CDs)

St Matthew Passion — highlights: soloists; Lausanne Vocal Ensemble and Chamber Orch; Michel Corboz cond.
Erato ECD-88 017

St Matthew Passion: Equiluz, Faulstich; Huttenlocher; Watkinson; Lausanne Vocal Ensemble and Chamber Orch; Coboz cond.
Erato ECD-88 063 (3CDs)

St Matthew Passion: Peter Schreier; Theo Adam; Lucia Popp; Marjana Lipovsek; Eberhard Buchner; Robert Hall; Dresden Boys' Choir; Leipzig Radio Chorus; Staatskapelle Dresden, Peter Schreier cond.
Philips (DDD) 412 527-2 (3CDs)

Suite BWV996, toccata BWV914; capriccio BWV992, fantasia and fugue BWV904; etc: Gustav Leonhardt, harpsichord
Philips (DDD) 416 141-2

Suite for flute and orch; plus — suite for flute and orch (Teleman): Madeira Festival Orch; Newman cond.
MMG MCD 10008

Suite in B minor BWV1067; concerto BWV1060; etc: Maurice Andre, trumpet; Jean-Francois Paillard Chamber Orchestra, J-F Paillard cond.
Erato ECD-88 016

Suites for violincello solo, arranged for flute solo by Aurele Nicolet: Suite 1 in G major, BWV1007; E flat major, BWV1010: Aurele Nicolet, flute
Denon C37-7383

The Bach Trumpet — 13 works: Ludwig Guttler, trumpet
Capriccio 10.039

The Musical Offering: Academy of St Martin-in-the-Fields, Neville Marriner cond.
Philips (ADD) 412 800-2

The six motets, BWV225-230: Bach Choir Stockholm; Concentus Musicus Vienna, Nikolaus Harnoncourt cond.
Teldec 8.42 663

The Well Tempered Clavier Vol 1 & II: Friedrich Gulda, piano
Philips (ADD) 412 794-2 (4CDs)

The Well Tempered Clavier, Pt I and II: Sviatoslav Richter, piano
Ariola-Eurodisc 610 276-234 (4CDs)

Three concerti after Vivaldi BWV593, 594 and 596; fugue in B minor BWV579: Daniel Chorzempa, organ
Philips (DDD) 412 116-2

Three concertos for harpsichord and orch (recorded with a piano): Abdel Rahman El Bacha, piano; Greenoble Chamber Orch; K. Redel cond.
Forlane UCD-16 537

Three concertos for violin and orchestra: Jean-Jacques Kantarow, violin; Sigrid Cenariu, 2nd violin; Munchener Kammerorchester, Hans Stadlmair cond.
Denon C37-7096

Three flute concertos: Jean-Pierre Rampal, flute; ARS Rediviva Orch
CBS CD 39022

Three keyboard concertos: in D minor, BWV1052; A major, BWV1055; F minor, BWV1056: Andras Schiff, piano; English chamber Orch; George Malcolm cond
Denon C37-7236

Three sonatas and three partitas for violin solo, BWV1001-1006: Jean-Jacques Kantarow, violin
Denon C37-7405-7 (3CDs)

Toccata and fugue in D minor BWV565; prelude, largo and fugue in C BWV529 No. 2/BWV545; prelude and fugue in E flat BWV552: Daniel Chorzempa, organ
Philips (DDD) 410 038-2

Toccata and fugue, BWV565; Jesu bleibet meinen Freude, BWV47; Wachet auf, ruft uns die Stimme; et: Tatyana Nikolayeva, piano
Ariola-Eurodisc 880 000-231

Toccata and fugue; passacaglia; etc: Marie-Claire Alain, organ



Professional sound is his business, Onkyo is his pleasure.

Peter Crossley is a man with considerably more than your average knowledge of high fidelity sound.

He is an electro-acoustics engineer with leading Australian consulting engineers Lobely, Treidel Davies & Partners.

Peter's job is designing and supervising the installation of audio visual systems for concert and convention centres. The futuristic Jupiters Casino on Broadbeach Island, Queensland, is his latest project.

"The most important requirement in a hi-fi system is good transient response – that strong, crisp, immediate sound is the first thing I look for.

That's what I like about my Onkyo system. It handles transient sounds excellently, reproducing every note beautifully sharp and crisp, coping with the extremes of soft and loud very satisfactorily."

To achieve that reproduction of rich, beautiful sound we have developed our very own testing equipment. One is a computerised audio spectrum analyzer that

provides far more analysis information than conventional equipment is capable of producing. At the end of our automated and computerised production line is a central testing device that checks every product for purity of quality and excellence of performance.

Onkyo's wealth of innovative technology assures you of sound that is as close as possible to the original. At the heart of Peter Crossley's system is the **A-8057 Integrated Amplifier.**

It delivers 65 Watts RMS per channel of clean Onkyo power. The Onkyo developed Delta Power Supply expands the dynamic range by virtually eliminating power-generated modulation noise. Delicate sounds that other systems mask are clearly heard. Super Servo assures that nothing but the original audio signal is sent to the speakers.



Complementing his amp is the **T-4057 Computer Controlled Stereo Tuner** – reception, performance and convenience that is outstanding. It controls three FM reception modes according to the quality of the incoming signal, and also features a 20-station memory and an automatic scan tuning mode.



Peter's choice of a tape deck is the **3-Motor Microcomputer TA-2047** excellence in Onkyo precision. It features elapsed time modes, single song/full side repeat playback, Dolby B and CNR, AMCS in the forward and reverse directions.

To play his beloved classical collection, Peter selected the fully automatic



Direct-Drive CP-1057F Turntable.

Onkyo's top of the range turntable is virtually isolated from vibrations through a unique triple stage isolation system that shuts out both air and structure-borne vibrations at three different stages.

The CP-1057F features a 2-speed search, repeat play functions, and brushless



quartz PLL direct-drive motor. Sleek styling and advanced technology that delivers superior all-round performance clearly defines Onkyo as a company in the forefront of audio component manufacture.

Make it your business to enjoy the pleasure of Onkyo sound.

ONKYO®

Artistry in sound.

Available at selected outlets.

For more information, telephone Peter McFarland (02) 449 5666 or Ross Mather (03) 61 3541 or write to Regent Audio N.S.W., P.O. Box 42, Pymble, N.S.W. 2073.

COMPACT DISC CATALOGUE

Erato ECD-88 004

Toccata; Organ works; Oeuvres pour orgue; Orgelwerke: Toccata and Fugue in D minor, BWV565, etc: Peter Hurford cond.
Argo 411 824-2

Trio Sonatas, BWV525-528
Capriccio 10.037

Trio sonatas, BWV529-30, 583-84, 769
Capriccio 10.040

Trios in D minor, BWV1036 and G minor, BWV1029; Instrumentalsatz, BWV1040; also, CPE Bach — Trios in D major and A minor: Aurele Nicolet, Flute; Heinz Holliger, oboe; Christiane Jaccottet, harpsichord
Denon C37-7093

Two and Three part Inventions; Inventions a deux et trois voix; Zwei-und dreistimmeige Inventionen: Andras Schiff, piano
Decca DH 411 974-2

Viola de gamba sonatas: Yo-Yo Ma
CBS CD 37794

Viola sonatas
Capriccio 10.043

Violin Concerto: Jaap Schroder, violin; Hiron Academy of Ancient Music, Christopher Hogwood cond.
L'Oiseau Lyre 400 080-2

Violin concertos No 1 and 2; concertos for 1, 2, 3 and 4 harpsichords (special box set): Simon Standage; Elizabeth Wilcock; Gilbert Mortensen; The English Concert, Trevor Pinnock cond.
Archiv 413 634-2

Violin concertos No 1 and No 2; double concerto: Simon Standage and Elizabeth Wilcock, violins; The English Concert, Trevor Pinnock cond.
Archiv 410 646-2

Violin concertos, BWV 1041-1043: Gidon Kremer, violin and director, Academy of St Martins-in-the-Fields
Philips (DDD) 411 108-2

Violin concertos, BWV1041-43: Alice Harnoncourt, violin; Concentus Musicus Vienna, Nikolaus Harnoncourt cond.
Teldec 8.41 227

Violin concertos, BWV1041-43: S. Kuijken, violin; La Petite Bande
Harmonia Mundi 567-1 99 743-3

Violin concertos: Itzhak Perlman, violin
EMI 747073

Works for harpsichord: fantasia and fugue in D minor, BWV903; concerto in F major, BWV971; fantasia in C minor, BWV906; prelude and fugue in A minor, BWV894: Huguette Dreyfus, harpsichord
Denon C37-7233

BACH, J.S and sons

Trio sonatas: Jean-Pierre Rampal, flute; Isaac Stern, violin; J. Ritter, harpsichord; L. Parnas, cello
CBS CD 37813

BACH, W.F.

Six duets for two flutes: Aurele and Christiane Nicolet, flutes
Denon C37-7287

BARBER

Cello concerto; plus — cello concerto (Shostakovich): Rafael Wallfisch, cello; English Chamber Orch; Geoffrey Simon cond.
Chandos CHAN-8322

BARTOK

Piano concerto No 3; plus — piano concerto No 3 (Prokofiev): Vladimir Ashkenazy; London Philharmonic Orchestra, Georg Solti cond.
Decca 411 804-2

Bluebeard's Castle; Nesterenko; Obratzsova; Ferencsik; Hungaraton
HCD 12254-2

Concerto for orchestra; Dance Suite: Chicago Symphony Orchestra, Georg Solti cond.
Decca 400 052-2

Concerto for orchestra; Deux Images Op 10; Concertgebouw Orch; Amsterdam, Antal Dorati cond.
Philips (DDD) 411 132-2

Concerto for orchestra; music for strings, percussion and celeste; Berlin Philharmonic Orch; Herbert von Karajan cond.
DG 415 322-2

Miraculous Mandarin; etc; Philadelphia Orch, Eugene Ormandy cond.
EMI 747117

Music for strings, percussion and celesta; Romanian folk dances; Tokyo Metropolitan Symphony Orch; Moshe Atzmon cond.
Denon C37-7122

Schiff Plays Bartok: Dance suite Romanian dances; three rondos on folk tunes; Hungarian peasant songs; Andras Schiff, piano
Denon C37-7092

String quartets — complete. Takacs Quartet
Hungaraton HCD 12502-04-2 (3CDs)

The Miraculous Mandarin; Music for Strings, Percussion and Celeste: Detroit Symphony Orchestra, Antal Dorati cond.
Decca 411 894-2

Violin Concerto No 1; plus-Berg: Violin Concerto No 1; Kyung Wha Chung; Chicago Symphony Orch; Georg Solti cond.
Decca 411 804-2

BAX

Four tone poems — November Woods, etc; Ulster Orch; Bryden Thomson cond
Chandos CHAN-8307

Symphony No 4; Tintagel; Ulster Orch; Bryden Thomson cond.
Chandos CHAN-8312

Tone Poems Vol 2: Into The Twilight; In the Faery Hills; etc; Ulster Orch; Bryden Thomson cond.
Chandos CHAN-8367

BAYER

Die Puppenfee — complete ballet; State Philharmonia Rheinland-Pfalz, Eichhorn cond.

Ariola-Eurodisc 610 267-231

BEETHOVEN

Eroica variations Op 35; bagatelle in A minor, Op 59; Fur Elise; 6 bagatelles Op 126;6 ecossaises Op 83; Alfred Brendel, piano
Philips (DDD) 412 227-2

Les Nuits de; plus — Songs of a Wayfarer, Mahler; Agnes Baltsa, Gewandhausorchester Leipzig, Kurt Masur cond.
Philips (DDD) 412 744-2

An die ferne Geliebte: 7 lieder; plus — six lieder (Brahms); Dieter Fischer-Dieskau, baritone; Jorg Demus, piano
DG (ADD) 415 189-2

Cello sonatas No 3 and 5; Yo-Yo Ma, cello
CBS CD 39024

Early quartets Alban Berg Quartet
EMI 747127

Favourite Beethoven sonatas; Vladimir Horowitz, piano
CBS CD 34509

Fidelio — complete opera; Altmeyer; Jerusalem; Adam; Radio Chorus and Gewandhaus Orch Leipzig, Kurt Masur cond.
Ariola-Eurodisc 610 093-233 (3CDs)

Fidelio; Behrens; Hofmann; Sotin; Chicago Symphony Orch and Chorus; Georg Solti
Decca 410 227-2 (2CDs)

Late Quartets; Alban Berg Quartet
EMI 747135

Lieder; Hermann Prey; Wolfgang Sawallisch, piano
Ariola-Eurodisc 610 124-231

Mass in C major; Kuhse; Burmeister; Schreier; Adam; Leipzig Radio Chorus; Gewandhaus Orch; Herbert Kegel cond.
Teldec 8.41 286

Middle Quartets; Alban Berg Quartet
EMI 747131

Missa Solemnis; Moser; Schwarz; Rene Kollo; Moll; Rundfunkchor Hilversum; Concertgebouw Amsterdam, Leonard Bernstein cond.
DG (ADD) 413 780-2 (2CDs)

Overtures: Fidelio; Prometheus; etc; London Philharmonic Orch; Klaus Tennstedt cond.
EMI 747086

Overtures; Philharmonia Orch; Otto Klemperer cond.
EMI 747190

Piano concerto No 1 in C, Op 15; rondos; Russell Sherman, piano; Czech Philharmonic Václav Neumann cond.
Pro Arte PA-CDD 175

Piano concerto No 1; Maurizio Pollini; Vienna Philharmonic Orch; Eugen Jochum cond.
DG (DDD) 410 511-2

Piano concerto No 2 and No 4; Maurizio Pollini; Vienna Philharmonic Orch, Eugen Jochum cond. (No 2) Karl Boehm cond. (No 4)
DG (DDD) 413 445-2

Piano concerto No 2 and No 4; Rudolf Serkin, piano; Boston Symphony Orch; Seiji Ozawa cond.
Telarc 80064

Piano concerto No 2 in B flat major; also — piano concerto in D major (Haydn); Martha Argerich, piano; London Sinfonietta, M. Argerich cond.
Denon C37-7322

Piano concerto No 3; choral fantasy; Rudolf Serkin, piano; Boston Symphony Orch; Seiji Ozawa cond.
Telarc 80063

Piano concerto No 3; piano sonata No 31; Maurizio Pollini; Vienna Philharmonic Orch; Karl Boehm cond.
DG (ADD) 413 446-2

Piano concerto No 5 'Emperor'; Maurizio Pollini; Vienna Philharmonic Orch; Karl Boehm cond.
DG (ADD) 413 447-2

Piano concerto No 5 'Emperor'; Vladimir Ashkenazy; Wiener Philharmoniker; Zubin Mehta, cond.
Decca 411 903-2

Piano concerto No 5 'Emperor'; Rudolf Serkin, piano; Boston Symphony Orch; Seiji Ozawa cond.
Telarc 80065

Piano concerto No 5 'Emperor'; piano sonata No 31 Op 110; Alfred Brendel; Chicago Symphony Orch; James Levine cond.
Philips (DDD) 412 789-2

Piano concerto No 1: 6 bagatelles; Vladimir Ashkenazy; Wiener Philharmoniker, Zubin Mehta, cond.
Decca (DH) 411 901-2

Piano concerto No 2 & 4; Vladimir Ashkenazy; Wiener Philharmoniker, Zubin Mehta, cond.
Decca (DH) 411 902-2

Piano concertos — complete; Rudolf Serkin, piano; Boston Symphony Orch; Seiji Ozawa cond.
Telarc 80061-3 (3CDs)

Piano concertos No 1 and 2; Alfred Brendel; Chicago Symphony Orch; James Levine, cond.
Philips (DDD) 412 789-2

Piano concertos No 3 and 4; Alfred Brendel; Chicago Symphony Orch; James Levine, cond.
Philips (DDD) 412 788-2

Piano sonata No 32, Op 111; plus — Symphonic Etudes; Toccata (Schumann); Ivo Pogorelich, piano
DG (DDD) 410 520-2

Piano sonata No 23 in F minor, Op 57 'Appassionata'; and No 32 in C, Op 111 'Last Sonata'; Carol Rosenberger, piano (Bosendorfer Imperial Grand)
Delos 3009

Piano sonata No 26 in E flat 'Les Adieux'; Rudolf Buchbinder, piano
Teldec 8.43 206

Piano sonata No 29 'Hammerclavier'; Emil Gilels, piano
DG (DDD) 410 527-2

Piano sonata No 7 in D; Murray Perahia, piano
CBS CD 39344

Piano sonata No 32 in C minor Op 111; plus — Winter Meditation (Gulda); Friedrich Gulda, piano
Philips (DDD) 412 114-2

Piano sonatas: 'Moonlight'; 'Appassionata'; 'Pathetique'; Vladimir Ashkenazy cond.
Decca 410 260-2

Piano sonatas — No 8, Op 13 'Pathetique'; No 14 Op 7/2 'Moonlight'; No 23, Op 57 'Appassionata'; Rudolf Buchbinder, piano
Teldec 8.42 913

Piano sonatas — the three last — No 30 in E, Op 109; No 31 in A flat, Op 110; No 32 in C minor, Op 111; Rudolf Buchbinder, piano
Teldec 8.43 027

Piano sonatas in C sharp minor and E minor; Yukie Nagai, piano
BIS BISCD-281

Piano sonatas No 1-15; Daniel Barenboim, piano
DG (DDD) 413 759-2 (6 CDs)

Piano sonatas No 16-32; Daniel Barenboim, piano
DG (DDD) 413 766-2

Piano sonatas No 21, Op 53 'Waldstein'; No 11, Op 22; and No 27, Op 90. Rudolf Buchbinder, piano
Teldec 8.43 111

Piano sonatas No 48, Op 7; and No 13, Op 27 No 1; plus — piano sonatas in B flat and F major (Mozart); Abdel Rahman El Bacha, piano
Forlane UCD-16 532

Piano sonatas No 8 'Pathetique'; No 13; No 14 'Moonlight'; Emil Gilels, piano
DG (DDD) 400 036-2

Piano sonatas, No 29 in B flat, Op 106 'Hammerclavier'; and No 28 in A, Op 101; Rudolf Buchbinder, piano
Teldec 8.42 761

Piano sonatas: 'Pathetique', 'Moonlight', 'Appassionata'; Alfred Brendel
Philips (ADD) 411 470-2

Piano Trio in B flat major, Op 97 'Archduke'; Suk Trio
Denon C37-7078

Piano trio Op 97 'Archduke'; piano trio Op 70 No 1; Beaux Arts Trio
Philips (DDD) 412 891-2

Piano trios No 5 in D major, Op 70 No 1 'Geister'; No 6 in E flat major, Op 70 No 2; Suk Trio
Denon C37-7284

Quintet in E flat major for oboe, clarinet, horn, bassoon and piano; also — quintet in E flat major (Mozart); Winds of the Berlin Philharmonic; Alfons Kontarsky, piano

Denon C37-7090

Sonata No 23 'Appassionata'; Andre-Michel Schub, piano
MMG MCD 10009

Sonata Op 78 'A Therese'; sonata Op 106 'Hammerklavier'; Alfred Brendel
Philips (ADD) 412 723-2

Sonatas for cello and piano, No 1 and No 2; Yo-Yo Ma, cello; Emanuel Ax, piano
CBS CD 37251

Sonatas for piano and violin, Op 12 No 1-3; Gidon Kremer, violin; Martha Argerich, piano
DG (DDD) 415 138-2

Sonatas No 1 and 2 for cello and piano; Yo-Yo Ma, cello
CBS CD37251

Sonatas No 23 in F minor 'Appassionata'; No 21 in C 'Waldstein'; Russell Sherman, piano
Pro Arte PA-CDD 108

Sonatas No 32 in C minor Op 111 and No 7 in D, Op 10; Claudio Arrau, piano
Philips (DDD) 412 268-2

String quartet No 1 in F major, Op 18, No 1; string quartet No 5 in A major, Op 18, No 5; Smetana Quartet
Denon C37-7036

String quartet No 12 in E flat major, Op 127; Vermeer Quartet
Teldec 8.43 190

String quartet No 12, Op 130; and No 17, Op 133; Vermeer Quartet
Teldec 8.42 982

String quartet No 13 in B flat major, Op 130; Grosse Fuga in B flat major, Op 133; Smetana Quartet
Denon C37-7088

String quartet No 14 in C minor, Op 131; Smetana Quartet
Denon C37-7312

String quartet No 15 in A minor, Op 132; Smetana Quartet
Denon C37-7086

String quartet No 7 in F major, Op 59 No 1 'Rasoumovsky'; Smetana Quartet
Denon C37-7025

String quartet No 8 in E minor, Op 59, No 2, 'Rasoumovsky'; No 2; Smetana Quartet
Denon C37-7033

String quartet No 13, Op 133; Great Fugue Op 133; Fitzwilliam String Quartet
Decca 411 943-2

String quartet No 15, Op 132; Fitzwilliam String Quartet
Decca 411 643-2

String quartets No 2 in G major, Op 18 No 2; and No 4 in C minor, Op 18, No 4; Smetana Quartet
Denon C37-7041

String quartets No 3 in D major, Op 18 No 3;

COMPACT DISC CATALOGUE

- and No 6 in B flat, Op 18 No 6: Smetana Quartet
Denon C37-7049
- String quartets No 9 in C major, Op 59 No 3 'Rasoumovsky No 3'; No 10 in E flat major, Op 74 'Harp': Smetana Quartet
Denon C37-7125
- String quartets No 11 in F minor, Op 95 'Seroso'; No 12 in E flat major Op 127: Smetana Quartet
Denon C37-7063
- Symphonies No 1 and No 7: Philharmonia Orch; Otto Klemperer cond.
EMI 747184
- Symphonies No 2 and No 4: Philharmonia Orch; Otto Klemperer cond.
EMI 747185
- Symphonies No 5 and No 8: Philharmonia Orch; Otto Klemperer cond.
EMI 747187
- Symphonies No 8 in F major, Op 93; and No 1 in C major, Op 21: Staatskapelle Berlin, Otmar Suitner cond.
Denon C37-7128
- Symphony No 6 in F, Op 68 'Pastorale'; overture Leonore II: Berlin Philharmonic Orch; Herbert von Karajan cond.
DG (ADD) 413 779-2
- Symphony No 1 in C major, Op 21; Symphony No 2 in D major, Op 36: Dresden Philharmonic Orch; Herbert Kegel cond.
Capriccio 10.001
- Symphony No 1; piano concerto No 1: Verney, Hanover Band
Nimbus NIM 5003
- Symphony No 2 in D major, Op 36; Egmont overture; Coriolan overture; Leonore overture: Staatskapelle Berlin, Otmar Suitner cond.
Denon C37-7367
- Symphony No 3 'Eroica': Philharmonia Orch; Otto Klemperer cond.
EMI 747186
- Symphony No 3 'Eroica': Cleveland Orch; Christolph von Dohnanyi cond.
Telarc 80090
- Symphony No 3 in E flat major, Op 55 'Eroica'; Dresden Phil Orch; Herbert Kegel cond.
Capriccio 10.002
- Symphony No 3 in E flat major, Op 55 'Eroica': Staatskapelle Berlin, Otmar Suitner cond.
Denon C37-7011
- Symphony No 3 'Eroica': Academy of St Martin-in-the-Fields, Neville Marriner cond.
Philips (DDD) 410 044-2
- Symphony No 3 'Eroica'; Egmont overture: Vienna Philharmonic Orch; Leonard Bernstein cond.
DG ADD 413 778-2
- Symphony No 4 and No 9 'Choral': Dresden Phil Orch; Herbert Kegel cond.
Capriccio 10.006/7 (2 CDs)
- Symphony No 4 in B flat major, Op 60: Staatskapelle Berlin, Otmar Suitner cond.
Denon C37-7077
- Symphony No 4 in B flat, Op 60; and No 7 in A, Op 92: Berlin Philharmonic Orch; Herbert von Karajan cond.
DG (DDD) 415 121-2
- Symphony No 4: Bavarian State Orch; Kleiber cond.
Orfeo ORF C100
- Symphony No 5 and No 6 in F, Op 68 'Pastorale': Berlin Philharmonic Orch; Herbert von Karajan cond.
DG (DDD) 413 932-2
- Symphony No 5 and No 8: NHK Symphony Orch; Sawallisch cond.
Erato ECD-88 043
- Symphony No 5 in C minor, Op 67: Vienna Phil Orch; Wilhelm Furtwangler cond.
EMI 747120
- Symphony No 5 in C minor, Op 67: Los Angeles Philharmonic Orch; Carlo Maria Giulini cond.
DG (DDD) 410 028-2
- Symphony No 5 in C minor, Op 67: Symphony No 8, Op 93; Dresden Phil Orch; Herbert Kegel cond.
Capriccio 10.003
- Symphony No 5 in C minor, Op 67: Staatskapelle Berlin, Otmar Suitner cond.
Denon C37-7001
- Symphony No 5, Op 67: Vienna Philharmonic Orch; Lorin Maazel cond.
CBS CD 36711
- Symphony No 5; also — Symphony No 8 (Schubert): Vienna Philharmonic, Lorin Maazel cond.
CBS CD36711
- Symphony No 5; Egmont overture: Boston Symphony Orch; Seija Ozawa cond.
Telarc 80060
- Symphony No 5; overtures — Egmont, Creatures of Prometheus: Hanover Band
Nimbus NIM 5007
- Symphony No 5; Overture Leonore No 3: Philharmonia orch; Vladimir Ashkenazy, cond.
Decca 400 060-2
- Symphony No 6, Overtures Coriolan, Egmont: Philharmonia Orch; Vladimir Ashkenazy, cond.
Decca 410 941-2
- Symphony No 6 'Pastoral': Philharmonia orch; Vladimir Ashkenazy cond.
Decca 410 003-2
- Symphony No 6 'Pastoral': Philharmonia Orch; Otto Klemperer cond.
EMI 747188
- Symphony No 6 in F major, Op 68 'Pastoral': Vienna Phil Orch; Wilhelm Furtwangler cond.
EMI 747121
- Symphony No 6 'Pastoral': Staatskapelle Berlin, Otmar Suitner cond.
Denon C37-7040
- Symphony No 6 'Pastoral': Y Chamber Symphony of New York, Gerard Schwarz cond.
Delos 3017
- Symphony No 6 'Pastoral': Dresden Phil Orch; Herbert Kegel cond.
Capriccio 10.004
- Symphony No 7 (version for winds): Octophorus Ensemble
Accent ACC 48434
- Symphony No 7 in A major, OP 92: Staatskapelle Berlin, Otmar Suitner cond.
Denon C37-7032
- Symphony No 7 in A major, Op 92; Coriolan overture: Dresden Phil Orch; Herbert Kegel cond.
Capriccio 10.005
- Symphony No 7 in A, Op 92: Philharmonia Symphony Orch; Carlos Paita cond.
Lodia LOCD 786
- Symphony No 7: Collegium Aureum, F.J. Maier cond.
Harmonia Mundi 567-1 99 872-2
- Symphony No 7; overtures — Egmont and Leonore: Berlin Philharmonic Orch; Joseph Keilberth cond. (Historical series)
Teldec 8.43 192
- Symphony No 8 in F; plus — Symphony No 8 'Unfinished' (Schubert): Cleveland Orch; Christolph von Dohnanyi cond.
Telarc 80091
- Symphony No 9 'Choral': Elisabeth Schwarzkopf; Bayreuth Festival Orch and Chorus, Wilhelm Furtwangler cond.
EMI 747081
- Symphony No 9 'Choral': Philharmonia Orch; Otto Klemperer cond.
EMI 747189
- Symphony No 9 in D minor, 'Choral': Lorin Maazel, cond.
CBS CD 76999
- Symphony No 9 in D minor, Op 125 'Choral': Rundfunkchor Berlin, Dietrich Knothe chorusmaster; Staatskapelle Berlin, Otmar Suitner cond.
Denon C37-7021
- Symphony No 9 in D minor, Op 125 'Choral': Perry; Baltas; Cole; van Dam; Vienna Singverein; Berlin Philharmonic Orch; Herbert von Karajan cond.
DG (DDD) 410 987-2
- Symphony No 9 'Choral': Janet Price; Brigit Finnila; Horst Laubenthal; Marius Rintzler; chorus of the Concertgebouw Orch; Amsterdam, Bernard Haitink cond.
Philips (DDD) 410 036-2
- Symphonies No 1-9 — complete: Staatskapelle Berlin, Otmar Suitner cond.
Denon C37-7251

Symphonies No 1-9; Gewandhausorchester Leipzig, Kurt Mazur cond.
Philips (ADD) 416 274-2 (6CDs)

The complete piano sonatas: Alfred Brendel piano
Philips (ADD) 412 575-2 (11CDs)

The five piano concertos; Alfred Brendel; Chicago Symphony Orch; James Levine cond.
Philips (DDD) 411 189-2 (3CDs)

The sonatas for piano and cello: Sviatoslav Richter, piano; Mstislav Rostropovich cello
Philips (ADD) 412 256-2 (2CDs)

The sonatas for violin and piano: David Oistrakh; Lev Oborin
Philips (AAD) 412 570-2

Trio IV in B major, Op 1 'Gassenhauer'; Trio III in C minor, Op 1 No 3: Haydn Trio Vienna
Teldec 8.43 157

Trio No 7 in B flat, 'Archduke': Itzhak Perlman, violin; Vladimir Ashkenazy, piano; Lynn Harrell, cello
EMI 747010

Trios for piano, violin and cello: No 3 in C minor, Op 1 No 3; and No 4 in B flat major, Op 11 'Gassenhauer': Suk Trio
Denon C37-7421

Triple concerto for violin, cello and piano in C: Mark Zelser, piano; Anne-Sophie Mutter, violin; Yo-Yo Ma, cello; Berlin Philharmonic Orch; Herbert von Karajan cond.
DG (ADD) 415 276-2

Violin concerto: Itzhak Perlman, violin
EMI 747002

Violin concerto (cadenzas: Alfred Schnittke): Gidon Kramer; Academy of St Martin-in-the-Fields, Neville Marriner cond.
Philips (DDD) 410 549-2

Violin concerto in D, Op 61; Consecration of the House overture: Joseph Silverstein, violin; Utah Symphony Orch; Joseph Silverstein cond.
Pro Arte PA-CDD 228

Violin concerto in D; plus — concerto in D (Brahms): Jascha Heifetz, violin; Chicago Symphony Orch; Reiner cond; Boston Symphony Orch; Munch cond.
RCA RCD15402

Violin concerto: Anne-Sophie Mutter; Berlin Philharmonic Orch; Herbert von Karajan cond.
DG (ADD) 413 818-2

Violin concerto: Kyung Wha-chung; Weiner Philharmoniker; Kirill Kondrashin, cond.
Decca 400 048-2

Violin concerto; plus — violin concerto (Mendelssohn): Yehudi Menuhin, violin; Wilhelm Furtwangler
EMI 747119

Violin sonata No 5 'Spring'; violin sonata No 9 'Kreutzer': David Oistrakh; Lev Oborin
Philips (ADD) 412 255-2

Violin sonatas No 7 and No 10; Vladimir Ashkenazy; Itzhak Perlman
Decca 411 948-2

Violin sonatas: No 9, 'Kreutzer'; No 5, 'Spring': Vladimir Ashkenazy; Itzhak Perlman
Decca 410 554-2

Wellington's Victory, Op 91; Battle of the Huns (Liszt): Cincinnati Symphony Orch; Erich Kunzel cond.
Telarc 80079

BEETHOVEN/LISZT

Symphony No 7; plus — Chaconne (Bach/Buson); Ronald Smith, piano
Nimbus NIM 5013

BERG, Alban

Violin concerto — To the Memory of an Angel; three orchestral pieces Op. 6: Gidon Kremer, violin; Bavarian Radio Symphony Orch; Colin Davis cond.
Phillips (DDD) 412 523-2

Violin concerto; plus — violin concerto in D major (Stravinsky); Itzhak Perlman, violin; Boston Symphony Orch; Seiji Ozawa cond.
DG (ADD) 413 725-2

Violin concerto; plus — violin concerto No 1 (Bartok); Kyung Wha-chung, violin; Chicago Symphony Orchestra and Chorus; Georg Solti
Decca 411 804-2

BERIO

Sinfonia; Impressions; New Single Singers; Orch Nationale de France; Pierre Boulez cond.
Erato ECD-88 151

BERLIOZ

Harold in Italy; Mala, viola; Czech Phil Orch; Jilek cond.
Supraphon SUP CD7244

Harold in Italy; Roman Carnival; Wolfram Christ, viola; Berlin Philharmonic Orch; Lorin Maazel cond.
DG (DDD) 415 109-2

La Damnation de Faust; extracts; Reigel; von Stade; van Dam; Chicago Symphony Orchestra and Chorus; Georg Solti cond.
Decca 410-18-2

Les Nuits d'Ete; La Mort du Cleopatre; Kiri Te Kanawa; Jessye Norman; Orch de Paris; Daniel Barenboim cond.
DG (DDD) 410 966-2

Les Nuits d'Ete; plus — Pelleas et Melisande (Faure); Elly Ameling.
Telarc 80084

Les Nuits d'Ete; plus — Sheherazade (Ravel); Jessye Norman; London Symphony Orch, Colin Davis cond.
Philips (ADD) 412 493-2

Les Nuits d'Ete; plus — Sheherazade (Ravel); Hildegard Behrens; Wiener Symphoniker; Francis Travers cond.
Decca 411 895-2

Les Troyens a Carthage ballet music; plus — Invitation to the Dance (Weber); National Philharmonic Orchestra; Richard Bonygne cond.

Decca 411 898-2

Overtures; Rob Roy, King Lear, Le Corsaire, Beatrice and Benedict, Le Carnaval Romain; etc; Scottish National Orch; Alexander Gibson cond.
Chandos CHAN-8316

Requiem: Ronald Dowd; Wandsworth School Boys' Choir; London Symphony Chorus and Orch; Colin Davis cond.
Philips (ADD) 416 283-2 (2CDs)

Requiem; plus — Te Deum (Verdi); etc.
Telarc 80109-2 (2 CDs)

Symphonie Fantastique; Concertgebouw Orch Amsterdam; Colin Davis cond.
Philips (ADD) 411 425-2

Symphonie Fantastique; Cleveland Orch; Lorin Maazel cond.
CBS CD 76652

Symphonie Fantastique; New York Philharmonic Orchestra; Zubin Mehta Cond.
Decca 400 046-2

Symphonie Fantastique; Orchestre Symphonique de Montreal; Charles Dutoit cond.
Decca 414 203-2

Symphonie Fantastique; Orch Nationale de France; James Conlon cond.
Erato ECD-88 028

Symphonie Fantastique; Berlin Philharmonic Orch; Daniel Barenboim cond.
CBS CD 39859

Symphonie Fantastique; Philadelphia Orch; Riccardo Muti cond.
EMI 747278

Symphonie Fantastique; Tokyo Metropolitan Symphony Orch, Jean Fournet cond.
Denon C37-7087

Symphonie Fantastique; Chicago Symphony Orch; Claudio Abbado cond.
DG (DDD) 410 895-2

Symphonie Fantastique; Chicago Symphony Orch; Lorin Maazel cond.
Telarc 80076

Te Deum; Francisco Araiza; London Symphony Chorus; London Philharmonic Choir; European Community Youth Orch; Claudio Abbado cond.
DG (DDD) 410 696-2

BERNSTEIN, Leonard

Complete works for solo piano; El Salon Mexico (Copland); James Tocco, piano.
Pro Arte PA-CDD 109

West Side Story — complete; plus — On The Waterfront (symphonic suite); Kiri Te Kanawa; Jose Carreras; Marilyn Horne; chorus and orch; Leonard Bernstein cond.
DG (DDD) 415 253-2 (2 CDs)

West Side Story — symphonic dances; plus — Rhapsody In Blue (Gershwin); Los Angeles Philharmonic Orch; Leonard Bernstein cond.
DG (DDD) 410 025-2

COMPACT DISC CATALOGUE

BERTRAND

Amours de Ronsard; Ensemble Janequin.
Harmonia Mundi HM 90 1147

BIZET

Carmen, suites Nos 1 and 2; L'Arlesienne suites
No 1 and 2: London Symphony Orch; Neville
Marriner cond.
Philips (ADD) 412 464-2

Carmen — complete opera; Julia Migenes;
Plácido Domingo; Ruggero Raimondi; Chorus
of Radio France; Orch Nationale de France;
Lorin Maazel cond.
Erato ECD-88 037 (3 CDs)

Carmen — highlights; Julia Migenes; Plácido
Domingo; Ruggero Raimondi; Chorus of Radio
France; Orch Nationale de France; Lorin
Maazel cond.
Erato ECD-88 041

Carmen — highlights; Agnes Baltsa; Jose
Carreras; Jose van Dam; Katia Ricciarelli;
chorus of the Paris Opera; Berlin Philharmonic
Orch; Herbert von Karajan cond.
DG (DDD) 413 322-2

Carmen and L'Arlesienne suites; Orch
Nationale de Lille; Jean-Claude Casadesu
cond.
Forlane UCD-16 533

Carmen suite; plus — Peer Gynt (Grieg); St
Louis Symphony Orch. Telarc 80048

Carmen suite; L'Arlesienne suites 1 and 2: Orch
Nationale de France; Seiji Ozawa cond.
EMI 747064

Carmen; Tryonanos; Domingo; Te Kanawa;
Royal Opera House Chorus and Orchestra;
Georg Solti cond.
Decca 414 489-2 (3 CDs)

Complete piano works; Setrak, piano;
Chant du Monde LDC 278 776/7 (2 CDs)

L'Arlesienne — suites No 1 and 2; Carmen —
suite No. 1; Daniel Deffayet, saxophone; Berlin
Philharmonic Orch; Herbert von Karajan cond.
DG (DDD) 415 106-2

BIZET

Carmen Suite; Moscow Virtuosi; Percussion
Ensemble of the Bolshoi Theatre; V. Spivakov
cond.
Ariola-Eurodisc 610 315-231

BOCCHERINI

Minuet; plus — Albinoni, Bach, Pachelbel, etc;
Stuttgarter Kammerorchester.
Decca 411 973-2

String quintets 'Night Music of Madrid';
Boccherini Quintet.
Ensayo 3403

BOEHM, George

Harpsichord suites; Robert Woolley;
harpsichord.
Meridian ECD-84 087

BOITO

Mefistofele; Ghiaurov; Pavarotti; Freni;
Caballe; National Philharmonic Orchestra;
Oliverio de Fabritiis cond.
Decca 410 175-2 (3 CDs)

Nerone — complete; Eve Queler.
Hungaraton HCD 12487-89-2 (3 CDS)

BORODIN

Polovotsian Dances; Orch de la Suisse
Romande; Ernest Ansermet cond.
Decca 414 124-2

Symphonies No 1 and 3; Academy of USSR
Symphony Orch; Svetlanov cond.
Chant de Monde LDC 278 781

BOULEZ

'Pli selon pli'; BBC Symphony Orch; Pierre
Boulez cond.
Erato ECD-88 074

BOYCE

Symphonies No 1-8 — complete;
Bournemouth Sinfonietta; Ronald Thomas
cond.
CRD CRD 3413

BRAHMS

Haydn variations; Hungarian dances Nos
1-10; Concertgebouw Orch Amsterdam;
Bernard Haitink cond.
Phillips (DDD) 416 147-2

A German Requiem; Atlanta Symphony
Orch; Robert Shaw cond. (71min).
Telarc 80092

A German Requiem; Song of Destiny;
Gundala Janowitz; Tom Krause; Chorus of
the Vienna State Opera; Vienna
Philharmonic Orch; Bernard Haitink cond.
Philips (DDD) 411 436-2

A German Requiem; Barbara Hendricks;
Jose van Dam; Vienna Singverein; Vienna
Philharmonic Orch; Herbert von Karajan
cond.
DG (DDD) 410 521-2 (2 CDs)

Alto Rhapsody; Nania; Alfreda Hodgson;
Bavarian Symphony Orch; Bernard Haitink
cond.
Orfeo ORF C025

Ballades and rhapsodies; Glenn Gould,
piano.
CBS CD 37800

Cello sonatas; Lyn Harrell; Vladimir
Askenazy.
Decca 414 558-2

Clarinet quintet, Op 115; Karl Leister;
clarinet; Vermeer Quartet.
Orfeo ORF C068

Concerto for violin, cello and orch in A
minor; Tragic overture; Janos Starker, cello;
Emmy Verhey, violin; Amsterdam
Philharmonic Orch.
Sefel SEFD 5023 CD

Concerto No 2 in D flat; Chicago Symphony
Orch.
RCA RCD 15406

Double concerto; Janos Starker, cello;
Emmy Verhey, violin; Amsterdam Phil
Orch; Arpad Joo cond.
Sefel SEF-CD 5023

Double concerto; Academic Festival
overture; Gidon Kremer, violin; Mischa

Maisky, cello; Vienna Philharmonic Orch;
Leonard Bernstein cond.
DG (DDD) 410 031-2

Double concerto; Tragic overture;
Ann-Sophie Mutter, violin; Antonio
Meneses, cello; Berlin Philharmonic Orch;
Herbert von Karajan cond.
DG (DDD) 410 603-2

Four ballades; plus — piano sonata D537
(Schubert); Arturo Benedetti Michelangeli,
piano.
DG (DDD) 400 043-2

Horn trio; trio pour violin, cor et piano; plus
— violin sonata (Franck); Vladimir
Ashkenazy; Itzhak Perlman; Barry Tuckwell.
Decca 414 128-2

Hungarian Dances No 1-21: Vienna
Philharmonic Orch; Claudio Abbado cond.
DG (DDD) 410 615-2

Liebeslieder walzer, Op 65; Neue
Liebeslieder walzer, Op 65; Los Angeles
Vocal Arts Ensemble.
WEA 79008-2

Lullaby and other German children's songs;
Lucia Popp.
Orfeo ORF C078

Piano concerto No 1: Krystian Zimerman,
piano; Vienna Philharmonic Orch; Leonard
Bernstein cond.
DG (DDD) 413 472-2

Piano concerto No 1: Vladimir Ashkenazy;
Concertgebouw Orch; Bernard Haitink cond.
Decca 410 009-2

Piano concerto No 2: Wilhelm Backhaus;
Wiener Philharmoniker; Karl Boehm cond.
Decca 414 142-2

Piano concerto No 2: Vladimir Ashkenazy;
Wiener Philharmoniker; Bernard Haitink
cond.
Decca 410 199-2

Piano quintet Op. 34: Andre Previn, piano;
Musikvereinsquartett.
Philips (DDD) 412 608-2

Scherzo in E minor Op. 4; ballades Op. 10;
klavierstucke Op 76; Stephen
Bishop-Kovacevich, piano.
Philips (DDD) 411 103-2

Serenade No 1 in D, Op 11: Los Angeles
Chamber Orch.
WEA 79056-2

Sonata No 3 in F minor, Op 5: Zoltan
Kocsis, piano.
Hungaraton HCD 12601-2

Sonatas for piano and cello, Op 38 and 39;
Mstislav Rostropovich, cello; Rudolf Serkin,
piano.
DG (DDD) 410 510-2

Songs and romances for chorus; Musica
Sacra.
RCA RCD14916

String quartets, Op 51 No 1 and No 2: Alban
Berg Quintet.

Teldec 8.43 115

Symphony No 1: London Phil Orch; Klaus Tennstedt cond.
EMI 747029

Symphony No 1: Berlin Philharmonic Orch, Joseph Keilberth cond. (Historical series).
Teldec 8.43 193

Symphony No 1: Los Angeles Philharmonic Orch; Carlo Maria Giulini cond.
DG (DDD) 410 023-2

Symphony No 1: North German Radio Orch; Gunther Wand cond.
Harmonia Mundi 567-199 974-2

Symphony No 1: Vienna Philharmonic Orch; Leonard Bernstein cond.
DG (DDD) 410 081-2

Symphony No 2: Los Angeles Philharmonic Orch; Carlo Maria Giulini cond.
DG (DDD) 400 066-2

Symphony No 2: Akademische Festouvertüre; Vienna Philharmonic Orch; Leonard Bernstein cond.
DG (DDD) 410 082-2

Symphony No 3: plus — Variations (Haydn); Vienna Philharmonic Orch; Leonard Bernstein cond.
DG (DDD) 410 083-2

Symphony No 4: North German Radio Orch;

Gunther Wand cond.
Harmonia Mundi 567-169 530-2

Symphony No 4: Vienna Philharmonic Orch; Carlos Keiber cond.
DG (DDD) 400 037-2

Symphony No 4: Tragic overture; Vienna Philharmonic Orch; Leonard Bernstein cond.
DG (DDD) 410 084-2

Symphony No 1: Chicago Symphony Orch; Georg Solti cond.
Decca 414 458-2

Symphony No 2: Chicago Symphony Orch; Georg Solti cond.
Decca 414 563 and Decca 414 487-2

Symphony No 4 Romantic: Vienna Philharmonic Orch, Bernard Haitink cond.
Philips (ADD) 412 735-2

Symphony No 8: plus — Siegfried Idyll (Wagner); Concertgebouw Orch Amsterdam; Bernard Haitink cond.
Philips (DDD) 412 465-2 (2CDs)
Symphony No 9: Concertgebouw Orch; Amsterdam, Bernard Haitink cond.
Philips (DDD) 410 039-2

The 21 Hungarian dances;
Gewandhausorchester Leipzig, Kurt Masur cond.
Philips (DDD) 411 426-2

The three piano trios; Borodin Trio.

Chandos CHAN-8334/5 (2CDS)

Vier ernste Gesänge, Op 121: 6 lieder; plus — An die ferne Geliebte; 7 lieder; Dietrich Fischer-Dieskau, baritone; Jorg Demus, piano.
DG (ADD) 415 189-2

Violin concerto: Boris Belkin; London Symphony Orch; Ivan Fischer cond.
Decca 411 677-2

Violin concerto: Gidon Kremer, violin; Vienna Phil Orch; L. Bernstein cond.
DG (DDD) 410 029-2

Violin concerto: Anne-Sophie Mutter, violin; Berlin Philharmonic Orch; Herbert von Karajan cond.
DG (DDD) 400 064-2
BRITTEN

Music for Strings; Bournemouth Sinfonietta; R Thomas cond.
Chandos CHAN-8376

Soirees Musicales; Matinees Musicales; plus — La Boutique Fantasque (Rossini-Repighi); National Philharmonic Orch; Richard Bonyng cond.
Decca 410 139-2

Symphony for cello and orch, Op 68; Death in Venice suite; Rafael Wallfisch, cello, English Chamber Orch; S. Bedford cond.
Chandos CHAN-8363

Shure's new FP31 Mixer. All the features without the weight.

The most innovative field production mixer of its kind, Shure's new FP31 packs in the same important features as much larger, heavier mixers. Plus a few of its own. You won't find another mixer this small with these features, dependability and ease of operation.

- ☐ Size just 6 1/3" x 5 1/3" x 1 7/8"
- ☐ Weight 2.2lbs ☐ Mic/line level on every channel
- ☐ Limiter with adjustable



SHURE

Audio Engineers P/L 342 Kent Street Sydney 2000 (02) 29 6731
Audio Engineers QLD (07) 44 8947
Marketec (WA) (09) 361 5954
Audio Engineers VIC contact Sydney (02) 29 6731

- threshold ☐ Internal (2x9V) or external 12V power
- ☐ Phantom and A-B power
- ☐ Slate tone and built-in mike for voice slating

- ☐ Two mic-line outputs for two camera shoots plus tape output for a cassette
- ☐ Two stereo headphone jacks.

The FP31 has everything to make your mix a perfect success.

COMPACT DISC CATALOGUE

War Requiem: Pears, Fischer-Dieskau;
Vishnevskaya; London Symphony Orchestra;
Benjamin Britten cond.
Decca 414 383-2 (2 CDs)

War Requiem: Birmingham Symphony Orch;
Simon Rattle cond.
EMI 747034

BRUCH

Violin concerto No 1: Anne-Sophie Mutter,
violin; Berlin Philharmonic Orch; Herbert
von Karajan cond.
DG (DDD) 400 031-2

BRUCKNER

Symphony No 3 in D minor: Radio
Symphony Orch Frankfurt; Eliahu Inbal
cond.
Teldec 8.42 922

Symphony No 3: Berlin Philharmonic Orch;
Herbert von Karajan cond.
DG (DDD) 413 362-2

Symphony No 4 'Romantic'; Radio
Symphony Orch Frankfurt, Eliahu Inbal
cond.
Teldec 8.42 921

Symphony No 4 'Romantic'; Berlin
Philharmonic Orch; Herbert von Karajan
cond.
DG (ADD) 415 277-2

Symphony No 4 'Romantic'; Staatskapelle
Dresden; Herbert Blomstedt cond.
Denon C37-7126

Symphony No 6 (original version): Berlin
Philharmonic Orch; Joseph Keilberth cond.
(Historical series).
Teldec 8.43 194

Symphony No 6: Bavarian Symphony Orch,
Wolfgang Sawallisch cond.
Orfeo ORF C024

Symphony No 7 in E major: Staatskapelle
Dresden; Herbert Blomstedt cond.
Denon C37-7286

Symphony No 8 in C minor: Radio
Symphony Orch Frankfurt; Eliahu Inbal
cond.
Teldec 8.43 218 (2 CDs)

Symphony No 8; plus — prelude and
Liebestod from Tristan and Isolde (Wagner);
New Phil Orch; Carlos Paita cond.
Lodia LOCD 783/4 (2 CDs)

Symphony No 4: Chicago Symphony Orch;
Georg Solti cond.
Decca 410 290-2

Symphony No 4: Weiner Philharmoniker;
Karl Boehm cond.
Decca 410 550-2

Symphony No 7: Radio Symp Orch Berlin,
Riccardo Chailly cond.
Decca 414 290-2

BULL

Works for harpsichord: Bob van Asperen,
harpsichord.
Teldec 8.42 874

BUXTEHUDE

Organ works, Vol 1.
Bellaphon 690.01.007

Organ works Vol 2.
Bellaphon 690.01.017

Organ works Vol 3; Colmar.
Bellaphon 690.01.023

Organ works Vol 4: Zurzach.
Bellaphon 690.01.024

Organ works Vol 5: Frauenfeld.
Bellaphon 690.01.028

Organ works Vol 6.
Bellaphon 690.01.029

Organ works Vol 7: Colmar
Bellaphon 690.01.033

BYRD

Cantiones Sacrae of 1589: Choir of New College
Oxford; Higginbottom cond.
CRD CRD 3408

CANTALOUBE

Chants d'Auvergne: Frederica von Stade, mezzo
soprano.
CBS CD37299

Chants d'Auvergne, Series 1-3: Kiri Te
Kanawa; English Chamber Orchestra; Jeffrey
Tate cond.
Decca 410 004-2

Chants d'Auvergne, Series 4-5; plus —
Bachianas Brasileras No 5 (Villa-Lobos); Kiri
Te Kanawa; English Chamber Orchestra;
Jeffrey Tate cond
Decca 411 730-2

CHABRIER

Joyeuse Marche; suite pastorale; etc: Orch Nat
de France; Armin Jordan cond.
Erato ECD-88 018

CHAN/KANG

Butterfly Lovers — pipe concerto: He
Shu-Ying; Shanghai Folk Orch.
Hong Kong HK 8.240277

Violin concerto 'Butterfly Lovers'; Takako
Nishizaki, violin; Nagoya Phl Orch; Lim cond.
Hong Kong HK 8.001003

Violin concerto 'Butterfly Lovers' (revised);
Takako Nishizaki, violin; Gumma Symphony
Orch; Shek cond.
Hong Kong HK 8.240233

CHARPENTIER

Acteon: Les Arts Florissants, Christie.
Harmonia Mundi HM 90.1095

Lecons de Tenebre: K. Widmer; M.
Verschaeye; Musica Polyphonica, L. Devos
cond.
Erato ECD-88 145

Lecons de Tenebres du Mercredi Sainct:
Concerto Vocale. Harmonia Mundi HM 90.1005

Medee — complete: Feldman; Bona; Boulin;
Les Arts Florissants; Christie cond.
Harmonia Mundi HM 90. 1139/41 (3 CDs)

Motets: Judith Nelson; Rene Jacobs; William

Christie.
Harmonia Mundi HM 90.1149

Pastorale: Les Arts Florissants, Christie.
Harmonia Mundi HM 90.1082

Te Deum; Laudate Dominum; Magnificat;
soloists; Gent Madrigal Choir; Musica
Polyphonica; L. Devos cond.
Erato ECD-88 027

CHAUSSON

Concerto for piano and orch, Op 21: Pasquier,
violin; Pennetier, piano.
Harmonia Mundi HM 90.1135

Concerto for violin, piano and strings: Itzhak
Perlman, violin; Jorge Bolet, piano; Juillard
String Quartet.
CBS CD 37814

Poeme de L'Amour et de la Mer; Chansson
Perpetuelle; etc: Jessye Norman; Michel
Dalberto; quartet and Monte Carlo Phil Orch;
Armin Jordan cond.
Erato EDC-88 012

Symphony in B flat, Op 20; Soir de Fete, Op
32; The Tempest (2 scenes); Brussels Radio
Orch; Jose Serebrier cond.
Chandos CHAN-8369

CHAVEZ

Symphonies: London Symphony Orch, Mata
cond.
MMG MCD 10002

CHERUBINI

Maria Callas sings Medea; Maria Callas; Milan
La Scala Orch and Chorus, Serafin cond.
Rodolphe RPC 32376

Medea, tragic opera: Maria Callas; Renato
Scotto; Mirto Picchi; Miriam Pirazzini;
Giuseppe Modesti; Orchestra and chorus of La
Scala, Milan; Tullio Serafin cond.
Denon C37-7336-7 (2 CDs)

CHINESE

Long March Symphony; Hong Kong Phil Orch;
Fukumura cond.
Hong Kong HK 8.240292

Yellow River concerto; Yitkin Seow, piano;
Gumma Symphony Orch, Lim Kek-Tjiang
cond.
Hong Kong HK 8.240055

CHOPIN

14 waltzes; Claudio Arrau, piano.
Philips (AAD) 400 025-2

19 waltzes; Zoltan Kocsis, piano.
Philips (DDD) 412 890-2

4 ballades; 4 scherzos; Cyprien Katsaris, piano.
Teldec 8.43 053

4 scherzi; Polonaise-Fantasie Op 61; Claudio
Arrau.
Philips (DDD) 412 610-2

Ballades No 1-4; impromptu No 4 Op 66; Bella
Davidovich.
Philips (DDD) 411 427-2

Ballades; Polonaise Heroique; Francois-Rene
Duchable, piano.
Erato ECD-88 023

THE FASCINATING WORLD OF ELECTRONICS CAN BE DELIVERED TO YOUR LETTERBOX EACH MONTH

Electronics Australia is the country's biggest selling electronics magazine. Each month we bring you interesting projects to build and all the latest on the fascinating world of electronics.

TO WELCOME IN THE YEAR OF THE COMET AND ALL THE NEWEST IN 1986 FROM THE ELECTRONICS INDUSTRY — ELECTRONICS AUSTRALIA IS MAKING A MOST EXCITING SUBSCRIPTION OFFER.

ALL SUBSCRIPTIONS RECEIVED DURING AND UP TO THE 28TH FEBRUARY 1986 WILL BE PLACED IN A BARREL AND THE LUCKY WINNER OF THE SHARP DX-110 COMPACT DISC PLAYER WILL BE DRAWN IN THE FIRST WEEK OF MARCH.

★
BUY A ONE-YEAR
SUBSCRIPTION AND
YOU COULD
WIN A FABULOUS
SHARP
DX-110 COMPACT
DISC PLAYER



Sharp's DX-110 Compact Disc Player.

Sharp's Compact Disc Player lets you enjoy the best in State-of-the-art

Home Entertainment. Sharp's DX-110 has all the best features in Compact Disc Technology.

As Australia's top-selling electronics magazine, Electronics Australia brings you reviews of the latest HI-FI and VIDEO equipment, exciting and easy-to-build DO-IT-YOURSELF PROJECTS plus regular columns written by experts. **SUBSCRIBE NOW** and you'll get 12 issues for just \$26... that's a

SAVING of \$5.20 on the normal price.

And if you subscribe for 2 years you'll **SAVE** over \$10.

That's the best electronics news around...

So SUBSCRIBE TODAY AND SAVE!

It's this easy

1. Simply complete the special subscription card

in this issue

2. Choose 1 or 2 years
3. Mail the POST FREE card to us.

If the card is missing, write to:

Electronics Australia
FREEPOST No. 4
The Federal Publishing
Company Pty Ltd
P.O. Box 227, Waterloo,
N.S.W. 2017.
(no postage stamp required)

This offer is not applicable where it contravenes state laws.

COMPACT DISC CATALOGUE

Concerto No 1; Philadelphia Orch; Eugene Ormandy cond.
RCA RCD 15317

Etudes Op 10 and 25; Francois-Rene Duchable, piano.
Erato ECD-88 001

Etudes, Op 10 and Op 25; Vladimir Ashkenazy.
Decca (DH) 414 127-2

Four scherzos; Sviatoslav Richter, piano;
Ariola-Eurodisc.
610 128-231

Nineteen waltzes; Cyprien Katsaris, piano.
Teldec 8.43 056

Nocturnes; Vlado Perlemuter, piano
Nimbus NIM 5012

Piano concerto No 2; London Philharmonic Orch; Andre Previn cond.
CBS CD 39153

Piano concerto No 2 Krakowiak; Bella Davidovich; London Symphony Orch; Neville Marriner cond.
Philips (DDD) 410 042-2

Piano concerto No 2; plus — piano concerto (Schumann); Andras Schiff; Concertgebouw Orchestra; Antal Dorati cond.
Decca 411 942-2

Piano music — Nocturne Op 55; Polonaise, Op 44; etc.
Capriccio 10.024

Piano music: Polonaise in A flat major, Op 35 'Heroic'; variations brillantes, Op 12; waltzes; etc; Malcolm Frager, piano.
Telarc 80040

Piano sonata No 2, Op 35; prelude, Op 45; scherzo Op 39; nocturne, Op 55 No. 2; Etudes, Op 10 No 8 and 10; Op 25 No 6; Ivo Pogorelich, piano.
DG (ADD) 415 123

Piano Works, Vol VIII; Vladimir Ashkenazy.
Decca 410 122-2

Polonaises No 1-7; Maurizio Pollini, piano.
DG (ADD) 413 795-2

Popular piano pieces; Vladimir Ashkenazy, piano.
Decca 410 180-2

Preludes; Dezso Ranki, piano.
Hungaraton HCD 12316-2

Sonata No 2, Op 35 'Funeral March'; andante spianato and Grande Polonaise Brillante, Op 22; etudes, Op 10 No 3 and 4; nocturne, Op 27 No. 2; John Bingham, piano.
Meridan ECD-84 070

Sonatas No 2 and No 3; Francois-Rene Duchable, piano.
Erato ECD-88 083

Ten mazurkas; prelude in C sharp minor; ballade No 1; scherzo No 2; Arturo Benedetti Michelangeli, piano.
DG (ADD) 413 499-2

The Most Popular Chopin — Polonaise in A

flat; Mazurka in A minor; prelude in E minor; 'Military' polonaise; Minute Waltz; etc; Meral Guneyman, piano.
WEA 90116-2

Thirteen nocturnes; Daniel Barenboim, piano.
DG (DDD) 415 117-2

Twelve etudes, Op 10; 12 etudes, Op 25; Maurizio Pollini, piano.
DG (ADD) 413 794-2

Twenty-four preludes; Maurizio Pollini, piano.
DG (ADD) 413 796-2

Valse brillante in A flat major, Op 34 No 1; valse brillante in A minor; valse brillante in F major, etc; also Liszt works, incl ballade No 2 in D minor; Liebestraume No 3 in A flat major; etc; Jean-Yves Thibaudet, piano.
Denon C37-7050

Waltzes — No 1-14; Maria Joao Pires, piano.
Erato ECD-88 067

Piano concerto No 1; plus — piano concerto No 1 (Liszt); Martha Argerich, piano; London Symphony Orch; Claudio Abbado cond.
DG (ADD) 415 061-2

Piano concerto No 2; Polonaise, Op 44; Ivo Pogorelich, piano; Chicago Symphony Orch; Claudio Abbado cond.
DG (DDD) 410 507-2

CHRISTMAS MUSIC

A Christmas Concert: O du Frohliche; Ubers Gebirg Maria Geht; Adeste Fideles; Stille Nacht, heilige Nacht; etc; Regensburger Domspatzen; Georg Ratzinger cond.
DG (ADD) 413 724-2

Baroque Christmas; Capella Savaria.
Hungaraton HCD 12561-2

Carols For Brass: Galliard Brass Ensemble.
ASV DCA 527

Christmas Carols — 29 tracks.
Capriccio 10.014

Christmas Carols: Up! Awake! From Highest Steeple; Remember O Thou Man; There Stood in Heaven a Linden Tree; The Holly and the Ivy; Ding Dong Merrily on high; Hark! The Herald Angel Sings; etc; Westminster Abbey Choir; Simon Preston.
DG (DDD) 413 590-2

Christmas: Concentus Musicus Vienna, Nikolaus Harnoncourt cond.
Teldec 8.43 200

Festive Christmas Concert (in German) — 'Es ist ein Ros entsprungen'; Peter Schreier; Hermann Prey; Rene Kollo; Koeth; Julia Migenes; Rudolf Schock; etc.
Ariola-Eurodisc 610 119-231

Many Moods of Christmas: Atlanta Symphony Orch and Chorus.
Telarc 80087

Merry Christmas: Stille Nacht heilige Nacht; Kling, Glockchen, klingelingeling; Sracherl; etc Vienna Boys' Choir, Wiener Volksoperorchester, Uwe Christian Harrer.
Decca (DDD) 412 551-2

Twenty Christmas Carols: Choir St George's Chapel, Windsor Castle; John Porter, organ.
Abbey CD-MVP827

Vespers for Christmas and Easter; Schola Hungarica.
Hungaraton HCD 12533-2

See also: J. S. Bach — Christmas oratorio; Corelli — Christmas concerto.

COPLAND

Appalachian Spring; plus — Adagio for strings (Barber); Candide overture (Bernstein); American Festival overture (Schumann); Los Angeles Philharmonic Orch; Leonard Bernstein cond.
DG (DDD) 413 324-2

El Salon Mexico; Dance Symphony; Fanfare for the Common Man; 4 Dance Episodes from

Rodeo; Detroit Symphony Orch; Antal Dorati cond.
Decca (DH) 414 273-2

Fanfare For The Common Man; Rodeo; Appalachian Spring; Atlanta Symphony Orch; Louis Lane cond.
Telarc 80078

COREA, Chick

Children's songs Nos 19 and 20; plus — variations; for Paul; prelude and fugue; sonatina for Rico (Baroque Rock); Friedrich Gulda, piano.
Philips (DDD) 412 115-2

CORELLI

Christmas concerto; plus Torelli; J. S. Bach; Handel; Academy of Ancient Music, Christopher Hogwood cond.
Decca (OH) 410 179-2

Concerti grossi, Op 6 No 5-8; I Solisti Veneti, Claudio Scimone cond.
Erato ECD-88 080

Trio sonatas, Op 5: S. Kuijken; W. Kuijken, R. Kohnen.
Accent. ACC 48433

Twelve concerti grossi, Op 6: Cantilena, Adrian Shepherd cond.
Chandos CHAN-8336/7/8 (3 CDs)

COUPERIN

Anna Magdalena Bach Notebook 1725; plus — French suite No 5 (J. S. Bach); aria — So oft ich meine Tobacks-Pfeife (G. H. Bach); Minuet in G (Bohm); etc. Blegier; Luxon; Kipnis.
WEA 79020-2

Les Nations I (la Francois; L'Espagnole); Jordi Savall, violin; Hesperion XX.
Astree E7701

Les Nations II (L'Imperiale; la Piedmontese); Jordi Savall, violin; Hesperion XX.
Astree E7702

Motets: Feldman; Poulenc.
Harmonia Mundi HM 90.1150

Pieces de Clavecin: Huguette Dreyfus; clavecin.
Denon C37-7070

CRUSELL

Clarinet concerto No 2; plus — clarinet concerto No 2 (Weber); Thea King, clarinet; London Symphony Orch; Francis cond. Hyperion HYP CDA66088

DEBUSSY

Children's Corner: Reverie; d'Un Cahier d'Esquisses Berseuse Heroique; Danse; Mazurka; etc; Jacques Rouvier, piano. Denon C37-7372

Four scherzi Op 20, 31, 39, 54; Polonaise No 7 in A flat Op 61 (Polonaise-Fantaisie); Claudio Arrau, piano. Philips (DDD) 412 610-2

Images — complete; Estampes; des par sur le neige; Ivan Moravec, piano. MMG MCD 10003

Images; etc; London Symphony Orch. Andre Previn cond. EMI 747001

La Boite a Joujoux; Epigraphes Antiques; La Sarabande; Basle Symphony Orch, Armin Jordan cond. Erato ECD-88 073

La Mer; Apres-Midi d'un Faun; danses; St Louis Symphony Orch; Leonard Slatkin cond. Telarc 80071

La Mer; Nocturnes: Tanglewood Festival Chorus; Boston Symphony Orch; Colin Davis cond. Philips (DDD) 411 433-2

La Mer; Nocturnes: London Symphony Orch; Andre Previn cond. EMI 747028

La Mer; Nocturnes; Prelude a l'apres midi d'un faune; Orchestra de la Suisse Romande, Ernest Ansermet. Decca (DH) 414 040-2

Prelude Premier Livre: Jacques Rouvier, piano. Denon C37-7121

Preludes Deuxieme Livre: Jacques Rouvier, piano. Denon (C37-7043

Preludes, Vol 1: Arturo Benedetti Michelangeli, piano. DG (DDD) 413 450-2

Quartet No 1, Op 10; plus — quartet 1902-03, (Ravel); Enesco Quartet. Forlane UCD-16 521

Recital: Frederica von Stade, mezzo-soprano. CBS CD 39098

Snowflakes Are Dancing: Reverie; Gardens In The Rain; Clair de Lune; etc; Isoa Tomita, percussion. RCA RCD 14587

String quartet; plus — string quartet (Ravel); Orlando Quartet. Philips (DDD) 411 050-2

Suite bergamasque; images (oubliees); pour le piano, Estampes; Zoltan Kocsis, piano. Philips (DDD) 412 118-2

The Prodigal Son: Jessye Norman; Jose Carreras; Dietrich Fischer-Dieskau; Stuttgart Radio Symphony Orch and Chorus; Bertini cond. Orfeo ORF 0012

Trois nocturnes; Jeux: Women's voices of the Collegium Musicum Amstelodamense. Philips (AAD) 400 023-2

DEBUSSY/RAVEL

String quartets: Galimir Quartet. Vanguard CD-25 009

DEL TREDICI, David

In Memory of a Summer Day: David Del Tredici. WEA 79043-2

DELANDE

Symphony pour les Soupers du Roy: Jean-Francois Paillard Chamber Orchestra; J-F Paillard cond. Erato ECD-88 088

DELIUS

Miniatures: Bournemouth Sinfonietta; N del Mar cond. Chandos CHAN-8372

Song of the High Hills: Walker; Lott; Johnson. Unicorn DKP(CD) 9029

Summer Night on the River; On Hearing the First Cuckoo in Spring; etc; plus — The Wasps overture; Serenade to Music; etc (Vaughan-Williams). Chandos CHAN-8330

Violin concerto; suite; legende; Ralph Holmes, violin; Royal Phil Orch; Vernon Handley cond. Unicorn DKP(CD) 9040

DIABELLI

Sonata for Guitar in F major; plus — Guilianil Legnani; Paginini; Eduardo Fernandez, guitar. Decca 414 160-2

DIETRICH

Violin concerto; plus — notturno (Joachim): Maile; Berlin Radio Symphony Orch; Lopez-Cobos cond. Schwann SCH 11622

DONIZETTI

Don Pasquale — highlights: Gregor; Ivan Fisher. Hungaraton HCD 12610-2


L'Elisir d'Amore — complete opera: Lucia Popp; Weikl; Nestorenko; Munich Radio Orch and Chorus; Wallberg cond. Ariola-Eurodisc 610 097-233 (3CDs)

Lucia de Lammermoor: Sutherland; Milnes; Pavarotti; Ghiaurov, Royal Opera House Orchestra and Chorus; Richard Bonyng cond. Decca (DH) 410 193-2

DUKAS

Ariane et Barbe-Bleue: soloists; Chorus of Radio France; New Philharmonic Orch; Armin Jordan cond. Erato ECD-88 097 (2 CDs)

Float[®]



After 50 Years, something New in headphone design

Swiss craftsman has created the world's most comfortable headphone. **The Jecklin Float is available in both electrostatic and dynamic versions**, both of which lead their field in audio fidelity, while offering extraordinary comfort.

Most headphones sit on or enclose the ear, but the **Jecklin Float** lightly surrounds your ears. Yet it provides full, deep bass response and an airy top end with accurate overtone balance.

The **Jecklin Float** rests on top of the head and the weight, mere ounces, is distributed by means of a wide headband over a large surface resulting in complete freedom of pressure.

The **Jecklin Float** does not press against the ear or physically contact the ear or the head area surrounding the ear, except behind the ear.

As a result of this design, the **Jecklin Float** can be used for long periods and at high sound levels unlike conventional headphones which invariably induce listener fatigue and sometimes headaches or vertigo. It is no wonder that sound engineers can work for hours with the **Jecklin Float** without the discomfort, fatigue, perspiration, etc., that they previously experienced with other headphones. For your nearest Dealer or further information contact:

Audio Dynamics

155 Camberwell Road
Hawthorn East, 3123 Vic., Australia
Tel: (03) 813 1923 Tlx: 38409

A Division of Tivoli Electronics P/L

COMPACT DISC CATALOGUE

La Peri; Symphony in C: Orch de la Suisse Romande, Armin Jordan cond.
Erato ECD-88 0889

DURUFLE

Requiem; motets on Gregorian themes: Teresa Berganza; Jose van Dam; Ensemble Voc Audite Nova de Paris; Cologne Chorus and Orch;
Corboz cond.
Erato ECD-88 132

DVORAK

Cello concerto in B minor, Op 104; plus — cello concerto Elgar; Heinrich Schiff, Concertgebouw Orch Amsterdam; Sir Colin Davis cond.
Philips (DDD) 412 880-2

Cello concerto in B minor; Waldsruhe for cello and orch: Frans Helmerson, cello; Gothenburg Symphony Orch; Neeme Jarvi cond.
BIS BIS CD-245

Cello concerto; plus — Kol Nidrei (Bruch); Lyn Harrell cello; Philharmonia Orchestra; Vladimir Ashkenazy cond.
Decca 410 144-2

Cello concerto; plus — Rococo variations (Tchaikovsky); Mstislav Rostropovich, cello; Berlin Philharmonic Orch; Herbert von Karajan cond.
DG (DDD) 413 819-2

Gypsy melodies and love songs: Peter Schreier, tenor.
Capriccio 10.053

Legends: Rochester Philharmonic Orch, David Zinman cond.
WEA 79066-2

Piano trio No 3, Op 65; Borodin Trio.
Chandos CHAN-8320

Piano quintets in A, Op 5 and 81; Sviatoslav Richter, piano; Borodin Quartet.
Philips (DDD) 412 429-2

Polanaise; plus — Vocalise Rachmaninoff; Malinconia Sibelius; Heinrich Schiff; Elisabeth Leonskaja.
Philips (DDD) 412 732-2

Requiem, Op 89; Benackova; Czech Phil Orch; Wolfgang Sawallisch cond.
Supraphon SUP CD7427/28 (2 CDs)

Rusalka — complete: Benackova Novak; Czech Phil orch, Neumann cond.
Supraphon SUP CD7201/3 (3 CDs)

Serenade for strings in E; serenade for wind instruments in D minor; Chamber Orch of Europe; Alexander Schneider cond.
ASV COE 801

Serenade for strings, Op 22; plus — serenade, Op 48 (Tchaikovsky); Berlin Philharmonic Orch; Herbert von Karajan cond.
DG (DDD) 400 038-2

Serenade for winds, Op 44; plus — Petite Symphony (Gounod); Munich Wind Academy; Brezina cond.
Orfeo ORF C051

Serenade in E Op 22; serenade in D minor Op

44; Academy of St Martin-in-the-Fields; Neville Marriner cond.
Philips (DDD) 400 020-2

Serenade, Op 22; Nocturne, Op 40; waltzes: Prague Musici; Sagrestano cond.
Rodolphe RPC 32401

Serenade, Op 22; Waldsruhe, Op 68; Notturmo, Op 40; Douglas Davis, cello; Los Angeles Chamber Orch.
Delos 3011

Slavonic dances, Op 46 and 72; Czech Phil Orch; Neumann cond.
Supraphon SUP CD7491

Slavonic dances, Op 46 and Op 72: American Suite; Royal Philharmonic Orch; Antal Dorati, cond.
Decca (DH2) 411 735-2

Slavonic dances; Slavonic rhapsodies: Czech Phil Orch; Vaclav Neumann cond.
Teldec 8.42 203

Stabat Mater, Op 58: Benackova; Wenkel; Dvorsky; Rootering; Czech Phil Orch; Wolfgang Sawallisch cond.
Supraphon SUP CD7378/79 (2 CDs)

String quartet No 10; plus — string quartet in E minor (Verdi); Vermeer Quartet.
Teldec 8.43 105

String quartet No 12 in F major 'American'; quintet in A major for piano and string quartet; Smetana Quartet; Josef Hala, piano.
Denon C37-7339

String quartet No 2: Turina String Quartet.
Bellaphon 690.01.032

String quartets No 10 in E flat major, Op 51; No 14 in A flat major, Op 105; Kocian Quartet.
Denon C37-7235

String quartets No 12 in F major, Op 96 'American'; No 13 in G major, Op 106; Kocian Quartet.
Denon C37-7234

String quartets No 2, Op 87, and 14, Op 105.
Bellaphon 690.01.018

Symphonies Nos 7 and 8; symphony No 9: Minnesota Orch; Neville Marriner cond.
Philips (DDD) 412 542-2 (2 CDs)

Symphony No 4: Czech Phil Orch; Neumann cond.
Supraphon SUP CD7442

Symphony No 5: Czech Phil Orch; Neumann cond.
Supraphon SUP CD7377

Symphony No 6: Czech Phil Orch; Neumann cond.
Supraphon SUP CD7242

Symphony No 7: Vienna Philharmonic Orch; Lorin Maazel cond.
DG (DDD) 410 997-2

Symphony No 7: Czech Phil Orch; Neumann cond.
Supraphon SUP CD7067

Symphony No 7: Philharmonic Symphony Orch;

Carlos Paita cond.
Lodia LOCD 782

Symphony No 8 in G, Op 88; Nocturne for strings: London Philharmonic Orch; Vernon Handley cond.
Chandos CHAN-205-2

Symphony No 8: Vienna Philharmonic Orch; Lorin Maazel cond.
DG (DDD) 415 205-2

Symphony No 8: Czech Phil Orch; Neumann cond.
Supraphon SUP CD7073

Symphony No 9 From the New World: Minnesota Orch; Neville Marriner cond.
Philips (DDD) 412 224-2

Symphony No 9 'From the New World': Czech Phil Orch; Neumann cond.
Supraphon SUP CD7002

Symphony No 9 'From The New World': London Symphony Orch; Enrique Batiz cond.
Varese Sarabande 47216

Symphony No 9 'From the New World': Vienna Philharmonic Orch; Lorin Maazel cond.
DG (DDD) 410 032-2

Symphony No 9 in E minor 'From the New World': Berlin Philharmonic Orch; Klaus Tennstedt cond.
EMI 747071

Symphony No 9 in E minor, Op 9: Chicago Symphony Orch; James Levine cond.
RCA RCD14552

Symphony No 9, 'New World'; Carnival overture, Op 92: London Philharmonic Orch; James Conlon cond.
Erato ECD-88 036

Symphony No 9 'From the New World': Chicago Symphony Orch; Sir Georg Solti, cond.
Decca (DH) 410 116-2

Symphony No 9 'From the New World': Wiener Philharmoniker; Kiril Kondrashin cond.
Decca (DH) 400 047

Te Deum; Psalm 149; Hymnus; Benackova; Czech Phil Orch; Neumann cond.
Supraphon SUP CD7230

Trio No 4 in E minor, Op 90 'Dumky' Suk Trio.
Denon C37-7057

ELGAR

Cello concerto; plus — cello concerto (Dvorak); Staatskapelle Dresden; Neville Marriner cond.
Philips (DDD) 412 880-2

Four overtures — In The South, etc; Scottish National Orch; Alexander Gibson cond.
Chandos CHAN-8309

Miniatures (with L. Goossens); Bournemouth Sinfonietta; N. del Mar cond.
Chandos CHAN-8371

Music for violin and piano; Nigel Kennedy, violin; Peter Pettinger, piano.
Chandos CHAN-8380

Piano quintet; string quintet; John Bingham, piano; Medici Quartet.
Meridian ECD-84 082

Violin concerto, Op 61; Itzhak Perlman, violin; Chicago Symphony Orch; Daniel Barenboim cond.
DG (DDD) 413 312-2

Violin concerto; Nigel Kennedy, violin; London Philharmonic Orch; Vernon Handley cond.
EMI 747210

Wand of Youth suites; Nursery suite; Ulster Orch, Bryden Thomson cond.
Chandos CHAN-8318

Works for string orch; English String Orch.
Nimbus NIM 5008

Enigma variations; Crown of India suite; March of the Mogul Emperors; Pomp and Circumstance marches No 1 and 2; BBC Symphony Orch; Leonard Bernstein cond.
DG (DDD) 413 490-2

ERKEL, Ferenc

Hunyadi Laszio; Gulyas; Sass; Kalmar; Solyom-Nagy; Denes; Molnar, Janos Kovacs.
Hungaraton HCD 12581-83-2 (3 CDs)

de FALLA

Nights in the Gardens of Spain; plus Albeniz: Rapsodia Espanola; Turina; Rapsodia Sinfonica; London Philharmonica Orch; Rafael Frubeck de Burgos cond.
Decca (DH) 410 289-1

The Three Cornered Hat (complete ballet); El amor brujo; Ritual Fire Dance; Frederica von Stade; Pittsburgh Symphony Orch; Andre Previn cond.
Philips (DDD) 411 046-2

The Three Cornered Hat; Orchestre Symphonique de Montreal; Charles Dutoit cond.
Decca 410 008-2

The Three Cornered Hat; La Vida Breve—interlude and dance; Teresa Berganza; Orch de la Suisse Romande; Ernest Ansermet cond.
Decca 414 039-2

FAURE

Pelleas et Melisande-Suite Pavane; Masque et Bergamasque—Suite; Academy of St Martin-in-the-Fields; Neville Marriner cond.
Argo 110 552-2

Requiem Op 48; Lucia Popp; Simon Estes; Staatskapelle Dresden; Colin Davis cond.
Philips (DDD) 412 743-2

Requiem; Elgie; Messe Basse for female voices and organ; Monte Carlo Phil Orch, Armin Jordan cond; Marie-Claire Alain, organ.
Erato ECD-88 126

Requiem; Messe Basse: B. Thomas Chamber Orch and Piquemal Chors.
Forlane UCD-16 536

FIELD

Piano concertos No 6 and No 7; John O'Connor, piano; New Irish Chamber Orch; Furst cond.
Sound 3414

FRANCK

3 Chorals for organ; Peter Hurford.
Argo (ZH) 411 710-2

Organ Works, Vol 2; Jennifer Bate, organ.
Unicorn DKP(CD)9014

Organ Works, Vol 3; Jennifer Bate, organ.
Unicorn DKP(CD)9030

Organ works; Marie-Claire Alain, organ.
Erato ECD-88 110

Symphony in D minor; plus—Le Rouet d'Omphale (Saint-Saens); Orch Nationale de France; Leonard Bernstein cond.
DG (DDD) 400 070-2

Three chorals; prelude, fugue and variation, Op 18; Pastorale, Op 19; Peter Hurford, St Sernin Basilica organ, Toulouse.
Decca (DDD) 411 710-2

Violin sonata; also Ravel—violin sonata; Jean-Jacques Kantarow, violin; Jacques Rouvier, piano.
Denon C37-7079

Violin sonata; plus horn trio (Brahms); Itzhak Perlman; Vladimir Ashkenazy.
Decca 414 128-2

FUCIK

Entry of the Gladiators; Florentine March; etc; Czech Phil Orch; Vaclav Neumann cond.
Teldec 8.42 337

GERSHWIN

A Symphonic Picture of Porgy and Bess; (arr. Bennet); plus Grand Canyon Suite (Grove).
Detroit Symphony Orchestra; Anton Dorati cond.
Decca 410 110-2

An American In Paris; Cuban Overture; Porgy and Bess; Dallas Symphony Orch; Eduardo Mata cond.
RCA RCD14551

Porgy and Bess (highlights); Simon Estes; Roberta Alexander; Diane Curry; Siegfried Stockist; Berlin Radio Chorus; Berlin Symphony Orch; Leonard Slatkin cond.
Philips (DDD) 412 720-2

Porgy and Bess; etc; London Symphony Orch; Andre Previn cond.
EMI 747021

Rhapsody In Blue; An American In Paris; Cincinatti Symphony Orch; Erich Kunzel cond.
Telarc 80058

Rhapsody In Blue; An American In Paris; piano concerto in F; Andre Previn piano; Pittsburgh Symphony Orch; Andre Previn cond.
Philips (DDD) 412 611-2

Rhapsody In Blue; etc; London Symphony Orch; Andre Previn cond.
EMI 747161

Rhapsody In Blue; I Got Rhythm; etc; Alexis Weissenberg, piano; Berlin Philharmonic Orch; Seiji Ozawa cond.
EMI 747152

Rhapsody In Blue; plus—West Side Story;

symphonic dances (Bernstein); Los Angeles Philharmonic Orch; Leonard Bernstein cond.
DG (DDD) 410 025-2

GIODANO

Andrea Chenier; Pavarotti, Cabrelle; Nucci, National Philharmonic Orchestra; Ricardo Chailly cond.
Decca 410 117-2 (2 CDs)

GIULIANI

3 Guilianate from Op. 148; etc; Eduardo Fernandez, guitar.
Decca (DH) 414 160-2

GLUCK

Dance of the Blessed Spirits; plus Albinoni, Boccherini; Pachelbel; etc; Stuttgarter Kammerorch; Karl Munchinger cond.
Decca (DH) 411 972-2

Orpheo and Euridice; Kweksilber; Jacobs; Falewicz; La Petite Band; Kuijken.
Accent ACC 48223/4 (2 CDs)

GOLDMARK

Overtures, Budapest Philharmonic; Korodi cond.
Hungaraton HCD 12552-2

GOTTSCALK

Piano works — 'The Lady Fainted'; Alan Marks, piano.
Nimbus NIM 5014

GOUNOD

Faust Ballet; Ballet aus Margaret; plus Offenbach; Gaite Parisienne; Orchestre Symphonique de Montreal; Charles Dutoit cond. Cecilia Mass; Barbara Hendricks; Nouvel Phil Orch; Georges Pretre cond.
EMI 747094

GRAINGER

Music of Percy Grainger; Youthful suite, etc; Bournemouth Sinfonietta; K. Montgomery cond.
Chandos CHAN-8377

GRANDADOS

Goyescas; El Pelele; Alicia de Larroche
Decca (DH) 411 958-2

Seis piezas sobre cantos populares espanoles; Allegro de concierto; Escenas romanticas; Alicia de Larroche.
Decca (DH) 410 288-2

Spanish Dances; Alicia de Larroche.
Decca 414 557-2

Favourite Guitar Pieces by Grandos, Ponce, Terrega Scharom Isbin and Machiko Kikuchi, guitars; Tokyo Metropolitan Symphony Orch; Hideomi Kuroiwa cond.
Denon C37-7054

GRIEG

Holberg suite Op. 40; 2 lyric pieces; plus—Karelia suite and The Swan Of Tuonela (Sibelius); Academy of St Martin-in-the-Fields; Neville Marriner cond.
Philips (DDD) 412 727-2

Peer Gynt suite; Academy of St Martin-in-the-Fields; Neville Marriner cond.
EMI 747003


Peer Gynt suites No 1 and 2; plus—Pelleas et

JANUARY CROSSWORD

DOWN

1. Directed physical quantity. (6)
2. Unwanted audio frequency modulation. (7)
3. Lightning. (4)

4. Type of TV aerial. (6)
5. The application of electronics to aircraft. (6)
6. Radio and electronics engineers organisation. (1,1,1,1)




7. Said of design, etc, having the most elegant simplicity. (7)
8. Useful tool for constructors. (8)
14. Name of a connection method used to transform 3-phase to 2-phase.
15. Regions of low potential. (5)
18. This can amplify microwaves. (8)
19. Again cover wire, etc, with tubing. (8)
21. Connects to a point of zero potential. (7)
23. Entered the telephone service. (7)
24. Physicist famous for his ionising radiation detector. (6)
29. An emergency device is the _____ switch. (4)
30. What EPIRBs do with signals. (4)

ACROSS

2. Process of construction of semiconductor devices, etc. (11)
9. A CCD is a charge _____ device. (7)
10. Computers often do this. (7)
11. A prefix used in electronics where light is involved. (4)
13. Physicist after whom an electrical law is named. (4)

SOLUTION FOR DECEMBER



10. Path of 26 across. (5)
17. In semiconductors, gallium may be an _____ impurity. (8)
20. Device that interacts with a computerised display. (5-3)
22. Type of control. (5)
26. Stationary trace on a CRO. (4)
27. Part of a lead-acid cell. (5)
28. Electrode of a bipolar transistor. (4)
31. Period to execute a program. (3,4)
32. Interval between device operation and response. (4,3)
33. Said of a device that oscillates, etc, without a separate circuit. (4-7)

Car Burglar Alarm Flasher

This is the "Claytons" burglar alarm — the alarm you connect when you can't be bothered fitting a proper alarm. It simply flashes a light on the dashboard.

CD Adaptor for Cars

How do you connect a portable compact disc player to your car sound system? With our CD Adaptor, of course. It's a simple circuit and easy to build.

Annual Hifi Awards

Next month, we will announce the winners of the 1985 Hifi Grand Prix Awards. The awards have eight categories: best amplifier, tuner, receiver, CD player, cassette deck, turntable, loudspeaker system and a special category labelled "technological development"

Note: Although these articles have been prepared for publication, circumstances may change the final content.

Next month in Electronics Australia

Radio Direction Finder



Employing an electronically "rotating" antenna, this radio direction finder rapidly indicates the direction of a transmitted radio signal. It should find ready use with radio amateurs, CB operators and marine enthusiasts.

COMPACT DISC CATALOGUE

Melisande (Sibelius); Berlin Philharmonic Orch;
Herbert von Karajan cond.
DG (DDD) 410 026-2

Peer Gynt, Op. 23—incidental music; Elly
Ameling, soprano; San Francisco Symphony
Orch and Chorus; Edo de Waart cond.
Philips (DDD) 4111 038-2

Piano concerto; plus—piano concerto
(Schumann); Krystian Zimerman, piano; Berlin
Philharmonic Orch; Herbert von Karajan cond.
DG (DDD) 410 021-2

Piano concerto; plus Schumann: piano concerto:
Radu Lupu, piano; London Symphony
Orchestra; Andre Previn cond.
Decca (DH) 414 432-2

Piano works, incl Lyric Pieces; Norwegian
dances No 2 and 4; Morning Mood from Peer
Gynt Suite 1; Cyprien Katsaris, piano.
Teldec 8.42 925

Sonatas for violin: Sitkovetsky, violin;
Davidovich, piano.
Orfeo ORF CO47

GROFE

Grand Canyon Suite; plus Symphonic Picture of
Porgy and Bess (Gershwin arr Bennett); Detroit
Symphony Orchestra; Antal Dorati cond.
Decca (DH) 410 110-2

GUITAR MUSIC

Bizet; Carmen Suite; Chapi: La Revoltosa;
Fallá: Dances from La vida breve; El sombrero
Espanol No 4, 5 and 7; Torroba; Sonata
trianera: Los Romeros.
Philips (DDD) 412 609-2

Famous Spanish Guitar Music; Anon Jeux
Interdits; Albeniz; Asturias; Malats; Serenta
espanola; Sor: Introduction and variations on a
theme by Mozart; Tarrega: Recuerdos de la
Alhambra; etc; Pepe Romero, guitar.
Philips (DDD) 411 033-2

Famous Spanish Dances for 2 guitars by
Granados; De Falla Albeniz; Transcriptions;
Pepe Romero; Celin Romero.
Philips (DDD) 411 432-2

GULDA

Variations; For Paul; prelude and fugue;
sonatina; for Rico (Baroque Rock); plus—
Children's songs Nos 19 and 20, Corea;
Friedrich Gulda, piano.
Philips (DDD) 412 115-2

HANDEL

12 concerti grossi Op 6: Academy of St
Martin-in-the-Fields; Iona Brown; Neville
Marriner.
Philips (DDD) 410 048-2 (3 CDs)

6 concerti grossi Op 3: Academy of St
Martin-in-the-Fields; Neville Marriner cond.
Philips (DDD) 411 482-2

Alexander's Feast concerto: Alice Harnoncourt,
cello; Herbert Tachezi, organ.
Teldec 8.43 050

Alexander's Feast: Palmer; Johnson; Roberts;
Bach Choir Stockholm; Concentus Musicus
Vienna; Nikolaus Harnoncourt cond.
Teldec 8.35 671 (3 CDs)

Aminta and Fillede: Fisher; Kwella; London
Handel Orch; Darlow cond.
Hyperion HYP CDA66118

Arias—recital: Marilyn Horne, mezzo; I Solisti
Veneti; Claudio Scimone cond.
Erato ECD-88 034

Ballet music—Alcina; Il Pastor Fido;
Terpsichore: English Baroque Soloists, John
Eliot Gardiner cond.
Erato ECD-88 084

Belshazar—complete: Tear; Palmer; Esswood;
Stockholm Chamber Choir; Concentus Musicus
Vienna; Nikolaus Harnoncourt cond.
Teldec 8.35 326 (3 CDs)

Chamber cantatas and duets: Concerto Vocale.
Harmonia Mundi HM 90.1004

Choice of Hercules.
Capriccio 10.019

Concerti grossi Op 3: Concentus Musicus
Vienna; Nikolaus Harnoncourt cond.
Teldec 8.35 545 (2 CDs)

Concerti grossi, Op 6 No 1-12: Concentus
Musicus Vienna; Nikolaus Harnoncourt cond.
Teldec 8.35 603 (3 CDs)

Concerti grossi, Op 6 No 1-4: The English
Concert; Trevor Pinnock cond.
Archiv (DDD) 410 897-2

Concerti grossi, Op 6 No 5-8: The English
Concert; Trevor Pinnock cond.
Archiv (DDD) 410 898-2

Concerti grossi, Op 6 No 9-12: The English
Concert; Trevor Pinnock cond.
Archiv (DDD) 410 899-2

Concerto a due cori: Academy of Ancient
Music; Christopher Hogwood cond.
Decca (DH) 411 721-2

Concerto grossi, No 1-4.
Capriccio 10.021

Concerto grossi, No 5-8.
Capriccio 10.022

Concerto grossi, No 9-12.
Capriccio 10.023

Concertos for organ: Edgard Krapp, organ.
Ariola-Eurodisc 610 260-234

Coronation Anthem: Choir of Westminster
Abbey; Simon Preston, organ; The English
Concert, Trevor Pinnock cond.
Archiv (DDD) 410 030-2

Coronation Anthems; excerpts from Judas
Maccabeus; Academy of St Martin-in-the-Fields
and chorus; Neville Marriner cond.
Philips (DDD) 412 733-2

TO BE CONTINUED

Due to a limit on space in this issue, we
will continue our listing of classical and
popular compact discs in the February
issue.

FLUKE 20 SERIES ANALOG/DIGITAL MULTIMETERS FOR THE TOUGHEST ENVIRONMENTS



FLUKE 21 & 23

Yellow case colour
Analog/Digital display
Touch Hold™ function (23)
0°C to 50°C operation
0.5% & 0.3% basic accuracy
100 μ V to 1000V dc
1mV to 750Vac
10 μ A to 10A (23), all fused
10 μ A to 320 mA (21), fused
Three-year warranty

FLUKE 25 & 27

Charcoal or yellow case
colour
Analog/Digital display
Touch Hold™ function
-15°C to 55°C operation
0.1% basic accuracy
100 μ V to 1000V ac and dc
0.1 μ A to 10A, all fused
Relative (difference)
mode (27)
MIN/MAX recording
mode (27)
Ruggedized, waterproof
case

Two-year warranty

FROM THE WORLD LEADER
IN DIGITAL MULTIMETERS.



See the Fluke 20 series at leading electronics
stores or contact us for data

ELMEASCO Instruments Pty. Ltd.

NEW SOUTH WALES	VICTORIA	QUEENSLAND
15 McDonald Street	12 Maroondah Highway	Tel (07) 369 8688
MORTLAKE	RINGWOOD	S AUSTRALIA
P O Box 30 CONCORD	P O Box 623 RINGWOOD	Tel (08) 344 9000
NSW 2137	VIC 3134	W AUSTRALIA
Tel (02) 736 2888	Tel (03) 879 2322	Tel (09) 481 1500
Telex AA25887	Telex AA30418 ELTENT	



Information centre

Voice operation for CB transceiver

I am undertaking a project to do away with the PTT switch on my hand-set on the CB. I purchased a voice-operated switch kit (EA) and built it. Now I want to know how to connect it to the PTT switch to make it transmit on talk and receive on silence.

Also, a lot of my projects used the buzzer type warning and call for intercoms. I wish to change this to the same tone as on Telecom phones. Please advise on the circuit, if possible. (C.P., Arrawarra Headland, NSW).

• Fitting a voice-operated relay system to a CB radio may not be very straightforward although it may seem simple enough initially. First, the relay must be connected into your CB so that it effectively replaces the PTT contacts which change over operation from transmit to receive. That much should be fairly easy.

Second, the microphone output signal from the VOX must be substituted for the output of the preamplifier in your CB. You will need a copy of your CB's circuit to do this.

Having achieved that, you will then have to make sure that the VOX circuit is not affected by the RF output of your CB and is not triggered by the sound of the received signal coming from the speaker. The latter may simply be a matter of keeping the microphone well away from the loudspeaker and keeping the audio gain low.

We are not sure what tone you mean when you refer to Telecom phones. We have designed a circuit (Telephone Bell Extender, February 1984) which approximates the ringing tone of a telephone. It must be used with a speaker rather than a buzzer.

Inverters for solar electricity supply

I am writing to seek your assistance concerning inverters for use in a solar electricity supply to our somewhat remotely located home. I hope you will be patient while I explain our problems

before getting down to specifics!

We have installed a solar panel-battery bank which is adequate for our projected needs, providing some 600 ampere-hours of storage and 200 watts input. Initially, we installed 12V fluorescent lighting in the house as recommended and supplied by a leading solar firm. Expensive disaster! Reasonable lighting but intolerable radio interference, especially on AM. The problem is exacerbated by interference between each individual inverter in each lamp. There seems no solution to this and additionally we found that the power consumption was greater than expected, a 20W lamp using closer to 35W.

We then considered a single inverter feeding a house full of Phillips' SQ type lamps, which should be better. We purchased a 400VA inverter which works well but we discovered a characteristic of these devices — low efficiency at low power output. While it will be most useful for intermittent power supply, drills, mixers, small vacuum cleaners, etc, we cannot use it for lighting.

Having tried SQ lamps we are impressed with them and calculate that we can light the whole house and most of the farm with about 100W of power. This is the option we wish to pursue along with a 12V supply for radio and TV. There seems no point in going to the large sophisticated 1000VA+ inverters. In those times when we need big power we may as well use our petrol generator.

Our difficulty has been to locate inverter circuits in the required power range. Among other less suitable ones, we encountered those published by you in May and June 1982. The latter is too big for our needs. The former, 12V/230V 40VA inverter, is just a little too low powered. This brings me to my specific questions.

1. The 40VA inverter: both the Darlingtons and the 2N3055s are capable of handling higher currents than provided for, and presumably it is the selection of the transformer which limits the circuit. Can the circuit be modified with another transformer and changed component values to give a higher output?

80-100 watts would be fine but 60W might do us. You also mentioned that the circuit given will not start fluoros. Will it start SQs, and if not can it be made to do so?

2. Can some of the regulator circuitry of your 300VA inverter, (EA, June, '82) be grafted on to the smaller one, particularly the error regulation circuit, to increase the efficiency at lower powers? There are times for instance when we may wish to use only two 9W SQ lamps. Sounds pretty stingy, doesn't it? But we get 100 inches of rain a year and there are periods of prolonged cloud so we need the option of being conservative.

3. The inverters are both clearly differentiated into signal generator and power amplifier stages. Can we arrange to use one signal section to drive more than one power stage so that effectively one selects an output to suit the load? Is it also possible to feed the outputs of such synchronous inverters into the same household power circuit? Losing 35W in inefficiencies represents the output of one \$400 solar panel.

4. Our 400W inverter gives a little RF interference, again more on AM than FM and not as bad as the fluoros. Is this inherent in square wave inverters and how is it best alleviated? How much more inefficient would be the use of sine wave? Can some of the cheap 50W-100W power audio amplifiers in kit form be used as output stages for inverters?

5. Our 400VA inverter has a stand-by starter. How do these devils work and can one be incorporated into the modified 40VA circuit?

Reading this, I realise that I seem to have battered you with questions. Forgive me but in the two years that we have been trying to get ourselves going our biggest problem has been to get reliable information. With many "expert alternative energy advisers" the advice goes little beyond telling you to plug this gizmo in here and switch on the light. And the natty gizmo will cost you an arm and a leg!

There must be many people like us tucked away under bushes in the jungles

of Australia, not really hippies but a bit odd and not willing to spend \$10,000 to bring the power in half a kilometre.

If in the future your magazine were to publish an extensive summary of inverter and regulator circuits and their problems it would be received with acclaim. Please can you help us? (K.P., Berry, NSW.)

• Let us answer your questions in order. 1. The 40VA inverter can be upgraded simply by increasing the size of the transformer as you suggest. An updated version along these lines was published in our July 1985 issue but it would probably not be big enough to suit your purpose. Unfortunately too, we are unable to nominate a suitable off-the-shelf transformer with a rating around 100VA.

As an alternative why not consider the new 300VA version published in the September 1985 issue? This has the virtue that it is quite efficient at low outputs. It is also more efficient than the 40VA version, mainly because of the toroidal transformer. It would probably also drive Philips' SQ lamps although we must stress that we have not tried this. Note that it also has an auto-start circuit.

It would be possible to arrange for the front end of the 300VA inverter to drive two or more output stages but they would really need to be in parallel, driving the one large transformer so that the feedback system could work properly.

Unfortunately, all square wave inverters inherently produce some radio interference, more on the AM bands than on FM. Putting in filter components to remove this interference is bound to have the effect of reducing overall efficiency.

Deluxe Car Burglar Alarm

I have recently fitted the Deluxe Car Burglar Alarm and at the time of purchase I also bought the optional hazard flasher components. Some difficulty has been encountered when attempting to wire this option to my car, a 1985 Magna.

The problem occurs because the hazard lamp wiring in the Magna differs from that used in earlier cars. The relay on the alarm system is intended to close a set of points and bridge out a single pole hazard lamp switch. However, the hazard lamp switch in the Magna is a multi-pole unit.

The easiest way I can see to overcome the problem is to use the existing relay contacts to control a second slave relay which has enough poles to bridge the Magna's multi-pole hazard switch. Maybe someone else has encountered this and solved it another way.

The Magna has in a convenient position a relay box to hold numerous Repco relays, of which possibly another one could be utilized to solve this problem. (B.R., Kurri Kurri, NSW.)

• The easiest way of overcoming your problem would be to substitute a multi-pole relay directly for a single-pole relay originally specified.

This could be mounted off the board and wired using short lengths of hook up wire.

Trouble with low-power inverter

I have purchased the inverter kit described in the May 1982 edition. I am having trouble with it and would appreciate your advice. The no-load current is very high (2.5 amps), the waveform shows various spikes and peaks which are unexpected and the output drops off prematurely to 110V with a 30W load.

The only modification I have made is to replace the PL18/40VA transformer with a PL18/60VA. I have included a pencil sketch of the various waveforms, with a few extra notes. I hope you could suggest some way of improving the performance, or some component which I may try replacing. (M.P., Kelvin Grove, Qld.)

• By the look of your waveforms, nothing appears to be seriously wrong with most of the circuit although, unfortunately, you have not bothered to show the amplitude of the waveforms.

The no-load current is high but that is probably partly attributable to the use of the bigger transformer.

We suggest you check the waveform between emitter and collector of each of the output transistors, Q2 and Q4. Check that they are saturating (ie, 1V or less at the collector) when they are turned on. If not, check that they are getting full drive from the Darlingtons via the paralleled 150Ω resistors.

Using the Railmaster with Marklin locos

In Information Centre for March 1985, R.B. of Sydney presented a rather interesting solution to the problem of

FOR QUALITY AND VALUE TALK TO THESE PEOPLE ABOUT FLUKE MULTIMETERS

A.C.T.

Actec Pty Ltd
34 Geelong St Fyshwick
(062) 80 6576

N.S.W.

Ames Agency Pty Ltd
605 Elizabeth St Redfern
699 4524

George Brown & Co Pty Ltd
174 Parramatta Rd
Camperdown - 519 5555
Newcastle - 69 6399
Canberra - 80 4355

Bryan Catt Industries Pty Ltd
10/59-61 Gympie Bay Rd
Gymea
526 2222

Collier Tools (Aust) Pty Ltd
185 Parramatta Rd
Homebush
763 1888

D G E Systems Pty Ltd
103 Broadmeadow Rd
Broadmeadow
(049) 69 1625

Davred Electronics Pty Ltd
127 York St Sydney
267 1385

W F Dixon & Co Pty Ltd
P O Box 42 Wickham
(049) 61 5628

Macelec Pty Ltd
99 Kenny St Wollongong
(042) 29 1455

Paul's (Merchants) Pty Ltd
22 Canterbury Rd
Bankstown
709 2311

Radio Despatch Service
869 George St Sydney
211 0291

Selectro Parts Pty Ltd
482 Hume Hwy Yagoona
708 3244

Standard Communications Pty Ltd
6 Frank St Gladesville
896 1755

Geoff Wood Electronics Pty Ltd
656A Darling St Rozelle
810 6845

WESTERN AUSTRALIA

Atkins Carlyle Ltd
1 Milligan St Perth
321 0101

Dobbie Instruments (Aust) Pty Ltd
9 Boag Rd Morley
276 8888

Cairns Instrument Services
32 Wickham St East Perth
325 3144

Willis Trading Co Pty Ltd
165 Albany Hwy
Victoria Park
470 1118

VICTORIA

Radio Parts Pty Ltd
562 Spencer St
West Melbourne
329 7888

G B Telespares Pty Ltd
504 Queensbury Rd
North Melbourne
328 3371

Browntronic Pty Ltd
93 Sackville St Collingwood
419 3986

R K B Agency
20 Council St Hawthorn
82 7704

A J Ferguson & Co Pty Ltd
558-568 Swanston St Carlton
347 6688

SIRS Sales Pty Ltd
4 Edols Pl North Geelong
(052) 78 1251

TASMANIA

George Harvey Electrics
Head Office
76 York St Launceston
(003) 31 6533
Hobart - (002) 34 2233

SOUTH AUSTRALIA

Protronics Pty Ltd
174 Wright St Adelaide
212 3111

Trio Electrix Pty Ltd
177 Gilbert St Adelaide
212 6235

Redarc Electronics
253 Main Rd Blackwood
278 7488

QUEENSLAND

L E Boughen & Co
33 Railway Tce Milton
369 1277

Colourview Wholesale
5 Commerce St Salisbury
275 3188

Fred Hoe & Sons Pty Ltd
246 Evans Rd Salisbury Nth
277 4311

Nortek
36 Punari St Townsville
(077) 79 8600

St Lucia Electronics
71-77 Brunswick St
Fortitude Valley
52 7466

Selectro Parts (Qld)
44 Esher St Ekibin
394 2422

NORTHERN TERRITORY

Thew & McCann (NT) Pty Ltd
Menmuir St Winellie Darwin
(089) 84 4999



ELMEASCO

Instruments Pty. Ltd.

NEW SOUTH WALES 15 McDonald Street, MORTLAKE
VICTORIA 12 Maroonah Highway, RINGWOOD
P.O. Box 30, CONCORD NSW 2137
Tel: (02) 736 2888
Telex AA25887


QUEENSLAND Tel: (07) 369 8688
S. AUSTRALIA Tel: (08) 344 9000
W. AUSTRALIA Tel: (09) 481 1500

ECONOMIC ELECTRONICS

287 WATER STREET
FORTITUDE VALLEY
PH: (07) 52 3762

SOUTHPORT
ELECTRONICS SHOP
11 DAVENPORT ST,
SOUTHPORT
PH: (075) 32 3632

REGULATOR SELL OUT



1.5 AMP POSITIVE & NEGATIVE 3 TERMINAL REGULATORS

	1-24	25-99	100 +
7805T 5V	0.75¢	0.62¢	0.46 ¢
7812T 12V	0.75¢	0.62¢	0.46 ¢
7815T 15V	0.75¢	0.62¢	0.46 ¢
7905T 5V	0.75¢	0.62¢	0.46 ¢
7912T 12V	0.75¢	0.62¢	0.46 ¢
7915T 15V	0.75¢	0.62¢	0.46 ¢
LM317T ADJ	1.60¢	1.35¢	1.05 ¢
LM337T ADJ	1.75¢	1.40¢	1.15 ¢

* ALL PRICES PLUS TAX 20% *

78H05	5AMP	5V	\$6.00
78H12	5AMP	12V	\$7.35
78P05	10AMP	5V	\$11.00
78P12	10AMP	12V	\$15.00
78HG	5AMP	ADJ	\$6.50
79HG NEG	5AMP	ADJ	\$12.00
78PG	10AMP	ADJ	\$14.30


NEW!!

4AMP SWITCH MODE
POWER SUPPLY MODULE
MAX. INPUT 40 VOLT

ONLY \$60.00

GSR400V 5-48V
GSR405.5V
GSR412.12V

PHONE:
(07) 52 3762



Information Centre . . . ctd

running Marklin AC operated locos with the Railmaster controller.

However, it would appear that there is a simpler solution. All that is necessary to convert the loco to DC operation is to place a diode in series with each of the two field windings as shown in the circuit, and disconnect everything else.


Best of all is the fact that this method completely eliminates the jerky and totally unrealistic reversing changeover caused by the application of 24V to the track to operate the reversing solenoid.

Note that the field windings have opposite senses which is necessary with AC operation to permit rotation in either direction (using a mechanical reversing switch inside the loco). Only one field winding is in use at any given time.

For DC operation, the two diodes select one or the other field windings, depending on the polarity applied to the track. The back EMF generated by the operational winding will be blocked by the diode, but operation of the loco is nonetheless quite smooth.

As the motor appears to perform equally well on either AC or DC, I

would dearly like to know why Marklin have chosen the relatively complex AC arrangement with its associated cumbersome reversing solenoid, particularly as nearly all other makes of locos and controllers run on DC. (A.H., Morley, WA.)



• Thank you for your letter. Your solution is delightfully simple and will no doubt be received with much interest by Marklin operators. Incidentally, while the back-EMF may be blocked by one of your diodes, it will be conducted by the other and so the feedback feature will work.

Notes and Errata

RALLY COMPUTER (June 1985, 3/AU/43): The Fairchild FND508 ± 1 digit display is now in short supply. An equivalent is the Fairchild FND568 which is a higher brightness version. The matching brightness FND567 7-segment display is equivalent to the FND507.

Alternatively, Radio Spares stock pin equivalent displays under catalogue

number 587-945 for the 7-segment type and 587-967 for the ± 1 type. These do not have the integral red filter.

As a last resort, the FND507 or FND567 can be used in place of the FND508. In this case, the "1" will be displayed as normal. However, the plus sign will be indicated by the "A" segment and the minus by the "D" segment.

Control Data Institute

Continued from page 24

For many students it would be impossible to pay cash on the spot, so the Institute runs two schemes which can either forestall the payments, or at least make them more manageable.

There is a pay-as-you-study scheme in which the student pays a monthly sum during the course. The other method is to qualify for a loan from a branch of

the National Australia Bank, specified by the Control Data Institute. Repayments to the bank do not start until one month after the student's graduation date.

Control Data Institute have branches in Melbourne and Brisbane. In Sydney, the telephone number is (02) 438-1300.

EA marketplace EA marketplace

ADVERTISING RATES FOR THIS PAGE


SMALL ADS: The minimum acceptable size of 2 centimetres x one column costs only \$40. Other sizes up to a maximum of 10 centimetres are rated at \$20 a centimetre. **CLASSIFIEDS:** \$4 for 40 letters. Just count the letters divide by 40 and multiply by \$4, ROUND UP TO NEAREST WHOLE NUMBER. **CLOSING DATE:** Ads may be accepted up to the 18th of the month two months prior to issue date. **PAYMENT:** Please enclose payment with your advertisement. Address your letter to THE ADVERTISING MANAGER, ELECTRONICS AUSTRALIA, PO BOX 227, WATERLOO, NSW 2017.

FOR SALE

AMIDON FERROMAGNETIC CORES: Large range for all receiver and transmitter applications. For data and price list send 105X220 SASE to: R.J. & U.S. Imports, PO Box 157, Mortdale, NSW 2223. NSW: Geoff Wood Electronics, Rozelle. ACT: Electronic Components, Fyshwick Plaza. VIC: Truscott Electronics, Croydon. WA: Willis Trading Co, Perth.

SUPER 80: Assembler and full screen Editor \$15. Disassembler \$9. Vowels, 93 Park Dv, Parkville 3052.

MODEM: Build it yourself for under \$100.00. Based on 7910 World Chip, 300 baud, full duplex, orig/answer, also 1200/75 Bd half duplex for "Viatal". RS232 or TTL to suit Commodore. PC board and documentation \$20. P & P \$2. Dreamsoft, 12 Wayne Court, Nth Bayswater, Victoria 3153.



With these selected projects from *Electronics Australia* you can add all of the gadgets and gizmos you've dreamed of —

Cruise Control
Deluxe Burglar Alarm — Courtesy Light Delay
Audible Reversing Alarm — Headlight Reminder
Transistor-assisted Ignition with Optoelectronic Trigger and many more easy-to-build projects to add value, interest and safety to your pride and joy!

Available from your Newsagent Now! Or send \$3.95 plus \$1.00 post and packing for each title to Electronics Australia, PO Box 227, Waterloo 2017, NSW.

SUPER 80 USERS: We will always stock Super 80 products. For catalogue, write to: Matrix Software, P.O. Box 291, Kensington 2033.

NEW RADIO VALVES: For entertainment or industrial use. Waltham Dan, 96 Oxford St, Darlinghurst, Sydney. Phone (02) 331 3360.

VIATEL MODEM

The mini sized modem with a maxi punch. Viatal system at the flick of a switch; 75/1200 (equalised); 1200/75 (equalised); 1200 HD (half duplex); 300 Baud — answer; 300 Baud — Originate; Switched Bell System, switches all modes to bell system; CTS LED display (clear to send); CD LED display (carrier detect); Will work on any computer with RS 232 port; Full instructions; Telecom approved components used throughout. Attractively finished. Using the latest up to the minute technology. This has allowed us to reduce the thunderer modem to a handy size (15 x 8 x 5cm). Will fit into any nook. Doesn't need a shelf of its own. Standard Accessories: RS232 plug and line; Phone plug and line. (All three wired into unit. Ready to go). Power supply. We're so confident of the quality and durability of our product we are offering a two year guarantee, free of labour and parts costs.

\$230.00 (without phone) **\$250.00** (with PB/last re dial phne)
Post & pack \$10.00; Please note. Unit is fully assembled, tested and thundering to go!

Bankcard. Mastercard. American Express welcome.

ACETRONICS PCB'S

112 Robertson Road, Bass Hill 2197

Ph: (02) 645-1241

GENERATE ELECTRICITY FROM THE SUN

ARCO PV PANELS

M73B 40 WATTS 12V

Provide power for pumping, lighting and refrigeration. Now only \$295 each.

ELANTE PTY LTD

5 CREMORNE ST, RICHMOND, VIC.

Phone (03) 429 9733

RCS. RADIO PTY. LTD.

Established 1933
IS THE ONLY COMPANY
WHICH MANUFACTURES AND
SELLS EVERY PCB & FRONT PANEL
published in EA and ETI
651 Forest Road Bexley 2207
AUSTRALIA

RING (02) 587 3491 FOR INSTANT PRICES
24-HOUR TURNAROUND SERVICE

HI FI SPEAKER KITS: Raw drivers, X-overs, plans, replacement speakers and accessories from the world's finest manufacturers. For audiophiles and beginners. Dynaudio, Focal, Foster, Kef, Magnavox, Peerless, Scanspeak, Vifa etc. "Siderealkaps", premium audio grade capacitors just arrived from USA. We ship anywhere within Aust and export to NZ and Pacific. Send \$2 for latest catalogue. Audiocraft, PO Box 725, Toowong, Brisbane, Australia 4066.

EX-ABC AUDIO TAPES: 1/4" wide on 10 1/2" Standard metal spool \$6.85. **Robust** metal spool \$7.85. 7" spool \$2.25. 5" spool \$1.25. Post extra. Also in stock 1/2", 1" and 2" tapes. Waltham Dan, 96 Oxford St., Darlinghurst, Sydney. Phone (02) 331-3360.

A NEW CONCEPT FOR LOW VOLTAGE PROJECTS

COPPER FOIL TAPE: thin pure copper tape backed by special hi-tack adhesive. Current carrying capacity, 5 amps, FULLY TESTED at 24V 5A. Not recommended for mains voltage.

4mm...RRP \$8.03 6mm...RRP \$9.84 33 metre rolls

GIFFORD PRODUCTIONS

PO BOX 62 St Kilda, Vic 3182 (03) 534 3482

UHF CONVERTER

Converts UHF band signal to VHF Channel 1

Can be used to convert Channel 28 to VHF Price \$69.00

Available From:

WAGNER ELECTRONIC SERVICES Pty. Ltd.

305 Liverpool Road, ASHFIELD 213
Telephone: (02) 798 9233

ARE YOU BUILDING AN EA KIT?

If you have purchased an EA kit you may not have all the info you need to build it and get it going properly. Kit suppliers often do not include all the information published on a particular project. If you want to be sure of having all the info on a kit, you need to go to the original source: *Electronics Australia*. We can supply photostat copies of any article we have published for a fee of \$3, including postage. If the article was spread over more than one issue, the charge is \$6. These photostats include any relevant Notes & Errata.

Write to: The Assistant Editor,
"Electronics Australia"
PO Box 227,
Waterloo, NSW, 2017

**EDITOR**

Leo Simpson, B.Bus. (NSWIT)

ASSISTANT EDITOR

Greg Swain, B.Sc. (Hons. Sydney)

EDITORIAL CONSULTANT

Neville Williams

F.I.R.E.E (Aust.) (VK2XV)

TECHNICAL STAFF

John Clarke, B.E. (Elect. NSWIT)

Colin Dawson

Robert Flynn

Louise Upton, B.A. (Hons. Sydney)

ART DIRECTOR

Brian Jones

ART PRODUCTION

Alana Horak

SECRETARIAL

Carmel Triulcio

ADVERTISING PRODUCTION

Danny Hooper

ADVERTISING MANAGER

Selwyn Sayers

PUBLISHER

Michael Hannan

Editorial and Advertising Office: 140 Joynton Avenue (PO Box 227), Waterloo, NSW 2017. Phone: (02) 663 9999. Telex: AA74488. Facsimile: 662 1007. Representative: Norman Palmer.

Melbourne: 23rd Floor, 150 Lonsdale Street, Melbourne, Vic 3000. Phone (03) 662 1222. Representative: John Oliver, B.A. (Hons. Essex).

Adelaide: Admedia Group, 24 Kensington Road, Rose Park, SA 5067. Phone (08) 332 8144. Representative: Steve Birbeck.

Brisbane: 25 Balaclava St, Woollahrabba, Qld 4012. Phone (07) 391 8922. Representative: Bernie Summers.

Perth: Tony Allen and Associates, 7 Fore St, Perth, WA 6000. Phone (09) 328 9833. Representative: Jim Wells.

Distribution: Distributed by Gordon and Gotch Limited, Sydney.

Registered by Australia Post — publication No. NBP0240. ISSN 0313-0150.

Typeset and printed by Eastern Suburbs Newspapers, Joynton Ave, Waterloo, NSW, for The Federal Publishing Company Pty Ltd.

*Recommended and maximum price only.

©Double Bay Newspapers Pty Limited, General Newspapers Pty Limited and Suburban Publications Pty Limited (trading as "Eastern Suburbs Newspapers"), 1985.

Published by the Federal Publishing Company Pty Limited, under licence from Double Bay Newspapers Pty Limited, General Newspapers Pty Limited and Suburban Publications Pty Limited.

ADVERTISING INDEX

Adilam	76
Altronics	40,41,42,43
Amtex	81
Audio Engineers	109
Australian School Electronics	12
Australian Government RAAF	IBC

Camlogan Nomin (Knox)	75
Cashmore Sound	93
Commodore Business	19
Control Data	12
Copispec	68

Daneva	11
David Reid Electronics	50
Diamond Systems	94
Dick Smith Electronics	22,23,87,95
	loose insert

Economics Electronics	120
Eclipse Computers	67
Elante	121
Electronic Brokers Australia	96
Elmeasco Instruments	7,13,117,119

Federal Publishing	56,78,79
--------------------	----------

Gifford Productions	121
---------------------	-----

IEI	85
-----	----

Jaycar	34,35,70,71
--------	-------------

Ody Communications	25
Ophir	47

Pro-Data	82
----------	----

RCS Radio	121
Rank Industries	103
Rod Irving Electronics	57,58,59,60,61

Scan Audio	83
Sony	OBC
Stotts Correspondence College	77

Tivoli Hi-fi	113
Truscotts	94

Vanfi	IFC
-------	-----

Electronics Australia Reader Service

"Electronics Australia" provides the following services:

BACK ISSUES: Available until stocks are depleted. Price \$4 including postage and handling. When back copies are exhausted, reprints of articles may be obtained for the same cost. If the issue you require is not shown on the list below, please nominate the article you would like photocopied and the issue in which it appeared. Send cheque, money order or credit card number (American Express, Bankcard, Master Card), name and address to: Elizabeth Barnett, Direct Marketing Division, Federal Publishing Company, PO Box 227, Waterloo 2017.

AVAILABLE BACK ISSUES:

1981: Jun, Jul.

1982: May, Oct.

1983: Jan, Mar, Apr, May, Jul, Aug, Nov, Dec.

1984: Jan, Feb, Apr, May, Oct, Nov.

1985: Jan, Feb, Mar, Apr, May, Jun, Jul, Aug, Sep, Oct, Nov, Dec.

PC BOARD PATTERNS: High contrast, actual size transparencies: \$3, including postage. Please specify positive or negative.

PROJECT QUERIES: Members of our technical staff are not normally available to discuss individual projects, either in person at our office, or by telephone.

REPLIES BY POST: Limited to advice concerning projects published within the last three years. Charge \$3. We cannot provide lengthy answers, undertake special research, or discuss design changes. Nor can we provide any information on commercial equipment.

OTHER QUERIES: Technical queries outside the scope of "Replies by Post" or submitted without fee may be answered in the "Information Centre" pages, at the discretion of the Editor.

COMPONENTS: We do not sell electronic components. Prices and specifications should be sought from advertisers or agents.

REMITTANCES: Must be negotiable in Australia and made payable to "Electronics Australia". Where the exact charge may be in doubt, we recommend submitting an open cheque endorsed with a suitable limitation.

ADDRESS: All requests to the Assistant Editor, "Electronics Australia", Box 227, Waterloo, 2017.

Total price of magazines/photocopies,
including postage and handling.

No off issues reg x \$4 = \$.....

Send to Elizabeth Barnett,
Direct Marketing Division,
Federal Publishing Company Pty Ltd,
PO Box 227, Waterloo 2017.

Cheque/Money Order ☐ Please tick box to indicate
method of payment:

*Please make payable to the Federal Publishing Company Pty Ltd.

Mastercard ☐ American Express ☐ Bankcard ☐ Tick ☒

Card Expiry Date

Credit Card No.

Signature
(Unsigned Orders cannot be accepted)

NAME:

ADDRESS:

..... POSTCODE.....

Australia's early warning security is in the hands of the Airborne Electronics Analyst.

So no one asks an AEA if he has trouble getting out of bed on a Monday.

It's the AEA's task to lead his flight to "friend or foe" targets, across enormous distances of hostile ocean.

He determines target status by operating a vast array of complex detection systems, and analysing the data presented by them.

All from a sophisticated flying electronics platform known as a P3C Orion Maritime Surveillance Aircraft.

Together with the Pilot and Navigator Tactician, the AEA forms a close-knit team called Aircrew.

And like the Pilot and Navigator

Tactician, he's well versed on avionics, the theory of flight.

As an AEA, you could be locating a merchant vessel floundering in a boiling sea. Pin-pointing a fleet of foreign trawlers poaching in Australian waters.

Or on exercises with the Royal Australian Navy, detecting "unfriendly" subs lurking beneath the waves.

It's an exciting, well-paid career with excellent security. And it could take you all around the world.

To apply, you must be 17

You must have completed year 11 or higher with prescribed passes in specific subjects.

You must also be an Australian citizen or be eligible to become one.

If you meet our selection require-

ments, you'll be in the air in no time at all.

Hunting the oceans instead of the classifieds.

Send off this coupon now to find out more about your career as an Airborne Electronics Analyst.

To: RAAF Careers, GPO Box XYZ
(in the Capital City nearest you).

Name _____


Address _____

Postcode _____

Date of Birth _____ Highest Educ.

level attained _____ or

being studied _____

 **AEA** Airborne Electronics Analyst

Authorised by Director-General of Recruiting, Dept. of Defence.

Instead of hunting for jobs, you could be hunting for subs.



Video 8

The biggest, smallest and sharpest thing to happen to video in years.

The autofocus CCD-V8

The biggest thing to happen to video in years is incredibly small. In fact, it's only 8mm.

And, because it is completely auto-focusing and its recording standards are so high, it presents some of the sharpest images you'll ever see on home video.

Big Performance.

Sony's VIDEO 8 camera recorder, the CCD-V8AF, is a sophisticated video recorder and automatic focusing camera in the same miniature package weighing only 2.3kg.

It allows you to shoot and record up to three hours on a single VIDEO 8 cassette, and play back on the detachable viewfinder or any television or monitor.

As well, it offers all the features you'd expect from a full-size video recorder, even off-air recording with its optional tuner.

When shooting, an innovative

new kind of erase head enables smooth, professional-looking edits in the camera, automatically.

Small Size.

The cassette it uses is about the same size as your everyday audio cassette, yet, because of the new and greatly enhanced type of tape it uses, its picture quality is unparalleled.

And because VIDEO 8 employs the same FM audio recording method as hi-fi video recorders, its sound quality is probably superior to what you're using now.

Completely Compatible.

This new VIDEO 8 format has been agreed upon by 127* of the world's leading video-related companies.

And this milestone in miniaturisation has been designed from the ground up to complement your existing video system.

Whatever format you currently use, Sony's new VIDEO 8 works side by side as the most portable, most flexible, most extraordinary home video system ever conceived.

And, being covered by the Sony Service Seal, a two-year warranty, including heads, applies.

Totally Unique.

Sony's new VIDEO 8 auto-focus camera recorder, the CCD-V8AF, is like no other system you've seen before.

It has so many unexpected and sophisticated features that you will immediately recognise it as the biggest thing to happen to video in a decade.

It's also the smallest.

SONY®

SHARE THE VISION

CCD-V8AF
(Auto-Focus)



Sydney: (02) 887 6666. Melbourne: (03) 836 4011. Brisbane: (07) 44 6554. Adelaide: (08) 212 2877. Perth: (09) 323 8640. Launceston: (003) 431 022. Wollongong: (042) 71 5777.

As at February 1985

Recording of TV programmes is not permitted unless permission is granted by the copyright owner.

V 113 0964